ArubaOS DRT 1.0_73310

aruba

a Hewlett Packard
Enterprise company

Release Notes

Copyright Information

© Copyright 2019 Hewlett Packard Enterprise Development LP

Open Source Code

This product includes code licensed under the GNU General Public License, the GNU Lesser General Public License, and/or certain other open source licenses. A complete machine-readable copy of the source code corresponding to such code is available upon request. This offer is valid to anyone in receipt of this information and shall expire three years following the date of the final distribution of this product version by Hewlett-Packard Enterprise Company. To obtain such source code, send a check or money order in the amount of US $10.00 to:

Hewlett-Packard Enterprise Company
Attn: General Counsel
6280 America Center Drive
San Jose, CA 95002
USA

Please specify the product and version for which you are requesting source code.

You may also request a copy of this source code free of charge at: http://hpe.com/software/opensource.

Contents 3

Downloadable Regulatory Table 14

Overview 14

Contacting Support 14

Uploading and Activating the DRT 15

Important Points to Remember 15

Copying the DRT 15

For ArubaOS 6.x: 15

In the WebUI 15

In the CLI 15

For ArubaOS 8.x: 16

In the WebUI 16

In the CLI 16

Activating the DRT 16

For ArubaOS 6.x: 16

In the WebUI 16

In the CLI 16

For ArubaOS 8.x: 17

In the CLI 17

Supported Countries 18

Afghanistan 23

Åland Islands 25

Albania 28

Algeria 31

American Samoa 34

Andorra 36

Angola 39

Antarctica 41

Antigua and Barbuda 42

Argentina 44
Aruba 47
Australia 48
Austria 51
Azerbaijan 54
Bahamas 57
Bahrain 59
Bangladesh 62
Barbados 65
Belarus 67
Belgium 70
Bermuda 73
Bolivia 75
Bonaire Saint Eustatius and Saba 78
Bosnia and Herzegovina 79
Botswana 82
Brazil 84
Brunei Darussalam 87
Bulgaria 88
Burkina Faso 91
Cambodia 92
Cameroon 93
Canada 95
Chad 98
Cayman Islands 99
Chile 102
China 105
Colombia 108
Costa Rica 111
Côtes d'Ivorie 114
Croatia 116
Curacao 119

Cyprus 121
Czech Republic 124
Democratic Republic of the Congo 127
Denmark 128
Dominican Republic 131
Ecuador 134
Egypt 137
El Salvador 140
Estonia 143
Faroe Islands 146
Federated States of Micronesia 149
Finland 152
France 155
French Guiana 158
French Polynesia 161
French Southern Territories 164
Georgia 166
Germany 169
Ghana 172
Greece 175
Greenland 178
Grenada 181
Guadeloupe 183
Guam 185
Guatemala 188
Guernsey 191
Guyana 194
Haiti 196
Vatican City 198
Honduras 201
Hong Kong 203
Hungary 206

Iceland 209
India 212
Indonesia 215
Iraq 218
Ireland 219
Isle of Man 222
Israel 225
Italy 228
Jamaica 231
Japan 233
Jersey 236
Jordan 239
Kazakhstan 241
Kenya 244
Kosovo 246
Kuwait 248
Laos 251
Latvia 254
Lebanon 257
Libya 259
Liechtenstein 261
Lithuania 264
Luxembourg 267
Macau 270
Macedonia 273
Malawi 276
Malaysia 278
Maldives 281
Mali 283
Malta 284
Maritime Forward Operating Base 287
Maritime Offshore 290

Marshall Islands 293
Martinique 296
Mauritania 299
Mauritius 302
Mayotte 304
Mexico 306
Moldova 309
Monaco 312
Monserrat 314
Montenegro 315
Morocco 318
Mozambique 320
Myanmar 323
Namibia 326
Nepal 329
Netherlands 331
New Caledonia 334
New Zealand 337
Nicaragua 340
Niger 342
Nigeria 343
North Mariana Islands 345
Norway 348
Oman 352
Pakistan 355
Panama 358
Papua New Guinea 360
Paraguay 361
Peru 363
Philippines 366
Poland 369
Portugal 372

Puerto Rico 376
Qatar 379
Republic of the Congo 382
Réunion 383
Romania 386
Russia 389
Rwanda 392
Saint Barthélemy 395
Saint Kitts and Nevis 397
Saint Lucia 398
Saint Martin 400
Saint Pierre and Miquelon 403
Saint Vincent and the Grenadines 406
San Marino 408
Saudi Arabia 411
Senegal 414
Serbia 417
Singapore 420
Slovak Republic 423
Slovenia 426
South Africa 429
South Korea 432
Spain 435
Sri Lanka 438
Suriname 440
Svalbard and Jan Mayen 442
Sweden 445
Switzerland 448
Taiwan 451
Tanzania 454
Thailand 456
Trinidad and Tobago 459

Tunisia 461
Turkey 463
Turkmenistan 466
Uganda 467
Ukraine 469
United Arab Emirates 472
United Kingdom 475
United States of America 478
Uruguay 482
Uzbekistan 485
Venezuela 487
Vietnam 489
Virgin Islands (US) 492
Wallis and Futuna 495
Zambia 498
Zimbabwe 501
DRT Versions 503
1.0_73310 507
1.0_73142 508
1.0_72905 511
1.0_72670 512
1.0_72500 514
1.0_72277 519
1.0_72057 525
1.0_71892 526
1.0_71647 529
1.0_71451 536
1.0_71313 539
1.0_71072 545
1.0_70855 552
1.0_70671 557

1.0_70537 558
1.0_70267 565
1.0_70076 566
1.0_69842 572
1.0_69660 574
1.0_69377 580
1.0_69166 582
1.0_68979 584
1.0_68720 591
1.0_68474 594
1.0_68143 596
1.0_68046 597
1.0_67861 598
1.0_67494 604
1.0_67280 608
1.0_67041 609
1.0_66781 610
1.0_66547 614
1.0_66351 617
1.0_66152 621
1.0_65937 622
1.0_65685 623
1.0_65473 624
1.0_65328 626
1.0_65103 627
1.0_64825 634
1.0_64657 635
1.0_64450 636
1.0_64331 638
1.0_64134 639
1.0_63879 644
1.0_63727 647

1.0_63516 648
1.0_63392 652
1.0_63102 653
1.0_63044 654
1.0_62783 658
1.0_62496 661
1.0_62311 663
1.0_62141 667
1.0_61955 668
1.0_61690 669
1.0_61527 670
1.0_61313 672
1.0_61045 673
1.0_60944 674
1.0_60744 675
1.0_60518 676
1.0_60362 677
1.0_60114 680
1.0_59989 681
1.0_59783 682
1.0_59591 684
1.0_59241 688
1.0_59118 693
1.0_59015 696
1.0_58653 705
1.0_58258 708
1.0_58226 710
1.0_57815 714
1.0_57776 715
1.0_57440 718
1.0_57223 721
1.0_57023 723

1.0_56912 725
1.0_56643 730
1.0_56452 731
1.0_56308 732
1.0_56128 733
1.0_56050 735
1.0_55859 738
1.0_55642 740
1.0_55489 743
1.0_55384 744
1.0_54870 745
1.0_54672 750
1.0_54367 752
1.0_54219 753
1.0_54079 754
1.0_53811 756
1.0_53631 757
1.0_53420 759
1.0_53255 760
1.0_52991 761
1.0_52858 762
1.0_52699 763
1.0_52480 764
1.0_52238 767
1.0_52042 769
1.0_51997 770
1.0_51685 773
1.0_51477 774
1.0_51362 776
1.0_51155 777
1.0_50970 778
1.0_50775 780

1.0_50552 781
1.0_50379 782
1.0_50288 785
1.0_49986 786
1.0_49810 787
1.0_49596 788
1.0_49422 790
1.0_49142 792
1.0_48902 794
1.0_48713 801
1.0_48460 805
1.0_48188 809
1.0_48019 810
1.0_47726 811
1.0_47469 812
1.0_47156 815
1.0_46705 817
1.0_46413 818
1.0_46245 819
1.0_45530 821
1.0_45134 822
1.0_44265 825

The Downloadable Regulatory Table (DRT) features allow new regulatory approvals to be distributed without waiting for a new software patch and upgrade. The file containing AP Regulatory-certification information will be released periodically on the customer support site. The Downloadable Regulatory Table file can then be uploaded to an Aruba controller and communicated to deployed APs.

NOTE

Use of the Downloadable Regulatory Table feature requires ArubaOS 6.4.1 or newer.

Overview

Uploading and Activating the DRT on page 15 explains how to upload and activate the Regulatory-Cert.

Contacting Support

Table 1: *Contact Information*

Main Site	arubanetworks.com
Support Site	support.arubanetworks.com
Airheads Social Forums and Knowledge Base	community.arubanetworks.com
North American Telephone	1-800-943-4526 (Toll Free) 1-408-754-1200
International Telephone	arubanetworks.com/support-services/contact-support/
Software Licensing Site	hpe.com/networking/support
End of Support Information	arubanetworks.com/support-services/end-of-life
Security Incident Response Team (SIRT)	http://www.arubanetworks.com/support-service/security-bulletins/ Email: sirt@arubanetworks.com

Uploading and Activating the DRT

The following section describes the process for uploading and activating the Downloadable Regulatory Table (DRT).

Important Points to Remember

- Before a new DRT file is activated, the version number is checked against the default version built into ArubaOS. The DRT file version must be greater than the default version. If the DRT file is not greater than the default version, the activation will fail. The CLI of the controller/managed device displays the following message upon failure:

```
(host) #ap regulatory activate reg-data-1.0_00002.dat
Failed to activate regulatory file reg-data-1.0_00002.dat. File  Version should be greater
than 1.0_43859
```

- APs do not rebootstrap or reboot when activating a new DRT file.
- If there is a change in channel list or power level, APs will change the channel or power level. Impact is same as that of ARM chanel or power change in that case.
- Clients are not disconnected upon regulatory file activation. Max latency impact during activation (with no channel or power level changes) are less than 1 second.
- With channel change, the impact is similar to ARM channel change (depends on client behavior and id CSA is enabled or not).
- If support for the AP (Country) is added, the AP will move from AM to AP mode (if the AP is configured in AP mode of operation)

Copying the DRT

You can use the following protocols to copy the DRT file to a controller/managed device:

- FTP
- TFTP
- SCP

Additionally, DRT file saved to a USB drive can be uploaded to a controller/managed device equipped with a USB port.

The DRT can be copied to the controller/managed device using the WebUI or CLI.

For ArubaOS 6.x:

In the WebUI

- Navigate to the **Maintenance > File > Copy Files** page.
- Select the source (TFTP, FTP, SCP or USB) where the file exists.
- The controller WebUI will automatically select **Flash File System** under the **Destination Selection** menu.
- Click **Apply**.

In the CLI

Use one of the following **copy** commands to download the DRT file to the controller:

```
copy
   ftp: <ftphost> <user> <filename> {flash: <destfilename>|system:partition [0|1]
   scp: <scphost> <username> <filename> flash: <destfilename>
   tftp: <tftphost> <filename> flash: <destfilename>
   usb: partition <partition-number> <filename> flash: <destfilename>
```

For ArubaOS 8.x:

In the WebUI

- In the **Mobility Master > host** node hierarchy, navigate to the **Diagnostics > Technical Support > Copy Files** page.
- Select the source (TFTP, FTP, SCP or USB) where the file exists.
- The managed device WebUI will automatically select **Flash File System** under the **Destination Selection** menu.
- Click **Copy**.

In the CLI

Use one of the following **copy** commands to download the DRT file to the managed device:

```
copy
   ftp: <ftphost> <user> <filename>
   scp: <scphost> <username> <filename> flash: <destfilename>
   tftp: <tftphost> <filename> flash: <destfilename>
   usb: partition <partition-number> <filename> flash: <destfilename>
```

Activating the DRT

Once the DRT file has been added to the controller/managed device, the new regulatory information must be activated and pushed to the APs.

For ArubaOS 6.x:

In the WebUI

To activated a specific DRT file using the WebUI:

- Navigate to the **Maintenance > File > Regulatory Files**.
- Select a regulatory file from the **File list**.
- Click **Activate**.

In the CLI

To activate a specific DRT file loaded on the controllers, use the following command:

```
ap regulatory activate <filename>
```

To return to the factory default DRT file, use the following command:

```
ap regulatory reset
```

In a master-local-standby deployment, the file syncing profile can be enabled to ensure that the regulatory-cert that is stored on the master is shared with its subordinate controllers. File syncing is enabled by default, with a default sync time of 30 minutes. The sync time can be set between 30 to 180 minutes, To configure the file syncing profile, use the following commands:

```
(host) (config) #file syncing profile
(host) (File syncing profile) #file-syncing-enable
(host) (File syncing profile) #sync-time 30
```

To view the currently active regulatory file of controllers connected to the master controller, execute the following command:

```
show switches regulatory
```

To view the file syncing profile settings, execute the following command:

```
show file syncing profile
```

To view the currently active regulatory certificate, execute the following commands:

```
show ap regulatory
```

To view the allowed channels on a specific AP name, country code, or IP address, execute the following command:

```
show ap allowed-channels
   ap-name <ap-name>
   country-code <country-code> [ap-type <ap-type>]
   ip-addr <ip-addr>
```

To view the power table for an AP, execute the following commands:

```
show ap debug power-table {ap-name <ap-name>|ip-addr <ip-addr>|ip6-addr <ip6-addr>}{radio
<radio id>}
```

For ArubaOS 8.x:

In the CLI

To activate a specific DRT file loaded on the managed device, use the following command:

```
ap regulatory activate <filename>
```

To return to the factory default DRT file, use the following command:

```
ap regulatory reset
```

In a Mobility Master-Managed Device deployment, the file syncing profile can be enabled to ensure that the regulatory-cert that is stored on the Mobility Master is shared with the managed devices.

File synchronization occurs when the DRT file is activated in the Mobility Master and the Mobility Master synchronizes the DRT file to all managed devices within the synchronization time and is automatically activated. File syncing is enabled by default, with a default sync time of 30 minutes. The sync time can be set between 30 to 180 minutes, To configure the file syncing profile, use the following commands:

```
(host) [md] (config) #file syncing profile
(host) [md] (File syncing profile) #file-syncing-enable
(host) [md] (File syncing profile) #sync-time 30
```

To view information about the currently active regulatory file of managed devices connected to the Mobility Master, execute the following command:

```
(host) [md] #show switches regulatory
```

To view the file syncing profile settings, execute the following command:

```
(host) [md] #show file syncing profile
```

To view the currently active regulatory cert, execute the following command:

```
show ap regulatory
```

To view the allowed channels on a specific AP name, country code, or IP address, execute the following command:

```
show ap allowed-channels
   ap-name <ap-name>
   country-code <country-code> [ap-type <ap-type>]
   ip-addr <ip-addr>
```

To view the regulatory power limits per channel for a specified AP, execute the following command:

```
show ap allowed-max-EIRP {ap-name <ap-name>}|{ ip-addr <ip-addr>}
```

To view the downloaded regulatory table for an AP, execute the following command:

```
show ap debug received-reg-table {ap-name <ap-name>}|{bssid <bssid>}|{ip-addr <ip-addr>}|{ip6-
addr <ip6-addr>}
```

Supported Countries

This section contains a list of all countries and APs that are currently supported in this release of the Downloadable Regulatory Table.

- Afghanistan
- Åland Islands
- Albania
- Algeria
- American Samoa
- Andorra
- Angola
- Antarctica
- Antigua and Barbuda
- Argentina
- Aruba
- Australia
- Austria
- Azerbaijan
- Bahamas
- Bahrain
- Bangladesh
- Barbados
- Belarus
- Belgium
- Bermuda
- Bolivia
- Bosnia and Herzegovina
- Brazil
- Brunei Darussalam
- Bulgaria
- Burkina Faso
- Canada
- Chile
- China
- Colombia
- Costa Rica
- Croatia
- Curacao
- Cyprus
- Czech Republic
- Democratic Republic of the Congo
- Denmark

- Dominican Republic
- Ecuador
- Egypt
- El Salvador
- Estonia
- Faroe Islands
- Federated States of Micronesia
- Finland
- France
- French Guiana
- French Polynesia
- French Southern Territories
- Germany
- Ghana
- Greece
- Greenland
- Grenada
- Guadeloupe
- Guam
- Guatemala
- Guyana
- Haiti
- Hong Kong
- Hungary
- Iceland
- India
- Indonesia
- Ireland
- Isle of Man
- Israel
- Italy
- Japan
- Jersey
- Jordan
- Kazakhstan
- Kenya
- Kuwait
- Laos
- Latvia
- Lebanon
- Libya
- Liechtenstein

- Lithuania
- Luxembourg
- Macau
- Macedonia
- Malawi
- Malaysia
- Mali
- Malta
- Maritime Forward Operating Base
- Maritime Offshore
- Marshall Islands
- Martinique
- Mauritius
- Mayotte
- Mexico
- Moldova
- Monaco
- Monserrat
- Montenegro
- Morocco
- Mozambique
- Myanmar
- Netherlands
- New Zealand
- Nicaragua
- Niger
- Nigeria
- North Mariana Islands
- Norway
- Oman
- Pakistan
- Panama
- Papua New Guinea
- Paraguay
- Peru
- Philippines
- Poland
- Portugal
- Puerto Rico
- Qatar
- Republic of the Congo
- Réunion

- Romania
- Russia
- Rwanda
- Saint Barthélemy
- Saint Kitts and Nevis
- Saint Lucia
- Saint Martin
- Saint Pierre and Miquelon
- San Marino
- Saint Vincent and the Grenadines
- Saudi Arabia
- Senegal
- Serbia
- Singapore
- Slovak Republic
- Slovenia
- South Africa
- South Korea
- Spain
- Sri Lanka
- Suriname
- Svalbard and Jan Mayen
- Sweden
- Switzerland
- Taiwan
- Tanzania
- Thailand
- Trinidad and Tobago
- Tunisia
- Turkey
- Turkmenistan
- Uganda
- Ukraine
- United Arab Emirates
- United Kingdom
- United States of America
- Uruguay
- Vatican City
- Virgin Islands (US)
- Venezuela
- Vietnam
- Wallis and Futuna

- Zambia
- Zimbabwe

Afghanistan

The following devices are currently supported in the Afghanistan regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AF ap-type <ap-type>`

Table 2: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-203H	DRT 1.0_64450
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-207	DRT 1.0_59241
AP-214	DRT 1.0_69377
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_59015
AP-305	DRT 1.0_62783
AP-314	DRT 1.0_70855
AP-315	DRT 1.0_68143
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_56912
AP-325	DRT 1.0_56912
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 2: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-365	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-108	DRT 1.0_56912
RAP-109	DRT 1.0_56912

Åland Islands

The following devices are currently supported in the Åland Islands regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AX ap-type <ap-type>`

Table 3: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713

Table 3: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076

Table 3: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-3WNP	DRT 1.0_48713

Albania

The following APs are currently supported in the Albania regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AL ap-type <ap-type>`

Table 4: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_48713
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_48713
AP-203H	DRT 1.0_59015
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-204	DRT 1.0_59015

Table 4: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044

Table 4: *Supported Devices*

Device	Minimum Supported DRT Version
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Algeria

The following APs are currently supported in the Algeria regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code DZ ap-type <ap-type>`

Table 5: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_59015
AP-103H	DRT 1.0_69842
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_59015
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59015
AP-203R	DRT 1.0_65685
AP-203RP	DRT 1.0_65685
AP-205	DRT 1.0_59015
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_59015
AP-225	DRT 1.0_59015
AP-228	DRT 1.0_59015
AP-274	DRT 1.0_48019

Table 5: *Supported Devices*

Device	Minimum Supported DRT Version
AP-275	DRT 1.0_59015
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_69166
AP-304	DRT 1.0_59015
AP-305	DRT 1.0_59015
AP-314	DRT 1.0_59015
AP-315	DRT 1.0_59015
AP-318	DRT 1.0_69377
AP-324	DRT 1.0_59015
AP-325	DRT 1.0_59015
AP-334	DRT 1.0_59015
AP-335	DRT 1.0_59015
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-365	DRT 1.0_59015
AP-367	DRT 1.0_59015
AP-374	DRT 1.0_72057
AP-375	DRT 1.0_72057
AP-377	DRT 1.0_72057
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69660

Table 5: *Supported Devices*

Device	Minimum Supported DRT Version
AP-515	DRT 1.0_69660
AP-534	DRT 1.0_70671
AP-535	DRT 1.0_70671
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859

American Samoa

The following APs are currently supported in the American Samoa regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AS ap-type <ap-type>`

Table 6: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_56050
AP-103H	DRT 1.0_56050
AP-105	DRT 1.0_48902
AP-114	DRT 1.0_48902
AP-115	DRT 1.0_48902
AP-135	DRT 1.0_48902
AP-175P	DRT 1.0_48902
AP-203H	DRT 1.0_59591
AP-204	DRT 1.0_56050
AP-205	DRT 1.0_56050
AP-214	DRT 1.0_56050
AP-215	DRT 1.0_56050
AP-224	DRT 1.0_56050
AP-225	DRT 1.0_56050
AP-228	DRT 1.0_56050
AP-274	DRT 1.0_56050
AP-275	DRT 1.0_56050
AP-277	DRT 1.0_53811
AP-303	DRT 1.0_63879

Table 6: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303H	DRT 1.0_71892
AP-303P	DRT 1.0_67861
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-318	DRT 1.0_68720
AP-324	DRT 1.0_52238
AP-325	DRT 1.0_52238
AP-334	DRT 1.0_56128
AP-335	DRT 1.0_56128
AP-344	DRT 1.0_63044
AP-345	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-93	DRT 1.0_48902
RAP-108	DRT 1.0_56050
RAP-109	DRT 1.0_56050
RAP-155	DRT 1.0_56050
RAP-155P	DRT 1.0_56050
RAP-3WNP	DRT 1.0_48902

Andorra

The following APs are currently supported in the Andorra regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AD ap-type <ap-type>`

Table 7: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 7: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-315	DRT 1.0_68143
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 7: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Angola

The following devices are currently supported in the Angola regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AO ap-type <ap-type>`

Table 8: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-135	DRT 1.0_53811
AP-203H	DRT 1.0_64450
AP-207	DRT 1.0_62783
AP-215	DRT 1.0_58653
AP-225	DRT 1.0_53811
AP-275	DRT 1.0_58653
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62783
AP-305	DRT 1.0_62783
AP-318	DRT 1.0_64134
AP-325	DRT 1.0_55384
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979

Table 8: *Supported Devices*

Device	Minimum Supported DRT Version
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Antarctica

The following APs are currently supported in the Aruba regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AQ ap-type <ap-type>`

Table 9: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-215	DRT 1.0_73310

Antigua and Barbuda

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AG ap-type <ap-type>`

Table 10: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-204	DRT 1.0_60518
AP-205	DRT 1.0_52858
AP-207	DRT 1.0_60362
AP-224	DRT 1.0_60518
AP-225	DRT 1.0_60362
AP-228	DRT 1.0_60362
AP-275	DRT 1.0_52858
AP-303	DRT 1.0_63879
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_62783
AP-305	DRT 1.0_62783
AP-314	DRT 1.0_72500
AP-315	DRT 1.0_72500
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979

Table 10: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Argentina

The following APs are currently supported in the Argentina regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AR ap-type <ap-type>`

Table 11: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_45134
AP-103H	DRT 1.0_48188
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_64450
AP-203R	DRT 1.0_64450
AP-203RP	DRT 1.0_64450
AP-204	DRT 1.0_48188
AP-205	DRT 1.0_48188
AP-205H	DRT 1.0_55384
AP-207	DRT 1.0_63102
OC-20	DRT 1.0_59989
AP-214	DRT 1.0_48188
AP-215	DRT 1.0_48188

Table 11: *Supported Devices*

Device	Minimum Supported DRT Version
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_48460
AP-228	DRT 1.0_50552
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-303	DRT 1.0_67041
AP-303H	DRT 1.0_64331
AP-303P	DRT 1.0_69842
AP-304	DRT 1.0_63102
AP-305	DRT 1.0_63102
AP-314	DRT 1.0_60518
AP-315	DRT 1.0_60518
AP-318	DRT 1.0_67041
AP-334	DRT 1.0_60518
AP-335	DRT 1.0_60518
AP-344	DRT 1.0_65328
AP-345	DRT 1.0_65103
AP-365	DRT 1.0_65328
AP-367	DRT 1.0_65328
AP-374	DRT 1.0_67041
AP-375	DRT 1.0_67041
AP-377	DRT 1.0_67041
AP-514	DRT 1.0_70537
AP-515	DRT 1.0_70537

Table 11: *Supported Devices*

Device	Minimum Supported DRT Version
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_72057
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Aruba

The following APs are currently supported in the Aruba regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AW ap-type <ap-type>`

Table 12: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-225	DRT 1.0_48460

Australia

The following APs are currently supported in the Australia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AU ap-type <ap-type>`

Table 13: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_60362
AP-203R	DRT 1.0_60362
AP-203RP	DRT 1.0_60362
AP-204	DRT 1.0_59015

Table 13: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_49810
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_48188
AP-225	DRT 1.0_48188
AP-228	DRT 1.0_49596
AP-274	DRT 1.0_54079
AP-275	DRT 1.0_54079
AP-277	DRT 1.0_48713
AP-303	DRT 1.0_65328
AP-303H	DRT 1.0_59241
AP-304	DRT 1.0_59591
AP-305	DRT 1.0_59591
AP-314	DRT 1.0_56452
AP-315	DRT 1.0_56452
AP-318	DRT 1.0_64825
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-334	DRT 1.0_56452
AP-335	DRT 1.0_56452
AP-344	DRT 1.0_64134
AP-345	DRT 1.0_64134

Table 13: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_64134
AP-375	DRT 1.0_64134
AP-377	DRT 1.0_64134
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_72905
AP-505	DRT 1.0_72905
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_71072
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Austria

The following APs are currently supported in the Austria regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AT ap-type <ap-type>`

Table 14: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_57815
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 14: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311

Table 14: *Supported Devices*

Device	Minimum Supported DRT Version
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Azerbaijan

The following APs are currently supported in the Azerbaijan regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AZ ap-type <ap-type>`

Table 15: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_59241
AP-105	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-203H	DRT 1.0_64450
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-204	DRT 1.0_55859
AP-205	DRT 1.0_55859
AP-207	DRT 1.0_59241
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_59241
AP-225	DRT 1.0_55859
AP-274	DRT 1.0_72905
AP-275	DRT 1.0_72905

Table 15: *Supported Devices*

Device	Minimum Supported DRT Version
AP-277	DRT 1.0_72905
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62783
AP-305	DRT 1.0_62783
AP-314	DRT 1.0_59241
AP-315	DRT 1.0_59241
AP-318	DRT 1.0_64134
AP-334	DRT 1.0_59591
AP-335	DRT 1.0_59591
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076

Table 15: *Supported Devices*

Device	Minimum Supported DRT Version
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859

Bahamas

The following APs are currently supported in the Bahamas regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BS ap-type <ap-type>`

Table 16: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_56452
AP-203H	DRT 1.0_65473
AP-203R	DRT 1.0_65473
AP-203RP	DRT 1.0_65473
AP-204	DRT 1.0_56050
AP-205	DRT 1.0_56050
AP-205H	DRT 1.0_65473
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_68474
AP-224	DRT 1.0_56050
AP-225	DRT 1.0_56050
AP-228	DRT 1.0_71647
AP-274	DRT 1.0_56050
AP-275	DRT 1.0_56050
AP-277	DRT 1.0_56128
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_68474
AP-303P	DRT 1.0_68474

Table 16: *Supported Devices*

Device	Minimum Supported DRT Version
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_56128
AP-315	DRT 1.0_56128
AP-318	DRT 1.0_65473
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_65328
AP-345	DRT 1.0_65328
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-377	DRT 1.0_65328
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-3WN	DRT 1.0_65473
RAP-3WNP	DRT 1.0_65473

Bahrain

The following APs are currently supported in the Bahrain regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BH ap-type <ap-type>`

Table 17: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_50552
AP-103H	DRT 1.0_50552
AP-105	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_63044
AP-203R	DRT 1.0_60518
AP-203RP	DRT 1.0_60518
AP-204	DRT 1.0_50775
AP-205	DRT 1.0_50775
AP-205H	DRT 1.0_49810
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_55642
AP-215	DRT 1.0_55642
AP-224	DRT 1.0_50775
AP-225	DRT 1.0_46245
AP-228	DRT 1.0_49596

Table 17: *Supported Devices*

Device	Minimum Supported DRT Version
AP-274	DRT 1.0_50775
AP-275	DRT 1.0_50775
AP-277	DRT 1.0_48460
AP-303	DRT 1.0_65328
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_69377
AP-305	DRT 1.0_67861
AP-314	DRT 1.0_59241
AP-318	DRT 1.0_65328
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_71647
AP-335	DRT 1.0_71647
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-365	DRT 1.0_71647
AP-367	DRT 1.0_71647
AP-374	DRT 1.0_65937
AP-375	DRT 1.0_65473
AP-377	DRT 1.0_65937
AP-514	DRT 1.0_69377
AP-515	DRT 1.0_69377
AP-534	DRT 1.0_71647
AP-535	DRT 1.0_71647

Table 17: *Supported Devices*

Device	Minimum Supported DRT Version
AP-555	DRT 1.0_71647
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
RAP-109	DRT 1.0_57440

Bangladesh

The following APs are currently supported in the Bangladesh regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BD ap-type <ap-type>`

Table 18: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_57023
AP-104	DRT 1.0_57023
AP-105	DRT 1.0_57023
AP-114	DRT 1.0_57023
AP-115	DRT 1.0_57023
AP-120	DRT 1.0_57023
AP-121	DRT 1.0_57023
AP-124	DRT 1.0_57023
AP-125	DRT 1.0_57023
AP-134	DRT 1.0_57023
AP-135	DRT 1.0_57023
AP-175AC	DRT 1.0_57023
AP-175DC	DRT 1.0_57023
AP-175P	DRT 1.0_57023
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-204	DRT 1.0_57023
AP-205	DRT 1.0_57023
AP-205H	DRT 1.0_57023

Table 18: *Supported Devices*

Device	Minimum Supported DRT Version
AP-207	DRT 1.0_62783
AP-214	DRT 1.0_57023
AP-215	DRT 1.0_57023
AP-224	DRT 1.0_57023
AP-225	DRT 1.0_57023
AP-228	DRT 1.0_57023
AP-275	DRT 1.0_57023
AP-277	DRT 1.0_57023
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_62783
AP-305	DRT 1.0_62783
AP-314	DRT 1.0_57023
AP-315	DRT 1.0_57023
AP-324	DRT 1.0_57023
AP-325	DRT 1.0_57023
AP-334	DRT 1.0_57023
AP-335	DRT 1.0_57023
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979

Table 18: *Supported Devices*

Device	Minimum Supported DRT Version
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Barbados

The following APs are currently supported in the Barbados regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BB ap-type <ap-type>`

Table 19: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_72500
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-205H	DRT 1.0_57023
AP-207	DRT 1.0_60944
AP-214	DRT 1.0_69377
AP-225	DRT 1.0_48460
AP-274	DRT 1.0_56128
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_69377
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_69377
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842

Table 19: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-374	DRT 1.0_72057
AP-375	DRT 1.0_72057
AP-377	DRT 1.0_72057
AP-387	DRT 1.0_69660
AP-514	DRT 1.0_69377
AP-515	DRT 1.0_69377
AP-534	DRT 1.0_70855
AP-535	DRT 1.0_70855
AP-555	DRT 1.0_70537

Belarus

The following APs are currently supported in the Belarus regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BY ap-type <ap-type>`

Table 20: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_59015
AP-103H	DRT 1.0_59015
AP-104	DRT 1.0_59015
AP-105	DRT 1.0_59015
AP-114	DRT 1.0_59015
AP-115	DRT 1.0_59015
AP-120	DRT 1.0_59015
AP-121	DRT 1.0_59015
AP-124	DRT 1.0_59015
AP-125	DRT 1.0_59015
AP-134	DRT 1.0_59015
AP-135	DRT 1.0_59015
AP-175AC	DRT 1.0_59015
AP-175DC	DRT 1.0_59015
AP-175P	DRT 1.0_59015
AP-203H	DRT 1.0_60944
AP-203R	DRT 1.0_57223
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_59015

Table 20: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_59015
AP-207	DRT 1.0_59241
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_59015
AP-225	DRT 1.0_59015
AP-228	DRT 1.0_59015
AP-274	DRT 1.0_57223
AP-275	DRT 1.0_57223
AP-277	DRT 1.0_59015
AP-303	DRT 1.0_65328
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_69166
AP-304	DRT 1.0_59015
AP-305	DRT 1.0_59015
AP-314	DRT 1.0_59015
AP-315	DRT 1.0_59015
AP-318	DRT 1.0_65937
AP-324	DRT 1.0_59015
AP-325	DRT 1.0_59015
AP-334	DRT 1.0_59015
AP-335	DRT 1.0_59015
AP-374	DRT 1.0_65473

Table 20: *Supported Devices*

Device	Minimum Supported DRT Version
AP-375	DRT 1.0_65473
AP-377	DRT 1.0_65473
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_70076
AP-515	DRT 1.0_70076
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_59015
AP-93	DRT 1.0_59015
AP-93H	DRT 1.0_59015
RAP-108	DRT 1.0_59015
RAP-109	DRT 1.0_59015
RAP-5WN	DRT 1.0_59015
RAP-3WN	DRT 1.0_59015

Belgium

The following APs are currently supported in the Belgium regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BE ap-type <ap-type>`

Table 21: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 21: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_54672
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303H	DRT 1.0_57776
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 21: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Bermuda

The following APs are currently supported in the Bermuda regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BM ap-type <ap-type>`

Table 22: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_57440
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-205	DRT 1.0_57440
AP-205H	DRT 1.0_57440
AP-207	DRT 1.0_57440
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_72277
AP-224	DRT 1.0_50379
AP-225	DRT 1.0_50379
AP-303	DRT 1.0_63879

Table 22: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303H	DRT 1.0_60518
AP-303P	DRT 1.0_69166
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_69377
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Bolivia

The following APs are currently supported in the Bolivia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BO ap-type <ap-type>`

Table 23: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-105	DRT 1.0_43859
AP-120	DRT 1.0_49810
AP-121	DRT 1.0_49810
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-135	DRT 1.0_49810
AP-203H	DRT 1.0_67861
AP-203R	DRT 1.0_67861
AP-203RP	DRT 1.0_67861
AP-205	DRT 1.0_57440
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_68720
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_67861
AP-274	DRT 1.0_66781
AP-275	DRT 1.0_53420
AP-277	DRT 1.0_67861
AP-303	DRT 1.0_63879

Table 23: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_69166
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_66781
AP-324	DRT 1.0_67861
AP-325	DRT 1.0_67861
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_67861
AP-367	DRT 1.0_67861
AP-374	DRT 1.0_66781
AP-375	DRT 1.0_66781
AP-377	DRT 1.0_66781
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_70076

Table 23: *Supported Devices*

Device	Minimum Supported DRT Version
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
RAP-155	DRT 1.0_54079
RAP-155P	DRT 1.0_54079
RAP-3WNP	DRT 1.0_52699

Bonaire Saint Eustatius and Saba

The following APs are currently supported in the Bonaire Sint Eustatius and Saba regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BQ ap-type <ap-type>`

Table 24: *Supported Devices*

Device	Minimum Supported DRT Version
AP-225	DRT 1.0_49596

Bosnia and Herzegovina

The following APs are currently supported in the Bosnia and Herzegovina regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BA ap-type <ap-type>`

Table 25: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_45134
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_64450
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-204	DRT 1.0_60362

Table 25: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_56912
AP-325	DRT 1.0_56912
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647

Table 25: *Supported Devices*

Device	Minimum Supported DRT Version
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Botswana

The following APs are currently supported in the Botswana regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BW ap-type <ap-type>`

Table 26: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-135	DRT 1.0_47469
AP-203H	DRT 1.0_67861
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-207	DRT 1.0_66152
AP-214	DRT 1.0_68474
AP-215	DRT 1.0_68474
AP-225	DRT 1.0_43859
AP-303	DRT 1.0_69166
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_71072
AP-305	DRT 1.0_71072
AP-314	DRT 1.0_70855
AP-315	DRT 1.0_68143
AP-334	DRT 1.0_70855
AP-335	DRT 1.0_70855
AP-344	DRT 1.0_67494
AP-345	DRT 1.0_67494

Table 26: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_68474
AP-375	DRT 1.0_68474
AP-377	DRT 1.0_68474
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-108	DRT 1.0_66152
RAP-109	DRT 1.0_66152

Brazil

The following APs are currently supported in the Brazil regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BR ap-type <ap-type>v`

Table 27: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_48019
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175	DRT 1.0_47726
AP-175P	DRT 1.0_47726
AP-203H	DRT 1.0_62141
AP-203R	DRT 1.0_63102
AP-203RP	DRT 1.0_63102
AP-204	DRT 1.0_46245
AP-205	DRT 1.0_46245
AP-205H	DRT 1.0_52480

Table 27: *Supported Devices*

Device	Minimum Supported DRT Version
OC-20	DRT 1.0_59989
AP-207	DRT 1.0_61527
AP-214	DRT 1.0_48460
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_52480
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_51362
AP-303	DRT 1.0_66351
AP-303H	DRT 1.0_61955
AP-303P	DRT 1.0_69166
AP-304	DRT 1.0_61527
AP-305	DRT 1.0_61527
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_66152
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-334	DRT 1.0_58226
AP-335	DRT 1.0_58226
AP-344	DRT 1.0_63516
AP-345	DRT 1.0_63516

Table 27: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_61527
AP-367	DRT 1.0_61527
AP-374	DRT 1.0_65685
AP-375	DRT 1.0_65685
AP-377	DRT 1.0_65685
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_71451
AP-535	DRT 1.0_71451
AP-555	DRT 1.0_71451
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_47726
AP-93	DRT 1.0_47726
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_57776
RAP-155P	DRT 1.0_57776
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Brunei Darussalam

The following APs are currently supported in Brunei Darussalam regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:

```
show ap allowed-channels country-code BN ap-type <ap-type>
```

Bulgaria

The following APs are currently supported in the Bulgaria regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BG ap-type <ap-type>`

Table 28: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_54672
AP-125	DRT 1.0_54672
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_57815
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 28: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 28: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Burkina Faso

The following APs are currently supported in the Burkina Faso regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BF ap-type <ap-type>`

Table 29: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-215	DRT 1.0_72670

Cambodia

The following APs are currently supported in the Cambodia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code KH ap-type <ap-type>`

Table 30: *Supported Devices*

Device	Channels
AP-203H	DRT 1.0_68979
AP-214	DRT 1.0_69377
AP-303	DRT 1.0_69166
AP-303P	DRT 1.0_68979
RAP-109	DRT 1.0_57776

Cameroon

The following APs are currently supported in the Cameroon regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CM ap-type <ap-type>`

Table 31: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-203H	DRT 1.0_64450
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-207	DRT 1.0_62783
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_68720
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62783
AP-305	DRT 1.0_62783
AP-314	DRT 1.0_59591
AP-318	DRT 1.0_64134
AP-334	DRT 1.0_59591
AP-335	DRT 1.0_59591
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044

Table 31: *Supported Devices*

Device	Minimum Supported DRT Version
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-3WN	DRT 1.0_64825
RAP-3WNP	DRT 1.0_64825

Canada

The following APs are currently supported in the Canada regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CA ap-type <ap-type>`

Table 32: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_55859
AP-103H	DRT 1.0_45134
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_59015

Table 32: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_55384
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_55859
AP-225	DRT 1.0_55859
AP-228	DRT 1.0_55859
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_54219
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_56912
AP-305	DRT 1.0_56912
AP-314	DRT 1.0_56128
AP-315	DRT 1.0_56128
AP-318	DRT 1.0_63879
AP-324	DRT 1.0_55859
AP-325	DRT 1.0_55859
AP-334	DRT 1.0_55859
AP-335	DRT 1.0_55859
AP-365	DRT 1.0_59241

Table 32: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63727
AP-375	DRT 1.0_63727
AP-377	DRT 1.0_63727
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Chad

The following APs are currently supported in the Chad regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code TD ap-type <ap-type>`

Table 33: *Supported Devices*

Device	Regulatory-Cert Version
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859

Cayman Islands

The following APs are currently supported in Cayman Islands regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code KY ap-type <ap-type>`

Table 34: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_54870
AP-103H	DRT 1.0_54870
AP-104	DRT 1.0_54870
AP-105	DRT 1.0_54870
AP-114	DRT 1.0_54870
AP-115	DRT 1.0_54870
AP-120	DRT 1.0_54870
AP-121	DRT 1.0_54870
AP-124	DRT 1.0_54870
AP-125	DRT 1.0_54870
AP-134	DRT 1.0_54870
AP-135	DRT 1.0_54870
AP-175AC	DRT 1.0_54870
AP-175DC	DRT 1.0_54870
AP-175P	DRT 1.0_54870
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-204	DRT 1.0_54870
AP-205	DRT 1.0_54870

Table 34: *Supported Devices*

Device	Minimum Supported DRT Version
AP-207	DRT 1.0_62783
AP-214	DRT 1.0_54870
AP-215	DRT 1.0_54870
AP-224	DRT 1.0_54870
AP-225	DRT 1.0_54870
AP-228	DRT 1.0_54870
AP-274	DRT 1.0_54870
AP-275	DRT 1.0_54870
AP-277	DRT 1.0_54870
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_62783
AP-305	DRT 1.0_62783
AP-314	DRT 1.0_70855
AP-315	DRT 1.0_70855
AP-318	DRT 1.0_69377
AP-324	DRT 1.0_54870
AP-325	DRT 1.0_54870
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-374	DRT 1.0_70076

Table 34: *Supported Devices*

Device	Minimum Supported DRT Version
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_54870
AP-92	DRT 1.0_54870
AP-93	DRT 1.0_54870
AP-93H	DRT 1.0_54870
RAP-108	DRT 1.0_54870
RAP-109	DRT 1.0_54870
RAP-155	DRT 1.0_54870
RAP-155P	DRT 1.0_54870
RAP-3WN	DRT 1.0_54870
RAP-3WNP	DRT 1.0_54870

Chile

The following APs are currently supported in the Chile regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CL ap-type <ap-type>`

Table 35: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72670
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_46245
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-124abg	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-125abg	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_60944
AP-203RP	DRT 1.0_60944
AP-204	DRT 1.0_43859
AP-205	DRT 1.0_43859
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_59591
AP-214	DRT 1.0_46245

Table 35: *Supported Devices*

Device	Minimum Supported DRT Version
AP-215	DRT 1.0_46245
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49596
AP-274	DRT 1.0_44265
AP-275	DRT 1.0_44265
AP-277	DRT 1.0_52480
AP-303	DRT 1.0_66547
AP-303H	DRT 1.0_65103
AP-303P	DRT 1.0_71647
AP-304	DRT 1.0_59591
AP-305	DRT 1.0_59591
AP-314	DRT 1.0_57440
AP-315	DRT 1.0_57440
AP-318	DRT 1.0_66547
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-334	DRT 1.0_57440
AP-335	DRT 1.0_57440
AP-344	DRT 1.0_66547
AP-345	DRT 1.0_66547
AP-365	DRT 1.0_63044
AP-367	DRT 1.0_65103
AP-374	DRT 1.0_66547

Table 35: *Supported Devices*

Device	Minimum Supported DRT Version
AP-375	DRT 1.0_66547
AP-377	DRT 1.0_66547
AP-387	DRT 1.0_72057
AP-514	DRT 1.0_71451
AP-515	DRT 1.0_71451
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

China

The following APs are currently supported in the China regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CN ap-type <ap-type>`

Table 36: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59118
AP-203R	DRT 1.0_62496
AP-203RP	DRT 1.0_62496
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015

Table 36: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57023
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_50288
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_45134
AP-277	DRT 1.0_64825
AP-303	DRT 1.0_63727
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_70671
AP-304	DRT 1.0_57776
AP-305	DRT 1.0_57776
AP-315	DRT 1.0_57023
AP-318	DRT 1.0_63727
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-334	DRT 1.0_57776
AP-335	DRT 1.0_57776
AP-344	DRT 1.0_63727
AP-345	DRT 1.0_63727
AP-365	DRT 1.0_59241

Table 36: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63727
AP-375	DRT 1.0_63727
AP-377	DRT 1.0_63727
AP-514	DRT 1.0_70267
AP-515	DRT 1.0_70267
AP-68	DRT 1.0_43859
AP-68P	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-3WN	DRT 1.0_48460
RAP-3WNP	DRT 1.0_43859

Colombia

The following APs are currently supported in the Colombia regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CO ap-type <ap-type>`

Table 37: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_45134
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_67861
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-204	DRT 1.0_43859

Table 37: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_43859
AP-205H	DRT 1.0_52042
AP-214	DRT 1.0_48188
AP-215	DRT 1.0_48188
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_52480
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_51997
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_59015
AP-305	DRT 1.0_59015
AP-315	DRT 1.0_68143
AP-318	DRT 1.0_66152
AP-324	DRT 1.0_52480
AP-325	DRT 1.0_52480
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_67494
AP-345	DRT 1.0_67494
AP-365	DRT 1.0_59015

Table 37: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_59015
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Costa Rica

The following APs are currently supported in the Costa Rica regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CR ap-type <ap-type>`

Table 38: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_60362
AP-103H	DRT 1.0_48188
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_47156
AP-115	DRT 1.0_47156
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-203H	DRT 1.0_63044
AP-203R	DRT 1.0_63044
AP-203RP	DRT 1.0_63044
AP-204	DRT 1.0_49142
AP-205	DRT 1.0_49142
AP-205H	DRT 1.0_50970
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_49422
AP-215	DRT 1.0_49422
AP-224	DRT 1.0_49142
AP-225	DRT 1.0_59015
AP-228	DRT 1.0_49810

Table 38: *Supported Devices*

Device	Minimum Supported DRT Version
AP-274	DRT 1.0_49596
AP-275	DRT 1.0_49596
AP-277	DRT 1.0_49142
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_63044
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_59015
AP-305	DRT 1.0_58653
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-318	DRT 1.0_66351
AP-324	DRT 1.0_52238
AP-325	DRT 1.0_52238
AP-334	DRT 1.0_70855
AP-335	DRT 1.0_70855
AP-344	DRT 1.0_63044
AP-345	DRT 1.0_63044
AP-365	DRT 1.0_63044
AP-367	DRT 1.0_63044
AP-374	DRT 1.0_66351
AP-375	DRT 1.0_66351
AP-377	DRT 1.0_66351
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647

Table 38: *Supported Devices*

Device	Minimum Supported DRT Version
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
RAP-108	DRT 1.0_47156
RAP-109	DRT 1.0_47156
RAP-155	DRT 1.0_51685
RAP-3WN	DRT 1.0_48188
RAP-3WNP	DRT 1.0_48188
RAP-155	DRT 1.0_51997

Côtes d'Ivorie

The following APs are currently supported in the Côtes d'Ivorie regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CI ap-type <ap-type>`

Table 39: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-135	DRT 1.0_47469
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-207	DRT 1.0_70855
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_68474
AP-225	DRT 1.0_47469
AP-303	DRT 1.0_69166
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_71072
AP-305	DRT 1.0_71072
AP-315	DRT 1.0_70855
AP-325	DRT 1.0_60362
AP-334	DRT 1.0_70855
AP-335	DRT 1.0_70855
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-374	DRT 1.0_68474

Table 39: *Supported Devices*

Device	Minimum Supported DRT Version
AP-375	DRT 1.0_68474
AP-377	DRT 1.0_68474
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313
RAP-109	DRT 1.0_60362

Croatia

The following APs are currently supported in the Croatia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code HR ap-type <ap-type>`

Table 40: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_54672
AP-103H	DRT 1.0_45134
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_64450
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362
AP-205	DRT 1.0_60362

Table 40: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_54672
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_48019
AP-228	DRT 1.0_49142
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_64331
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_70855
AP-367	DRT 1.0_70855

Table 40: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Curacao

The following APs are currently supported in the Curacao regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CW ap-type <ap-type>`

Table 41: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_57440
AP-205	DRT 1.0_57440
AP-205H	DRT 1.0_57440
AP-207	DRT 1.0_57440
AP-225	DRT 1.0_49596
AP-303	DRT 1.0_63879
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-325	DRT 1.0_55384
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647

Table 41: *Supported Devices*

Device	Minimum Supported DRT Version
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Cyprus

The following APs are currently supported in the Cyprus regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CY ap-type <ap-type>`

Table 42: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_54672
AP-125	DRT 1.0_54672
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 42: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_56308
AP-335	DRT 1.0_56308
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241

Table 42: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Czech Republic

The following APs are currently supported in the Czech Republic regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CZ ap-type <ap-type>`

Table 43: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_45134
AP-125	DRT 1.0_45134
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 43: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_56308
AP-335	DRT 1.0_56308
AP-344	DRT 1.0_62311

Table 43: *Supported Devices*

Device	Minimum Supported DRT Version
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Democratic Republic of the Congo

The following APs are currently supported in the Democratic Republic of the Congo regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CD ap-type <ap-type>`

Table 44: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-215	DRT 1.0_72905

Denmark

The following APs are currently supported in the Denmark regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code DK ap-type <ap-type>`

Table 45: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 45: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311

Table 45: *Supported Devices*

Device	Minimum Supported DRT Version
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Dominican Republic

The following APs are currently supported in the Dominican Republic regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code DO ap-type <ap-type>`

Table 46: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_48902
AP-103H	DRT 1.0_48902
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-205	DRT 1.0_48902

Table 46: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205H	DRT 1.0_50970
AP-207	DRT 1.0_57440
AP-207	DRT 1.0_56912
AP-214	DRT 1.0_48902
AP-215	DRT 1.0_48902
AP-224	• Non-DFS: DRT 1.0_43859 • DFS: DRT 1.0_45134
AP-225	DRT 1.0_49596
AP-228	DRT 1.0_55859
AP-274	DRT 1.0_51155
AP-275	DRT 1.0_51155
AP-277	DRT 1.0_54079
AP-303	DRT 1.0_63879
AP-303P	DRT 1.0_68474
AP-305	DRT 1.0_63392
AP-318	DRT 1.0_69377
AP-324	DRT 1.0_52238
AP-325	DRT 1.0_52238
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979

Table 46: *Supported Devices*

Device	Minimum Supported DRT Version
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_48902
AP-93H	DRT 1.0_43859
OC-30	DRT 1.0_63392
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Ecuador

The following APs are currently supported in the Ecuador regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code EC ap-type <ap-type>`

Table 47: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_48902
AP-103H	DRT 1.0_60944
AP-105	DRT 1.0_43859
AP-135	DRT 1.0_48713
AP-203H	DRT 1.0_61313
AP-203R	DRT 1.0_61313
AP-203RP	DRT 1.0_61313
AP-204	DRT 1.0_49142
AP-205	DRT 1.0_49142
AP-205H	DRT 1.0_53420
AP-207	DRT 1.0_59241
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_49422
AP-224	DRT 1.0_58226
AP-225	DRT 1.0_49422
AP-228	DRT 1.0_66547
AP-275	DRT 1.0_49422
AP-277	DRT 1.0_58226
AP-303	DRT 1.0_66152

Table 47: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303H	DRT 1.0_62783
AP-303P	DRT 1.0_68979
AP-314	DRT 1.0_57776
AP-315	DRT 1.0_57776
AP-318	DRT 1.0_69377
AP-324	DRT 1.0_58653
AP-325	DRT 1.0_58653
AP-334	DRT 1.0_70855
AP-335	DRT 1.0_70855
AP-344	DRT 1.0_63727
AP-345	DRT 1.0_63727
AP-365	DRT 1.0_65685
AP-367	DRT 1.0_65685
AP-374	DRT 1.0_66152
AP-375	DRT 1.0_66152
AP-377	DRT 1.0_66152
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_69377
AP-515	DRT 1.0_69377
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 47: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-155	DRT 1.0_51685
RAP-155P	DRT 1.0_52480
RAP-3WN	DRT 1.0_51685
RAP-3WNP	DRT 1.0_51685

Egypt

The following APs are currently supported in the Egypt regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code EG ap-type <ap-type>`

Table 48: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_48019
AP-103H	DRT 1.0_48019
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_48019
AP-114	DRT 1.0_48188
AP-115	DRT 1.0_48188
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_48188
AP-125	DRT 1.0_48188
AP-134	DRT 1.0_48188
AP-135	DRT 1.0_48188
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_48188
AP-203H	DRT 1.0_63102
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-204	DRT 1.0_60362
AP-205	DRT 1.0_60362

Table 48: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205H	DRT 1.0_49986
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_56308
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_48188
AP-225	DRT 1.0_48188
AP-228	DRT 1.0_49810
AP-274	DRT 1.0_49810
AP-275	DRT 1.0_49142
AP-277	DRT 1.0_49142
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_63044
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_58226
AP-314	DRT 1.0_56452
AP-315	DRT 1.0_56452
AP-318	DRT 1.0_64450
AP-324	DRT 1.0_51685
AP-325	DRT 1.0_51685
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59783
AP-367	DRT 1.0_63102

Table 48: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_63102
AP-375	DRT 1.0_63102
AP-377	DRT 1.0_63102
AP-387	DRT 1.0_72670
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_71647
AP-535	DRT 1.0_71647
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_48188
AP-93	DRT 1.0_48188
AP-93H	DRT 1.0_48188
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

El Salvador

The following APs are currently supported in the El Salvador regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code SV ap-type <ap-type>`

Table 49: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_48902
AP-103H	DRT 1.0_48902
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_48713
AP-115	DRT 1.0_48713
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_68979
AP-205	DRT 1.0_48902
AP-205H	DRT 1.0_50970
AP-207	DRT 1.0_56912
AP-214	DRT 1.0_48902
AP-215	DRT 1.0_48902
AP-224	DRT 1.0_48019
AP-225	DRT 1.0_48019
AP-228	DRT 1.0_55859

Table 49: *Supported Devices*

Device	Minimum Supported DRT Version
AP-274	DRT 1.0_51155
AP-275	DRT 1.0_51155
AP-277	DRT 1.0_54079
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_60518
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_62783
AP-305	DRT 1.0_62783
AP-318	DRT 1.0_69377
AP-324	DRT 1.0_52238
AP-325	DRT 1.0_52238
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076

Table 49: *Supported Devices*

Device	Minimum Supported DRT Version
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-93	DRT 1.0_48902
RAP-108	DRT 1.0_48902
RAP-109	DRT 1.0_48902
RAP-155	DRT 1.0_54079
RAP-155P	DRT 1.0_52480
RAP-3WNP	DRT 1.0_48902

Estonia

The following APs are currently supported in the Estonia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code EE ap-type <ap-type>`

Table 50: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 50: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 50: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Faroe Islands

The following APs are currently supported in the Faroe Islands regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code FO ap-type <ap-type>`

Table 51: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 51: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 51: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Federated States of Micronesia

The following APs are currently supported in the Federated States of Micronesia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code FM ap-type <ap-type>`

Table 52: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_56050
AP-103H	DRT 1.0_56050
AP-105	DRT 1.0_48902
AP-114	DRT 1.0_48902
AP-115	DRT 1.0_48902
AP-135	DRT 1.0_48902
AP-175P	DRT 1.0_48902
AP-203H	DRT 1.0_67861
AP-204	DRT 1.0_56050
AP-205	DRT 1.0_56912
AP-205H	DRT 1.0_50970
AP-207	DRT 1.0_56912
AP-214	DRT 1.0_56050
AP-215	DRT 1.0_56050
AP-224	DRT 1.0_56050
AP-225	DRT 1.0_56050
AP-228	DRT 1.0_56050
AP-274	DRT 1.0_56050
AP-275	DRT 1.0_56050

Table 52: *Supported Devices*

Device	Minimum Supported DRT Version
AP-277	DRT 1.0_54079
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_60518
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_57223
AP-305	DRT 1.0_57223
AP-314	DRT 1.0_56128
AP-315	DRT 1.0_56128
AP-318	DRT 1.0_68720
AP-324	DRT 1.0_52238
AP-325	DRT 1.0_52238
AP-334	DRT 1.0_56128
AP-335	DRT 1.0_56128
AP-344	DRT 1.0_63044
AP-345	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-93	DRT 1.0_48902

Table 52: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-108	DRT 1.0_56050
RAP-109	DRT 1.0_56050
RAP-155	DRT 1.0_56050
RAP-155P	DRT 1.0_56050
RAP-3WNP	DRT 1.0_48902

Finland

The following APs are currently supported in the Finland regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code FI ap-type <ap-type>`

Table 53: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_57815
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 53: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 53: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

France

The following APs are currently supported in the France regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code FR ap-type <ap-type>`

Table 54: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 54: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_58226
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 54: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

French Guiana

The following APs are currently supported in the French Guiana regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GF ap-type <ap-type>`

Table 55: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 55: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 55: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

French Polynesia

The following APs are currently supported in the French Polynesia regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code PF ap-type <ap-type>`

Table 56: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_49596
AP-103H	DRT 1.0_49596
AP-105	DRT 1.0_49596
AP-114	DRT 1.0_49596
AP-115	DRT 1.0_49596
AP-135	DRT 1.0_49596
AP-175P	DRT 1.0_49596
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_49596
AP-205	DRT 1.0_49596
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_49596
AP-215	DRT 1.0_49596
AP-224	DRT 1.0_49596
AP-225	DRT 1.0_49810
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_49596
AP-275	DRT 1.0_49596

Table 56: *Supported Devices*

Device	Minimum Supported DRT Version
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-93	DRT 1.0_49596
RAP-108	DRT 1.0_49596

Table 56: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-109	DRT 1.0_49596
RAP-3WN	DRT 1.0_49596
RAP-3WNP	DRT 1.0_49596

French Southern Territories

The following APs are currently supported in the French Southern Territories regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code TF ap-type <ap-type>`

Table 57: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48448
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48448
AP-114	DRT 1.0_48448
AP-115	DRT 1.0_48448
AP-135	DRT 1.0_48448
AP-175P	DRT 1.0_48448
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713
AP-275	DRT 1.0_48713

Table 57: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Georgia

The following APs are currently supported in the Georgia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GE ap-type <ap-type>`

Table 58: *Supported Devices*

Device	Regulatory-Cert Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_51997
AP-103H	DRT 1.0_51997
AP-104	DRT 1.0_51997
AP-105	DRT 1.0_51997
AP-114	DRT 1.0_51997
AP-115	DRT 1.0_51997
AP-120	DRT 1.0_51997
AP-121	DRT 1.0_51997
AP-124	DRT 1.0_51997
AP-125	DRT 1.0_51997
AP-134	DRT 1.0_51997
AP-135	DRT 1.0_51997
AP-175DC	DRT 1.0_51997
AP-175AC	DRT 1.0_51997
AP-175P	DRT 1.0_51997
AP-203H	DRT 1.0_64450
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 58: *Supported Devices*

Device	Regulatory-Cert Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_51997
AP-207	DRT 1.0_62783
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_51997
AP-225	DRT 1.0_51997
AP-228	DRT 1.0_51997
AP-274	DRT 1.0_51997
AP-275	DRT 1.0_51997
AP-277	DRT 1.0_51997
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311

Table 58: *Supported Devices*

Device	Regulatory-Cert Version
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_51997
AP-92	DRT 1.0_51997
AP-93	DRT 1.0_51997
AP-93H	DRT 1.0_51997
RAP-108	DRT 1.0_51997
RAP-109	DRT 1.0_51997
RAP-155	DRT 1.0_51997
RAP-155P	DRT 1.0_51997
RAP-3WN	DRT 1.0_51997
RAP-3WNP	DRT 1.0_51997

Germany

The following APs are currently supported in the Germany regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code DE ap-type <ap-type>`

Table 59: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 59: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 59: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Ghana

The following APs are currently supported in the Ghana regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GH ap-type <ap-type>`

Table 60: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-125	DRT 1.0_43859
AP-203H	DRT 1.0_66351
AP-203R	DRT 1.0_66351
AP-204	DRT 1.0_66351
AP-205	DRT 1.0_66351
AP-205H	DRT 1.0_66351
AP-207	DRT 1.0_66351
AP-214	DRT 1.0_66351
AP-215	DRT 1.0_66351
AP-224	DRT 1.0_66351
AP-225	DRT 1.0_51155
AP-228	DRT 1.0_66351
AP-274	DRT 1.0_66351
AP-275	DRT 1.0_66351
AP-277	DRT 1.0_66351
AP-303	DRT 1.0_66351
AP-303H	DRT 1.0_66351
AP-303P	DRT 1.0_69166
AP-304	DRT 1.0_66351

Table 60: *Supported Devices*

Device	Minimum Supported DRT Version
AP-305	DRT 1.0_66351
AP-314	DRT 1.0_66351
AP-315	DRT 1.0_66351
AP-318	DRT 1.0_66351
AP-324	DRT 1.0_66152
AP-325	DRT 1.0_66152
AP-334	DRT 1.0_66351
AP-335	DRT 1.0_66351
AP-344	DRT 1.0_66351
AP-345	DRT 1.0_66351
AP-365	DRT 1.0_66351
AP-367	DRT 1.0_66351
AP-374	DRT 1.0_66351
AP-375	DRT 1.0_66351
AP-377	DRT 1.0_66351
AP-387	DRT 1.0_70671
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313

Table 60: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-108	DRT 1.0_66351
RAP-109	DRT 1.0_62141
RAP-155	DRT 1.0_66351

Greece

The following APs are currently supported in the Greece regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GR ap-type <ap-type>`

Table 61: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 61: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_56308
AP-335	DRT 1.0_56308
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 61: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Greenland

The following APs are currently supported in the Greenland regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GL ap-type <ap-type>`

Table 62: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 62: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 62: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Grenada

The following APs are currently supported in the Grenada regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GD ap-type <ap-type>`

Table 63: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_72277
AP-103	DRT 1.0_56643
AP-205	DRT 1.0_56912
AP-207	DRT 1.0_57440
AP-225	DRT 1.0_48460
AP-303	DRT 1.0_63879
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979

Table 63: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Guadeloupe

The following APs are currently supported in the Guadeloupe regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GP ap-type <ap-type>`

Table 64: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_56050
AP-203H	DRT 1.0_64450
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_50970
AP-207	DRT 1.0_57440
AP-275	DRT 1.0_56050
AP-277	DRT 1.0_54079
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62783
AP-305	DRT 1.0_62783
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_64134
AP-334	DRT 1.0_58653

Table 64: *Supported Devices*

Device	Minimum Supported DRT Version
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Guam

The following APs are currently supported in the Guam regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GU ap-type <ap-type>`

Table 65: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_56050
AP-103H	DRT 1.0_56050
AP-105	DRT 1.0_48902
AP-114	DRT 1.0_48902
AP-115	DRT 1.0_48902
AP-135	DRT 1.0_48902
AP-175P	DRT 1.0_48902
AP-203H	DRT 1.0_59591
AP-204	DRT 1.0_56050
AP-205	DRT 1.0_56050
AP-205H	DRT 1.0_50970
AP-207	DRT 1.0_56912
AP-214	DRT 1.0_56050
AP-215	DRT 1.0_56050
AP-224	DRT 1.0_56050
AP-225	DRT 1.0_56050
AP-228	DRT 1.0_56050
AP-274	DRT 1.0_56050
AP-275	DRT 1.0_56050

Table 65: *Supported Devices*

Device	Minimum Supported DRT Version
AP-277	DRT 1.0_54079
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_60518
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_57223
AP-305	DRT 1.0_57223
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-318	DRT 1.0_68720
AP-324	DRT 1.0_52238
AP-325	DRT 1.0_52238
AP-334	DRT 1.0_56128
AP-335	DRT 1.0_56128
AP-344	DRT 1.0_63044
AP-345	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-93	DRT 1.0_48902

Table 65: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-108	DRT 1.0_56050
RAP-109	DRT 1.0_56050
RAP-155	DRT 1.0_56050
RAP-155P	DRT 1.0_56050
RAP-3WNP	DRT 1.0_48902

Guatemala

The following APs are currently supported in the Guatemala regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GT ap-type <ap-type>`

Table 66: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_48902
AP-103H	DRT 1.0_48902
AP-115	DRT 1.0_48902
AP-135	DRT 1.0_48902
AP-175P	DRT 1.0_48902
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-204	DRT 1.0_48902
AP-205	DRT 1.0_48902
AP-205H	DRT 1.0_50970
AP-207	DRT 1.0_56912
AP-214	DRT 1.0_48902
AP-215	DRT 1.0_48902
AP-224	DRT 1.0_48902
AP-225	DRT 1.0_48902
AP-228	DRT 1.0_55859
AP-275	DRT 1.0_51155
AP-303	DRT 1.0_63879

Table 66: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303H	DRT 1.0_60518
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_58226
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_69377
AP-324	DRT 1.0_52238
AP-325	DRT 1.0_52238
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-93	DRT 1.0_48902
RAP-108	DRT 1.0_48902
RAP-109	DRT 1.0_48902

Table 66: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-155	DRT 1.0_54079
RAP-155P	DRT 1.0_54079
RAP-3WNP	DRT 1.0_48902

Guernsey

The following APs are currently supported in the Guernsey regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GG ap-type <ap-type>`

Table 67: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48448
AP-114	DRT 1.0_48448
AP-115	DRT 1.0_48448
AP-135	DRT 1.0_48448
AP-175P	DRT 1.0_48448
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 67: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 67: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Guyana

The following APs are currently supported in the Guyana regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GY ap-type <ap-type>`

Table 68: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_72277
AP-103	DRT 1.0_57023
AP-205H	DRT 1.0_57023
AP-207	DRT 1.0_57440
AP-275	DRT 1.0_57023
AP-277	DRT 1.0_57023
AP-303	DRT 1.0_63879
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979

Table 68: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Haiti

The following APs are currently supported in the Hati regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code HT ap-type <ap-type>`

Table 69: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_57440
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-205	DRT 1.0_57776
AP-205H	DRT 1.0_57440
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_69377
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_68979
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_69377
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 69: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Vatican City

The following APs are currently supported in Vatican City regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code VA ap-type <ap-type>`

Table 70: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 70: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 70: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Honduras

The following APs are currently supported in the Honduras regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code HN ap-type <ap-type>`

Table 71: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_57223
AP-205H	DRT 1.0_57223
AP-207	DRT 1.0_57440
AP-225	DRT 1.0_51685
AP-303	DRT 1.0_63879
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-324	DRT 1.0_72670
AP-325	DRT 1.0_72670
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647

Table 71: *Supported Devices*

Device	Minimum Supported DRT Version
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-155	DRT 1.0_54079
RAP-155P	DRT 1.0_54079
RAP-3WN	DRT 1.0_51685

Hong Kong

The following APs are currently supported in the Hong Kong regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code HK ap-type <ap-type>`

Table 72: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72670
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_46245
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_60518
AP-203RP	DRT 1.0_60518
AP-204	DRT 1.0_60744
AP-205	DRT 1.0_60744
AP-205H	DRT 1.0_60744

Table 72: *Supported Devices*

Device	Minimum Supported DRT Version
AP-207	DRT 1.0_60744
AP-214	DRT 1.0_60744
AP-215	DRT 1.0_60744
AP-224	DRT 1.0_44265
AP-225	DRT 1.0_44265
AP-228	DRT 1.0_60744
AP-274	DRT 1.0_60744
AP-275	DRT 1.0_60744
AP-277	DRT 1.0_60744
AP-303	DRT 1.0_66152
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_60744
AP-305	DRT 1.0_60744
AP-314	DRT 1.0_60744
AP-315	DRT 1.0_60744
AP-318	DRT 1.0_66152
AP-324	DRT 1.0_60744
AP-325	DRT 1.0_60744
AP-334	DRT 1.0_60744
AP-335	DRT 1.0_60744
AP-344	DRT 1.0_66152
AP-345	DRT 1.0_66152
AP-365	DRT 1.0_60744

Table 72: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_60744
AP-374	DRT 1.0_66152
AP-375	DRT 1.0_66152
AP-377	DRT 1.0_66152
AP-387	DRT 1.0_70076
AP-504	DRT 1.0_72670
AP-505	DRT 1.0_72670
AP-514	DRT 1.0_68474
AP-515	DRT 1.0_68474
AP-534	DRT 1.0_71313
AP-535	DRT 1.0_71313
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Hungary

The following APs are currently supported in the Hungary regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code HU ap-type <ap-type>`

Table 73: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 73: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 73: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Iceland

The following APs are currently supported in the Iceland regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code IS ap-type <ap-type>`

Table 74: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-204	DRT 1.0_43859
AP-205	DRT 1.0_43859
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_54672

Table 74: *Supported Devices*

Device	Minimum Supported DRT Version
AP-215	DRT 1.0_54672
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303P	DRT 1.0_67861
AP-318	DRT 1.0_64134
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859

Table 74: *Supported Devices*

Device	Minimum Supported DRT Version
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

India

The following APs are currently supported in the India regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code IN ap-type <ap-type>`

Table 75: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_54219
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59783
AP-203R	DRT 1.0_64134
AP-203RP	DRT 1.0_64134
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_49596

Table 75: *Supported Devices*

Device	Minimum Supported DRT Version
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49810
AP-274	DRT 1.0_45134
AP-275	DRT 1.0_45134
AP-277	DRT 1.0_48902
AP-303	DRT 1.0_64331
AP-303H	DRT 1.0_59591
AP-303P	DRT 1.0_68720
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_58226
AP-314	DRT 1.0_57023
AP-315	DRT 1.0_57023
AP-318	DRT 1.0_64657
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-334	DRT 1.0_57023
AP-335	DRT 1.0_57023
AP-344	DRT 1.0_63879
AP-345	DRT 1.0_63879
AP-365	DRT 1.0_59591

Table 75: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_59591
AP-374	DRT 1.0_63879
AP-375	DRT 1.0_63879
AP-377	DRT 1.0_63879
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70855
AP-535	DRT 1.0_70855
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Indonesia

The following APs are currently supported in the Indonesia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code ID ap-type <ap-type>`

Table 76: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_46705
AP-104	DRT 1.0_50970
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_50970
AP-115	DRT 1.0_46245
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_50970
AP-175P	DRT 1.0_46245
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_61527
AP-203RP	DRT 1.0_61527
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_54219
AP-207	DRT 1.0_57776
OC-20	DRT 1.0_59989
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859

Table 76: *Supported Devices*

Device	Minimum Supported DRT Version
AP-225	DRT 1.0_46245
AP-228	DRT 1.0_50288
AP-274	DRT 1.0_50970
AP-275	DRT 1.0_50970
AP-277	DRT 1.0_50775
AP-303	DRT 1.0_66152
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_71647
AP-304	DRT 1.0_59015
AP-314	DRT 1.0_58226
AP-315	DRT 1.0_58226
AP-318	DRT 1.0_65685
AP-324	DRT 1.0_53255
AP-325	DRT 1.0_61045
AP-334	DRT 1.0_58226
AP-335	DRT 1.0_58226
AP-344	DRT 1.0_64825
AP-345	DRT 1.0_65685
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_66547
AP-375	DRT 1.0_67041
AP-377	DRT 1.0_67041
AP-387	DRT 1.0_72057

Table 76: *Supported Devices*

Device	Minimum Supported DRT Version
AP-514	DRT 1.0_70537
AP-515	DRT 1.0_70537
AP-535	DRT 1.0_72670
AP-68	DRT 1.0_50970
AP-92	DRT 1.0_50970
AP-93	DRT 1.0_50970
AP-93H	DRT 1.0_50970
RAP-108	DRT 1.0_46245
RAP-109	DRT 1.0_46245
RAP-155	DRT 1.0_46245
RAP-155P	DRT 1.0_46245
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_50970

Iraq

The following APs are currently supported in the Iraq regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code IQ ap-type <ap-type>`

Table 77: *Supported Devices*

Device	Minimum Supported DRT Version
AP-215	DRT 1.0_52858
AP-275	DRT 1.0_52858
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
RAP-3WNP	DRT 1.0_52858

Ireland

The following APs are currently supported in the Ireland regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code IE ap-type <ap-type>`

Table 78: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_57815
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 78: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241

Table 78: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Isle of Man

The following APs are currently supported in the Isle of Man regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code IM ap-type <ap-type>`

Table 79: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 79: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 79: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Israel

The following APs are currently supported in the Israel regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code IL ap-type <ap-type>`

Table 80: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_57223
AP-103H	DRT 1.0_53255
AP-104	DRT 1.0_46245
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_61527
AP-203R	DRT 1.0_61527
AP-203RP	DRT 1.0_61527
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_53255
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015

Table 80: *Supported Devices*

Device	Minimum Supported DRT Version
AP-224	DRT 1.0_57223
AP-225	DRT 1.0_57223
AP-274	DRT 1.0_50288
AP-275	DRT 1.0_50288
AP-277	DRT 1.0_53255
AP-303	DRT 1.0_65103
AP-303H	DRT 1.0_61527
AP-303P	DRT 1.0_69166
AP-304	DRT 1.0_59015
AP-305	DRT 1.0_59015
AP-314	DRT 1.0_59015
AP-315	DRT 1.0_59015
AP-318	DRT 1.0_65937
AP-324	DRT 1.0_59015
AP-325	DRT 1.0_59015
AP-334	DRT 1.0_58226
AP-335	DRT 1.0_58226
AP-344	DRT 1.0_65103
AP-345	DRT 1.0_65103
AP-365	DRT 1.0_61527
AP-367	DRT 1.0_61527
AP-374	DRT 1.0_65937
AP-375	DRT 1.0_65937
AP-377	DRT 1.0_65937

Table 80: *Supported Devices*

Device	Minimum Supported DRT Version
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70671
AP-535	DRT 1.0_70671
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Italy

The following APs are currently supported in the Italy regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code IT ap-type <ap-type>`

Table 81: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 81: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 81: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Jamaica

The following APs are currently supported in the Jamaica regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code JM ap-type <ap-type>`

Table 82: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_56643
AP-203H	DRT 1.0_71451
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-204	DRT 1.0_71451
AP-205	DRT 1.0_58653
AP-207	DRT 1.0_60114
AP-214	DRT 1.0_71451
AP-215	DRT 1.0_71451
AP-224	DRT 1.0_71451
AP-225	DRT 1.0_47726
AP-228	DRT 1.0_71451
AP-274	DRT 1.0_71451
AP-275	DRT 1.0_71451
AP-277	DRT 1.0_71451
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_69166
AP-304	DRT 1.0_58226

Table 82: *Supported Devices*

Device	Minimum Supported DRT Version
AP-305	DRT 1.0_57440
AP-318	DRT 1.0_66547
AP-324	DRT 1.0_71451
AP-325	DRT 1.0_71451
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_71451
AP-367	DRT 1.0_71451
AP-374	DRT 1.0_66547
AP-375	DRT 1.0_66547
AP-377	DRT 1.0_66547
AP-387	DRT 1.0_70671
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313

Japan

The following APs are currently supported in the Japan regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code JP ap-type <ap-type>`

Table 83: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72905
AP-103	DRT 1.0_52238
AP-103H	DRT 1.0_52238
AP-104	DRT 1.0_52238
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_52238
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_52238
AP-121	DRT 1.0_52238
AP-124	DRT 1.0_52238
AP-125	DRT 1.0_52238
AP-134	DRT 1.0_52238
AP-135	DRT 1.0_52238
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_61313
AP-203R	DRT 1.0_61313
AP-203RP	DRT 1.0_61313
AP-204	DRT 1.0_59015

Table 83: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_51685
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_50970
AP-225	DRT 1.0_50970
AP-228	DRT 1.0_56912
AP-274	DRT 1.0_50970
AP-275	DRT 1.0_55489
AP-277	DRT 1.0_50970
AP-303	DRT 1.0_63392
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_58226
AP-314	DRT 1.0_57776
AP-315	DRT 1.0_57776
AP-318	DRT 1.0_63516
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-334	DRT 1.0_60362
AP-335	DRT 1.0_60362
AP-344	DRT 1.0_63516

Table 83: *Supported Devices*

Device	Minimum Supported DRT Version
AP-345	DRT 1.0_63516
AP-365	DRT 1.0_61313
AP-367	DRT 1.0_61313
AP-374	DRT 1.0_63516
AP-375	DRT 1.0_63516
AP-377	DRT 1.0_63516
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_72500
AP-505	DRT 1.0_72500
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70855
AP-535	DRT 1.0_70855
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Jersey

The following APs are currently supported in the Jersey regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code JE ap-type <ap-type>`

Table 84: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 84: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 84: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Jordan

The following APs are currently supported in the Jordan regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code JO ap-type <ap-type>`

Table 85: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_47469
AP-104	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-203H	DRT 1.0_61527
AP-203R	DRT 1.0_60518
AP-203RP	DRT 1.0_60518
AP-205H	DRT 1.0_51477
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_68474
AP-225	DRT 1.0_48713
AP-275	DRT 1.0_59241
AP-277	DRT 1.0_48713
AP-303	DRT 1.0_65473
AP-303H	DRT 1.0_61527
AP-303P	DRT 1.0_69377
AP-314	DRT 1.0_59241

Table 85: *Supported Devices*

Device	Minimum Supported DRT Version
AP-315	DRT 1.0_59241
AP-303H	DRT 1.0_59015
AP-324	DRT 1.0_56912
AP-325	DRT 1.0_56912
AP-334	DRT 1.0_58226
AP-335	DRT 1.0_58226
AP-344	DRT 1.0_63392
AP-345	DRT 1.0_63392
AP-365	DRT 1.0_59591
AP-367	DRT 1.0_59591
AP-374	DRT 1.0_72057
AP-375	DRT 1.0_65473
AP-377	DRT 1.0_72500
AP-514	DRT 1.0_69660
AP-515	DRT 1.0_69660
AP-534	DRT 1.0_70671
AP-535	DRT 1.0_70671
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-109	DRT 1.0_57440
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Kazakhstan

The following APs are currently supported in the Kazakhstan regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code KZ ap-type <ap-type>`

Table 86: *Supported Devices*

Device	Minimum Supported DRT Version
AP-104	DRT 1.0_59591
AP-105	DRT 1.0_59591
AP-120	DRT 1.0_59591
AP-121	DRT 1.0_59591
AP-124	DRT 1.0_59591
AP-125	DRT 1.0_59591
AP-134	DRT 1.0_59591
AP-135	DRT 1.0_59591
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-204	DRT 1.0_59591
AP-205	DRT 1.0_59591
AP-205H	DRT 1.0_59591
AP-207	DRT 1.0_59591
AP-214	DRT 1.0_59591
AP-215	DRT 1.0_59591
AP-225	DRT 1.0_52480
AP-228	DRT 1.0_59591
AP-277	DRT 1.0_59591

Table 86: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303	DRT 1.0_65328
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_69166
AP-304	DRT 1.0_59591
AP-305	DRT 1.0_59591
AP-314	DRT 1.0_59591
AP-315	DRT 1.0_59591
AP-318	DRT 1.0_65937
AP-324	DRT 1.0_56912
AP-325	DRT 1.0_59591
AP-334	DRT 1.0_59591
AP-335	DRT 1.0_59591
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-374	DRT 1.0_65473
AP-375	DRT 1.0_65473
AP-377	DRT 1.0_65473
AP-387	DRT 1.0_72670
AP-514	DRT 1.0_70076
AP-515	DRT 1.0_70076
AP-534	DRT 1.0_71647
AP-535	DRT 1.0_71647
AP-555	DRT 1.0_71647
RAP-108	DRT 1.0_47469

Table 86: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-109	DRT 1.0_47469
RAP-155	DRT 1.0_47469
RAP-155P	DRT 1.0_47469

Kenya

The following APs are currently supported in the Kenya regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code KE ap-type <ap-type>`

Table 87: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_48460
AP-115	DRT 1.0_47469
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_63392
AP-135	DRT 1.0_63392
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-205	DRT 1.0_47469
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_47469
AP-225	DRT 1.0_47469
AP-275	DRT 1.0_47469
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_68979
AP-304	DRT 1.0_59015
AP-314	DRT 1.0_59015

Table 87: *Supported Devices*

Device	Minimum Supported DRT Version
AP-315	DRT 1.0_59015
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-365	DRT 1.0_59015
AP-367	DRT 1.0_59015
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_71451
AP-535	DRT 1.0_71451
AP-555	DRT 1.0_71313
RAP-108	DRT 1.0_56912
RAP-109	DRT 1.0_56912
RAP-155P	DRT 1.0_54079
RAP-3WN	DRT 1.0_52699

Kosovo

The following APs are currently supported in the Jamaica regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code XK ap-type <ap-type>`

Table 88: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-203H	DRT 1.0_64450
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-207	DRT 1.0_62783
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-318	DRT 1.0_64134
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647

Table 88: *Supported Devices*

Device	Minimum Supported DRT Version
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Kuwait

The following APs are currently supported in the Kuwait regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code KW ap-type <ap-type>`

Table 89: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_48460
AP-103H	DRT 1.0_48460
AP-105	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-115	DRT 1.0_51155
AP-203H	DRT 1.0_59783
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-205	DRT 1.0_51155
AP-205H	DRT 1.0_50552
AP-207	DRT 1.0_57223
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_48188
AP-225	DRT 1.0_47156
AP-228	DRT 1.0_51685
AP-303	DRT 1.0_63879

Table 89: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_68979
AP-314	DRT 1.0_57223
AP-315	DRT 1.0_57223
AP-318	DRT 1.0_65328
AP-324	DRT 1.0_52238
AP-325	DRT 1.0_52238
AP-334	DRT 1.0_57223
AP-335	DRT 1.0_57223
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-365	DRT 1.0_59241
AP-374	DRT 1.0_64657
AP-375	DRT 1.0_64657
AP-377	DRT 1.0_65937
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_71451
AP-535	DRT 1.0_71451
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859

Table 89: *Supported Devices*

Device	Minimum Supported DRT Version
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
RAP-109	DRT 1.0_48460
RAP-155	DRT 1.0_48460
RAP-3WN	DRT 1.0_63392
RAP-3WNP	DRT 1.0_63392

Laos

The following APs are currently supported in the Laos regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code LA ap-type <ap-type>`

Table 90: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_49596
AP-103H	DRT 1.0_49596
AP-104	DRT 1.0_53420
AP-105	DRT 1.0_53420
AP-114	DRT 1.0_49596
AP-115	DRT 1.0_49596
AP-120	DRT 1.0_53420
AP-121	DRT 1.0_53420
AP-124	DRT 1.0_53420
AP-125	DRT 1.0_53420
AP-134	DRT 1.0_53420
AP-135	DRT 1.0_43859
AP-175AC	DRT 1.0_53420
AP-175DC	DRT 1.0_53420
AP-175P	DRT 1.0_49596
AP-203H	DRT 1.0_68979
AP-204	DRT 1.0_49596
AP-205	DRT 1.0_49596
AP-205H	DRT 1.0_53420

Table 90: *Supported Devices*

Device	Minimum Supported DRT Version
AP-207	DRT 1.0_62783
AP-214	DRT 1.0_49596
AP-215	DRT 1.0_49596
AP-224	DRT 1.0_49596
AP-225	DRT 1.0_49596
AP-274	DRT 1.0_51155
AP-275	DRT 1.0_51155
AP-277	DRT 1.0_54079
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_72277
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_66781
AP-305	DRT 1.0_63392
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-324	DRT 1.0_53420
AP-325	DRT 1.0_53420
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647

Table 90: *Supported Devices*

Device	Minimum Supported DRT Version
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_53420
AP-92	DRT 1.0_53420
AP-93	DRT 1.0_53420
AP-93H	DRT 1.0_53420
OC-30	DRT 1.0_63392
RAP-108	DRT 1.0_49596
RAP-109	DRT 1.0_49596
RAP-155	DRT 1.0_53420
RAP-155P	DRT 1.0_53420
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_53420

Latvia

The following APs are currently supported in the Latvia regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code LV ap-type <ap-type>`

Table 91: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 91: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_58226
AP-325	DRT 1.0_58226
AP-334	DRT 1.0_56308
AP-335	DRT 1.0_56308
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 91: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Lebanon

The following APs are currently supported in the Lebanon regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code LB ap-type <ap-type>`

Table 92: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_58226
AP-103H	DRT 1.0_59241
AP-105	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-205H	DRT 1.0_50288
AP-207	DRT 1.0_58258
AP-215	DRT 1.0_52042
AP-224	DRT 1.0_59591
AP-225	DRT 1.0_47156
AP-277	DRT 1.0_49986
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258

Table 92: *Supported Devices*

Device	Minimum Supported DRT Version
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_59241
AP-315	DRT 1.0_59241
AP-318	DRT 1.0_64134
AP-334	DRT 1.0_59591
AP-335	DRT 1.0_59591
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
RAP-109	DRT 1.0_58653
RAP-155p	DRT 1.0_52480

Libya

The following APs are currently supported in the Libya regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code LY ap-type <ap-type>`

Table 93: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-203H	DRT 1.0_67861
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-207	DRT 1.0_66152
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_68474
AP-303	DRT 1.0_69166
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_66781
AP-305	DRT 1.0_66781
AP-314	DRT 1.0_70855
AP-315	DRT 1.0_68143
AP-334	DRT 1.0_70855
AP-335	DRT 1.0_70855
AP-344	DRT 1.0_67494
AP-345	DRT 1.0_67494
AP-374	DRT 1.0_68474
AP-375	DRT 1.0_68474

Table 93: *Supported Devices*

Device	Minimum Supported DRT Version
AP-377	DRT 1.0_68474
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-535	DRT 1.0_70076
RAP-108	DRT 1.0_66152
RAP-109	DRT 1.0_66152

Liechtenstein

The following APs are currently supported in the Liechtenstein regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code LI ap-type <ap-type>`

Table 94: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 94: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-318	DRT 1.0_64134
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647

Table 94: *Supported Devices*

Device	Minimum Supported DRT Version
AP-505	DRT 1.0_71647
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Lithuania

The following APs are currently supported in the Lithuania regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code LT ap-type <ap-type>`

Table 95: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_45134
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_57815
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362
AP-205	DRT 1.0_60362

Table 95: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241

Table 95: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Luxembourg

The following APs are currently supported in the Luxembourg regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code LU ap-type <ap-type>`

Table 96: *Supported Devices*

Device	Regulatory-Cert Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 96: *Supported Devices*

Device	Regulatory-Cert Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_57776
AP-214	DRT 1.0_54672
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241

Table 96: *Supported Devices*

Device	Regulatory-Cert Version
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Macau

The following APs are currently supported in the Macau regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MO ap-type <ap-type>`

Table 97: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_47469
AP-103H	DRT 1.0_47469
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_56050
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59783
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60744
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_62141

Table 97: *Supported Devices*

Device	Minimum Supported DRT Version
AP-207	DRT 1.0_60744
AP-214	DRT 1.0_60744
AP-215	DRT 1.0_60744
AP-224	DRT 1.0_62141
AP-225	DRT 1.0_56050
AP-228	DRT 1.0_52858
AP-274	DRT 1.0_60744
AP-275	DRT 1.0_60744
AP-277	DRT 1.0_60744
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_69166
AP-304	DRT 1.0_60744
AP-305	DRT 1.0_60744
AP-314	DRT 1.0_60744
AP-315	DRT 1.0_60744
AP-318	DRT 1.0_69377
AP-324	DRT 1.0_60744
AP-325	DRT 1.0_59783
AP-334	DRT 1.0_59783
AP-335	DRT 1.0_56128
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59989

Table 97: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_59989
AP-374	DRT 1.0_72057
AP-375	DRT 1.0_72057
AP-377	DRT 1.0_72057
AP-387	DRT 1.0_70671
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_56050
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Macedonia

The following APs are currently supported in the Macedonia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MK ap-type <ap-type>`

Table 98: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_45134
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_64450
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842

Table 98: *Supported Devices*

Device	Minimum Supported DRT Version
AP-204	DRT 1.0_60362
AP-205	DRT 1.0_60362
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_54672
AP-215	DRT 1.0_68720
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_47077
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-315	DRT 1.0_68143
AP-318	DRT 1.0_64134
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979

Table 98: *Supported Devices*

Device	Minimum Supported DRT Version
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Malawi

The following APs are currently supported in the Malawi regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MW ap-type <ap-type>`

Table 99: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-203H	DRT 1.0_67861
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-207	DRT 1.0_66152
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_68474
AP-303	DRT 1.0_69166
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_71072
AP-305	DRT 1.0_71072
AP-314	DRT 1.0_70855
AP-315	DRT 1.0_68143
AP-334	DRT 1.0_70855
AP-335	DRT 1.0_70855
AP-344	DRT 1.0_67494
AP-345	DRT 1.0_67494
AP-374	DRT 1.0_68474
AP-375	DRT 1.0_68474

Table 99: *Supported Devices*

Device	Minimum Supported DRT Version
AP-377	DRT 1.0_68474
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-108	DRT 1.0_66152
RAP-109	DRT 1.0_66152

Malaysia

The following APs are currently supported in the Malaysia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MY ap-type <ap-type>`

Table 100: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_46705
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_61955
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_61313
AP-203R	DRT 1.0_61313
AP-203RP	DRT 1.0_61313
AP-204	DRT 1.0_46245
AP-205	DRT 1.0_46245
AP-205H	DRT 1.0_51477
AP-207	DRT 1.0_59241

Table 100: *Supported Devices*

Device	Minimum Supported DRT Version
OC-20	DRT 1.0_59989
AP-214	DRT 1.0_59241
AP-215	DRT 1.0_59241
AP-224	DRT 1.0_59241
AP-225	DRT 1.0_59241
AP-228	DRT 1.0_59241
AP-274	DRT 1.0_59241
AP-275	DRT 1.0_59241
AP-277	DRT 1.0_59241
AP-303	DRT 1.0_64450
AP-303H	DRT 1.0_60362
AP-303P	DRT 1.0_68979
AP-304	DRT 1.0_60944
AP-305	DRT 1.0_60944
AP-314	DRT 1.0_58226
AP-315	DRT 1.0_58226
AP-318	DRT 1.0_66152
AP-324	DRT 1.0_52480
AP-325	DRT 1.0_52480
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_63516
AP-345	DRT 1.0_63044
AP-365	DRT 1.0_61045

Table 100: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_59989
AP-374	DRT 1.0_65937
AP-375	DRT 1.0_64331
AP-377	DRT 1.0_64450
AP-387	DRT 1.0_72057
AP-504	DRT 1.0_72905
AP-505	DRT 1.0_72905
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71647
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_53420
RAP-3WNP	DRT 1.0_43859

Maldives

The following APs are currently supported in the Maldives regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MV ap-type <ap-type>`

Table 101: *Supported Devices*

Device	Regulatory-Cert Version
AP17	DRT 1.0_71647
AP-203H	DRT 1.0_72905
AP-203R	DRT 1.0_72905
AP-207	DRT 1.0_70855
AP-228	DRT 1.0_72905
AP-274	DRT 1.0_72905
AP-275	DRT 1.0_72905
AP-277	DRT 1.0_72905
AP-303	DRT 1.0_71892
AP-303H	DRT 1.0_71892
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_66781
AP-305	DRT 1.0_66781
AP-314	DRT 1.0_57440
AP-315	DRT 1.0_57440
AP-318	DRT 1.0_72905
AP-324	DRT 1.0_56912
AP-325	DRT 1.0_56912
AP-334	DRT 1.0_59591
AP-335	DRT 1.0_59591

Table 101: *Supported Devices*

Device	Regulatory-Cert Version
AP-344	DRT 1.0_72905
AP-345	DRT 1.0_72905
AP-365	DRT 1.0_72905
AP-367	DRT 1.0_72905
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Mali

The following APs are currently supported in the Mali regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code ML ap-type <ap-type>`

Table 102: *Supported Devices*

Device	Minimum Supported DRT Version
AP-105	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-215	DRT 1.0_72670
AP-303	DRT 1.0_71451
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859

Malta

The following APs are currently supported in the Malta regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MT ap-type <ap-type>`

Table 103: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 103: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_54672
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241

Table 103: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Maritime Forward Operating Base

The following APs are currently supported in the Maritime Forward Operating Base regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MB ap-type <ap-type>`

Table 104: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72670
AP-103	DRT 1.0_49142
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_49142
AP-115	DRT 1.0_49142
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59015
AP-204	DRT 1.0_43859
AP-205	DRT 1.0_43859
AP-224	DRT 1.0_43859

Table 104: *Supported Devices*

Device	Minimum Supported DRT Version
AP-225	DRT 1.0_43859
AP-303H	DRT 1.0_61045
AP-303P	DRT 1.0_72670
AP-304	DRT 1.0_61045
AP-305	DRT 1.0_61045
AP-314	DRT 1.0_55384
AP-315	DRT 1.0_55384
AP-318	DRT 1.0_72670
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-334	DRT 1.0_61045
AP-335	DRT 1.0_61045
AP-345	DRT 1.0_65473
AP-374	DRT 1.0_61045
AP-375	DRT 1.0_61045
AP-377	DRT 1.0_61045
AP-504	DRT 1.0_72670
AP-505	DRT 1.0_72670
AP-514	DRT 1.0_72670
AP-515	DRT 1.0_72670
AP-534	DRT 1.0_72670
AP-535	DRT 1.0_72670
AP-555	DRT 1.0_72670
AP-68	DRT 1.0_43859

Table 104: *Supported Devices*

Device	Minimum Supported DRT Version
AP-68P	DRT 1.0_49142
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_49142
RAP-109	DRT 1.0_49142
RAP-155	DRT 1.0_49142
RAP-155P	DRT 1.0_49142
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859
AP-345	DRT 1.0_65473
AP-504	DRT 1.0_72670
AP-505	DRT 1.0_72670
AP-514	DRT 1.0_72670
AP-515	DRT 1.0_72670
AP-534	DRT 1.0_72670
AP-535	DRT 1.0_72670
AP-555	DRT 1.0_72670

Maritime Offshore

The following APs are currently supported in the Maritime Offshore regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MI ap-type <ap-type>`

Table 105: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72670
AP-103	DRT 1.0_49142
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_49142
AP-115	DRT 1.0_49142
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59015
AP-204	DRT 1.0_43859
AP-205	DRT 1.0_43859
AP-224	DRT 1.0_43859

Table 105: *Supported Devices*

Device	Minimum Supported DRT Version
AP-225	DRT 1.0_43859
AP-303H	DRT 1.0_61045
AP-303P	DRT 1.0_72670
AP-304	DRT 1.0_59015
AP-305	DRT 1.0_61045
AP-314	DRT 1.0_55384
AP-315	DRT 1.0_55384
AP-318	DRT 1.0_72670
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-334	DRT 1.0_61045
AP-335	DRT 1.0_61045
AP-374	DRT 1.0_61045
AP-375	DRT 1.0_61045
AP-377	DRT 1.0_61045
AP-504	DRT 1.0_72670
AP-505	DRT 1.0_72670
AP-514	DRT 1.0_72670
AP-515	DRT 1.0_72670
AP-534	DRT 1.0_72670
AP-535	DRT 1.0_72670
AP-555	DRT 1.0_72670
AP-68	DRT 1.0_43859
AP-68P	DRT 1.0_49142

Table 105: *Supported Devices*

Device	Minimum Supported DRT Version
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_49142
RAP-109	DRT 1.0_49142
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Marshall Islands

The following APs are currently supported in the Marshall Islands regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MH ap-type <ap-type>`

Table 106: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_56050
AP-103H	DRT 1.0_54870
AP-105	DRT 1.0_48902
AP-114	DRT 1.0_48902
AP-115	DRT 1.0_48902
AP-135	DRT 1.0_48902
AP-175P	DRT 1.0_48902
AP-203H	DRT 1.0_67861
AP-204	DRT 1.0_54870
AP-205	DRT 1.0_54870
AP-205H	DRT 1.0_50970
AP-207	DRT 1.0_56912
AP-214	DRT 1.0_54870
AP-215	DRT 1.0_54870
AP-224	DRT 1.0_54870
AP-225	DRT 1.0_54870
AP-228	DRT 1.0_56050
AP-274	DRT 1.0_54870
AP-275	DRT 1.0_54870

Table 106: *Supported Devices*

Device	Minimum Supported DRT Version
AP-228	DRT 1.0_55859
AP-277	DRT 1.0_54079
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_71892
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_57223
AP-305	DRT 1.0_57223
AP-318	DRT 1.0_68720
AP-324	DRT 1.0_52238
AP-325	DRT 1.0_52238
AP-344	DRT 1.0_63044
AP-345	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-93	DRT 1.0_48902
RAP-108	DRT 1.0_48902
RAP-109	DRT 1.0_48902

Table 106: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-155	DRT 1.0_54870
RAP-155P	DRT 1.0_54870
RAP-3WNP	DRT 1.0_48902

Martinique

The following APs are currently supported in the Martinique regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MQ ap-type <ap-type>`

Table 107: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 107: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 107: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Mauritania

The following APs are currently supported in the Mauritania regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MR ap-type <ap-type>`

Table 108: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_65473
AP-103H	DRT 1.0_65473
AP-104	DRT 1.0_65473
AP-105	DRT 1.0_65473
AP-114	DRT 1.0_65473
AP-115	DRT 1.0_65473
AP-124	DRT 1.0_65473
AP-125	DRT 1.0_65473
AP-134	DRT 1.0_65473
AP-135	DRT 1.0_65473
AP-175DC	DRT 1.0_65473
AP-175AC	DRT 1.0_65473
AP-175P	DRT 1.0_65473
AP-203H	DRT 1.0_65473
AP-203R	DRT 1.0_65473
AP-203RP	DRT 1.0_65473
AP-204	DRT 1.0_65473
AP-205	DRT 1.0_65473
AP-205H	DRT 1.0_65473

Table 108: *Supported Devices*

Device	Minimum Supported DRT Version
AP-214	DRT 1.0_65473
AP-215	DRT 1.0_65473
AP-224	DRT 1.0_65473
AP-225	DRT 1.0_65473
AP-228	DRT 1.0_65473
AP-274	DRT 1.0_65473
AP-275	DRT 1.0_65473
AP-277	DRT 1.0_65473
AP-303	DRT 1.0_65473
AP-303H	DRT 1.0_65473
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_65473
AP-305	DRT 1.0_65473
AP-314	DRT 1.0_65473
AP-315	DRT 1.0_65473
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_65473
AP-325	DRT 1.0_65473
AP-334	DRT 1.0_63727
AP-335	DRT 1.0_63727
AP-344	DRT 1.0_65473
AP-345	DRT 1.0_65473
AP-365	DRT 1.0_65473
AP-367	DRT 1.0_65473

Table 108: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_65473
AP-375	DRT 1.0_65473
AP-377	DRT 1.0_65473
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_65473
AP-93	DRT 1.0_65473
AP-93H	DRT 1.0_65473
RAP-108	DRT 1.0_65473
RAP-109	DRT 1.0_65473
RAP-155	DRT 1.0_65473
RAP-155P	DRT 1.0_65473
RAP-3WN	DRT 1.0_65473
RAP-3WNP	DRT 1.0_65473

Mauritius

The following APs are currently supported in the Mauritius regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MU ap-type <ap-type>`

Table 109: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-135	DRT 1.0_46245
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-207	DRT 1.0_62783
AP-224	DRT 1.0_45134
AP-225	DRT 1.0_45134
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_59015
AP-315	DRT 1.0_68143
AP-318	DRT 1.0_64134
AP-334	DRT 1.0_59591
AP-335	DRT 1.0_59591
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-387	DRT 1.0_68979

Table 109: *Supported Devices*

Device	Minimum Supported DRT Version
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Mayotte

The following APs are currently supported in the Mayotte regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code YT ap-type <ap-type>`

Table 110: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_48902
AP-103H	DRT 1.0_48902
AP-105	DRT 1.0_48902
AP-114	DRT 1.0_48902
AP-115	DRT 1.0_48902
AP-135	DRT 1.0_48902
AP-175P	DRT 1.0_48902
AP-204	DRT 1.0_48902
AP-205	DRT 1.0_48902
AP-214	DRT 1.0_48902
AP-215	DRT 1.0_48902
AP-224	DRT 1.0_48902
AP-225	DRT 1.0_48902
AP-274	DRT 1.0_48902
AP-275	DRT 1.0_48902
AP-303	DRT 1.0_63516
AP-303P	DRT 1.0_67861
AP-314	DRT 1.0_56050
AP-315	DRT 1.0_56050

Table 110: *Supported Devices*

Device	Minimum Supported DRT Version
AP-318	DRT 1.0_64134
AP-334	DRT 1.0_56050
AP-335	DRT 1.0_56050
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-93	DRT 1.0_48902
RAP-108	DRT 1.0_48902
RAP-109	DRT 1.0_48902
RAP-3WNP	DRT 1.0_48902

Mexico

The following APs are currently supported in the Mexico regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MX ap-type <ap-type>`

Table 111: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_47156
AP-103H	DRT 1.0_46413
AP-104	DRT 1.0_48902
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_61690
AP-203R	DRT 1.0_62141
AP-203RP	DRT 1.0_62141
AP-204	DRT 1.0_46245
AP-205	DRT 1.0_46245
AP-205H	DRT 1.0_54367
AP-207	DRT 1.0_59989

Table 111: *Supported Devices*

Device	Minimum Supported DRT Version
OC-20	DRT 1.0_59989
AP-214	DRT 1.0_48188
AP-215	DRT 1.0_46705
AP-224	DRT 1.0_46705
AP-225	DRT 1.0_46705
AP-228	DRT 1.0_51155
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_46245
AP-277	DRT 1.0_51997
AP-303	DRT 1.0_66547
AP-303H	DRT 1.0_61527
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_61527
AP-305	DRT 1.0_59989
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_67041
AP-324	DRT 1.0_53631
AP-325	DRT 1.0_53631
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_64134
AP-345	DRT 1.0_64134
AP-365	DRT 1.0_60518

Table 111: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_60518
AP-374	DRT 1.0_67041
AP-375	DRT 1.0_66781
AP-377	DRT 1.0_66547
AP-387	DRT 1.0_71072
AP-514	DRT 1.0_70267
AP-515	DRT 1.0_70267
AP-534	DRT 1.0_71451
AP-535	DRT 1.0_71451
AP-555	DRT 1.0_72905
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_47469
RAP-155P	DRT 1.0_47469
RAP-3WN	DRT 1.0_61527
RAP-3WNP	DRT 1.0_61527

Moldova

The following APs are currently supported in the Moldova regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MD ap-type <ap-type>`

Table 112: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_61690
AP-103H	DRT 1.0_61690
AP-104	DRT 1.0_61690
AP-105	DRT 1.0_61690
AP-114	DRT 1.0_61690
AP-115	DRT 1.0_61690
AP-120	DRT 1.0_61690
AP-121	DRT 1.0_61690
AP-124	DRT 1.0_61690
AP-125	DRT 1.0_61690
AP-134	DRT 1.0_61690
AP-135	DRT 1.0_61690
AP-175AC	DRT 1.0_61690
AP-175DC	DRT 1.0_61690
AP-175P	DRT 1.0_61690
AP-203H	DRT 1.0_61690
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_59015

Table 112: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_61690
AP-207	DRT 1.0_61690
AP-210 Series	DRT 1.0_61690
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_61690
AP-225	DRT 1.0_61690
AP-228	DRT 1.0_61690
AP-274	DRT 1.0_61690
AP-275	DRT 1.0_61690
AP-277	DRT 1.0_61690
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_61690
AP-305	DRT 1.0_61690
AP-314	DRT 1.0_61690
AP-315	DRT 1.0_61690
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_61690
AP-325	DRT 1.0_61690
AP-334	DRT 1.0_61690
AP-335	DRT 1.0_61690

Table 112: *Supported Devices*

Device	Minimum Supported DRT Version
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_61690
AP-367	DRT 1.0_61690
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_61690
AP-92	DRT 1.0_61690
AP-93	DRT 1.0_61690
AP-93H	DRT 1.0_61690
RAP-108	DRT 1.0_61690
RAP-109	DRT 1.0_61690
RAP-155	DRT 1.0_61690
RAP-155P	DRT 1.0_61690
RAP-3WN	DRT 1.0_61690
RAP-3WNP	DRT 1.0_61690

Monaco

The following APs are currently supported in the Monaco regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MC ap-type <ap-type>`

Table 113: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175	DRT 1.0_48460
AP-203H	DRT 1.0_68979
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 113: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_72277
AP-303P	DRT 1.0_67861
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Monserrat

The following APs are currently supported in Monserrat regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:

```
show ap allowed-channels country-code MS ap-type <ap-type>
```

Montenegro

The following APs are currently supported in the Montenegro regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code ME ap-type <ap-type>`

Table 114: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_45134
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-204	DRT 1.0_60362
AP-205	DRT 1.0_43859
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_54672
AP-215	DRT 1.0_68720

Table 114: *Supported Devices*

Device	Minimum Supported DRT Version
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_57776
AP-315	DRT 1.0_59241
AP-318	DRT 1.0_64134
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076

Table 114: *Supported Devices*

Device	Minimum Supported DRT Version
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859

Morocco

The following APs are currently supported in the Morocco regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MA ap-type <ap-type>`

Table 115: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_48902
AP-105	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-203H	DRT 1.0_64450
AP-205	DRT 1.0_48460
AP-207	DRT 1.0_61955
AP-215	DRT 1.0_48902
AP-225	DRT 1.0_46413
AP-303	DRT 1.0_69166
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_69377
AP-304	DRT 1.0_62783
AP-305	DRT 1.0_62783
AP-314	DRT 1.0_63044
AP-315	DRT 1.0_63044
AP-318	DRT 1.0_64134
AP-325	DRT 1.0_55384
AP-334	DRT 1.0_56912

Table 115: *Supported Devices*

Device	Minimum Supported DRT Version
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59783
AP-367	DRT 1.0_65473
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_69377
AP-515	DRT 1.0_69377
AP-534	DRT 1.0_72057
AP-535	DRT 1.0_72057
AP-555	DRT 1.0_72057
RAP-109	DRT 1.0_57440
RAP-3WN	DRT 1.0_47726
RAP-3WNP	DRT 1.0_47726
RAP-155P	DRT 1.0_51997

Mozambique

The following APs are currently supported in the Mozambique regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MZ ap-type <ap-type>`

Table 116: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_65473
AP-103H	DRT 1.0_65473
AP-104	DRT 1.0_65473
AP-105	DRT 1.0_65473
AP-114	DRT 1.0_65473
AP-115	DRT 1.0_65473
AP-124	DRT 1.0_65473
AP-125	DRT 1.0_65473
AP-134	DRT 1.0_65473
AP-135	DRT 1.0_65473
AP-175DC	DRT 1.0_65473
AP-175AC	DRT 1.0_65473
AP-175P	DRT 1.0_65473
AP-203H	DRT 1.0_65473
AP-203R	DRT 1.0_65473
AP-203RP	DRT 1.0_65473
AP-204	DRT 1.0_65473
AP-205	DRT 1.0_65473
AP-205H	DRT 1.0_65473

Table 116: *Supported Devices*

Device	Minimum Supported DRT Version
AP-214	DRT 1.0_65473
AP-215	DRT 1.0_65473
AP-224	DRT 1.0_65473
AP-225	DRT 1.0_65473
AP-228	DRT 1.0_65473
AP-274	DRT 1.0_65473
AP-275	DRT 1.0_65473
AP-277	DRT 1.0_65473
AP-303	DRT 1.0_65473
AP-303H	DRT 1.0_65473
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_65473
AP-305	DRT 1.0_65473
AP-314	DRT 1.0_65473
AP-315	DRT 1.0_65473
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_65473
AP-325	DRT 1.0_65473
AP-334	DRT 1.0_64134
AP-335	DRT 1.0_64134
AP-344	DRT 1.0_65473
AP-345	DRT 1.0_65473
AP-365	DRT 1.0_65473
AP-367	DRT 1.0_65473

Table 116: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_65473
AP-375	DRT 1.0_65473
AP-377	DRT 1.0_65473
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_65473
AP-93	DRT 1.0_65473
AP-93H	DRT 1.0_65473
RAP-108	DRT 1.0_65473
RAP-109	DRT 1.0_65473
RAP-155	DRT 1.0_65473
RAP-155P	DRT 1.0_65473
RAP-3WN	DRT 1.0_65473
RAP-3WNP	DRT 1.0_65473

Myanmar

The following APs are currently supported in the Myanmar regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MM ap-type <ap-type>`

Table 117: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_55489
AP-103H	DRT 1.0_55489
AP-104	DRT 1.0_55489
AP-105	DRT 1.0_55489
AP-114	DRT 1.0_55489
AP-115	DRT 1.0_55489
AP-120	DRT 1.0_55489
AP-121	DRT 1.0_55489
AP-124	DRT 1.0_55489
AP-125	DRT 1.0_55489
AP-134	DRT 1.0_55489
AP-135	DRT 1.0_55489
AP-175AC	DRT 1.0_55489
AP-175DC	DRT 1.0_55489
AP-175P	DRT 1.0_55489
AP-203H	DRT 1.0_64450
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-204	DRT 1.0_55489

Table 117: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_55489
AP-205H	DRT 1.0_55642
AP-207	DRT 1.0_59241
AP-214	DRT 1.0_55642
AP-215	DRT 1.0_55642
AP-224	DRT 1.0_55489
AP-225	DRT 1.0_55642
AP-228	DRT 1.0_55859
AP-274	DRT 1.0_55859
AP-275	DRT 1.0_55859
AP-277	DRT 1.0_55859
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_59015
AP-314	DRT 1.0_55859
AP-315	DRT 1.0_55859
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_55859
AP-325	DRT 1.0_55859
AP-334	DRT 1.0_55859
AP-335	DRT 1.0_56050
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 117: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-109	DRT 1.0_58226

Namibia

The following APs are currently supported in the Namibia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code NA ap-type <ap-type>`

Table 118: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_65103
AP-103H	DRT 1.0_65103
AP-104	DRT 1.0_65103
AP-114	DRT 1.0_65103
AP-115	DRT 1.0_65103
AP-175DC	DRT 1.0_65103
AP-175AC	DRT 1.0_65103
AP-175P	DRT 1.0_65103
AP-203H	DRT 1.0_65103
AP-203R	DRT 1.0_65103
AP-203RP	DRT 1.0_65103
AP-204	DRT 1.0_65103
AP-205	DRT 1.0_65103
AP-205H	DRT 1.0_65103
AP-207	DRT 1.0_65103
AP-214	DRT 1.0_65103
AP-215	DRT 1.0_65103
AP-224	DRT 1.0_65103
AP-225	DRT 1.0_65103

Table 118: *Supported Devices*

Device	Minimum Supported DRT Version
AP-228	DRT 1.0_65103
AP-274	DRT 1.0_65103
AP-275	DRT 1.0_65103
AP-277	DRT 1.0_65103
AP-303	DRT 1.0_65103
AP-303H	DRT 1.0_65103
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_65103
AP-305	DRT 1.0_65103
AP-314	DRT 1.0_65103
AP-315	DRT 1.0_65103
AP-318	DRT 1.0_65103
AP-324	DRT 1.0_65103
AP-325	DRT 1.0_65103
AP-334	DRT 1.0_65103
AP-335	DRT 1.0_65103
AP-344	DRT 1.0_65103
AP-345	DRT 1.0_65103
AP-365	DRT 1.0_65103
AP-367	DRT 1.0_65103
AP-374	DRT 1.0_65103
AP-375	DRT 1.0_65103
AP-377	DRT 1.0_65103
AP-387	DRT 1.0_68979

Table 118: *Supported Devices*

Device	Minimum Supported DRT Version
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_65103
AP-93	DRT 1.0_65103
RAP-108	DRT 1.0_65103
RAP-109	DRT 1.0_65103
RAP-155	DRT 1.0_65103
RAP-3WN	DRT 1.0_65103
RAP-3WNP	DRT 1.0_65103

Nepal

The following APs are currently supported in the Nepal regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code NP ap-type <ap-type>`

Table 119: *Supported Devices*

Device	Channels
AP17	DRT 1.0_72277
AP-203H	DRT 1.0_67861
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-205	DRT 1.0_57223
AP-205H	DRT 1.0_57223
AP-207	DRT 1.0_70855
AP-215	DRT 1.0_57223
AP-303	DRT 1.0_67041
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_66781
AP-305	DRT 1.0_66781
AP-314	DRT 1.0_70855
AP-315	DRT 1.0_68143
AP-318	DRT 1.0_67041
AP-325	DRT 1.0_61955
AP-334	DRT 1.0_70855
AP-335	DRT 1.0_70855
AP-344	DRT 1.0_67494

Table 119: *Supported Devices*

Device	Channels
AP-345	DRT 1.0_67494
AP-365	DRT 1.0_67041
AP-367	DRT 1.0_67041
AP-374	DRT 1.0_67041
AP-375	DRT 1.0_67041
AP-377	DRT 1.0_67041
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-555	DRT 1.0_71313

Netherlands

The following APs are currently supported in the Netherlands regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code NL ap-type <ap-type>`

Table 120: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 120: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 120: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

New Caledonia

The following APs are currently supported in the New Caledonia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code NC ap-type <ap-type>`

Table 121: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_49596
AP-103H	DRT 1.0_49596
AP-105	DRT 1.0_49596
AP-114	DRT 1.0_49596
AP-115	DRT 1.0_49596
AP-135	DRT 1.0_49596
AP-175P	DRT 1.0_49596
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_49596
AP-205	DRT 1.0_49596
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_49596
AP-215	DRT 1.0_49810
AP-224	DRT 1.0_49596
AP-225	DRT 1.0_49810
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_49596
AP-275	DRT 1.0_49596

Table 121: *Supported Devices*

Device	Minimum Supported DRT Version
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-93	DRT 1.0_49596
RAP-108	DRT 1.0_49596

Table 121: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-109	DRT 1.0_49596
RAP-3WN	DRT 1.0_49596
RAP-3WNP	DRT 1.0_49596

New Zealand

The following APs are currently supported in the New Zealand regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code NZ ap-type <ap-type>`

Table 122: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-120 abg	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-125 abg	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_60362
AP-203R	DRT 1.0_60362
AP-203RP	DRT 1.0_60362

Table 122: *Supported Devices*

Device	Minimum Supported DRT Version
AP-204	DRT 1.0_48188
AP-205	DRT 1.0_48188
AP-205H	DRT 1.0_49810
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_48188
AP-215	DRT 1.0_48188
AP-224	DRT 1.0_48188
AP-225	DRT 1.0_48188
AP-228	DRT 1.0_49596
AP-274	DRT 1.0_48019
AP-275	DRT 1.0_48019
AP-277	DRT 1.0_48713
AP-303	DRT 1.0_65328
AP-303H	DRT 1.0_59241
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_59591
AP-305	DRT 1.0_59591
AP-314	DRT 1.0_56452
AP-315	DRT 1.0_56452
AP-318	DRT 1.0_64825
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-334	DRT 1.0_56452
AP-335	DRT 1.0_56452

Table 122: *Supported Devices*

Device	Minimum Supported DRT Version
AP-344	DRT 1.0_64134
AP-345	DRT 1.0_64134
AP-365	DRT 1.0_59015
AP-367	DRT 1.0_59015
AP-374	DRT 1.0_64134
AP-375	DRT 1.0_64134
AP-377	DRT 1.0_64134
AP-387	DRT 1.0_68979
AP-514	DRT 1.0_67861
AP-504	DRT 1.0_72905
AP-505	DRT 1.0_72905
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_71072
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Nicaragua

The following APs are currently supported in the Nicaragua regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code NI ap-type <ap-type>`

Table 123: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_57440
AP-105	DRT 1.0_43859
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-205	DRT 1.0_57440
AP-205H	DRT 1.0_57440
AP-207	DRT 1.0_57440
AP-215	DRT 1.0_52991
AP-225	DRT 1.0_43859
AP-275	DRT 1.0_53631
AP-303	DRT 1.0_63879
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-374	DRT 1.0_70076

Table 123: *Supported Devices*

Device	Minimum Supported DRT Version
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-155	DRT 1.0_52699
RAP-155P	DRT 1.0_52699
RAP-3WN	DRT 1.0_52699

Niger

The following APs are currently supported in the Niger regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code NE ap-type <ap-type>`

Table 124: *Supported Devices*

Device	Minimum Supported DRT Version
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-203H	DRT 1.0_59989
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_59015
AP-314	DRT 1.0_59591
AP-318	DRT 1.0_64134
AP-334	DRT 1.0_59591
AP-335	DRT 1.0_59591
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59783
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979

Nigeria

The following APs are currently supported in the Nigeria regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code NG ap-type <ap-type>`

Table 125: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_48902
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-203H	DRT 1.0_59015
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-205	DRT 1.0_50288
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_52238
AP-225	DRT 1.0_47469
AP-275	DRT 1.0_50288
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_68979
AP-314	DRT 1.0_59015
AP-315	DRT 1.0_59015
AP-318	DRT 1.0_69377

Table 125: *Supported Devices*

Device	Minimum Supported DRT Version
AP-324	DRT 1.0_56643
AP-325	DRT 1.0_56643
AP-334	DRT 1.0_70855
AP-335	DRT 1.0_70855
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-365	DRT 1.0_59015
AP-367	DRT 1.0_59015
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_71451
AP-535	DRT 1.0_71451
AP-555	DRT 1.0_70537
RAP-109	DRT 1.0_57815
RAP-155P	DRT 1.0_55489
RAP-3WN	DRT 1.0_52238
RAP-3WNP	DRT 1.0_52238

North Mariana Islands

The following APs are currently supported in the North Mariana Islands regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MP ap-type <ap-type>`

Table 126: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_56050
AP-103H	DRT 1.0_56050
AP-105	DRT 1.0_48902
AP-114	DRT 1.0_48902
AP-115	DRT 1.0_48902
AP-135	DRT 1.0_48902
AP-175P	DRT 1.0_48902
AP-203H	DRT 1.0_59591
AP-204	DRT 1.0_54870
AP-205	DRT 1.0_54870
AP-205H	DRT 1.0_50970
AP-207	DRT 1.0_56912
AP-214	DRT 1.0_56050
AP-215	DRT 1.0_56050
AP-224	DRT 1.0_56050
AP-225	DRT 1.0_56050
AP-228	DRT 1.0_56050
AP-274	DRT 1.0_56050
AP-275	DRT 1.0_56050

Table 126: *Supported Devices*

Device	Minimum Supported DRT Version
AP-277	DRT 1.0_54079
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_60518
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_57223
AP-305	DRT 1.0_57223
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-318	DRT 1.0_68720
AP-324	DRT 1.0_52238
AP-325	DRT 1.0_52238
AP-334	DRT 1.0_56128
AP-335	DRT 1.0_56128
AP-344	DRT 1.0_63044
AP-345	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-93	DRT 1.0_48902

Table 126: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-108	DRT 1.0_56050
RAP-109	DRT 1.0_56050
RAP-155	DRT 1.0_56050
RAP-155P	DRT 1.0_56050
RAP-3WNP	DRT 1.0_48902

Norway

The following APs are currently supported in the Norway regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code NO ap-type <ap-type>`

Table 127: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-120abg	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-121abg	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-124abg	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-125abg	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859

Table 127: *Supported Devices*

Device	Minimum Supported DRT Version
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_57815
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477

Table 127: *Supported Devices*

Device	Minimum Supported DRT Version
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859

Table 127: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Oman

The following APs are currently supported in the Oman regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code OM ap-type <ap-type>`

Table 128: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_48460
AP-103H	DRT 1.0_61955
AP-105	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_61955
AP-203R	DRT 1.0_60518
AP-203RP	DRT 1.0_60518
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_49986
AP-207	DRT 1.0_61955
AP-214	DRT 1.0_57023
AP-215	DRT 1.0_57023
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_49810

Table 128: *Supported Devices*

Device	Minimum Supported DRT Version
AP-274	DRT 1.0_48713
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_48713
AP-303	DRT 1.0_65103
AP-303H	DRT 1.0_61955
AP-303P	DRT 1.0_69377
AP-304	DRT 1.0_60944
AP-305	DRT 1.0_60944
AP-318	DRT 1.0_67280
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-365	DRT 1.0_60944
AP-367	DRT 1.0_60944
AP-374	DRT 1.0_64657
AP-375	DRT 1.0_64657
AP-514	DRT 1.0_71451
AP-515	DRT 1.0_71451
AP-534	DRT 1.0_71313
AP-535	DRT 1.0_71313
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859

Table 128: *Supported Devices*

Device	Minimum Supported DRT Version
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_48460
RAP-109	DRT 1.0_47726
RAP-155	DRT 1.0_47726

Pakistan

The following APs are currently supported in the Pakistan regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code PK ap-type <ap-type>`

Table 129: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72670
AP-103	DRT 1.0_54367
AP-103H	DRT 1.0_61527
AP-105	DRT 1.0_54367
AP-114	DRT 1.0_61527
AP-115	DRT 1.0_61527
AP-135	DRT 1.0_54367
AP-203H	DRT 1.0_61527
AP-203R	DRT 1.0_61527
AP-204	DRT 1.0_61527
AP-205	DRT 1.0_54367
AP-205H	DRT 1.0_61527
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_61527
AP-215	DRT 1.0_59989
AP-224	DRT 1.0_61527
AP-225	DRT 1.0_54367
AP-228	DRT 1.0_61527
AP-274	DRT 1.0_61527
AP-275	DRT 1.0_54367

Table 129: *Supported Devices*

Device	Minimum Supported DRT Version
AP-277	DRT 1.0_61527
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_61527
AP-304	DRT 1.0_58653
AP-305	DRT 1.0_58653
AP-314	DRT 1.0_56643
AP-315	DRT 1.0_56643
AP-324	DRT 1.0_56912
AP-325	DRT 1.0_56912
AP-334	DRT 1.0_56643
AP-335	DRT 1.0_56643
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-387	DRT 1.0_72670
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_71892
AP-515	DRT 1.0_71892
AP-534	DRT 1.0_71892
AP-535	DRT 1.0_71892
AP-555	DRT 1.0_71892

Table 129: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-108	DRT 1.0_61527
RAP-109	DRT 1.0_54367
RAP-155	DRT 1.0_54367

Panama

The following APs are currently supported in the Panama regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code PA ap-type <ap-type>`

Table 130: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_49142
AP-105	DRT 1.0_43859
AP-115	DRT 1.0_52699
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-135	DRT 1.0_47156
AP-175P	DRT 1.0_43859
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_49142
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-205	DRT 1.0_48713
AP-207	DRT 1.0_57440
AP-225	DRT 1.0_47156
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_70537

Table 130: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_69377
AP-325	DRT 1.0_55859
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
RAP-109	DRT 1.0_52042
RAP-155	DRT 1.0_52042P
RAP-3WN	DRT 1.0_51477

Papua New Guinea

The following APs are currently supported in the Papua New Guinea regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code PG ap-type <ap-type>`

Table 131: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-105	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-274	DRT 1.0_43859
AP-303	DRT 1.0_72500
AP-303H	DRT 1.0_72277
AP-304	DRT 1.0_72500
AP-305	DRT 1.0_72500
AP-324	DRT 1.0_72670
AP-325	DRT 1.0_72670
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-555	DRT 1.0_70537

Paraguay

The following APs are currently supported in the Paraguay regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code PY ap-type <ap-type>`

Table 132: *WebUI Fixed Issues*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-205H	DRT 1.0_57023
AP-207	DRT 1.0_57440
AP-225	DRT 1.0_51477
AP-303	DRT 1.0_63879
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_69377
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076

Table 132: *WebUI Fixed Issues*

Device	Minimum Supported DRT Version
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Peru

The following APs are currently supported in the Peru regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code PE ap-type <ap-type>`

Table 133: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_47156
AP-103H	DRT 1.0_46705
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_47156
AP-115	DRT 1.0_47156
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_47156
AP-203H	DRT 1.0_60362
AP-203R	DRT 1.0_60362
AP-205H	DRT 1.0_50970
AP-207	DRT 1.0_59783
AP-214	DRT 1.0_56912
AP-215	DRT 1.0_56912
AP-224	DRT 1.0_47156
AP-225	DRT 1.0_47469
AP-228	DRT 1.0_49596
AP-274	DRT 1.0_48460
AP-277	DRT 1.0_49596

Table 133: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303	DRT 1.0_66152
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_68979
AP-304	DRT 1.0_59015
AP-305	DRT 1.0_59015
AP-314	DRT 1.0_57776
AP-315	DRT 1.0_57776
AP-318	DRT 1.0_66152
AP-324	DRT 1.0_51685
AP-325	DRT 1.0_51685
AP-334	DRT 1.0_57776
AP-335	DRT 1.0_57776
AP-344	DRT 1.0_64825
AP-345	DRT 1.0_64825
AP-365	DRT 1.0_59591
AP-367	DRT 1.0_59591
AP-374	DRT 1.0_66152
AP-375	DRT 1.0_66152
AP-377	DRT 1.0_66152
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_69660
AP-515	DRT 1.0_69660

Table 133: *Supported Devices*

Device	Minimum Supported DRT Version
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-108	DRT 1.0_46705
RAP-109	DRT 1.0_47469
RAP-155	DRT 1.0_54079
RAP-155P	DRT 1.0_54079
RAP-3WN	DRT 1.0_47469

Philippines

The following APs are currently supported in the Philippines regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code PH ap-type <ap-type>`

Table 134: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72500
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_46245
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_61527
AP-203R	DRT 1.0_69842
AP-203RP	DRT 1.0_69842
AP-204	DRT 1.0_45134
AP-205	DRT 1.0_45134
AP-205H	DRT 1.0_49810
AP-214	DRT 1.0_46245
AP-215	DRT 1.0_46245

Table 134: *Supported Devices*

Device	Minimum Supported DRT Version
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49810
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_48713
AP-303	DRT 1.0_65328
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_69660
AP-314	DRT 1.0_56643
AP-315	DRT 1.0_56643
AP-318	DRT 1.0_64657
AP-324	DRT 1.0_51685
AP-325	DRT 1.0_51685
AP-334	DRT 1.0_56643
AP-335	DRT 1.0_56643
AP-344	DRT 1.0_64450
AP-345	DRT 1.0_64450
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_64657
AP-375	DRT 1.0_64657
AP-377	DRT 1.0_64657
AP-387	DRT 1.0_71451

Table 134: *Supported Devices*

Device	Minimum Supported DRT Version
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69660
AP-515	DRT 1.0_69660
AP-534	DRT 1.0_70855
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
RAP-108	DRT 1.0_45134
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Poland

The following APs are currently supported in the Poland regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code PL ap-type <ap-type>`

Table 135: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 135: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 135: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Portugal

The following APs are currently supported in the Portugal regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code PT ap-type <ap-type>`

Table 136: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-120 abg	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-125 abg	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015

Table 136: *Supported Devices*

Device	Minimum Supported DRT Version
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642

Table 136: *Supported Devices*

Device	Minimum Supported DRT Version
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859

Table 136: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Puerto Rico

The following APs are currently supported in the Puerto Rico regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code PR ap-type <ap-type>`

Table 137: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_56050
AP-103H	DRT 1.0_56050
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_61045
AP-204	DRT 1.0_56050
AP-205	DRT 1.0_56050
AP-205H	DRT 1.0_51997
AP-207	DRT 1.0_57223

Table 137: *Supported Devices*

Device	Minimum Supported DRT Version
AP-214	DRT 1.0_56050
AP-215	DRT 1.0_56050
AP-224	DRT 1.0_56050
AP-225	DRT 1.0_56050
AP-228	DRT 1.0_56050
AP-274	DRT 1.0_56050
AP-275	DRT 1.0_56050
AP-277	DRT 1.0_51997
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_60518
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_57223
AP-305	DRT 1.0_57223
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-318	DRT 1.0_68720
AP-324	DRT 1.0_56912
AP-325	DRT 1.0_56912
AP-334	DRT 1.0_56128
AP-335	DRT 1.0_56128
AP-344	DRT 1.0_63044
AP-345	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647

Table 137: *Supported Devices*

Device	Minimum Supported DRT Version
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_56050
RAP-109	DRT 1.0_56050
RAP-155	DRT 1.0_56050
RAP-155P	DRT 1.0_56050
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Qatar

The following APs are currently supported in the Qatar regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code QA ap-type <ap-type>`

Table 138: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175	DRT 1.0_55859P
AP-203H	DRT 1.0_61527
AP-203R	DRT 1.0_61527
AP-203RP	DRT 1.0_61527
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_49986
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_59015

Table 138: *Supported Devices*

Device	Minimum Supported DRT Version
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_49810
AP-225	DRT 1.0_49810
AP-228	DRT 1.0_49810
AP-274	DRT 1.0_59591
AP-275	DRT 1.0_59591
AP-277	DRT 1.0_59591
AP-303	DRT 1.0_65328
AP-303H	DRT 1.0_61527
AP-303P	DRT 1.0_68720
AP-304	DRT 1.0_59015
AP-314	DRT 1.0_58226
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_65685
AP-324	DRT 1.0_51685
AP-325	DRT 1.0_51685
AP-344	DRT 1.0_59591
AP-345	DRT 1.0_59591
AP-365	DRT 1.0_68720
AP-367	DRT 1.0_68720
AP-374	DRT 1.0_64825
AP-375	DRT 1.0_65103
AP-377	DRT 1.0_65103
AP-514	DRT 1.0_69377

Table 138: *Supported Devices*

Device	Minimum Supported DRT Version
AP-515	DRT 1.0_69377
AP-534	DRT 1.0_71451
AP-535	DRT 1.0_71451
AP-555	DRT 1.0_71451
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Republic of the Congo

The following APs are currently supported in the Republic of the Congo regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CG ap-type <ap-type>`

Table 139: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-215	DRT 1.0_72670

Réunion

The following APs are currently supported in the Réunion regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code RE ap-type <ap-type>`

Table 140: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 140: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 140: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Romania

The following APs are currently supported in the Romania regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code RO ap-type <ap-type>`

Table 141: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 141: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 141: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Russia

The following APs are currently supported in the Russia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code RU ap-type <ap-type>`

Table 142: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_56912
AP-103H	DRT 1.0_56912
AP-104	DRT 1.0_56912
AP-105	DRT 1.0_56912
AP-114	DRT 1.0_56912
AP-115	DRT 1.0_56912
AP-120	DRT 1.0_56912
AP-121	DRT 1.0_56912
AP-124	DRT 1.0_56912
AP-125	DRT 1.0_56912
AP-134	DRT 1.0_56912
AP-135	DRT 1.0_56912
AP-175DC	DRT 1.0_56912
AP-175AC	DRT 1.0_56912
AP-175P	DRT 1.0_56912
AP-203H	DRT 1.0_60944
AP-203R	DRT 1.0_61313
AP-203RP	DRT 1.0_61313
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015

Table 142: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205H	DRT 1.0_56912
AP-207	DRT 1.0_60114
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_56912
AP-225	DRT 1.0_56912
AP-228	DRT 1.0_56912
AP-274	DRT 1.0_56912
AP-275	DRT 1.0_56912
AP-277	DRT 1.0_56912
AP-303	DRT 1.0_65328
AP-303H	DRT 1.0_61313
AP-303P	DRT 1.0_69166
AP-304	DRT 1.0_59015
AP-305	DRT 1.0_59015
AP-314	DRT 1.0_57023
AP-315	DRT 1.0_57023
AP-318	DRT 1.0_65937
AP-324	DRT 1.0_56308
AP-325	DRT 1.0_56912
AP-334	DRT 1.0_59015
AP-335	DRT 1.0_59015
AP-344	DRT 1.0_65328
AP-345	DRT 1.0_65328

Table 142: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_61313
AP-367	DRT 1.0_61313
AP-374	DRT 1.0_65473
AP-375	DRT 1.0_65473
AP-377	DRT 1.0_65473
AP-387	DRT 1.0_71647
AP-514	DRT 1.0_70076
AP-515	DRT 1.0_70076
AP-534	DRT 1.0_70671
AP-535	DRT 1.0_70671
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_56912
RAP-3WNP	DRT 1.0_56912

Rwanda

The following APs are currently supported in the Mozambique regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code RW ap-type <ap-type>`

Table 143: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_66547
AP-103H	DRT 1.0_66547
AP-104	DRT 1.0_66547
AP-105	DRT 1.0_66547
AP-114	DRT 1.0_66547
AP-115	DRT 1.0_66547
AP-124	DRT 1.0_66547
AP-125	DRT 1.0_66547
AP-134	DRT 1.0_66547
AP-135	DRT 1.0_66547
AP-175AC	DRT 1.0_66547
AP-175DC	DRT 1.0_66547
AP-175P	DRT 1.0_66547
AP-203H	DRT 1.0_66547
AP-203R	DRT 1.0_66547
AP-204	DRT 1.0_66547
AP-205	DRT 1.0_66547
AP-205H	DRT 1.0_66547
AP-207	DRT 1.0_66547

Table 143: *Supported Devices*

Device	Minimum Supported DRT Version
AP-214	DRT 1.0_66547
AP-215	DRT 1.0_66547
AP-224	DRT 1.0_66547
AP-225	DRT 1.0_66547
AP-228	DRT 1.0_66547
AP-274	DRT 1.0_66547
AP-275	DRT 1.0_66547
AP-303	DRT 1.0_64134
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_68979
AP-304	DRT 1.0_66547
AP-305	DRT 1.0_66547
AP-314	DRT 1.0_66547
AP-315	DRT 1.0_66547
AP-318	DRT 1.0_66547
AP-324	DRT 1.0_66547
AP-325	DRT 1.0_66547
AP-334	DRT 1.0_66547
AP-335	DRT 1.0_66547
AP-344	DRT 1.0_66547
AP-345	DRT 1.0_66547
AP-365	DRT 1.0_66547
AP-367	DRT 1.0_66547
AP-374	DRT 1.0_66547

Table 143: *Supported Devices*

Device	Minimum Supported DRT Version
AP-375	DRT 1.0_66547
AP-377	DRT 1.0_66547
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_71451
AP-535	DRT 1.0_71451
AP-555	DRT 1.0_71313
AP-92	DRT 1.0_66547
AP-93	DRT 1.0_66547
AP-93H	DRT 1.0_66547
RAP-108	DRT 1.0_66547
RAP-109	DRT 1.0_66547
RAP-155	DRT 1.0_66547
RAP-155P	DRT 1.0_66547
RAP-3WN	DRT 1.0_66547
RAP-3WNP	DRT 1.0_66547

Saint Barthélemy

The following APs are currently supported in the Saint Barthélemy regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code BL ap-type <ap-type>`

Table 144: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 144: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-555	DRT 1.0_70537
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Saint Kitts and Nevis

The following APs are currently supported in the Saint Kitts and Nevis regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code KN ap-type <ap-type>`

Table 145: *Supported Devices*

Device	Minimum Supported DRT Version
AP-225	DRT 1.0_49596

Saint Lucia

The following APs are currently supported in the Saint Lucia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code LC ap-type <ap-type>`

Table 146: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-103	DRT 1.0_57440
AP-203H	DRT 1.0_64450
AP-205	DRT 1.0_57440
AP-205H	DRT 1.0_57440
AP-207	DRT 1.0_57440
AP-225	DRT_1.0 48460
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_64134
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044

Table 146: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-555	DRT 1.0_70537

Saint Martin

The following APs are currently supported in the Saint Martin regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code MF ap-type <ap-type>`

Table 147: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 147: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 147: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Saint Pierre and Miquelon

The following APs are currently supported in the Saint Pier and Miquelon regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code PM ap-type <ap-type>`

Table 148: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 148: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 148: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Saint Vincent and the Grenadines

The following APs are currently supported in the Saint Vincent and the Grenadines regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code VC ap-type <ap-type>`

Table 149: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_72277
AP-103	DRT 1.0_56643
AP-205	DRT 1.0_56643
AP-205H	DRT 1.0_56643
AP-207	DRT 1.0_57440
AP-225	DRT 1.0_49596
AP-303	DRT 1.0_63879
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_62783
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979

Table 149: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

San Marino

The following APs are currently supported in the San Marino regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code SM ap-type <ap-type>`

Table 150: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 150: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 150: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Saudi Arabia

The following APs are currently supported in the Saudi Arabia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code SA ap-type <ap-type>`

Table 151: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_46245
AP-104	DRT 1.0_43859
AP-103	DRT 1.0_50775
AP-105	DRT 1.0_46245
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_46245
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_61527
AP-203RP	DRT 1.0_61527

Table 151: *Supported Devices*

Device	Minimum Supported DRT Version
AP-204	DRT 1.0_45134
AP-205	DRT 1.0_45134
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_57023
AP-215	DRT 1.0_57023
AP-205H	DRT 1.0_49810
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49596
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_48460
AP-303	DRT 1.0_63879
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_59015
AP-314	DRT 1.0_59015
AP-315	DRT 1.0_59015
AP-318	DRT 1.0_65103
AP-324	DRT 1.0_51362
AP-325	DRT 1.0_51362
AP-344	DRT 1.0_63392
AP-345	DRT 1.0_63392
AP-374	DRT 1.0_65103
AP-375	DRT 1.0_64450

Table 151: *Supported Devices*

Device	Minimum Supported DRT Version
AP-377	DRT 1.0_64450
AP-387	DRT 1.0_71451
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_68720
AP-515	DRT 1.0_68720
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_59015
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Senegal

The following APs are currently supported in the Senegal regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code SN ap-type <ap-type>`

Table 152: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_64825
AP-103H	DRT 1.0_64825
AP-104	DRT 1.0_64825
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_64825
AP-115	DRT 1.0_64825
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175AC	DRT 1.0_64825
AP-175DC	DRT 1.0_64825
AP-175P	DRT 1.0_64825
AP-203H	DRT 1.0_64825
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-204	DRT 1.0_59015

Table 152: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_64825
AP-214	DRT 1.0_64825
AP-215	DRT 1.0_58653
AP-224	DRT 1.0_64825
AP-225	DRT 1.0_64825
AP-228	DRT 1.0_64825
AP-274	DRT 1.0_64825
AP-275	DRT 1.0_64825
AP-277	DRT 1.0_64825
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_59015
AP-315	DRT 1.0_68143
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_64825
AP-325	DRT 1.0_64825
AP-334	DRT 1.0_59591
AP-335	DRT 1.0_59591
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241

Table 152: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_64825
AP-375	DRT 1.0_64825
AP-377	DRT 1.0_64825
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-3WN	DRT 1.0_64825
RAP-3WNP	DRT 1.0_64825
RAP-155	DRT 1.0_64825
RAP-155P	DRT 1.0_64825
RAP-108	DRT 1.0_64825
RAP-109	DRT 1.0_64825

Serbia

The following APs are currently supported in the Serbia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code RS ap-type <ap-type>`

Table 153: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_57223
AP-103H	DRT 1.0_57223
AP-105	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-204	DRT 1.0_60362
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_56643
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_68720
AP-225	DRT 1.0_46705
AP-274	DRT 1.0_57223
AP-275	DRT 1.0_57223
AP-277	DRT 1.0_58653

Table 153: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_59015
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59783
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_65937
AP-375	DRT 1.0_65473
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68720
AP-515	DRT 1.0_68720
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076

Table 153: *Supported Devices*

Device	Minimum Supported DRT Version
AP-555	DRT 1.0_70537
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_57223
RAP-109	DRT 1.0_57223
RAP-155	DRT 1.0_57223
RAP-155P	DRT 1.0_57223
RAP-3WN	DRT 1.0_57223
RAP-3WNP	DRT 1.0_57223

Singapore

The following APs are currently supported in the Singapore regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code SG ap-type <ap-type>`

Table 154: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_49422
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59989
AP-203R	DRT 1.0_61313
AP-203RP	DRT 1.0_61313
AP-204	DRT 1.0_47156
AP-205	DRT 1.0_43859
AP-205H	DRT 1.0_50970
AP-207	DRT 1.0_58653

Table 154: *Supported Devices*

Device	Minimum Supported DRT Version
AP-214	DRT 1.0_43859
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_49596
AP-225	DRT 1.0_49596
AP-228	DRT 1.0_49596
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_48460
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_68979
AP-304	DRT 1.0_58653
AP-305	DRT 1.0_58653
AP-314	DRT 1.0_57776
AP-315	DRT 1.0_57776
AP-318	DRT 1.0_64825
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_57776
AP-335	DRT 1.0_57776
AP-344	DRT 1.0_63879
AP-345	DRT 1.0_63879
AP-365	DRT 1.0_63392
AP-367	DRT 1.0_63392

Table 154: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_63879
AP-375	DRT 1.0_63879
AP-377	DRT 1.0_63879
AP-387	DRT 1.0_71451
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_71451
AP-535	DRT 1.0_71451
AP-555	DRT 1.0_71451
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Slovak Republic

The following APs are currently supported in the Slovak Republic regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code SK ap-type <ap-type>`

Table 155: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 155: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_54672
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 155: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Slovenia

The following APs are currently supported in the Slovenia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code SI ap-type <ap-type>`

Table 156: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 156: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_56308
AP-335	DRT 1.0_56308
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 156: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

South Africa

The following APs are currently supported in the South Africa regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code ZA ap-type <ap-type>`

Table 157: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_46245
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_47156
AP-135	DRT 1.0_47156
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59118
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_50552
AP-214	DRT 1.0_59015

Table 157: *Supported Devices*

Device	Minimum Supported DRT Version
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49986
AP-274	DRT 1.0_45134
AP-275	DRT 1.0_45134
AP-277	DRT 1.0_62141
AP-303	DRT 1.0_65685
AP-303P	DRT 1.0_70537
AP-314	DRT 1.0_59015
AP-315	DRT 1.0_59015
AP-318	DRT 1.0_65937
AP-324	DRT 1.0_52480
AP-325	DRT 1.0_52480
AP-334	DRT 1.0_59015
AP-335	DRT 1.0_59015
AP-344	DRT 1.0_64450
AP-345	DRT 1.0_64450
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_66351
AP-375	DRT 1.0_66351
AP-377	DRT 1.0_66351
AP-514	DRT 1.0_69377

Table 157: *Supported Devices*

Device	Minimum Supported DRT Version
AP-515	DRT 1.0_69660
AP-534	DRT 1.0_72057
AP-535	DRT 1.0_72057
AP-555	DRT 1.0_72057
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

South Korea

The following APs are currently supported in the South Korea regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code KR ap-type <ap-type>`

Table 158: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_61527
AP-203R	DRT 1.0_61527
AP-203RP	DRT 1.0_61527
AP-204	DRT 1.0_46245
AP-205	DRT 1.0_46245
AP-205H	DRT 1.0_50552
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_46245

Table 158: *Supported Devices*

Device	Minimum Supported DRT Version
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_58226
AP-274	DRT 1.0_45530
AP-275	DRT 1.0_45530
AP-277	DRT 1.0_53420
AP-303	DRT 1.0_63392
AP-303H	DRT 1.0_59989
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_59015
AP-305	DRT 1.0_59015
AP-314	DRT 1.0_60362
AP-318	DRT 1.0_64450
AP-315	DRT 1.0_56912
AP-324	DRT 1.0_59989
AP-325	DRT 1.0_59989
AP-334	DRT 1.0_60362
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_64134
AP-345	DRT 1.0_64134
AP-365	DRT 1.0_60362
AP-367	DRT 1.0_60362
AP-374	DRT 1.0_64450

Table 158: *Supported Devices*

Device	Minimum Supported DRT Version
AP-375	DRT 1.0_64450
AP-377	DRT 1.0_64450
AP-514	DRT 1.0_69842
AP-515	DRT 1.0_69660
AP-534	DRT 1.0_70855
AP-535	DRT 1.0_70855
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_54079
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Spain

The following APs are currently supported in the Spain regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code ES ap-type <ap-type>`

Table 159: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 159: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-207	DRT 1.0_57440
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311

Table 159: *Supported Devices*

Device	Minimum Supported DRT Version
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Sri Lanka

The following APs are currently supported in the Sri Lanka regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code LK ap-type <ap-type>`

Table 160: *Supported Devices*

Device	Regulatory-Cert Version
AP-103	DRT 1.0_62783
AP-103H	DRT 1.0_62783
AP-105	DRT 1.0_46245
AP-135	DRT 1.0_46245
AP-203H	DRT 1.0_59783
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-204	DRT 1.0_63044
AP-205	DRT 1.0_62783
AP-205H	DRT 1.0_62783
AP-207	DRT 1.0_59241
AP-214	DRT 1.0_62783
AP-215	DRT 1.0_59015
AP-225	DRT 1.0_46245
AP-274	DRT 1.0_62783
AP-275	DRT 1.0_62783
AP-277	DRT 1.0_62783
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_69166

Table 160: *Supported Devices*

Device	Regulatory-Cert Version
AP-304	DRT 1.0_62783
AP-305	DRT 1.0_62783
AP-314	DRT 1.0_62783
AP-315	DRT 1.0_62783
AP-318	DRT 1.0_69377
AP-324	DRT 1.0_62783
AP-325	DRT 1.0_62783
AP-334	DRT 1.0_58226
AP-335	DRT 1.0_58226
AP-344	DRT 1.0_62783
AP-345	DRT 1.0_62783
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_62783
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313
RAP-108	DRT 1.0_62783
RAP-109	DRT 1.0_62783
RAP-3WN	DRT 1.0_62783
RAP-3WNP	DRT 1.0_62783

Suriname

The following APs are currently supported in Suriname regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code SR ap-type <ap-type>`

Table 161: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-103	DRT 1.0_57023
AP-205H	DRT 1.0_57023
AP-207	DRT 1.0_57440
AP-225	DRT 1.0_49422
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_71647
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_72670
AP-504	DRT 1.0_71647

Table 161: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_71451
AP-515	DRT 1.0_71451
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313

Svalbard and Jan Mayen

The following APs are currently supported in the Svalbard and Jan Mayen regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code SJ ap-type <ap-type>`

Table 162: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 162: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 162: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Sweden

The following APs are currently supported in the Sweden regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code SE ap-type <ap-type>`

Table 163: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 163: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241

Table 163: *Supported Devices*

Device	Minimum Supported DRT Version
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Switzerland

The following APs are currently supported in the Switzerland regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code CH ap-type <ap-type>`

Table 164: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 164: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_43859
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044

Table 164: *Supported Devices*

Device	Minimum Supported DRT Version
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Taiwan

The following APs are currently supported in the Taiwan regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code TW ap-type <ap-type>`

Table 165: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72670
AP-103	DRT 1.0_46245
AP-103H	DRT 1.0_47156
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_63392
AP-203RP	DRT 1.0_63392
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_50288

Table 165: *Supported Devices*

Device	Minimum Supported DRT Version
AP-207	DRT 1.0_59591
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_58226
AP-274	DRT 1.0_48019
AP-275	DRT 1.0_48019
AP-303	DRT 1.0_64134
AP-303H	DRT 1.0_60944
AP-304	DRT 1.0_60944
AP-305	DRT 1.0_60944
AP-314	DRT 1.0_56643
AP-315	DRT 1.0_56643
AP-318	DRT 1.0_65103
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-334	DRT 1.0_56643
AP-335	DRT 1.0_56643
AP-344	DRT 1.0_63727
AP-345	DRT 1.0_63727
AP-365	DRT 1.0_60362
AP-367	DRT 1.0_60362
AP-374	DRT 1.0_68720

Table 165: *Supported Devices*

Device	Minimum Supported DRT Version
AP-375	DRT 1.0_68720
AP-377	DRT 1.0_68720
AP-504	DRT 1.0_72905
AP-505	DRT 1.0_72905
AP-514	DRT 1.0_69377
AP-515	DRT 1.0_69377
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Tanzania

The following APs are currently supported in the Tanzania regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code TZ ap-type <ap-type>`

Table 166: *Supported Devices*

Device	Regulatory-Cert Version
AP17	DRT 1.0_72277
AP-203H	DRT 1.0_59015
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-205H	DRT 1.0_58226
AP-207	DRT 1.0_59241
AP-215	DRT 1.0_68720
AP-277	DRT 1.0_58226
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_68979
AP-304	DRT 1.0_59015
AP-318	DRT 1.0_69377
AP-334	DRT 1.0_59591
AP-335	DRT 1.0_59591
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69166

Table 166: *Supported Devices*

Device	Regulatory-Cert Version
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076

Thailand

The following APs are currently supported in the Thailand regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code TH ap-type <ap-type>`

Table 167: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-103	DRT 1.0_49422
AP-103H	DRT 1.0_49422
AP-104	DRT 1.0_49422
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_49422
AP-115	DRT 1.0_49422
AP-120	DRT 1.0_49422
AP-121	DRT 1.0_49422
AP-124	DRT 1.0_49422
AP-125	DRT 1.0_49422
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_49422
AP-175DC	DRT 1.0_49422
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_68979
AP-203R	DRT 1.0_61527
AP-203RP	DRT 1.0_61527
AP-204	DRT 1.0_59015

Table 167: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_59015
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_49422
AP-215	DRT 1.0_49422
AP-224	DRT 1.0_49422
AP-225	DRT 1.0_49422
AP-228	DRT 1.0_66547
AP-274	DRT 1.0_49422
AP-275	DRT 1.0_49422
AP-303	DRT 1.0_66781
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_69166
AP-314	DRT 1.0_56452
AP-315	DRT 1.0_56452
AP-318	DRT 1.0_66781
AP-334	DRT 1.0_56912
AP-335	DRT 1.0_56912
AP-344	DRT 1.0_64450
AP-345	DRT 1.0_64450
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_64657
AP-375	DRT 1.0_64657
AP-377	DRT 1.0_64657

Table 167: *Supported Devices*

Device	Minimum Supported DRT Version
AP-387	DRT 1.0_70671
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_49422
AP-93	DRT 1.0_49422
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_49422
RAP-109	DRT 1.0_49422
RAP-155	DRT 1.0_49422
RAP-155P	DRT 1.0_49422
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Trinidad and Tobago

The following APs are currently supported in the Trinidad and Tobago regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code TT ap-type <ap-type>`

Table 168: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_56308
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_67861
AP-205	DRT 1.0_55384
AP-205H	DRT 1.0_55384
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_51155
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-274	DRT 1.0_61313
AP-275	DRT 1.0_56308
AP-277	DRT 1.0_56308
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_67861

Table 168: *Supported Devices*

Device	Minimum Supported DRT Version
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_67494
AP-345	DRT 1.0_67494
AP-365	DRT 1.0_62496
AP-367	DRT 1.0_62496
AP-374	DRT 1.0_68474
AP-375	DRT 1.0_68474
AP-377	DRT 1.0_68474
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-155	DRT 1.0_51477
RAP-3WNP	DRT 1.0_51155

Tunisia

The following APs are currently supported in the Tunisia regulatory domain.

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code TN ap-type <ap-type>`

Table 169: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_72277
AP-105	DRT 1.0_47726
AP-125	DRT 1.0_43859
AP-203H	DRT 1.0_59783
AP-203R	DRT 1.0_59783
AP-203RP	DRT 1.0_59783
AP-205	DRT 1.0_52858
AP-214	DRT 1.0_55859
AP-215	DRT 1.0_55859
AP-225	DRT 1.0_52699
AP-274	DRT 1.0_63516
AP-275	DRT 1.0_63516
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_59783
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_71072
AP-305	DRT 1.0_71072
AP-318	DRT 1.0_66547
AP-325	DRT 1.0_55384
AP-334	DRT 1.0_59591

Table 169: *Supported Devices*

Device	Minimum Supported DRT Version
AP-335	DRT 1.0_59591
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_63516
AP-367	DRT 1.0_63516
AP-374	DRT 1.0_63516
AP-375	DRT 1.0_63516
AP-377	DRT 1.0_63516
AP-387	DRT 1.0_72670
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70671
AP-535	DRT 1.0_70671
AP-555	DRT 1.0_70537
RAP-109	DRT 1.0_43859

Turkey

The following APs are currently supported in the Turkey regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code TR ap-type <ap-type>`

Table 170: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 170: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-365	DRT 1.0_59241

Table 170: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

Turkmenistan

The following APs are currently supported in the Turkmenistan regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code TM ap-type <ap-type>`

Table 171: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-203H	DRT 1.0_64450
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-305	DRT 1.0_63392
AP-315	DRT 1.0_68143
AP-318	DRT 1.0_64134
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
OC-30	DRT 1.0_63392

Uganda

The following APs are currently supported in the Uganda regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code UG ap-type <ap-type>`

Table 172: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-105	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59015
AP-203R	DRT 1.0_59015
AP-203RP	DRT 1.0_59015
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_68474
AP-215	DRT 1.0_68474
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_68979
AP-304	DRT 1.0_59015

Table 172: *Supported Devices*

Device	Minimum Supported DRT Version
AP-314	DRT 1.0_59015
AP-315	DRT 1.0_59015
AP-318	DRT 1.0_69377
AP-334	DRT 1.0_70855
AP-335	DRT 1.0_70855
AP-344	DRT 1.0_69842
AP-345	DRT 1.0_69842
AP-365	DRT 1.0_59015
AP-367	DRT 1.0_59015
AP-387	DRT 1.0_69660
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_69166
AP-515	DRT 1.0_69166
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-3WN	DRT 1.0_64825
RAP-3WNP	DRT 1.0_64825

Ukraine

The following APs are currently supported in the Ukraine regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code UA ap-type <ap-type>`

Table 173: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_57223
AP-103H	DRT 1.0_45245
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_57223
AP-115	DRT 1.0_57223
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175P	DRT 1.0_52699
AP-203H	DRT 1.0_60944
AP-203R	DRT 1.0_61690
AP-203RP	DRT 1.0_61690
AP-204	DRT 1.0_60362
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_64134

Table 173: *Supported Devices*

Device	Minimum Supported DRT Version
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_57223
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_46413
AP-225	DRT 1.0_46413
AP-228	DRT 1.0_57223
AP-274	DRT 1.0_57223
AP-275	DRT 1.0_57223
AP-277	DRT 1.0_57223
AP-303	DRT 1.0_65937
AP-303H	DRT 1.0_64134
AP-303P	DRT 1.0_69842
AP-304	DRT 1.0_59241
AP-305	DRT 1.0_59241
AP-314	DRT 1.0_57223
AP-315	DRT 1.0_57223
AP-318	DRT 1.0_66152
AP-324	DRT 1.0_57223
AP-325	DRT 1.0_57223
AP-344	DRT 1.0_64450
AP-345	DRT 1.0_64450
AP-365	DRT 1.0_64134
AP-367	DRT 1.0_64134
AP-374	DRT 1.0_66152

Table 173: *Supported Devices*

Device	Minimum Supported DRT Version
AP-375	DRT 1.0_66152
AP-377	DRT 1.0_66152
AP-514	DRT 1.0_70537
AP-515	DRT 1.0_70537
AP-534	DRT 1.0_72057
AP-535	DRT 1.0_72057
AP-555	DRT 1.0_72057
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_46413
RAP-3WNP	DRT 1.0_46413

United Arab Emirates

The following APs are currently supported in the United Arab Emirates regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code AE ap-type <ap-type>`

Table 174: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_45907
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_60944
AP-203R	DRT 1.0_60944
AP-203RP	DRT 1.0_60944
AP-204	DRT 1.0_59015
AP-205	DRT 1.0_59015
AP-205H	DRT 1.0_57815

Table 174: *Supported Devices*

Device	Minimum Supported DRT Version
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_58226
AP-228	DRT 1.0_49596
AP-274	DRT 1.0_43859
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_57440
AP-303	DRT 1.0_64134
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_59015
AP-305	DRT 1.0_57223
AP-314	DRT 1.0_59241
AP-315	DRT 1.0_59241
AP-318	DRT 1.0_65103
AP-324	DRT 1.0_52480
AP-325	DRT 1.0_52480
AP-334	DRT 1.0_58226
AP-335	DRT 1.0_58226
AP-344	DRT 1.0_63516
AP-345	DRT 1.0_63516
AP-365	DRT 1.0_59591

Table 174: *Supported Devices*

Device	Minimum Supported DRT Version
AP-367	DRT 1.0_59591
AP-374	DRT 1.0_64450
AP-375	DRT 1.0_64450
AP-377	DRT 1.0_64825
AP-387	DRT 1.0_72670
AP-514	DRT 1.0_68720
AP-515	DRT 1.0_68720
AP-534	DRT 1.0_70671
AP-535	DRT 1.0_70671
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

United Kingdom

The following APs are currently supported in the United Kingdom regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code GB ap-type <ap-type>`

Table 175: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_43859
AP-104	DRT 1.0_43859
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_43859
AP-115	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175DC	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-203H	DRT 1.0_59591
AP-203R	DRT 1.0_57815
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_60362

Table 175: *Supported Devices*

Device	Minimum Supported DRT Version
AP-205	DRT 1.0_60362
AP-205H	DRT 1.0_49422
AP-207	DRT 1.0_58226
AP-214	DRT 1.0_59015
AP-215	DRT 1.0_59015
AP-224	DRT 1.0_43859
AP-225	DRT 1.0_43859
AP-228	DRT 1.0_49142
AP-275	DRT 1.0_43859
AP-277	DRT 1.0_47469
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_59015
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_58258
AP-305	DRT 1.0_58258
AP-314	DRT 1.0_55642
AP-315	DRT 1.0_55642
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51477
AP-325	DRT 1.0_51477
AP-334	DRT 1.0_55642
AP-335	DRT 1.0_55642
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311

Table 175: *Supported Devices*

Device	Minimum Supported DRT Version
AP-365	DRT 1.0_59241
AP-367	DRT 1.0_59241
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-68	DRT 1.0_43859
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_43859
RAP-109	DRT 1.0_43859
RAP-155	DRT 1.0_43859
RAP-155P	DRT 1.0_43859
RAP-3WN	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859

United States of America

The following APs are currently supported in the United States of America regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code US ap-type <ap-type>`

Table 176: *Supported Devices*

Device	Minimum Supported DRT Version	Regulatory Cert for DFS
AP17	DRT 1.0_71647	DRT 1.0_73142
AP-103	DRT 1.0_48460	DRT 1.0_55859
AP-103H	DRT 1.0_45134	DRT 1.0_55859
AP-104	DRT 1.0_43859	DRT 1.0_43859
AP-105	DRT 1.0_43859	DRT 1.0_43859
AP-114	DRT 1.0_43859	DRT 1.0_43859
AP-115	DRT 1.0_43859	DRT 1.0_43859
AP-120	DRT 1.0_43859	DRT 1.0_43859
AP-121	DRT 1.0_43859	DRT 1.0_43859
AP-124	DRT 1.0_43859	DRT 1.0_43859
AP-125	DRT 1.0_43859	DRT 1.0_43859
AP-134	DRT 1.0_43859	DRT 1.0_43859
AP-135	DRT 1.0_43859	DRT 1.0_43859
AP-175DC	DRT 1.0_43859	DRT 1.0_43859
AP-175AC	DRT 1.0_43859	DRT 1.0_43859
AP-175P	DRT 1.0_43859	DRT 1.0_43859
AP-203H	DRT 1.0_59591	DRT 1.0_61313
AP-203R	DRT 1.0_59241	DRT 1.0_61313
AP-203RP	DRT 1.0_59241	DRT 1.0_61313
AP-204	DRT 1.0_59015	DRT 1.0_59015

Table 176: *Supported Devices*

Device	Minimum Supported DRT Version	Regulatory Cert for DFS
AP-205	DRT 1.0_59015	DRT 1.0_59015
AP-205H	DRT 1.0_55384	DRT 1.0_50970
AP-207	DRT 1.0_57776	DRT 1.0_61313
AP-214	DRT 1.0_59015	DRT 1.0_59015
AP-215	DRT 1.0_59015	DRT 1.0_59015
AP-224	DRT 1.0_56050	DRT 1.0_56050
AP-225	DRT 1.0_56050	DRT 1.0_56050
AP-228	DRT 1.0_56050	DRT 1.0_56050
AP-274	DRT 1.0_56050	DRT 1.0_56050
AP-275	DRT 1.0_56050	DRT 1.0_56050
AP-277	DRT 1.0_55642	DRT 1.0_55642
AP-303	DRT 1.0_63879	DRT 1.0_64134
AP-303H	DRT 1.0_61045	DRT 1.0_61045
AP-303P	DRT 1.0_67861	DRT 1.0_67861
AP-304	DRT 1.0_56912	DRT 1.0_61313
AP-305	DRT 1.0_56912	DRT 1.0_61313
AP-314	DRT 1.0_56128	DRT 1.0_56128
AP-315	DRT 1.0_56128	DRT 1.0_56128
AP-318	DRT 1.0_64134	DRT 1.0_65103
AP-324	DRT 1.0_55642	DRT 1.0_55642
AP-325	DRT 1.0_55642	DRT 1.0_55642
AP-334	DRT 1.0_56128	DRT 1.0_56128
AP-335	DRT 1.0_56128	DRT 1.0_56128
AP-344	DRT 1.0_63044	DRT 1.0_63044

Table 176: *Supported Devices*

Device	Minimum Supported DRT Version	Regulatory Cert for DFS
AP-345	DRT 1.0_63044	DRT 1.0_63044
AP-365	DRT 1.0_59118	DRT 1.0_61313
AP-367	DRT 1.0_59241	DRT 1.0_61313
AP-374	DRT 1.0_63516	DRT 1.0_64134
AP-375	DRT 1.0_63516	DRT 1.0_64134
AP-377	DRT 1.0_63516	DRT 1.0_64134
AP-387	DRT 1.0_68979	DRT 1.0_71451
AP-504	DRT 1.0_71647	
AP-505	DRT 1.0_71647	
AP-514	DRT 1.0_67861	DRT 1.0_69660
AP-515	DRT 1.0_67861	DRT 1.0_69660
AP-534	DRT 1.0_70076	DRT 1.0_71892
AP-535	DRT 1.0_70076	DRT 1.0_71892
AP-555	DRT 1.0_70537	DRT 1.0_71892
AP-68	DRT 1.0_43859	DRT 1.0_43859
AP-68P	DRT 1.0_63879	
AP-92	DRT 1.0_43859	DRT 1.0_43859
AP-93	DRT 1.0_43859	DRT 1.0_43859
AP-93H	DRT 1.0_43859	DRT 1.0_43859
RAP-108	DRT 1.0_56050	DRT 1.0_56050
RAP-109	DRT 1.0_56050	DRT 1.0_56050
RAP-155	DRT 1.0_56050	DRT 1.0_56050

Table 176: *Supported Devices*

Device	Minimum Supported DRT Version	Regulatory Cert for DFS
RAP-155P	DRT 1.0_56050	DRT 1.0_56050
RAP-3WN	DRT 1.0_43859	DRT 1.0_43859
RAP-3WNP	DRT 1.0_43859	DRT 1.0_43859

Uruguay

The following APs are currently supported in the Uruguay regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code UY ap-type <ap-type>`

Table 177: *Supported Devices*

Device	Minimum Supported DRT Version
AP11D	DRT 1.0_72277
AP17	DRT 1.0_71647
AP-103	DRT 1.0_56452
AP-104	DRT 1.0_43859
AP-135	DRT 1.0_46079
AP-203H	DRT 1.0_72277
AP-203R	DRT 1.0_72277
AP-204	DRT 1.0_72277
AP-205	DRT 1.0_56643
AP-205H	DRT 1.0_56452
AP-214	DRT 1.0_72277
AP-215	DRT 1.0_51155
AP-224	DRT 1.0_72277
AP-225	DRT 1.0_46079
AP-228	DRT 1.0_72277
AP-274	DRT 1.0_72277
AP-275	DRT 1.0_51997
AP-277	DRT 1.0_72277
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_72277

Table 177: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653
AP-315	DRT 1.0_58653
AP-318	DRT 1.0_72277
AP-324	DRT 1.0_72277
AP-325	DRT 1.0_72277
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-344	DRT 1.0_72277
AP-345	DRT 1.0_72277
AP-365	DRT 1.0_72277
AP-367	DRT 1.0_72277
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-377	DRT 1.0_72057
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076

Table 177: *Supported Devices*

Device	Minimum Supported DRT Version
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
RAP-108	DRT 1.0_72277
RAP-109	DRT 1.0_72277
RAP-155	DRT 1.0_51155
RAP-155P	DRT 1.0_51685
RAP-3WNP	DRT 1.0_51155

Uzbekistan

The following APs are currently supported in the Uzbekistan regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code UZ ap-type <ap-type>`

Table 178: *Supported Devices*

Device	Regulatory-Cert Version
AP17	DRT 1.0_72277
AP-203H	DRT 1.0_73310
AP-203R	DRT 1.0_73310
AP-203RP	DRT 1.0_59015
AP-204	DRT 1.0_73310
AP-205	DRT 1.0_73310
AP-205H	DRT 1.0_73310
AP-207	DRT 1.0_73310
AP-214	DRT 1.0_73310
AP-215	DRT 1.0_73310
AP-224	DRT 1.0_73310
AP-225	DRT 1.0_73310
AP-228	DRT 1.0_71647
AP-274	DRT 1.0_73310
AP-275	DRT 1.0_73310
AP-277	DRT 1.0_73310
AP-303	DRT 1.0_71892
AP-303H	DRT 1.0_71647
AP-303P	DRT 1.0_71647
AP-304	DRT 1.0_66781

Table 178: *Supported Devices*

Device	Regulatory-Cert Version
AP-305	DRT 1.0_66781
AP-314	DRT 1.0_59591
AP-318	DRT 1.0_73310
AP-324	DRT 1.0_73310
AP-325	DRT 1.0_73310
AP-334	DRT 1.0_59591
AP-335	DRT 1.0_59591
AP-344	DRT 1.0_73310
AP-345	DRT 1.0_73310
AP-365	DRT 1.0_73310
AP-367	DRT 1.0_73310
AP-374	DRT 1.0_72057
AP-375	DRT 1.0_72057
AP-377	DRT 1.0_72057
AP-387	DRT 1.0_71072
AP-504	DRT 1.0_73142
AP-505	DRT 1.0_73142
AP-514	DRT 1.0_70855
AP-515	DRT 1.0_70855
AP-534	DRT 1.0_71072
AP-535	DRT 1.0_71072
AP-555	DRT 1.0_71313
RAP-108	DRT 1.0_73310
RAP-109	DRT 1.0_73310

Venezuela

The following APs are currently supported in the Venezuela regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code VE ap-type <ap-type>`

Table 179: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_56452
AP-105	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-175AC	DRT 1.0_43859
AP-175P	DRT 1.0_43859
AP-205	DRT 1.0_58653
AP-205H	DRT 1.0_56452
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_54079
AP-215	DRT 1.0_51685
AP-225	DRT 1.0_45134
AP-275	DRT 1.0_52238
AP-303	DRT 1.0_63879
AP-303H	DRT 1.0_71892
AP-303P	DRT 1.0_68474
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_57440
AP-314	DRT 1.0_58653

Table 179: *Supported Devices*

Device	Minimum Supported DRT Version
AP-315	DRT 1.0_58653
AP-334	DRT 1.0_58653
AP-335	DRT 1.0_58653
AP-365	DRT 1.0_43859
AP-367	DRT 1.0_43859
AP-374	DRT 1.0_70076
AP-375	DRT 1.0_70076
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_71451
AP-515	DRT 1.0_71451
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-155	DRT 1.0_54079
RAP-155P	DRT 1.0_54079
RAP-3WNP	DRT 1.0_54079

Vietnam

The following APs are currently supported in the Vietnam regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code VN ap-type <ap-type>`

Table 180: *Supported Devices*

Device	Minimum Supported DRT Version
AP-103	DRT 1.0_43859
AP-103H	DRT 1.0_59591
AP-104	DRT 1.0_46705
AP-105	DRT 1.0_43859
AP-114	DRT 1.0_66547
AP-115	DRT 1.0_45134
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-134	DRT 1.0_43859
AP-135	DRT 1.0_43859
AP-203H	DRT 1.0_61527
AP-203R	DRT 1.0_61527
AP-203RP	DRT 1.0_61527
AP-205	DRT 1.0_48460
AP-207	DRT 1.0_59015
AP-214	DRT 1.0_65685
AP-215	DRT 1.0_48460
AP-224	DRT 1.0_66547

Table 180: *Supported Devices*

Device	Minimum Supported DRT Version
AP-225	DRT 1.0_45134
AP-228	DRT 1.0_61955
AP-274	DRT 1.0_66547
AP-275	DRT 1.0_51477
AP-303	DRT 1.0_66547
AP-303H	DRT 1.0_65473
AP-303P	DRT 1.0_69660
AP-304	DRT 1.0_58226
AP-305	DRT 1.0_58226
AP-314	DRT 1.0_57440
AP-315	DRT 1.0_57440
AP-318	DRT 1.0_64450
AP-325	DRT 1.0_56452
AP-334	DRT 1.0_57440
AP-335	DRT 1.0_57440
AP-344	DRT 1.0_63392
AP-345	DRT 1.0_63392
AP-365	DRT 1.0_59591
AP-367	DRT 1.0_59591
AP-374	DRT 1.0_65937
AP-375	DRT 1.0_64657
AP-377	DRT 1.0_66781
AP-514	DRT 1.0_69660
AP-515	DRT 1.0_69660

Table 180: *Supported Devices*

Device	Minimum Supported DRT Version
AP-534	DRT 1.0_71313
AP-535	DRT 1.0_71313
AP-555	DRT 1.0_71313
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_66547
RAP-109	DRT 1.0_66547
RAP-155P	DRT 1.0_47469
RAP-3WNP	DRT 1.0_52480

Virgin Islands (US)

The following APs are currently supported in the US Virgin Islands regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code VI ap-type <ap-type>`

Table 181: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103H	DRT 1.0_54870
AP-105	DRT 1.0_54870
AP-114	DRT 1.0_48902
AP-115	DRT 1.0_48902
AP-135	DRT 1.0_48902
AP-175P	DRT 1.0_48902
AP-203H	DRT 1.0_59591
AP-204	DRT 1.0_56050
AP-205	DRT 1.0_56050
AP-207	DRT 1.0_56912
AP-214	DRT 1.0_56050
AP-215	DRT 1.0_56050
AP-224	DRT 1.0_56050
AP-225	DRT 1.0_56050
AP-228	DRT 1.0_56050
AP-274	DRT 1.0_56050
AP-275	DRT 1.0_56050
AP-277	DRT 1.0_54079
AP-303	DRT 1.0_63879

Table 181: *Supported Devices*

Device	Minimum Supported DRT Version
AP-303H	DRT 1.0_71647
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_57223
AP-305	DRT 1.0_57223
AP-314	DRT 1.0_56912
AP-315	DRT 1.0_56912
AP-324	DRT 1.0_52238
AP-325	DRT 1.0_52238
AP-334	DRT 1.0_56128
AP-335	DRT 1.0_56128
AP-344	DRT 1.0_63044
AP-345	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-93	DRT 1.0_48902
RAP-108	DRT 1.0_56050
RAP-109	DRT 1.0_56050

Table 181: *Supported Devices*

Device	Minimum Supported DRT Version
RAP-155	DRT 1.0_56050
RAP-155P	DRT 1.0_56050
RAP-3WNP	DRT 1.0_48902

Wallis and Futuna

The following APs are currently supported in the Wallis and Futuna regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code WF ap-type <ap-type>`

Table 182: *Supported Devices*

Device	Minimum Supported DRT Versions
AP17	DRT 1.0_71647
AP-93	DRT 1.0_48460
AP-103	DRT 1.0_48713
AP-103H	DRT 1.0_48713
AP-105	DRT 1.0_48460
AP-114	DRT 1.0_48460
AP-115	DRT 1.0_48460
AP-135	DRT 1.0_48460
AP-175P	DRT 1.0_48460
AP-203H	DRT 1.0_64450
AP-204	DRT 1.0_48713
AP-205	DRT 1.0_48713
AP-205H	DRT 1.0_50379
AP-207	DRT 1.0_57440
AP-214	DRT 1.0_48713
AP-215	DRT 1.0_48713
AP-224	DRT 1.0_48713
AP-225	DRT 1.0_48713
AP-228	DRT 1.0_50379
AP-274	DRT 1.0_48713

Table 182: *Supported Devices*

Device	Minimum Supported DRT Versions
AP-275	DRT 1.0_48713
AP-277	DRT 1.0_50379
AP-303	DRT 1.0_63516
AP-303H	DRT 1.0_66547
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_62496
AP-305	DRT 1.0_62496
AP-318	DRT 1.0_64134
AP-324	DRT 1.0_51997
AP-325	DRT 1.0_51997
AP-344	DRT 1.0_62311
AP-345	DRT 1.0_62311
AP-374	DRT 1.0_63044
AP-375	DRT 1.0_63044
AP-377	DRT 1.0_63044
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_67861
AP-515	DRT 1.0_67861
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537

Table 182: *Supported Devices*

Device	Minimum Supported DRT Versions
RAP-108	DRT 1.0_48713
RAP-109	DRT 1.0_48713
RAP-3WNP	DRT 1.0_48713

Zambia

The following APs are currently supported in the Zambia regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code ZM ap-type <ap-type>`

Table 183: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_65473
AP-103H	DRT 1.0_65473
AP-105	DRT 1.0_43859
AP-120	DRT 1.0_43859
AP-121	DRT 1.0_43859
AP-124	DRT 1.0_43859
AP-125	DRT 1.0_43859
AP-203H	DRT 1.0_65473
AP-203R	DRT 1.0_65473
AP-203RP	DRT 1.0_65473
AP-204	DRT 1.0_65473
AP-205	DRT 1.0_65473
AP-205H	DRT 1.0_65473
AP-207	DRT 1.0_65473
AP-214	DRT 1.0_65473
AP-215	DRT 1.0_65473
AP-224	DRT 1.0_65473
AP-225	DRT 1.0_65473
AP-228	DRT 1.0_65473

Table 183: *Supported Devices*

Device	Minimum Supported DRT Version
AP-274	DRT 1.0_65473
AP-275	DRT 1.0_65473
AP-277	DRT 1.0_65473
AP-303	DRT 1.0_65473
AP-303H	DRT 1.0_65473
AP-303P	DRT 1.0_68979
AP-304	DRT 1.0_65473
AP-305	DRT 1.0_65473
AP-314	DRT 1.0_65473
AP-315	DRT 1.0_65473
AP-318	DRT 1.0_65473
AP-324	DRT 1.0_65473
AP-325	DRT 1.0_65473
AP-334	DRT 1.0_65473
AP-335	DRT 1.0_65473
AP-344	DRT 1.0_65473
AP-345	DRT 1.0_65473
AP-365	DRT 1.0_65473
AP-367	DRT 1.0_65473
AP-374	DRT 1.0_65473
AP-375	DRT 1.0_65473
AP-377	DRT 1.0_65473
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647

Table 183: *Supported Devices*

Device	Minimum Supported DRT Version
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_69377
AP-515	DRT 1.0_69377
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
AP-92	DRT 1.0_43859
AP-93	DRT 1.0_43859
AP-93H	DRT 1.0_43859
RAP-108	DRT 1.0_65473
RAP-109	DRT 1.0_65473
RAP-155	DRT 1.0_65473
RAP-155P	DRT 1.0_65473
RAP-3WN	DRT 1.0_65473
RAP-3WNP	DRT 1.0_65473

Zimbabwe

The following APs are currently supported in the Zimbabwe regulatory domain.

NOTE

To view the approved channels for this country domain, use the following CLI command:
`show ap allowed-channels country-code ZW ap-type <ap-type>`

Table 184: *Supported Devices*

Device	Minimum Supported DRT Version
AP17	DRT 1.0_71647
AP-103	DRT 1.0_59989
AP-203H	DRT 1.0_67861
AP-205	DRT 1.0_59989
AP-207	DRT 1.0_66351
AP-214	DRT 1.0_69377
AP-215	DRT 1.0_68720
AP-225	DRT 1.0_59989
AP-303	DRT 1.0_71892
AP-303H	DRT 1.0_70537
AP-303P	DRT 1.0_67861
AP-304	DRT 1.0_71072
AP-305	DRT 1.0_71072
AP-315	DRT 1.0_68143
AP-334	DRT 1.0_70855
AP-335	DRT 1.0_70855
AP-344	DRT 1.0_67494
AP-345	DRT 1.0_67494
AP-374	DRT 1.0_68474
AP-375	DRT 1.0_68474

Table 184: *Supported Devices*

Device	Minimum Supported DRT Version
AP-377	DRT 1.0_68474
AP-387	DRT 1.0_68979
AP-504	DRT 1.0_71647
AP-505	DRT 1.0_71647
AP-514	DRT 1.0_68979
AP-515	DRT 1.0_68979
AP-534	DRT 1.0_70076
AP-535	DRT 1.0_70076
AP-555	DRT 1.0_70537
RAP-108	DRT 1.0_66351
RAP-109	DRT 1.0_66351

Chapter 2
DRT Versions

The following sections list the changes introduced in each release of the downloadable regulatory table. Each release includes the changes introduced in previous releases. The releases are listed from newest to oldest.

- 1.0_73310
- 1.0_73142
- 1.0_72905
- 1.0_72670
- 1.0_72500
- 1.0_72277
- 1.0_72057
- 1.0_71892
- 1.0_71647
- 1.0_71451
- 1.0_71313
- 1.0_71072
- 1.0_70855
- 1.0_70671
- 1.0_70537
- 1.0_70267
- 1.0_70076
- 1.0_69842
- 1.0_69660
- 1.0_69377
- 1.0_69166
- 1.0_68979
- 1.0_68720
- 1.0_68474
- 1.0_68143
- 1.0_68046
- 1.0_67861
- 1.0_67494
- 1.0_67280
- 1.0_67041
- 1.0_66781
- 1.0_66547
- 1.0_66351
- 1.0_66152
- 1.0_65937
- 1.0_65685

- 1.0_65473
- 1.0_65328
- 1.0_65103
- 1.0_64825
- 1.0_64657
- 1.0_64450
- 1.0_64331
- 1.0_64134
- 1.0_63879
- 1.0_63727
- 1.0_63516
- 1.0_63392
- 1.0_63102
- 1.0_63044
- 1.0_62783
- 1.0_62496
- 1.0_62311
- 1.0_62141
- 1.0_61955
- 1.0_61690
- 1.0_61527
- 1.0_61313
- 1.0_61045
- 1.0_60944
- 1.0_60744
- 1.0_60518
- 1.0_60362
- 1.0_59783
- 1.0_59989
- 1.0_59783
- 1.0_59591
- 1.0_59241
- 1.0_59118
- 1.0_59015
- 1.0_58653
- 1.0_58258
- 1.0_58226
- 1.0_57815
- 1.0_57776
- 1.0_57776
- 1.0_57440
- 1.0_57223

- 1.0_57023
- 1.0_56912
- 1.0_56643
- 1.0_56452
- 1.0_56308
- 1.0_56308
- 1.0_56128
- 1.0_56050
- 1.0_55859
- 1.0_55642
- 1.0_55642
- 1.0_55489
- 1.0_55384
- 1.0_54870
- 1.0_54672
- 1.0_54367
- 1.0_54219
- 1.0_54079
- 1.0_53811
- 1.0_53631
- 1.0_53420
- 1.0_53255
- 1.0_52991
- 1.0_52699
- 1.0_52238
- 1.0_52042
- 1.0_51362
- 1.0_51155
- 1.0_50970
- 1.0_50775
- 1.0_50552
- 1.0_50379
- 1.0_50288
- 1.0_49986
- 1.0_49810
- 1.0_49596
- 1.0_49422
- 1.0_49142
- 1.0_48902
- 1.0_48713
- 1.0_48460
- 1.0_48019
- 1.0_47726

- 1.0_47469
- 1.0_47156
- 1.0_46413
- 1.0_46245
- 1.0_45530
- 1.0_45134
- 1.0_44265

1.0_73310

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 185: *1.0_73310*

Regulatory Domain	Regulatory Changes
Antarctica	Support added for AP-215
Uzbekistan	• Support added for AP-203H, AP-203R, AP-204, AP-205, AP-205H, AP-207, AP-214, AP-215, AP-224, AP-225, AP-274, AP-275, AP-277, AP-318, AP-324, AP-344, AP-345, AP-365, AP-367, RAP-108 and RAP-109 • Channels updated for AP-325, AP-334 and AP-335

1.0_73142

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 186: *1.0_73142*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-504 and AP-505
American Samoa	Channels updated for AP17
Antigua And Barbuda	Channels updated for AP17
Bahamas	Channels updated for AP17
Bangladesh	Channels updated for AP17
Barbados	Channels updated for AP17
Bermuda	Channels updated for AP17
Bolivia	Channels updated for AP17
Brunei Darussalam	Channels updated for AP17
Canada	Channels updated for AP17
Cayman Islands	Channels updated for AP17
Colombia	Channels updated for AP17
Costa Rica	Channels updated for AP17
Cote D'ivoire	Support added for AP-504 and AP-505
Curacao	Channels updated for AP17
Dominican Republic	Channels updated for AP17
Ecuador	Channels updated for AP17
El Salvadore	Channels updated for AP17
Federated States Of Micronesia	Channels updated for AP17
Ghana	Support added for AP-504 and AP-505
Grenada	Channels updated for AP17

Regulatory Domain	Regulatory Changes
Guam	Channels updated for AP17
Guatemala	Channels updated for AP17
Guyana	Channels updated for AP17
Haiti	Channels updated for AP17
Honduras	Channels updated for AP17
Jamaica	Support added for AP-504 and AP-505
Kenya	Support added for AP-504 and AP-505
Kuwait	Support added for AP-504 and AP-505
Lao	Channels updated for AP17
Macau	Support added for AP-504 and AP-505
Maldives	Channels updated for AP17
Marshall Islands	Channels updated for AP17
Montserrat	Channels updated for AP17
Nepal	Support added for AP-504 and AP-505
Nicaragua	Channels updated for AP17
Nigeria	Support added for AP-504 and AP-505
Northern Mariana Islands	Channels updated for AP17
Pakistan	Support added for AP-504 and AP-505
Panama	Channels updated for AP17
Paraguay	Channels updated for AP17
Peru	Channels updated for AP17
Philippines	Support added for AP-504 and AP-505
Puerto Rico	Channels updated for AP17
Rwanda	Support added for AP-504 and AP-505
Saint Vincent And The Grenadines	Channels updated for AP17

Regulatory Domain	Regulatory Changes
Saudi Arabia	Support added for AP-504 and AP-505
Singapore	Support added for AP-504 and AP-505
Sri Lanka	Support added for AP-504 and AP-505
Suriname	Channels updated for AP17
Tanzania	Support added for AP-504 and AP-505
Thailand	Support added for AP-504 and AP-505
Trinidad And Tobago	Channels updated for AP17
Tunisia	Support added for AP-504 and AP-505
Uganda	Support added for AP-504 and AP-505
United States of America	Channels updated for AP17
Uruguay	Channels updated for AP17
Us Virgin Islands	Channels updated for AP17
Uzbekistan	Support added for AP-504 and AP-505
Venezuela	Channels updated for AP17

1.0_72905

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 187: *1.0_72905*

Regulatory Domain	Regulatory Changes
Australia	Support added for AP-504 and AP-505
Azerbaijan	Support added for AP-274, AP-275 and AP-277
Congo	Support added for AP-215
Japan	Support added for AP17
Malaysia	Support added for AP-504 and AP-505
Maldives	• Support added for AP-203H, AP-203R, AP-228, AP-274, AP-275, AP-277, AP-318, AP-344, AP-345, AP-365 and AP-367 • Channels updated for AP-324, AP-325, AP-334 and AP-335
Mexico	Support added for AP-555
New Zealand	Support added for AP-504 and AP-505
Philippines	Channels updated for AP-303 and AP-303H
Taiwan	Support added for AP-504 and AP-505

1.0_72670

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 188: *1.0_72670*

Regulatory Domain	Regulatory Changes
Algeria	Channels updated for AP-387
Barbados	Channels updated for AP-387
Bolivia	Channels updated for AP-387
Burkina Faso	Support added for AP-215
Chile	Support added for AP17
Cote D'ivoire	Channels updated for AP-387
Democratic Republic of the Congo	Support added for AP-215
Ecuador	Channels updated for AP-387
Egypt	Support added for AP-387
Ghana	Channels updated for AP-387
Haiti	Channels updated for AP-387
Honduras	Support added for AP-324 and AP-325
Hong Kong	Support added for AP17, AP-504 and AP-505
Indonisia	Support added for AP-535
Jamaica	Channels updated for AP-387
Kazakhstan	Support added for AP-387
Kenya	Channels updated for AP-387
Kuwait	Channels updated for AP-387
Macau	Channels updated for AP-387
Mali	Support added for AP-215
Maritime Forward Operating Base	Support added for AP17, AP-303P, AP-318, AP-504, AP-505, AP-514,AP-515,

Regulatory Domain	Regulatory Changes
	AP-534, AP-535 and AP-555
Maritime Offshore	Support added for AP17, AP-303P, AP-318, AP-504, AP-505, AP-514,AP-515, AP-534, AP-535 and AP-555
Nigeria	Channels updated for AP-387
Pakistan	Support added for AP17 and AP-387
Papua New Guinea	Support added for AP-324 and AP-325
Republic of the Congo	Support added for AP-215
Rwanda	Channels updated for AP-387
Suriname	Support added for AP-387
Taiwan	Support added for AP17
Tanzania	Channels updated for AP-387
Thailand	Channels updated for AP-387
Tunisia	Support added for AP-387
Uganda	Channels updated for AP-387
United Arab Emirates	Support added for AP-387

1.0_72500

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 189: *1.0_72500*

Regulatory Domain	Regulatory Changes
Afghanistan	Channels updated for AP-504 and AP-505
Aland Islands	Channels updated for AP-504 and AP-505
Albania	Channels updated for AP-504 and AP-505
Andorra	Channels updated for AP-504 and AP-505
Angola	Channels updated for AP-504 and AP-505
Antigua and Barbuda	Support added for AP-314 and AP-315
Australia	Channels updated for AP-377
Austria	Channels updated for AP-504 and AP-505
Azerbaijan	Channels updated for AP-504 and AP-505
Barbados	Support added for AP17
Belarus	Channels updated for AP-504 and AP-505
Belgium	Channels updated for AP-504 and AP-505
Bolivia	Channels updated for AP-203R and AP-377
Bosnia And Herzegowina	Channels updated for AP-504 and AP-505
Botswana	Channels updated for AP-504 and AP-505
Bulgaria	Channels updated for AP-504 and AP-505
Cameroon	Channels updated for AP-504 and AP-505
Canada	Channels updated for AP-377
Croatia	Channels updated for AP-504 and AP-505
Cyprus	Channels updated for AP-504 and AP-505
Czech Republic	Channels updated for AP-504 and AP-505

Regulatory Domain	Regulatory Changes
Denmark	Channels updated for AP-504 and AP-505
Estonia	Channels updated for AP-504 and AP-505
Ethiopia	Channels updated for AP-504 and AP-505
Faroe Islands	Channels updated for AP-504 and AP-505
Finland	Channels updated for AP-504 and AP-505
France	Channels updated for AP-504 and AP-505
French Guiana	Channels updated for AP-504 and AP-505
French Polynesia	Channels updated for AP-504 and AP-505
French Southern Territories	Channels updated for AP-504 and AP-505
Georgia	Channels updated for AP-504 and AP-505
Germany	Channels updated for AP-504 and AP-505
Greece	Channels updated for AP-504 and AP-505
Greenland	Channels updated for AP-504 and AP-505
Guadeloupe	Channels updated for AP-504 and AP-505
Guernsey	Channels updated for AP-504 and AP-505
Hong Kong	Channels updated for AP-377
Hungary	Channels updated for AP-504 and AP-505
Iceland	Channels updated for AP-504 and AP-505
India	Channels updated for AP-377
Ireland	Channels updated for AP-504 and AP-505
Isle Of Man	Channels updated for AP-504 and AP-505
Italy	Channels updated for AP-504 and AP-505
Japan	Support added for AP-504 and AP-505
Jersey	Channels updated for AP-504 and AP-505
Jordan	Support added for AP-377

Regulatory Domain	Regulatory Changes
Kosovo	Channels updated for AP-504 and AP-505
Latvia	Channels updated for AP-504 and AP-505
Lebanon	Channels updated for AP-504 and AP-505
Libya	Channels updated for AP-504 and AP-505
Liechtenstein	Channels updated for AP-504 and AP-505
Lithuania	Channels updated for AP-504 and AP-505
Luxembourg	Channels updated for AP-504 and AP-505
Macedonia	Channels updated for AP-504 and AP-505
Malawi	Channels updated for AP-504 and AP-505
Malta	Channels updated for AP-504 and AP-505
Martinique	Channels updated for AP-504 and AP-505
Mauritania	Channels updated for AP-504 and AP-505
Mauritius	Channels updated for AP-504 and AP-505
Mayotte	Channels updated for AP-504 and AP-505
Moldova	Channels updated for AP-504 and AP-505
Monaco	Channels updated for AP-504 and AP-505
Montenegro	Channels updated for AP-504 and AP-505
Morocco	Channels updated for AP-504 and AP-505
Mozambique	Channels updated for AP-504 and AP-505
Myanmar	Channels updated for AP-504 and AP-505
Namibia	Channels updated for AP-504 and AP-505
Netherlands	Channels updated for AP-504 and AP-505
New Caledonia	Channels updated for AP-504 and AP-505
New Zealand	Channels updated for AP-377
Nigeria	Channels updated for AP-504 and AP-505

Regulatory Domain	Regulatory Changes
Norway	Channels updated for AP-504 and AP-505
Papua New Guinea	• Channels updated for AP-504 and AP-505 • Support added for AP-303, AP-304 and AP-305
Philippines	Support added for AP17
Poland	Channels updated for AP-504 and AP-505
Portugal	Channels updated for AP-504 and AP-505
Reunion	Channels updated for AP-504 and AP-505
Romania	Channels updated for AP-504 and AP-505
Saint Barthelemy	Channels updated for AP-504 and AP-505
Saint Lucia	Channels updated for AP-504 and AP-505
Saint Martin	Channels updated for AP-504 and AP-505
Saint Pierre And Miquelon	Channels updated for AP-504 and AP-505
San Marino	Channels updated for AP-504 and AP-505
Senegal	Channels updated for AP-504 and AP-505
Serbia	Channels updated for AP-504 and AP-505
Slovakia	Channels updated for AP-504 and AP-505
Slovenia	Channels updated for AP-504 and AP-505
Spain	Channels updated for AP-504 and AP-505
Svalbard And Jan Mayen	Channels updated for AP-504 and AP-505
Sweden	Channels updated for AP-504 and AP-505
Switzerland	Channels updated for AP-504 and AP-505
Turkey	Channels updated for AP-504 and AP-505
Turkmenistan	Channels updated for AP-504 and AP-505
United Kingdom	Channels updated for AP-504 and AP-505
Vatican City	Channels updated for AP-504 and AP-505

Regulatory Domain	Regulatory Changes
Wallis And Futuna	Channels updated for AP-504 and AP-505
Zambia	Channels updated for AP-504 and AP-505
Zimbabwe	Channels updated for AP-504 and AP-505

1.0_72277

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 190: *1.0_72277*

Regulatory Domain	Regulatory Changes
Afghanistan	Channels updated for AP17
Aland Islands	Channels updated for AP17
Albania	Channels updated for AP17 and AP-303H
Algeria	Support added for AP17
Andorra	Channels updated for AP17
Angola	Channels updated for AP17
Antigua and Barbuda	Support added for AP-303H
Austria	Channels updated for AP17
Azerbaijan	Channels updated for AP17
Bangladesh	Channels updated for AP-314 and AP-315
Belarus	Channels updated for AP17
Belgium	Channels updated for AP17
Bermuda	Support added for AP-215
Bosnia And Herzegowina	Channels updated for AP17
Botswana	Channels updated for AP17
Brunei Darussalam	Support added for AP-303H
Bulgaria	Channels updated for AP17
Cameroon	Channels updated for AP17
Cote D'ivoire	Support added for AP17
Croatia	Channels updated for AP17
Curacao	Support added for AP-303H

Regulatory Domain	Regulatory Changes
Cyprus	Channels updated for AP17
Czech Republic	Channels updated for AP17
Denmark	Channels updated for AP17
Estonia	Channels updated for AP17
Ethiopia	Channels updated for AP17
Faroe Islands	Channels updated for AP17
Finland	Channels updated for AP17
France	Channels updated for AP17
French Guiana	Channels updated for AP17
French Polynesia	Channels updated for AP17
French Southern Territories	Channels updated for AP17
Georgia	Channels updated for AP17
Germany	Channels updated for AP17
Ghana	Support added for AP17
Greece	Channels updated for AP17
Greenland	Channels updated for AP17
Grenada	Support added for AP-303H
Guadeloupe	Channels updated for AP17
Guernsey	Channels updated for AP17
Guyana	Support added for AP-303H
Haiti	Channels updated for AP-314 and AP-315
Honduras	Support added for AP-303H
Hungary	Channels updated for AP17
Iceland	Channels updated for AP17
Ireland	Channels updated for AP17

Regulatory Domain	Regulatory Changes
Isle Of Man	Channels updated for AP17
Italy	Channels updated for AP17
Jamaica	Support added for AP17
Jersey	Channels updated for AP17
Kenya	Support added for AP17
Kosovo	Channels updated for AP17
Kuwait	Support added for AP17
Lao	Support added for AP-303H
Latvia	Channels updated for AP17
Lebanon	Channels updated for AP17
Libya	Channels updated for AP17
Liechtenstein	Channels updated for AP17
Lithuania	Channels updated for AP17
Luxembourg	Channels updated for AP17
Macau	• Support added for AP17 • Channels updated for AP-314 and AP-315
Macedonia	Channels updated for AP17
Malawi	Channels updated for AP17
Malta	Channels updated for AP17
Martinique	Channels updated for AP17
Mauritania	Channels updated for AP17
Mauritius	Channels updated for AP17 and AP-303H
Mayotte	Channels updated for AP17
Moldova	Channels updated for AP17
Monaco	• Channels updated for AP17 • Support added for AP-303H

Regulatory Domain	Regulatory Changes
Montenegro	Channels updated for AP17
Morocco	Channels updated for AP17
Mozambique	Channels updated for AP17
Myanmar	Channels updated for AP17
Namibia	Channels updated for AP17
Nepal	Support added for AP17
Netherlands	Channels updated for AP17
New Caledonia	Channels updated for AP17
Nicaragua	Support added for AP-303H
Niger	Channels updated for AP-303H
Nigeria	Channels updated for AP17
Norway	Channels updated for AP17
Papua New Guinea	• Channels updated for AP17 • Support added for AP-303H
Peru	Channels updated for AP-314 and AP-315
Poland	Channels updated for AP17
Portugal	Channels updated for AP17
Qatar	Support added for AP17
Reunion	Channels updated for AP17
Romania	Channels updated for AP17
Rwanda	Support added for AP17
Saint Barthelemy	Channels updated for AP17
Saint Lucia	Channels updated for AP17
Saint Martin	Channels updated for AP17
Saint Pierre And Miquelon	Channels updated for AP17

Regulatory Domain	Regulatory Changes
Saint Vincent and the Grenadine	Support added for AP-303H
San Marino	Channels updated for AP17
Saudi Arabia	Support added for AP17
Senegal	Channels updated for AP17
Serbia	Channels updated for AP17
Slovakia	Channels updated for AP17
Slovenia	Channels updated for AP17
Spain	Channels updated for AP17
Sri Lanka	Channels updated for AP-314 and AP-315
Suriname	Channels updated for AP-314 and AP-315
Svalbard And Jan Mayen	Channels updated for AP17
Sweden	Channels updated for AP17
Switzerland	Channels updated for AP17
Tanzania	Support added for AP17
Thailand	Support added for AP17
Tunisia	Support added for AP17
Turkey	Channels updated for AP17
Turkmenistan	Channels updated for AP17
Uganda	• Channels updated for AP17 • Channels updated for AP-314 and AP-315
United Kingdom	Channels updated for AP17
Uruguay	• Support added for AP11D, AP-203H, AP-203R, AP-204, AP-214, AP-224, AP-228, AP-274, AP-277, AP-303H, AP-318, AP-324, AP-325, AP-344, AP-345, AP-365, AP-367, RAP-108 and RAP-109 • Channels updated for AP-205, AP-205H, AP-207, AP-215, AP-225, AP-275, AP-303, AP-304, AP-305, AP-314, AP-315, AP-334 and AP-335
Uzbekistan	• Channels updated for AP-314 and AP-315 • Support added for AP17
Vatican City	Channels updated for AP17

Regulatory Domain	Regulatory Changes
Wallis And Futuna	Channels updated for AP17
Zambia	Channels updated for AP17
Zimbabwe	Channels updated for AP17

1.0_72057

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 191: *1.0_72057*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-374, AP-375 and AP-377
Argentina	• Channels updated for AP-534 and AP-535 • Support added for AP-555
Barbados	Support added for AP-374, AP-375 and AP-377
Bahrain	Channels updated for AP-374, AP-375 and AP-377
Chile	• Channels updated for AP-374, AP-375 and AP-377 • Update Chile country domain for regulatory domain file • Support added for AP-387
China	Channels updated for AP-374, AP-375 and AP-377
Indonesia	Support added for AP-387
Jordan	Support added for AP-374
Kazakhstan	Channels updated for AP-374, AP-375 and AP-377
Macau	Support added for AP-374, AP-375 and AP-377
Malaysia	Support added for AP-387
Morocco	Support added for AP-534, AP-535 and AP-555
South Africa	Support added for AP-534, AP-535 and AP-555
Ukraine	Support added for AP-534, AP-535 and AP-555
Uruguay	Support added for AP-377
Uzbekistan	Support added for AP-374, AP-375 and AP-377

1.0_71892

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 192: *1.0_71892*

Regulatory Domain	Regulatory Changes
American Samoa	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17 • Support added for AP-303H
Antigua And Barbuda	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Bahrain	• Channels updated for AP-303 and AP-303H • The EIRP of channel 149-165 is updated from 33 to 23 dBm for regulatory domain file
Bahamas	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Bangladesh	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17 and AP-303
Barbados	DFS channels enabled for AP-534, AP-535 and AP-555
Bermuda	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Bolivia	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Brunei Darussalam	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Canada	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Cayman Islands	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Colombia	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Costa Rica	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Curacao	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Dominican Republic	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17

Regulatory Domain	Regulatory Changes
Ecuador	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17 and AP-303
El Salvadore	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Ethiopia	Channels updated for AP-303H
Federated States Of Micronesia	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Grenada	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Guam	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Guatemala	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Guyana	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Haiti	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Honduras	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Lao	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Maldives	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17 • Support added for AP-303 and AP-303H
Marshall Islands	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17 • Support added for AP-303H
Montserrat	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Nicaragua	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Northern Mariana Islands	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Pakistan	Support added for AP-514, AP-515, AP-534, AP-535 and AP-555
Panama	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Paraguay	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17

Regulatory Domain	Regulatory Changes
Peru	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17 and AP-303
Puerto Rico	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Saint Vincent And The Grenadines	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Suriname	DFS channels enabled for AP-535
Taiwan	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Trinidad And Tobago	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Uganda	Channels updated for AP-303H
United States of America	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Uruguay	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Us Virgin Islands	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17
Uzebekstan	Support added for AP-303
Venezuela	• DFS channels enabled for AP-534, AP-535 and AP-555 • Channels updated for AP17 and AP-303 • Support added for AP-303H
Zimbabwe	Support added for AP-303

1.0_71647

This table describes the new regulatory changes to access points and channels introduced in this release.

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 193: *1.0_71647*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP17, AP-504 and AP-505
Aland Islands	Support added for AP17, AP-504 and AP-505
Albania	Support added for AP17, AP-504 and AP-505
American Samoa	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Andorra	Support added for AP17, AP-504 and AP-505
Angola	Support added for AP17, AP-504 and AP-505
Antigua And Barbuda	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Australia	Support added for AP17
Austria	Support added for AP17, AP-504 and AP-505
Azerbaijan	Support added for AP17, AP-504 and AP-505
Bahamas	• Support added for AP17, AP-228, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Bahrain	• Support added for AP-334, AP-335, AP-365, AP-367, AP-534, AP-535 and AP-555 • Channels updated for AP-318
Bangladesh	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Barbados	Channels updated for AP-534, AP-535 and AP-555
Belarus	Support added for AP17, AP-504 and AP-505
Belgium	Support added for AP17, AP-504 and AP-505
Bermuda	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Bolivia	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555

Regulatory Domain	Regulatory Changes
Bosnia and Herzegowina	Support added for AP17, AP-504 and AP-505
Botswana	Support added for AP17, AP-504 and AP-505
Brunei Darussalam	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Bulgaria	Support added for AP17, AP-504 and AP-505
Cameroon	Support added for AP17, AP-504 and AP-505
Canada	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Cayman Islands	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Chile	Support added for AP-303P
Colombia	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Costa Rica	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Croatia	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Curacao	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Cyprus	Support added for AP17, AP-504 and AP-505
Czech Republic	Support added for AP17, AP-504 and AP-505
Denmark	Support added for AP17, AP-504 and AP-505
Dominican Republic	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Ecuador	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Egypt	Support added for AP-534 and AP-535
El Salvadore	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Estonia	Support added for AP17, AP-504 and AP-505
Ethiopia	Support added for AP17, AP-504 and AP-505
Faroe Islands	Support added for AP17, AP-504 and AP-505

Regulatory Domain	Regulatory Changes
Federated States of Micronesia	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Finland	Support added for AP17, AP-504 and AP-505
France	Support added for AP17, AP-504 and AP-505
French Guiana	Support added for AP17, AP-504 and AP-505
French Polynesia	Support added for AP17, AP-504 and AP-505
French Southern Territories	Support added for AP17, AP-504 and AP-505
Georgia	Support added for AP17, AP-504 and AP-505
Germany	Support added for AP17, AP-504 and AP-505
Greece	Support added for AP17, AP-504 and AP-505
Greenland	Support added for AP17, AP-504 and AP-505
Grenada	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Guadeloupe	Support added for AP17, AP-504 and AP-505
Guam	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Guatemala	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Guernsey	Support added for AP17, AP-504 and AP-505
Guyana	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Haiti	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Honduras	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Hungary	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Iceland	Support added for AP17, AP-504 and AP-505
Indonesia	Support added for AP-303P
Ireland	Support added for AP17, AP-504 and AP-505

Regulatory Domain	Regulatory Changes
Isle of Man	Support added for AP17, AP-504 and AP-505
Israel	Channels updated for AP-555
Italy	Support added for AP17, AP-504 and AP-505
Jersey	Support added for AP17, AP-504 and AP-505
Kazakhstan	Support added for AP-534, AP-535 and AP-555
Kosovo	Support added for AP17, AP-504 and AP-505
Lao	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Latvia	Support added for AP17, AP-504 and AP-505
Lebanon	Support added for AP17, AP-504 and AP-505
Libya	Support added for AP17, AP-504 and AP-505
Liechtenstein	Support added for AP17, AP-504 and AP-505
Lithuania	Support added for AP17, AP-504 and AP-505
Luxembourg	Support added for AP17, AP-504 and AP-505
Macedonia	Support added for AP17, AP-504 and AP-505
Malawi	Support added for AP17, AP-504 and AP-505
Malaysia	• Channels updated for AP-534 and AP-535 • Support added for AP-555
Maldives	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Malta	Support added for AP17, AP-504 and AP-505
Marshall Islands	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Martinique	Support added for AP17, AP-504 and AP-505
Mauritania	Support added for AP17, AP-504 and AP-505
Mauritius	Support added for AP17, AP-504 and AP-505
Mayotte	Support added for AP17, AP-504 and AP-505

Regulatory Domain	Regulatory Changes
Moldova	Support added for AP17, AP-504 and AP-505
Monaco	Support added for AP17, AP-504 and AP-505
Montenegro	Support added for AP17, AP-504 and AP-505
Montserrat	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Morocco	Support added for AP17, AP-504 and AP-505
Mozambique	Support added for AP17, AP-504 and AP-505
Myanmar	Support added for AP17, AP-504 and AP-505
Namibia	Support added for AP17, AP-504 and AP-505
Netherlands	Support added for AP17, AP-504 and AP-505
New Caledonia	Support added for AP17, AP-504 and AP-505
New Zealand	Support added for AP17
Nicaragua	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Nigeria	Support added for AP17, AP-504 and AP-505
Northern Mariana Islands	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Norway	Support added for AP17, AP-504 and AP-505
Panama	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Papua New Guinea	Support added for AP17, AP-504 and AP-505
Paraguay	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Peru	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Poland	Support added for AP17, AP-504 and AP-505
Portugal	Support added for AP17, AP-504 and AP-505
Puerto Rico	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555

Regulatory Domain	Regulatory Changes
Reunion	Support added for AP17, AP-504 and AP-505
Romania	Support added for AP17, AP-504 and AP-505
Russia	Support added for AP-387
Saint Barthelemy	Support added for AP17, AP-504 and AP-505
Saint Lucia	Support added for AP17, AP-504 and AP-505
Saint Martin	Support added for AP17, AP-504 and AP-505
Saint Pierre and Miquelon	Support added for AP17, AP-504 and AP-505
Saint Vincent and The Grenadines	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
San Marino	Support added for AP17, AP-504 and AP-505
Senegal	Support added for AP17, AP-504 and AP-505
Serbia	Support added for AP17, AP-504 and AP-505
Slovakia	Support added for AP17, AP-504 and AP-505
Slovenia	Support added for AP17, AP-504 and AP-505
Spain	Support added for AP17, AP-504 and AP-505
Suriname	• Support added for AP17, AP-303P, AP-504 and AP-505 • Channels updated for AP-534 and AP-535
Svalbard and Jan Mayen	Support added for AP17, AP-504 and AP-505
Sweden	Support added for AP17, AP-504 and AP-505
Switzerland	Support added for AP17, AP-504 and AP-505
Taiwan	Channels updated for AP-534, AP-535 and AP-555
Trinidad and Tobago	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Turkey	Support added for AP17, AP-504 and AP-505
Turkmenistan	Support added for AP17, AP-504 and AP-505
Uganda	Support added for AP17
United Kingdom	Support added for AP17, AP-504 and AP-505

Regulatory Domain	Regulatory Changes
United States of America	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Uruguay	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Us Virgin Islands	• Support added for AP17, AP-303H, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Uzbekistan	Support added for AP-228, AP-303H and AP-303P
Vatican City	Support added for AP17, AP-504 and AP-505
Venezuela	• Support added for AP17, AP-504 and AP-505 • Channels updated for AP-534, AP-535 and AP-555
Wallis and Futuna	Support added for AP17, AP-504 and AP-505
Zambia	Support added for AP17, AP-504 and AP-505
Zimbabwe	Support added for AP17, AP-504 and AP-505

1.0_71451

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 194: *1.0_71451*

Regulatory Domain	Regulatory Changes
American Samoa	DFS bands is enabled for AP-387
Antigua and Barbuda	DFS bands is enabled for AP-387
Bahamas	DFS bands is enabled for AP-387
Bangladesh	DFS bands is enabled for AP-387
Barbados	DFS bands is enabled for AP-387
Bermuda	DFS bands is enabled for AP-387
Bolivia	DFS bands is enabled for AP-387
Brazil	Support added for AP-534, AP-535 and AP-555
Canada	DFS bands and 5150-5250MHz is enabled for AP-387
Cayman Islands	DFS bands is enabled for AP-387
Chile	Support added for AP-514 and AP-515
Colombia	DFS bands is enabled for AP-387
Costa Rica	DFS bands is enabled for AP-387
Curacao	DFS bands is enabled for AP-387
Dominican Republic	DFS bands is enabled for AP-387
Ecuador	DFS bands is enabled for AP-387
El Salvadore	DFS bands is enabled for AP-387
Federated States of Micronesia	DFS bands is enabled for AP-387
Grenada	DFS bands is enabled for AP-387
Guam	DFS bands is enabled for AP-387
Guatemala	DFS bands is enabled for AP-387

Regulatory Domain	Regulatory Changes
Guyana	DFS bands is enabled for AP-387
Haiti	DFS bands is enabled for AP-387
Honduras	DFS bands is enabled for AP-387
Jamaica	Support added for AP-203H, AP-204, AP-214, AP-215, AP-224, AP-228, AP-274, AP-275, AP-277, AP-324, AP-325, AP-365 and AP-367
Kenya	Support added for AP-534 and AP-535
Kuwait	Support added for AP-534 and AP-535
Lao	DFS bands is enabled for AP-387
Maldives	DFS bands is enabled for AP-387
Mali	Support added for AP-303
Marshall Islands	DFS bands is enabled for AP-387
Mexico	Support added for AP-534 and AP-535
Nicaragua	DFS bands is enabled for AP-387
Nigeria	Support added for AP-534 and AP-535
Northern Mariana Islands	DFS bands is enabled for AP-387
Oman	Support added for AP-514 and AP-515
Panama	DFS bands is enabled for AP-387
Paraguay	DFS bands is enabled for AP-387
Peru	DFS bands is enabled for AP-387
Philippines	5GHz operation is enabled for AP-387
Puerto Rico	DFS bands is enabled for AP-387
Quatar	Support added for AP-534, AP-535 and AP-555
Rwanda	Support added for AP-534 and AP-535
Saint Vincent and The Grenadines	DFS bands is enabled for AP-387
Saudi Arabia	5GHz and 60GHz operation is enabled for AP-387
Singapore	• 5GHz and 60GHz operation is enabled for AP-387

Regulatory Domain	Regulatory Changes
	• Support added for AP-534, AP-535 and AP-555
Suriname	Support added for AP-514 and AP-515
Trinidad And Tobago	DFS bands is enabled for AP-387
United States of America	DFS bands is enabled for AP-387
Uruguay	DFS bands is enabled for AP-387
Us Virgin Islands	DFS bands is enabled for AP-387
Uzbekistan	60GHz operation is enabled for AP-387
Venezuela	• Support added for AP-514 and AP-515 • DFS bands is enabled for AP-387

1.0_71313

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 195: *1.0_71313*

Regulatory Domain	Regulatory Changes
Afghanistan	Channels updated for AP-555
Aland Islands	Channels updated for AP-555
Albania	Channels updated for AP-387 and AP-555
American Samoa	Channels updated for AP-387
Andorra	Channels updated for AP-555
Angola	Channels updated for AP-555
Australia	Channels updated for AP-387 and AP-555
Austria	Channels updated for AP-387 and AP-555
Azerbaijan	Channels updated for AP-555
Bahamas	Channels update for AP-387
Belarus	Channels updated for AP-555
Belgium	Channels updated for AP-387 and AP-555
Bosnia And Herzegowina	Channels updated for AP-387 and AP-555
Botswana	Channels updated for AP-555
Bulgaria	Channels updated for AP-387 and AP-555
Cameroon	Channels updated for AP-555
Canada	Channels updated for AP-387
China	Channels updated for AP-387
Cote D'ivoire	Support added for AP-555
Croatia	Channels updated for AP-387 and AP-555
Cyprus	Channels updated for AP-387 and AP-555

Regulatory Domain	Regulatory Changes
Czech Republic	Channels updated for AP-387 and AP-555
Denmark	Channels updated for AP-387 and AP-555
Egypt	Support added for AP-555
Estonia	Channels updated for AP-387 and AP-555
Ethiopia	Channels updated for AP-555
Faroe Islands	Channels updated for AP-555
Federated States Of Micronesia	Channels updated for AP-387
Finland	Channels updated for AP-387 and AP-555
France	Channels updated for AP-387 and AP-555
French Guiana	Channels updated for AP-555
French Polynesia	Channels updated for AP-555
French Southern Territories	Channels updated for AP-555
Georgia	Channels updated for AP-555
Germany	Channels updated for AP-387 and AP-555
Ghana	Support added for AP-555
Greece	Channels updated for AP-387 and AP-555
Greenland	Channels updated for AP-555
Guadeloupe	Channels updated for AP-555
Guam	Channels updated for AP-387
Guernsey	Channels updated for AP-555
Hong Kong	• Channels updated for AP-387 • Support added for AP-534, AP-535 and AP-555
Hungary	Channels updated for AP-387 and AP-555
Iceland	Channels updated for AP-387 and AP-555
India	Support added for AP-555

Regulatory Domain	Regulatory Changes
Ireland	Channels updated for AP-387 and AP-555
Isle Of Man	Channels updated for AP-555
Italy	Channels updated for AP-387 and AP-555
Jamaica	Support added for AP-555
Japan	• Support added for AP-555 • Channels updated for AP-387
Jersey	Channels updated for AP-555
Kenya	Support added for AP-555
Kosovo	Channels updated for AP-387 and AP-555
Kuwait	Support added for AP-555
Latvia	Channels updated for AP-387 and AP-555
Lebanon	Channels updated for AP-555
Libya	Channels updated for AP-555
Liechtenstein	Channels updated for AP-387 and AP-555
Lithuania	Channels updated for AP-387 and AP-555
Luxembourg	Channels updated for AP-387 and AP-555
Macau	Support added for AP-555
Macedonia	Channels updated for AP-387 and AP-555
Malawi	Channels updated for AP-555
Malta	Channels updated for AP-387 and AP-555
Marshall Islands	Channels updated for AP-387
Martinique	Channels updated for AP-555
Mauritania	Channels updated for AP-555
Mauritius	Channels updated for AP-555
Mayotte	Channels updated for AP-555

Regulatory Domain	Regulatory Changes
Mexico	Channels updated for AP-387
Moldova	Channels updated for AP-555
Monaco	Channels updated for AP-555
Montenegro	Channels updated for AP-387 and AP-555
Morocco	Channels updated for AP-555
Mozambique	Channels updated for AP-555
Myanmar	Channels updated for AP-555
Namibia	Channels updated for AP-555
Nepal	Support added for AP-555
Netherlands	Channels updated for AP-387 and AP-555
New Caledonia	Channels updated for AP-555
New Zealand	Channels updated for AP-387 and AP-555
Nigeria	Channels updated for AP-555
Northern Mariana Islands	Channels updated for AP-387
Norway	Channels updated for AP-387 and AP-555
Oman	• Support added for AP-534, AP-535 and AP-555 • Channels 149-165 is disabled for indoor APs
Papua New Guinea	Channels updated for AP-555
Peru	Channels updated for AP-387
Philippines	• Channels updated for AP-387 • Support added for AP-555
Poland	Channels updated for AP-387 and AP-555
Portugal	Channels updated for AP-387 and AP-555
Puerto Rico	Channels updated for AP-387
Reunion	Channels updated for AP-555
Romania	Channels updated for AP-387 and AP-555

Regulatory Domain	Regulatory Changes
Rwanda	Support added for AP-555
Rwanda	Channels updated for AP-555
Saint Barthelemy	Channels updated for AP-555
Saint Lucia	Channels updated for AP-555
Saint Martin	Channels updated for AP-555
Saint Pierre And Miquelon	Channels updated for AP-555
San Marino	Channels updated for AP-555
Saudi Arabia	Support added for AP-555
Senegal	Channels updated for AP-555
Serbia	Channels updated for AP-387 and AP-555
Slovakia	Channels updated for AP-387 and AP-555
Slovenia	Channels updated for AP-387 and AP-555
South Korea	Support added for AP-555
Spain	Channels updated for AP-387 and AP-555
Sri Lanka	Support added for AP-555
Suriname	Support added for AP-555
Svalbard And Jan Mayen	Channels updated for AP-555
Sweden	Channels updated for AP-387 and AP-555
Switzerland	Channels updated for AP-387 and AP-555
Taiwan	Support added for AP-555
Tanzania	Channels updated for AP-555
Thailand	Support added for AP-555
Turkey	Channels updated for AP-387 and AP-555
Turkmenistan	Channels updated for AP-555
Uganda	Support added for AP-555

Regulatory Domain	Regulatory Changes
Uganda	Channels updated for AP-555
United Kingdom	Channels updated for AP-387 and AP-555
United States	Channels updated for AP-387
Us Virgin Islands	Channels updated for AP-387
Uzbekistan	Support added for AP-555
Vatican City	Channels updated for AP-555
Vietnam	Support added for AP-534, AP-535 and AP-555
Wallis And Futuna	Channels updated for AP-555
Zambia	Channels updated for AP-555
Zimbabwe	Channels updated for AP-555

1.0_71072

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 196: *1.0_71072*

Regulatory Domain	Regulatory Changes
Afghanistan	Channels updated for AP-534 and AP-535
Aland Islands	Channels updated for AP-534 and AP-535
Albania	Channels updated for AP-387, AP-534 and AP-535
American Samoa	Channels updated for AP-387, AP-534 and AP-535
Andorra	Channels updated for AP-534 and AP-535
Angola	Channels updated for AP-534 and AP-535
Antigua And Barbuda	Channels updated for AP-534 and AP-535
Argentina	Support added for AP-534 and AP-535
Australia	• Support added for AP-555 • Channels updated for AP-387, AP-534 and AP-535
Austria	Channels updated for AP-387, AP-534 and AP-535
Azerbaijan	Channels updated for AP-534 and AP-535
Bahamas	Channels updated for AP-387, AP-534 and AP-535
Bangladesh	Channels updated for AP-304, AP-305, AP-534 and AP-535
Barbados	Channels updated for AP-304, AP-305, AP-534 and AP-535
Belarus	Channels updated for AP-534 and AP-535
Belgium	Channels updated for AP-387, AP-534 and AP-535
Bermuda	Channels updated for AP-534 and AP-535
Bolivia	Channels updated for AP-304, AP-305, AP-534 and AP-535
Bosnia And Herzegowina	Channels updated for AP-387, AP-534 and AP-535
Botswana	• Support added for AP-304 and AP-305 • Channels updated for AP-534 and AP-535

Regulatory Domain	Regulatory Changes
Brunei Darussalam	Channels updated for AP-534 and AP-535
Bulgaria	Channels updated for AP-387, AP-534 and AP-535
Cameroon	Channels updated for AP-534 and AP-535
Canada	Channels updated for AP-387
Cayman Islands	Channels updated for AP-534 and AP-535
Chile	Channels updated for AP-304 and AP-305
China	Channels updated for AP-387
Colombia	Channels updated for AP-304, AP-305, AP-534 and AP-535
Costa Rica	Channels updated for AP-304, AP-305, AP-534 and AP-535
Cote D'ivoire	Support added for AP-304, AP-305, AP-534, AP-535 and AP-555
Croatia	Channels updated for AP-387, AP-534 and AP-535
Curacao	Channels updated for AP-534 and AP-535
Cyprus	Channels updated for AP-387, AP-534 and AP-535
Czech Republic	Channels updated for AP-387, AP-534 and AP-535
Denmark	Channels updated for AP-387, AP-534 and AP-535
Dominican Republic	Channels updated for AP-304, AP-305, AP-534 and AP-535
Ecuador	Channels updated for AP-534 and AP-535
Egypt	• Support added for AP-555 • Channels updated for AP-304 and AP-305
El Salvadore	Channels updated for AP-534 and AP-535
Estonia	Channels updated for AP-387, AP-534 and AP-535
Ethiopia	Channels updated for AP-534 and AP-535
Faroe Islands	Channels updated for AP-534 and AP-535
Federated States Of Micronesia	Channels updated for AP-387, AP-534 and AP-535
Finland	Channels updated for AP-387, AP-534 and AP-535

Regulatory Domain	Regulatory Changes
France	Channels updated for AP-387. AP-534 and AP-535
French Guiana	Channels updated for AP-534 and AP-535
French Polynesia	Channels updated for AP-534 and AP-535
French Southern Territories	Channels updated for AP-534 and AP-535
Georgia	Channels updated for AP-534 and AP-535
Germany	Channels updated for AP-387, AP-534 and AP-535
Ghana	Support added for AP-534, AP-535 and AP-555
Greece	Channels updated for AP-387, AP-534 and AP-535
Greenland	Channels updated for AP-534 and AP-535
Grenada	Channels updated for AP-534 and AP-535
Guadeloupe	Channels updated for AP-534 and AP-535
Guam	Channels updated for AP-387, AP-534 and AP-535
Guatemala	Channels updated for AP-534 and AP-535
Guernsey	Channels updated for AP-534 and AP-535
Guyana	Channels updated for AP-534 and AP-535
Haiti	Channels updated for AP-534 and AP-535
Honduras	Channels updated for AP-534 and AP-535
Hong Kong	Channels updated for AP-387
Hungary	Channels updated for AP-387, AP-534 and AP-535
Iceland	Channels updated for AP-387, AP-534 and AP-535
India	Support added for AP-555
Ireland	Channels updated for AP-387, AP-534 and AP-535
Isle Of Man	Channels updated for AP-534 and AP-535
Italy	Channels updated for AP-387, AP-534 and AP-535
Jamaica	Support added for AP-534, AP-535 and AP-555

Regulatory Domain	Regulatory Changes
Japan	• Channels upfated for AP-387 • Support added for AP-555
Jersey	Channels updated for AP-534 and AP-535
Kenya	Support added for AP-555
Kosovo	Channels updated for AP-387, AP-534 and AP-535
Kuwait	Support added for AP-555
Lao	Channels updated for AP-534 and AP-535
Latvia	Channels updated for AP-387, AP-534 and AP-535
Lebanon	Channels updated for AP-534 and AP-535
Libya	Channels updated for AP-534 and AP-535
Liechtenstein	Channels updated for AP-387, AP-534 and AP-535
Lithuania	Channels updated for AP-387, AP-534 and AP-535
Luxembourg	Channels updated for AP-387, AP-534 and AP-535
Macau	Support added for AP-534, AP-535 and AP-555
Macedonia	Channels updated for AP-534 and AP-535
Macedonia	Channels updated for AP-387
Malawi	• Support added for AP-304 and AP-305 • Channels updated for AP-534 and AP-535
Malaysia	Support added for AP-534 and AP-535
Maldives	Channels updated for AP-304, AP-305, AP-534 and AP-535
Malta	Channels updated for AP-387, AP-534 and AP-535
Marshall Islands	Channels updated for AP-387, AP-534 and AP-535
Martinique	Channels updated for AP-534 and AP-535
Mauritania	Channels updated for AP-534 and AP-535
Mauritius	Channels updated for AP-534 and AP-535
Mayotte	Channels updated for AP-534 and AP-535

Regulatory Domain	Regulatory Changes
Mexico	• Channels updated for AP-387 • Support added for AP-387
Moldova	Channels updated for AP-534 and AP-535
Monaco	Channels updated for AP-534 and AP-535
Montenegro	Channels updated for AP-387, AP-534 and AP-535
Montserrat	Channels updated for AP-534 and AP-535
Morocco	Channels updated for AP-534 and AP-535
Mozambique	Channels updated for AP-534 and AP-535
Myanmar	Channels updated for AP-534 and AP-535
Namibia	Channels updated for AP-534 and AP-535
Nepal	Support added for AP-555
Netherlands	Channels updated for AP-387, AP-534 and AP-535
New Caledonia	Channels updated for AP-534 and AP-535
New Zealand	• Support added for AP-555 • Channels updated for AP-387, AP-534 and AP-535
Nicaragua	Channels updated for AP-534 and AP-535
Northern Mariana Islands	Channels updated for AP-387, AP-534 and AP-535
Norway	Channels updated for AP-387, AP-534 and AP-535
Panama	Channels updated for AP-534 and AP-535
Papua New Guinea	Channels updated for AP-534 and AP-535
Paraguay	Channels updated for AP-534 and AP-535
Peru	Channels updated for AP-387, AP-534 and AP-535
Philippines	• Channels updated for AP-387 • Support added for AP-535
Poland	Channels updated for AP-387, AP-534 and AP-535
Portugal	Channels updated for AP-387, AP-534 and AP-535
Puerto Rico	Channels updated for AP-387, AP-534 and AP-535

Regulatory Domain	Regulatory Changes
Reunion	Channels updated for AP-534 and AP-535
Romania	Channels updated for AP-387, AP-534 and AP-535
Rwanda	Support added for AP-555
Saint Barthelemy	Channels updated for AP-534 and AP-535
Saint Lucia	Channels updated for AP-534 and AP-535
Saint Martin	Channels updated for AP-534 and AP-535
Saint Pierre And Miquelon	Channels updated for AP-534 and AP-535
Saint Vincent And The Grenadines	Channels updated for AP-534 and AP-535
San Marino	Channels updated for AP-534 and AP-535
Saudi Arabia	Support added for AP-534, AP-535 and AP-555
Senegal	Channels updated for AP-534 and AP-535
Serbia	Channels updated for AP-387, AP-534 and AP-535
Slovakia	Channels updated for AP-387, AP-534 and AP-535
Slovenia	Channels updated for AP-387, AP-534 and AP-535
South Korea	• Support added for AP-555 • Channels updated for AP-534 and AP-535
Spain	Channels updated for AP-387, AP-534 and AP-535
Sri Lanka	Support added for AP-534, AP-535 and AP-555
Suriname	Support added for AP-534 and AP-535
Suriname	• Support added for AP-555 • Channels updated for AP-534 and AP-535
Svalbard And Jan Mayen	Channels updated for AP-534 and AP-535
Sweden	Channels updated for AP-387, AP-534 and AP-535
Switzerland	Channels updated for AP-387, AP-534 and AP-535
Taiwan	Support added for AP-534, AP-535 and AP-555
Tanzania	Channels updated for AP-304, AP-305, AP-534 and AP-535

Regulatory Domain	Regulatory Changes
Thailand	Support added for AP-534, AP-535 and AP-555
Thailand	Channels updated for AP-534 and AP-535
Trinidad And Tobago	Channels updated for AP-534 and AP-535
Tunisia	Support added for AP-304 and AP-305
Turkey	Channels updated for AP-387, AP-534 and AP-535
Turkmenistan	Channels updated for AP-534 and AP-535
Uganda	Support added for AP-534 and AP-535
United Kingdom	Channels updated for AP-387, AP-534 and AP-535
United States of America	Channels updated for AP-387, AP-534 and AP-535
Uruguay	Channels updated for AP-534 and AP-535
Us Virgin Islands	Channels updated for AP-387, AP-534 and AP-535
Uzbekistan	Support added for AP-387, AP-534, AP-535 and AP-555
Vatican City	Channels updated for AP-534 and AP-535
Venezuela	Channels updated for AP-534 and AP-535
Wallis And Futuna	Channels updated for AP-534 and AP-535
Zambia	Channels updated for AP-534 and AP-535
Zimbabwe	• Support added for AP-304 and AP-305 • Channels updated for AP-534 and AP-535

1.0_70855

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 197: *1.0_70855*

Regulatory Domain	Regulatory Changes
Afghanistan	• Channels updated for AP-207 • Support added for AP-314
Aland Islands	Channels updated for AP-207
Albania	Channels updated for AP-207
Algeria	Channels updated for AP-207, AP-314 and AP-315
Andorra	Channels updated for AP-207
Angola	Channels updated for AP-207
Argentina	Channels updated for AP-207, AP-314, AP-315, AP-334 and AP-335
Australia	Channels updated for AP-534 and AP-535
Austria	Channels updated for AP-207
Barbados	Support added for AP-534 and AP-535
Bahrain	Channels updated for AP-314 and AP-315
Bangladesh	Channels updated for AP-207
Belgium	Channels updated for AP-207
Bolivia	Channels updated for AP-207, AP-334 and AP-335
Bosnia And Herzegowina	Channels updated for AP-207
Botswana	• Channels updated for AP-207 • Support added for AP-314, AP-334 and AP-335
Brazil	Channels updated for AP-314, AP-315, AP-334 and AP-335
Bulgaria	Channels updated for AP-207
Cayman Islands	Support added for AP-314 and AP-315
Cameroon	Channels updated for AP-207, AP-314 and AP-315

Regulatory Domain	Regulatory Changes
Chile	Channels updated for AP-314 and AP-315
China	Channels updated for AP-314, AP-315, AP-334 and AP-335
Colombia	Channels updated for AP-207, AP-314, AP-315, AP-334 and AP-335
Costa Rica	• Channels updated for AP-314 and AP-315 • Support added for AP-334 and AP-335
Cotes d'Ivories	Support added for AP-207, AP-315, AP-334 and AP-335
Croatia	• Channels updated for AP-207 • Support added for AP-365 and AP-367
Cyprus	Channels updated for AP-207
Czech Republic	Channels updated for AP-207
Denmark	Channels updated for AP-207
Ecuador	• Channels updated for AP-314 and AP-315 • Support added for AP-334 and AP-335
Estonia	Channels updated for AP-207
Ethiopia	Channels updated for AP-207, AP-314 and AP-315
Faroe Islands	Channels updated for AP-207
Finland	Channels updated for AP-207
France	Channels updated for AP-207
French Guiana	Channels updated for AP-207
French Polynesia	Channels updated for AP-207
French Southern Territories	Channels updated for AP-207
Georgia	Channels updated for AP-207
Germany	Channels updated for AP-207
Greece	Channels updated for AP-207
Greenland	Channels updated for AP-207
Guadeloupe	Channels updated for AP-207
Guernsey	Channels updated for AP-207

Regulatory Domain	Regulatory Changes
Hungary	Channels updated for AP-207
Iceland	Channels updated for AP-207
India	• Channels updated for AP-314, AP-315, AP-334 and AP-335 • Support added for AP-534 and AP-535
Ireland	Channels updated for AP-207
Isle Of Man	Channels updated for AP-207
Italy	Channels updated for AP-207
Japan	Support added for AP-534 and AP-535
Jersey	Channels updated for AP-207
Jordan	Channels updated for AP-334 and AP-335
Kazakhstan	Channels updated for AP-314, AP-315, AP-334 and AP-335
Kosovo	Channels updated for AP-207
Latvia	Channels updated for AP-207
Libya	• Channels updated for AP-207 • Support added for AP-314, AP-334 and AP-335
Liechtenstein	Channels updated for AP-207
Lithuania	Channels updated for AP-207
Luxembourg	Channels updated for AP-207
Macedonia	Channels updated for AP-207
Malawi	• Channels updated for AP-207 • Support added for AP-314, AP-334 and AP-335
Malaysia	Channels updated for AP-314, AP-315, AP-334 and AP-335
Maldives	• Channels updated for AP-314, AP-315, AP-334 and AP-335 • Support added for AP-207
Malta	Channels updated for AP-207
Martinique	Channels updated for AP-207
Mauritania	Channels updated for AP-207

Regulatory Domain	Regulatory Changes
Mauritius	Channels updated for AP-207
Moldova	Channels updated for AP-207
Monaco	Channels updated for AP-207
Montenegro	Channels updated for AP-207
Mozambique	Channels updated for AP-207
Myanmar	Channels updated for AP-207
Namibia	Channels updated for AP-207
Nepal	Support added for AP-207, AP-314, AP-334 and AP-335
Netherlands	Channels updated for AP-207
New Caledonia	Channels updated for AP-207
New Zealand	Channels updated for AP-534 and AP-535
Nigeria	• Channels updated for AP-314 and AP-315 • Support added for AP-334 and AP-335
Norway	Channels updated for AP-207
Oman	Channels updated for AP-314 and AP-315
Pakistan	Channels updated for AP-314, AP-315, AP-334 and AP-335
Peru	Channels updated for AP-207
Philippines	• Channels updated for AP-314, AP-315, AP-334 and AP-335 • Support added for AP-534
Poland	Channels updated for AP-207
Portugal	Channels updated for AP-207
Reunion	Channels updated for AP-207
Romania	Channels updated for AP-207
Saint Barthelemy	Channels updated for AP-207
Saint Martin	Channels updated for AP-207
Saint Pierre And Miquelon	Channels updated for AP-207

Regulatory Domain	Regulatory Changes
San Marino	Channels updated for AP-207
Singapore	Channels updated for AP-314, AP-315, AP-334 and AP-335
Slovakia	Channels updated for AP-207
Slovenia	Channels updated for AP-207
South Africa	Channels updated for AP-314, AP-315, AP-334 and AP-335
South Korea	Support added for AP-534 and AP-535
Spain	Channels updated for AP-207
Sri Lanka	Channels updated for AP-334 and AP-335
Suriname	Channels updated for AP-334 and AP-335
Svalbard And Jan Mayen	Channels updated for AP-207
Sweden	Channels updated for AP-207
Switzerland	Channels updated for AP-207
Taiwan	Channels updated for AP-314, AP-315, AP-334 and AP-335
Tanzania	Channels updated for AP-207, AP-314 and AP-315
Thailand	Channels updated for AP-314 and AP-315
Turkey	Channels updated for AP-207
Uganda	• Channels updated for AP-314 and AP-315 • Support added for AP-334 and AP-335
Ukraine	Channels updated for AP-314, AP-315, AP-334 and AP-335
United Kingdom	Channels updated for AP-207
Uzbekistan	Support added for AP-514 and AP-515
Vatican City	Channels updated for AP-207
Vietnam	Channels updated for AP-314, AP-315, AP-334 and AP-335
Wallis And Futuna	Channels updated for AP-207
Zambia	Channels updated for AP-207
Zimbabwe	• Channels updated for AP-207 • Support added for AP-334 and AP-335

1.0_70671

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 198: *1.0_70671*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-534 and AP-535
Argentina	Channels updated for AP-303P and AP-514
Canada	Channels updated for AP-387
China	Support added for AP-303P
Ghana	Support added for AP-387
Israel	Support added for AP-534 and AP-535
Jamaica	Support added for AP-387
Jordan	Support added for AP-534 and AP-535
Macau	Support added for AP-387
Russia	Support added for AP-534 and AP-535
Thailand	Support added for AP-387
Tunisia	Support added for AP-534 and AP-535
United Arab Emirates	Support added for AP-534 and AP-535

1.0_70537

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 199: *1.0_70537*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP-555
Aland Islands	Support added for AP-555
Albania	Support added for AP-555
Algeria	• Support added for AP-555 • Channels updated for AP-303P
American Samoa	Support added for AP-555
Andorra	Support added for AP-555
Angola	Support added for AP-555
Antigua And Barbuda	Support added for AP-555
Argentina	Support added for AP-514 and AP-515
Austria	Support added for AP-555
Azerbaijan	Support added for AP-555
Bahamas	Support added for AP-555
Bahrain	Support added for AP-303H
Bangladesh	Support added for AP-303H and AP-555
Barbados	Support added for AP-303H and AP-555
Belarus	Support added for AP-555
Belgium	Support added for AP-555
Bermuda	Support added for AP-555
Bolivia	Support added for AP-303H and AP-555
Bosnia And Herzegowina	Support added for AP-555

Regulatory Domain	Regulatory Changes
Botswana	Support added for AP-303H and AP-555
Brunei Darussalam	Support added for AP-555
Bulgaria	Support added for AP-555
Cameroon	Support added for AP-555
Canada	Support added for AP-387 and AP-555
Cayman Islands	Support added for AP-303H and AP-555
Chile	Channels updated for AP-303H
Colombia	• Channels updated for AP-303H • Support added for AP-555
Costa Rica	Support added for AP-555
Cote D'ivoire	Support added for AP-303H
Croatia	Support added for AP-555
Curacao	Support added for AP-555
Cyprus	Support added for AP-555
Czech Republic	Support added for AP-555
Denmark	Support added for AP-555
Dominican Republic	Support added for AP-555
Ecuador	• Channels updated for AP-303H • Support added for AP-555
El Salvadore	Support added for AP-555
Estonia	Support added for AP-555
Ethiopia	Support added for AP-555
Faroe Islands	Support added for AP-555
Federated States Of Micronesia	Support added for AP-555
Finland	Support added for AP-555
France	Support added for AP-555

Regulatory Domain	Regulatory Changes
French Guiana	Support added for AP-555
French Polynesia	Support added for AP-555
French Southern Territories	Support added for AP-555
Georgia	Support added for AP-555
Germany	Support added for AP-555
Greece	Support added for AP-555
Greenland	Support added for AP-555
Grenada	Support added for AP-555
Guadeloupe	Support added for AP-555
Guam	Support added for AP-555
Guatemala	Support added for AP-555
Guernsey	Support added for AP-555
Guyana	Support added for AP-555
Haiti	Support added fo AP-303H and AP-555
Honduras	Support added for AP-555
Hungary	Support added for AP-555
Iceland	Support added for AP-555
Indonesia	Support added for AP-514 and AP-515
Ireland	Support added for AP-555
Isle Of Man	Support added for AP-555
Israel	Support added for AP-555
Italy	Support added for AP-555
Jamaica	Support added for AP-303H
Jersey	Support added for AP-555
Jordan	Support added for AP-555

Regulatory Domain	Regulatory Changes
Kazakhstan	Support added for AP-303H
Kosovo	Support added for AP-555
Kuwait	Channels updated for AP-303H
Lao	Support added for AP-555
Latvia	Support added for AP-555
Lebanon	Support added for AP-555
Libya	Support added for AP-303H and AP-555
Liechtenstein	Support added for AP-555
Lithuania	Support added for AP-555
Luxembourg	Support added for AP-555
Macau	Support added for AP-303H
Macedonia	Support added for AP-555
Malawi	Support added for AP-303H and AP-555
Maldives	Support added for AP-555
Malta	Support added for AP-555
Marshall Islands	Support added for AP-555
Martinique	Support added for AP-555
Mauritania	Support added for AP-555
Mauritius	Support added for AP-555
Mayotte	Support added for AP-555
Mexico	Channels updated for AP-514 and AP-515
Moldova	Support added for AP-555
Monaco	Support added for AP-555
Montenegro	Support added for AP-555
Montserrat	Support added for AP-555

Regulatory Domain	Regulatory Changes
Morocco	Support added for AP-555
Mozambique	Support added for AP-555
Myanmar	Support added for AP-555
Namibia	Support added for AP-555
Nepal	Support added for AP-303H
Netherlands	Support added for AP-555
New Caledonia	Support added for AP-555
Nicaragua	Support added for AP-555
Nigeria	Support added for AP-303H and AP-555
Northern Mariana Islands	Support added for AP-555
Norway	Support added for AP-555
Panama	Support added for AP-303H and AP-555
Papua New Guinea	Support added for AP-555
Paraguay	Support added for AP-555
Peru	Support added for AP-303H and AP-555
Poland	Support added for AP-555
Portugal	Support added for AP-555
Puerto Rico	Support added for AP-555
Reunion	Support added for AP-555
Romania	Support added for AP-555
Russia	Support added for AP-555
Rwanda	Channels updated for AP-303H
Saint Barthelemy	Support added for AP-555
Saint Lucia	Support added for AP-555
Saint Martin	Support added for AP-555

Regulatory Domain	Regulatory Changes
Saint Pierre And Miquelon	Support added for AP-555
Saint Vincent And The Grenadines	Support added for AP-555
San Marino	Support added for AP-555
Senegal	Support added for AP-555
Serbia	Support added for AP-555
Slovakia	Support added for AP-555
Slovenia	Support added for AP-555
South Africa	Support added for AP-303P
Spain	Support added for AP-555
Suriname	Support added for AP-555
Svalbard And Jan Mayen	Support added for AP-555
Sweden	Support added for AP-555
Switzerland	Support added for AP-555
Tanzania	Channels updated for AP-303H
Trinidad And Tobago	Support added for AP-303H and AP-555
Tunisia	Support added for AP-555
Turkey	Support added for AP-555
Turkmenistan	Support added for AP-555
Uae	Support added for AP-555
Ukraine	Support added for AP-514 and AP-515
United Kingdom	Support added for AP-555
United States of America	• Channels updated for AP-387 • Support added for AP-555
Uruguay	Support added for AP-555
Us Virgin Islands	Support added for AP-555

Regulatory Domain	Regulatory Changes
Vatican City	Support added for AP-555
Venezuela	Support added for AP-555
Wallis And Futuna	Support added for AP-555
Zambia	Support added for AP-555
Zimbabwe	Support added for AP-303H and AP-555

1.0_70267

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 200: *1.0_70267*

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-514 and AP-515
China	Support added for AP-514 and AP-515
Mexico	Support added for AP-514 and AP-515

1.0_70076

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 201: *1.0_70076*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP-534 and AP-535
Aland Islands	Support added for AP-534 and AP-535
Albania	Support added for AP-534 and AP-535
American Samoa	Support added for AP-534 and AP-535
Andorra	Support added for AP-534 and AP-535
Angola	Support added for AP-534 and AP-535
Antigua And Barbuda	Support added for AP-374, AP-375, AP-534 and AP-535
Australia	Support added for AP-534 and AP-535
Austria	Support added for AP-534 and AP-535
Azerbaijan	Support added for AP-534 and AP-535
Bahamas	Support added for AP-374, AP-375, AP-534 and AP-535
Bangladesh	Support added for AP-374, AP-375, AP-534 and AP-535
Belarus	Support added for AP-514, AP-515, AP-534 and AP-535
Belgium	Support added for AP-534 and AP-535
Bermuda	Support added for AP-374, AP-375, AP-534 and AP-535
Bolivia	Support added for AP-534 and AP-535
Bosnia And Herzegowina	Support added for AP-534 and AP-535
Botswana	Support added for AP-534 and AP-535
Brunei Darussalam	Support added for AP-374, AP-375, AP-534 and AP-535
Bulgaria	Support added for AP-534 and AP-535
Cameroon	Support added for AP-534 and AP-535

Regulatory Domain	Regulatory Changes
Canada	Support added for AP-534 and AP-535
Cayman Islands	Support added for AP-374, AP-375, AP-534 and AP-535
Colombia	Support added for AP-374, AP-375, AP-534 and AP-535
Costa Rica	Support added for AP-534 and AP-535
Croatia	Support added for AP-534 and AP-535
Curacao	Support added for AP-374, AP-375, AP-534 and AP-535
Cyprus	Support added for AP-534 and AP-535
Czech Republic	Support added for AP-534 and AP-535
Denmark	Support added for AP-534 and AP-535
Dominican Republic	Support added for AP-374, AP-375, AP-534 and AP-535
Ecuador	Support added for AP-534 and AP-535
El Salvadore	Support added for AP-374, AP-375, AP-534 and AP-535
Estonia	Support added for AP-534 and AP-535
Ethiopia	Support added for AP-534 and AP-535
Faroe Islands	Support added for AP-534 and AP-535
Federated States Of Micronesia	Support added for AP-534 and AP-535
Finland	Support added for AP-534 and AP-535
France	Support added for AP-534 and AP-535
French Guiana	Support added for AP-534 and AP-535
French Polynesia	Support added for AP-534 and AP-535
French Southern Territories	Support added for AP-534 and AP-535
Georgia	Support added for AP-534 and AP-535
Germany	Support added for AP-534 and AP-535
Greece	Support added for AP-534 and AP-535
Greenland	Support added for AP-534 and AP-535

Regulatory Domain	Regulatory Changes
Grenada	Support added for AP-374, AP-375, AP-534 and AP-535
Guadeloupe	Support added for AP-534 and AP-535
Guam	Support added for AP-534 and AP-535
Guatemala	Support added for AP-374, AP-375, AP-534 and AP-535
Guernsey	Support added for AP-534 and AP-535
Guyana	Support added for AP-374, AP-375, AP-534 and AP-535
Haiti	Support added for AP-374, AP-375, AP-534 and AP-535
Honduras	Support added for AP-374, AP-375, AP-534 and AP-535
Hong Kong	Support added for AP-387
Hungary	Support added for AP-534 and AP-535
Iceland	Support added for AP-534 and AP-535
Ireland	Support added for AP-534 and AP-535
Isle Of Man	Support added for AP-534 and AP-535
Italy	Support added for AP-534 and AP-535
Jersey	Support added for AP-534 and AP-535
Kazakhstan	Support added for AP-514 and AP-515
Kosovo	Support added for AP-534 and AP-535
Lao	Support added for AP-374, AP-375, AP-534 and AP-535
Latvia	Support added for AP-534 and AP-535
Lebanon	Support added for AP-534 and AP-535
Libya	Support added for AP-534 and AP-535
Liechtenstein	Support added for AP-534 and AP-535
Lithuania	Support added for AP-534 and AP-535
Luxembourg	Support added for AP-534 and AP-535
Macedonia	Support added for AP-534 and AP-535

Regulatory Domain	Regulatory Changes
Malawi	Support added for AP-534 and AP-535
Maldives	Support added for AP-374, AP-375, AP-534 and AP-535
Malta	Support added for AP-534 and AP-535
Marshall Islands	Support added for AP-534 and AP-535
Martinique	Support added for AP-534 and AP-535
Mauritania	Support added for AP-534 and AP-535
Mauritius	Support added for AP-534 and AP-535
Mayotte	Support added for AP-534 and AP-535
Mexico	Channels updated for AP-303, AP-303H, AP-303P, AP-304, AP-305, AP-314, AP-315, AP-318, AP-334, AP-335, AP-344, AP-365, AP-367, AP-374, AP-375 and AP-377
Moldova	Support added for AP-534 and AP-535
Monaco	Support added for AP-534 and AP-535
Montenegro	Support added for AP-534 and AP-535
Montserrat	Support added for AP-374, AP-375, AP-534 and AP-535
Morocco	Support added for AP-534 and AP-535
Mozambique	Support added for AP-534 and AP-535
Myanmar	Support added for AP-534 and AP-535
Namibia	Support added for AP-534 and AP-535
Netherlands	Support added for AP-534 and AP-535
New Caledonia	Support added for AP-534 and AP-535
New Zealand	Support added for AP-534 and AP-535
Nicaragua	Support added for AP-374, AP-375, AP-534 and AP-535
Northern Mariana Islands	Support added for AP-534 and AP-535
Norway	Support added for AP-534 and AP-535
Panama	Support added for AP-374, AP-375, AP-534 and AP-535

Regulatory Domain	Regulatory Changes
Papua New Guinea	Support added for AP-534 and AP-535
Paraguay	Support added for AP-374, AP-375, AP-534 and AP-535
Peru	Support added for AP-534 and AP-535
Poland	Support added for AP-534 and AP-535
Portugal	Support added for AP-534 and AP-535
Puerto Rico	Support added for AP-534 and AP-535
Reunion	Support added for AP-534 and AP-535
Romania	Support added for AP-534 and AP-535
Russia	upport added for AP-514 and AP-515
Saint Barthelemy	Support added for AP-534 and AP-535
Saint Lucia	Support added for AP-534 and AP-535
Saint Martin	Support added for AP-534 and AP-535
Saint Pierre And Miquelon	Support added for AP-534 and AP-535
Saint Vincent And The Grenadines	Support added for AP-374, AP-375, AP-534 and AP-535
San Marino	Support added for AP-534 and AP-535
Senegal	Support added for AP-534 and AP-535
Serbia	Support added for AP-534 and AP-535
Slovakia	Support added for AP-534 and AP-535
Slovenia	Support added for AP-534 and AP-535
Spain	Support added for AP-534 and AP-535
Suriname	Support added for AP-374, AP-375, AP-534 and AP-535
Svalbard And Jan Mayen	Support added for AP-534 and AP-535
Sweden	Support added for AP-534 and AP-535
Switzerland	Support added for AP-534 and AP-535
Tanzania	Support added for AP-534 and AP-535

Regulatory Domain	Regulatory Changes
Thailand	Support added for AP-534 and AP-535
Trinidad And Tobago	Support added for AP-534 and AP-535
Turkey	Support added for AP-534 and AP-535
Turkmenistan	Support added for AP-534 and AP-535
United Kingdom	Support added for AP-534 and AP-535
United States	Support added for AP-534 and AP-535
Uruguay	Support added for AP-374, AP-375, AP-534 and AP-535
Us Virgin Islands	Support added for AP-534 and AP-535
Vatican City	Support added for AP-534 and AP-535
Venezuela	Support added for AP-374, AP-375, AP-534 and AP-535
Wallis And Futuna	Support added for AP-534 and AP-535
Zambia	Support added for AP-534 and AP-535
Zimbabwe	Support added for AP-534 and AP-535

1.0_69842

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 202: *1.0_69842*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP-203R and AP-203RP
Albania	Support added for AP-203R and AP-203RP
Algeria	• Channels updated for AP-514 and AP-515 • Support added for AP-103H, AP-344 and AP-345
Argentina	Support added for AP-303P
Azerbaijan	Support added for AP-203R and AP-203RP
Bahrain	Support added for AP-344 and AP-345
Bangladesh	Support added for AP-203R, AP-203RP, AP-344 and AP-345
Barbados	Support added for AP-203R, AP-203RP, AP-344 and AP-345
Bermuda	Support added for AP-203R, AP-203RP, AP-344 and AP-345
Bolivia	Channels updated for AP-203R and AP-203RP
Bosnia and Herzegovina	Support added for AP-203R and AP-203RP
Botswana	Support added for AP-203R and AP-203RP
Cayman Islands	Support added for AP-203R, AP-203RP, AP-344 and AP-345
Colombia	Channels updated for AP-203R and AP-203RP
Cotes d'ivoire	Support added for AP-203R, AP-203RP, AP-344 and AP-345
Dominican Republic	Support added for AP-203R, AP-203RP, AP-344 and AP-345
El Salvador	Support added for AP-344 and AP-345
Guadeloupe	Support added for AP-203R and AP-203RP
Guatemala	Support added for AP-203R and AP-203RP
Haiti	Support added for AP-203R and AP-203RP

Regulatory Domain	Regulatory Changes
Jamaica	Support added for AP-203R and AP-203RP
Kazakhstan	Support added for AP-203R, AP-203RP, AP-344 and AP-345
Kenya	Support added for AP-344 and AP-345
Kosovo	Support added for AP-203R and AP-203RP
Kuwait	Support added for AP-344 and AP-345
Libya	Support added for AP-203R and AP-203RP
Macau	Channels updated for AP-203R and AP-203RP
Macedonia	Support added for AP-203R and AP-203RP
Malawi	Support added for AP-203R and AP-203RP
Mauritius	Channels updated for AP-203R and AP-203RP
Montenegro	Support added for AP-203R and AP-203RP
Nepal	Support added for AP-203R and AP-203RP
Nicaragua	Support added for AP-203R and AP-203RP
Nigeria	Support added for AP-203R, AP-203RP, AP-344 and AP-345
Oman	Support added for AP-344 and AP-345
Panama	Support added for AP-203R, AP-203RP, AP-344 and AP-345
Paraguay	Support added for AP-203R, AP-203RP, AP-344 and AP-345
Peru	Channels updated for AP-203R and AP-203RP
Philippines	Support added for AP-203R and AP-203RP
Senegal	Channels updated for AP-203R and AP-203RP
Serbia	Channels updated for AP-203R and AP-203RP
South Korea	• Support added for AP-514 • Channels updated for AP-515
Sri Lanka	Channels updated for AP-203R and AP-203RP
Uganda	Support added for AP-344 and AP-345
Ukraine	Support added for AP-303P

1.0_69660

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 203: *1.0_69660*

Regulatory Domain	Regulatory Changes
Afghanistan	U-NII-3 band is enabled for AP-345
Aland Islands	U-NII-3 band is enabled for AP-345
Albania	U-NII-3 band is enabled for AP-345
Algeria	• Support added for AP-387, AP-514 and AP-515 • Channels updated for AP-303P • Regulatory domain file updated
American Samoa	DFS channels are enabled for AP-514 and AP-515
Andorra	U-NII-3 band is enabled for AP-345
Angola	U-NII-3 band is enabled for AP-345
Antigua And Barbuda	DFS channels are enabled for AP-514 and AP-515
Austria	U-NII-3 band is enabled for AP-345
Azerbaijan	• U-NII-3 band is enabled for AP-345 • Channels updated for AP-303H
Bahamas	DFS channels are enabled for AP-514 and AP-515
Bangladesh	DFS channels are enabled for AP-514 and AP-515
Barbados	• DFS channels are enabled for AP-514 and AP-515 • Support added for AP-387
Belarus	U-NII-3 band is enabled for AP-345
Belgium	U-NII-3 band is enabled for AP-345
Bermuda	DFS channels are enabled for AP-514 and AP-515
Bolivia	• DFS channels are enabled for AP-514 and AP-515 • Channels updated for AP-203H • Support added for AP-387
Bosnia And Herzegowina	U-NII-3 band is enabled for AP-345

Regulatory Domain	Regulatory Changes
Botswana	U-NII-3 band is enabled for AP-345
Bulgaria	U-NII-3 band is enabled for AP-345
Cameroon	• U-NII-3 band is enabled for AP-345 • Channels updated for AP-203H and AP-303H
Cayman Islands	DFS channels are enabled for AP-514 and AP-515
Colombia	DFS channels are enabled for AP-514 and AP-515
Costa Rica	DFS channels are enabled for AP-514 and AP-515
Cote D'ivoire	Support added for AP-387
Croatia	U-NII-3 band is enabled for AP-345
Curacao	DFS channels are enabled for AP-514 and AP-515
Cyprus	U-NII-3 band is enabled for AP-345
Czech Republic	U-NII-3 band is enabled for AP-345
Denmark	U-NII-3 band is enabled for AP-345
Dominican Republic	DFS channels are enabled for AP-514 and AP-515
Ecuador	• DFS channels are enabled for AP-514 and AP-515 • Support added for AP-387
El Salvadore	DFS channels are enabled for AP-514 and AP-515
Estonia	U-NII-3 band is enabled for AP-345
Ethiopia	U-NII-3 band is enabled for AP-345
Faroe Islands	U-NII-3 band is enabled for AP-345
Federated States Of Micronesia	DFS channels are enabled for AP-514 and AP-515
Finland	U-NII-3 band is enabled for AP-345
France	U-NII-3 band is enabled for AP-345
French Guiana	U-NII-3 band is enabled for AP-345
French Polynesia	U-NII-3 band is enabled for AP-345
French Southern Territories	U-NII-3 band is enabled for AP-345

Regulatory Domain	Regulatory Changes
Georgia	U-NII-3 band is enabled for AP-345
Germany	U-NII-3 band is enabled for AP-345
Greece	U-NII-3 band is enabled for AP-345
Greenland	U-NII-3 band is enabled for AP-345
Grenada	DFS channels are enabled for AP-514 and AP-515
Guadeloupe	• U-NII-3 band is enabled for AP-345 • Channels updated for AP-315
Guam	DFS channels are enabled for AP-514 and AP-515
Guatemala	DFS channels are enabled for AP-514 and AP-515
Guernsey	U-NII-3 band is enabled for AP-345
Guyana	DFS channels are enabled for AP-514 and AP-515
Haiti	• DFS channels are enabled for AP-514 and AP-515 • Support added for AP-387
Honduras	DFS channels are enabled for AP-514 and AP-515
Hungary	U-NII-3 band is enabled for AP-345
Iceland	U-NII-3 band is enabled for AP-345
Ireland	U-NII-3 band is enabled for AP-345
Isle Of Man	U-NII-3 band is enabled for AP-345
Italy	U-NII-3 band is enabled for AP-345
Jersey	U-NII-3 band is enabled for AP-345
Jordan	Support added for AP-514 and AP-515
Kenya	Support added for AP-387
Kosovo	U-NII-3 band is enabled for AP-345
Kuwait	Support added for AP-387
Lao	DFS channels are enabled for AP-514 and AP-515
Latvia	U-NII-3 band is enabled for AP-345

Regulatory Domain	Regulatory Changes
Lebanon	U-NII-3 band is enabled for AP-345
Libya	U-NII-3 band is enabled for AP-345
Liechtenstein	U-NII-3 band is enabled for AP-345
Lithuania	U-NII-3 band is enabled for AP-345
Luxembourg	U-NII-3 band is enabled for AP-345
Macedonia	U-NII-3 band is enabled for AP-345
Malawi	U-NII-3 band is enabled for AP-345
Maldives	DFS channels are enabled for AP-514 and AP-515
Mali	U-NII-3 band is enabled for AP-345
Malta	U-NII-3 band is enabled for AP-345
Marshall Islands	DFS channels are enabled for AP-514 and AP-515
Martinique	U-NII-3 band is enabled for AP-345
Mauritania	U-NII-3 band is enabled for AP-345
Mauritius	• U-NII-3 band is enabled for AP-345 • Channels updated for AP-315
Mayotte	U-NII-3 band is enabled for AP-345
Moldova	U-NII-3 band is enabled for AP-345
Monaco	U-NII-3 band is enabled for AP-345
Montenegro	U-NII-3 band is enabled for AP-345
Morocco	Channels updated for AP-303H
Mozambique	U-NII-3 band is enabled for AP-345
Myanmar	U-NII-3 band is enabled for AP-345
Namibia	• U-NII-3 band is enabled for AP-345 • Channels updated for AP-225
Netherlands	U-NII-3 band is enabled for AP-345
New Caledonia	U-NII-3 band is enabled for AP-345

Regulatory Domain	Regulatory Changes
Nicaragua	DFS channels are enabled for AP-514 and AP-515
Nigeria	Support added for AP-387
Northern Mariana Islands	DFS channels are enabled for AP-514 and AP-515
Norway	U-NII-3 band is enabled for AP-345
Panama	DFS channels are enabled for AP-514 and AP-515
Paraguay	DFS channels are enabled for AP-514 and AP-515
Peru	• DFS channels are enabled for AP-514 and AP-515 • Support added for AP-387
Philippines	Support added for AP-303P, AP-514 and AP-515
Poland	U-NII-3 band is enabled for AP-345
Portugal	U-NII-3 band is enabled for AP-345
Puerto Rico	DFS channels are enabled for AP-514 and AP-515
Reunion	U-NII-3 band is enabled for AP-345
Romania	U-NII-3 band is enabled for AP-345
Russia	• Regulatory domain file updated • Channels updated for AP-303P
Rwanda	Support added for AP-387
Saint Barthelemy	U-NII-3 band is enabled for AP-345
Saint Lucia	U-NII-3 band is enabled for AP-345
Saint Martin	U-NII-3 band is enabled for AP-345
Saint Pierre And Miquelon	U-NII-3 band is enabled for AP-345
Saint Vincent And The Grenadines	DFS channels are enabled for AP-514 and AP-515
San Marino	U-NII-3 band is enabled for AP-345
Senegal	U-NII-3 band is enabled for AP-345
Serbia	U-NII-3 band is enabled for AP-345
Slovakia	U-NII-3 band is enabled for AP-345

Regulatory Domain	Regulatory Changes
Slovenia	U-NII-3 band is enabled for AP-345
South Africa	Support added for AP-515
South Korea	Support added for AP-515
Spain	U-NII-3 band is enabled for AP-345
Svalbard And Jan Mayen	U-NII-3 band is enabled for AP-345
Sweden	U-NII-3 band is enabled for AP-345
Switzerland	U-NII-3 band is enabled for AP-345
Taiwan	DFS channels are enabled for AP-514 and AP-515
Tanzania	• U-NII-3 band is enabled for AP-345 • Support added for AP-387
Thailand	U-NII-3 band is enabled for AP-345
Trinidad And Tobago	DFS channels are enabled for AP-514 and AP-515
Turkey	U-NII-3 band is enabled for AP-345
Turkmenistan	U-NII-3 band is enabled for AP-345
Uganda	Support added for AP-387
United Kingdom	U-NII-3 band is enabled for AP-345
United States of America	DFS channels are enabled for AP-514 and AP-515
Uruguay	DFS channels are enabled for AP-514 and AP-515
US Virgin Islands	DFS channels are enabled for AP-514 and AP-515
Vatican City	U-NII-3 band is enabled for AP-345
Vietnam	Support added for AP-303P, AP-514 and AP-515
Wallis And Futuna	U-NII-3 band is enabled for AP-345
Zambia	U-NII-3 band is enabled for AP-345
Zimbabwe	U-NII-3 band is enabled for AP-345

1.0_69377

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 204: *1.0_69377*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-214 and AP-318
Afghanistan	Support added for AP-214
Azerbaijan	Support added for AP-214
Bahamas	Support added for AP-214
Bahrain	Support added for AP-303P, AP-514 and AP-515
Barbados	Support added for AP-214, AP-303P, AP-318, AP-514 and AP-515
Bermuda	Support added for AP-214 and AP-318
Bolivia	Support added for AP-214
Bosnia and Herzegovina	Support added for AP-214
Cambodia	Support added for AP-214
Cameroon	Support added for AP-214
Cayman Islands	Support added for AP-318
Cote D'Ivoire	Support added for AP-214
Dominican Republic	Support added for AP-318
Ecuador	• Support added for AP-214, AP-318, AP-514 and AP-515 • EIRP of channel 36-48 updated to 30
El Salvadore	Support added for AP-318
Guatemala	Support added for AP-318
Haiti	Support added for AP-214 and AP-318
Jordan	Support added for AP-214 and AP-303P
Kenya	Support added for AP-214
Kuwait	• Support added for AP-214

Regulatory Domain	Regulatory Changes
	• Channels updated for AP-318
Libya	Support added for AP-214
Macau	Support added for AP-318
Malawi	Support added for AP-214
Morocco	Support added for AP-303P, AP-514 and AP-515
Nigeria	Support added for AP-214 and AP-318
Oman	Support added for AP-303P
Panama	Support added for AP-214 and AP-318
Paraguay	Support added for AP-318
Qatar	Support added for AP-514 and AP-515
Rwanda	Channels updated for AP-318
South Africa	Support added for AP-514
Sri Lanka	Support added for AP-318
Taiwan	Support added for AP-514 and AP-515
Tanzania	Support added for AP-318
Trinidad & Tobago	Support added for AP-214
Uganda	Support added for AP-318
Zambia	Support added for AP-514 and AP-515
Zimbabwe	Support added for AP-214 and AP-318

1.0_69166

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 205: *1.0_69166*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-303P
Belarus	Support added for AP-303P
Bermuda	Support added for AP-303P
Bolivia	Support added for AP-303P, AP-514 and AP-515
Botswana	Support added for AP-303
Brazil	Support added for AP-303P, AP-514 and AP-515
Cambodia	Support added for AP-303, AP-514 and AP-515
Cote D'Ivoire	Support added for AP-303
Ghana	Support added for AP-303P, AP-514 and AP-515
Haiti	Support added for AP-514 and AP-515
Israel	Support added for AP-303P
Jamaica	Support added for AP-303P, AP-514 and AP-515
Kazakhstan	Support added for AP-303P
Kenya	Support added for AP-514 and AP-515
Kuwait	Support added for AP-514 and AP-515
Libya	Support added for AP-303
Macau	Support added for AP-303P, AP-514 and AP-515
Malawi	Support added for AP-303
Morocco	Support added for AP-303
Northern Mariana Island	Support added for AP-514 and AP-515
Russia	Support added for AP-303P

Regulatory Domain	Regulatory Changes
Rwanda	Support added for AP-514 and AP-515
Singapore	Support added for AP-377
Sri Lanka	Support added for AP-303P, AP-514 and AP-515
Tanzania	Support added for AP-514 and AP-515
Thailand	Support added for AP-303P, AP-514 and AP-515
Uganda	Support added for AP-514 and AP-515

1.0_68979

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 206: *1.0_68979*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP-387
Aland Islands	Support added for AP-387
Albania	Support added for AP-387
American Samoa	Support added for AP-387, AP-514 and AP-515
Andorra	Support added for AP-387
Angola	Support added for AP-387
Antigua and Barbuda	Support added for AP-387, AP-514 and AP-515
Armenia	Support added for AP-514 and AP-515
Australia	Support added for AP-387
Austria	Support added for AP-387
Azerbaijan	Support added for AP-387
Bahamas	Support added for AP-387, AP-514 and AP-515
Bangladesh	Support added for AP-387, AP-514 and AP-515
Belarus	Support added for AP-387
Belgium	Support added for AP-387
Bermuda	Support added for AP-203H, AP-387, AP-514 and AP-515
Bosnia And Herzegowina	Support added for AP-387
Botswana	Support added for AP-387, AP-514 and AP-515
Bulgaria	Support added for AP-387
Canada	Support added for AP-387
Cambodia	Support added for AP-203H and AP-303P

Regulatory Domain	Regulatory Changes
Cameroon	Support added for AP-387
Cayman Islands	Support added for AP-387, AP-514 and AP-515
Chile	Support added for AP-203H
Colombia	Support added for AP-387, AP-514 and AP-515
Costa Rica	Support added for AP-387, AP-514 and AP-515
Cote D'ivoire	Support added for AP-514 and AP-515
Croatia	Support added for AP-387
Curacao	Support added for AP-387, AP-514 and AP-515
Cyprus	Support added for AP-387
Czech Republic	Support added for AP-387
Denmark	Support added for AP-387
Dominican Republic	Support added for AP-203H, AP-387, AP-514 and AP-515
Ecuador	Support added for AP-303P
Egypt	• Channels updated for AP-175AC, AP-175DC and AP-175P • Support added for AP-514 and AP-515
El Salvadore	Support added for AP-203H, AP-387, AP-514 and AP-515
Estonia	Support added for AP-387
Ethiopia	Support added for AP-387, AP-514 and AP-515
Faroe Islands	Support added for AP-387
Federated States Of Micronesia	Support added for AP-387, AP-514 and AP-515
Finland	Support added for AP-387
France	Support added for AP-387
French Guiana	Support added for AP-387
French Polynesia	Support added for AP-387
French Southern Territories	Support added for AP-387

Regulatory Domain	Regulatory Changes
Georgia	Support added for AP-387
Germany	Support added for AP-387
Greece	Support added for AP-387
Greenland	Support added for AP-387
Grenada	Support added for AP-387, AP-514 and AP-515
Guadeloupe	Support added for AP-387
Guam	Support added for AP-387, AP-514 and AP-515
Guatemala	Support added for AP-203H, AP-387, AP-514 and AP-515
Guernsey	Support added for AP-387
Guyana	Support added for AP-387, AP-514 and AP-515
Haiti	Support added for AP-303P
Hong Kong	Support added for AP-203H
Honduras	Support added for AP-387, AP-514 and AP-515
Hungary	Support added for AP-387
Iceland	Support added for AP-387
India	Support added for AP-514 and AP-515
Indonesia	Support added for AP-203H
Ireland	Support added for AP-387
Isle Of Man	Support added for AP-387
Israel	Support added for AP-514 and AP-515
Italy	Support added for AP-387
Japan	Support added for AP-387
Jersey	Support added for AP-387
Kazakhstan	Support added for AP-203H
Kenya	Support added for AP-303P

Regulatory Domain	Regulatory Changes
Kosovo	Support added for AP-387
Kuwait	Support added for AP-303P
Lao	Support added for AP-203H, AP-387, AP-514 and AP-515
Latvia	Support added for AP-387
Lebanon	Support added for AP-203H, AP-387, AP-514 and AP-515
Libya	Support added for AP-387, AP-514 and AP-515
Liechtenstein	Support added for AP-387
Lithuania	Support added for AP-387
Luxembourg	Support added for AP-387
Macedonia	Support added for AP-387
Malawi	Support added for AP-387, AP-514 and AP-515
Malaysia	Support added for AP-303P, AP-514 and AP-515
Maldives	Support added for AP-387, AP-514 and AP-515
Malta	Support added for AP-387
Marshall Islands	Support added for AP-387, AP-514 and AP-515
Martinique	Support added for AP-387
Mauritania	Support added for AP-387
Mauritius	Support added for AP-387, AP-514 and AP-515
Mayotte	Support added for AP-387
Moldova	Support added for AP-387
Monaco	Support added for AP-203H, AP-387, AP-514 and AP-515
Montenegro	Support added for AP-203H and AP-387
Morocco	Support added for AP-387
Mozambique	Support added for AP-387
Myanmar	Support added for AP-387

Regulatory Domain	Regulatory Changes
Namibia	Support added for AP-387, AP-514 and AP-515
Nepal	Support added for AP-514 and AP-515
Netherlands	Support added for AP-387
New Caledonia	Support added for AP-387
New Zealand	Support added for AP-387
Nicaragua	Support added for AP-203H, AP-387, AP-514 and AP-515
Niger	Support added for AP-514 and AP-515
Nigeria	Support added for AP-303P, AP-514 and AP-515
Northern Mariana Islands	Support added for AP-387, AP-514 and AP-515
Norway	Support added for AP-387
Panama	Support added for AP-203H, AP-387, AP-514 and AP-515
Papua New Guinea	Support added for AP-387
Paraguay	Support added for AP-203H, AP-387, AP-514 and AP-515
Peru	Support added for AP-303P
Poland	Support added for AP-387
Portugal	Support added for AP-387
Puerto Rico	Support added for AP-387, AP-514 and AP-515
Reunion	Support added for AP-387
Romania	Support added for AP-387
Rwanda	Support added for AP-303P
Saint Barthelemy	Support added for AP-387
Saint Lucia	Support added for AP-387
Saint Martin	Support added for AP-387
Saint Pierre And Miquelon	Support added for AP-387
Saint Vincent And The Grenadines	Support added for AP-387, AP-514 and AP-515

Regulatory Domain	Regulatory Changes
San Marino	Support added for AP-387
Saudi Arabia	Support added for AP-203H
Senegal	Support added for AP-387, AP-514 and AP-515
Serbia	Support added forAP-203H and AP-387
Singapore	Support added for AP-303P, AP-514 and AP-515
Slovakia	Support added for AP-387
Slovenia	Support added for AP-387
Spain	Support added for AP-387
Svalbard And Jan Mayen	Support added for AP-387
Sweden	Support added for AP-387
Switzerland	Support added for AP-387
Tanzania	Support added for AP-303P
Thailand	Support added for AP-203H, AP-303P, AP-514 and AP-515
Trinidad And Tobago	Support added for AP-387, AP-514 and AP-515
Tunisia	• Channels updated for AP-274, AP-275, AP-277, AP-365, AP-367, AP-374, AP-375 and AP-377 • Support added for AP-514 and AP-515
Turkey	Support added for AP-387
Turkmenistan	Support added for AP-387, AP-514 and AP-515
Uganda	Support added for AP-303P
United Kingdom	Support added for AP-387
United States	Support added for AP-387
Uruguay	Support added for AP-387, AP-514 and AP-515
Us Virgin Islands	Support added for AP-387, AP-514 and AP-515
Vatican City	Support added for AP-387
Venezuela	Support added for AP-387

Regulatory Domain	Regulatory Changes
Wallis And Futuna	Support added for AP-387
Zambia	Support added for AP-303P and AP-387
Zimbabwe	Support added for AP-387, AP-514 and AP-515

1.0_68720

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 207: *1.0_68720*

Regulatory Domain	Regulatory Changes
American Samoa	• Channels updated for AP-377 • Support added for AP-318
Antigua And Barbuda	Channels updated for AP-377
Bahamas	Channels updated for AP-377
Bangladesh	Channels updated for AP-377
Bermuda	Channels updated for AP-377
Bolivia	Support added for AP-215
Cameroon	Support added for AP-215
Canada	DFS channels enabled for AP-514 and AP-515
Cayman Islands	Channels updated for AP-377
Colombia	Channels updated for AP-377
Costa Rica	Channels updated for AP-377
Curacao	Channels updated for AP-377
Dominican Republic	Channels updated for AP-377
El Salvadore	Channels updated for AP-377
Federated States Of Micronesia	• Channels updated for AP-377 • Support added for AP-318
Grenada	Channels updated for AP-377
Guam	• Channels updated for AP-377 • Support added for AP-318
Guatemala	Channels updated for AP-377
Guyana	Channels updated for AP-377
Honduras	Channels updated for AP-377

Regulatory Domain	Regulatory Changes
India	• Support added for AP-303P • Channels 36-144 updated
Lao	Channels updated for AP-377
Macedonia	Support added for AP-215
Malaysia	• Channels updated for AP-103, AP-103H, AP-204, AP-205, AP-205H, AP-334, AP-335, AP-345, AP-375, AP-377, RAP-108 and RAP-109 • Channels 132-144 disabled for this regulatory domain
Maldives	Channels updated for AP-377
Marshall Islands	• Channels updated for AP-377 • Support added for AP-318
Mexico	Channels 120-128 disabled for this regulatory domain
Montenegro	Support added for AP-215
Nicaragua	Channels updated for AP-377
Northern Mariana Islands	• Channels updated for AP-377 • Support added for AP-318
Panama	Channels updated for AP-377
Paraguay	Channels updated for AP-377
Philippines	Channels 100-144 enabled for AP-365 and AP-367
Puerto Rico	• Channels updated for AP-377 • Support added for AP-318
Qatar	• Support added for AP-303P, AP-365 and AP-367 • Channels 16-144 not allowed outdoors • Channels updated for AP-103, AP-114, AP-115, AP-204, AP-205, AP-214, AP-215, AP-228, AP-207, AP-274, AP-275, AP-303 and AP-318
Saint Vincent And The Grenadines	Channels updated for AP-377
Saudi Arabia	Support added for AP-514 and AP-515
Serbia	Support added for AP-215, AP-514 and AP-515
Taiwan	Support added for AP-374, AP-375 and AP-377
Tanzania	Support added for AP-215
Trinidad And Tobago	Channels updated for AP-377
Tunisia	• Channels 36-64 not allowed outdoors • Channels 100-120 allowed outdoors

Regulatory Domain	Regulatory Changes
United Arab Emirates	Support added for AP-514 and AP-515
United States	Channels updated for AP-377
Uruguay	Channels updated for AP-377
Us Virgin Islands	Channels updated for AP-377
Venezuela	Channels updated for AP-377
Vietnam	Channels 1-13 and 149-165 updated for this regulatory domain
Zimbabwe	Support added for AP-215

1.0_68474

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 208: *1.0_68474*

Regulatory Domain	Regulatory Changes
Afghanistan	Channels updated for AP-374, AP-375 and AP-377
Algeria	Support added for AP-303P
Antigua and Barbuda	Support added for AP-303P
Bahamas	Support added for AP-215, AP-303H and AP-303P
Bangladesh	Support added for AP-303P
Belarus	Channels updated for AP-374, AP-375 and AP-377
Bermuda	Support added for AP-303P
Botswana	Support added for AP-214, AP-215, AP-374, AP-375 and AP-377
Cayman Islands	Support added for AP-303P
Cotes d'Ioire	Support added for AP-215, AP-303P, AP-374, AP-375AP-377 and AP-377
Curacao	Support added for AP-303P
Dominican Republic	Support added for AP-303P
Egypt	• Channels updated for AP-374, AP-375 and AP-377 • Support added for AP-303P
El Salvadore	Support added for AP-303P
Grenada	Support added for AP-303P
Guatemala	Support added for AP-303P
Guyana	Support added for AP-303P
Hondura	Support added for AP-303P
Hong Kong	Support added for AP-514 and AP-515
Jordan	Support added for AP-215

Regulatory Domain	Regulatory Changes
Lao	Support added for AP-303P
Libya	Support added for AP-215, AP-374, AP-375 and AP-377
Malawi	Support added for AP-215, AP-374, AP-375 and AP-377
Maldives	Support added for AP-303P
Mexico	Support added for AP-303P
Nicaragua	Support added for AP-303P
Panama	Support added for AP-303P
Paraguay	Support added for AP-303P
Saint Vincent and the Grenadines	Support added for AP-303P
Saudi Arabia	Support added for AP-303P
South Korea	Support added for AP-303P
Trinidad and Tobago	Support added for AP-374, AP-375 and AP-377
Tunisia	Support added for AP-303P
United Arab Emirates	Support added for AP-303P
Uganda	Support added for AP-214 and AP-215
Uruguay	Support added for AP-303P
Venezuela	Support added for AP-303P
Zimbabwe	Support added for AP-374, AP-375 and AP-377

1.0_68143

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 209: *1.0_68143*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP-315
Andorra	Support added for AP-315
Azerbaijan	Channels updated for AP-315
Botswana	Support added for AP-315
Colombia	Support added for AP-315
Ethiopia	Support added for AP-315
Guadeloupe	Channels updated for AP-315
Jordan	Update this country domain to remove DFS from channels 36-48
Kuwait	Update this country domain to remove DFS from channels 36-48
Lao	Update this country domain to remove DFS from channels 36-48
Libya	Support added for AP-315
Macedonia	Support added for AP-315
Malawi	Support added for AP-315
Mauritius	Support added for AP-315
Montenegro	Channels updated for AP-315
Nepal	Support added for AP-315
Senegal	Support added for AP-315
Serbia	Channels updated for AP-315
Turkmenistan	Support added for AP-315
Zimbabwe	Support added for AP-315

1.0_68046

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 210: *1.0_68046*

Regulatory Domain	Regulatory Changes
American Samoa	Channels updated for AP-514 and AP-515
Canada	Channels updated for AP-514 and AP-515
Federated States of Micronesia	Channels updated for AP-514 and AP-515
Guam	Channels updated for AP-514 and AP-515
Marshall Islands	Channels updated for AP-514 and AP-515
Northern Mariana Islands	Channels updated for AP-514 and AP-515
Puerto Rico	Channels updated for AP-514 and AP-515
United States	Channels updated for AP-514 and AP-515
US Virgin Islands	Channels updated for AP-514 and AP-515

1.0_67861

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 211: *1.0_67861*

Regulatory Domain	Regulatory Changes
Afghanistan	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Aland Islands	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Albania	Support added for AP-303P, AP-514 and AP-515
American Samoa	Support added for AP-303P
Andorra	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Angola	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Austria	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Azerbaijan	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Belgium	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Bolivia	Support added for AP-203H, AP-203R, AP-203RP, AP-228, AP-277, AP-303H, AP-303P, AP-324, AP-325, AP-365, AP-367, AP-514, AP-515
Bosnia And Herzegowina	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Botswana	Support added for AP-203H and AP-303P
Bulgaria	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Cameroon	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Canada	Support added for AP-303P
Colombia	Support added for AP-203H and AP-303P
Costa Rica	Support added for AP-303P

Regulatory Domain	Regulatory Changes
Croatia	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Cyprus	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Czech Republic	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Denmark	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Estonia	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Ethiopia	Support added for AP-303P
Faroe Islands	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Federated States of Micronesia	Support added for AP-203H and AP-303P
Finland	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
France	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
French Guiana	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
French Polynesia	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
French Southern Territories	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Georgia	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Germany	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Greece	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Greenland	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Guadeloupe	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Guam	Support added for AP-303P
Guernsey	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515

Regulatory Domain	Regulatory Changes
Hong Kong	Support added for AP-303P
Hungary	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Iceland	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Ireland	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Isle Of Man	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Italy	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Japan	Support added for AP-303P
Jersey	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Kosovo	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Latvia	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Lebanon	Support added for AP-303P, AP-514 and AP-515
Libya	Support added for AP-203H and AP-303P
Liechtenstein	• Channels updated for AP-203H • Support added for AP-303P
Lithuania	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Luxembourg	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Macedonia	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Malawi	Support added for AP-203H and AP-303P
Malta	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Marshall Islands	Support added for AP-203H and AP-303P
Martinique	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Mauritania	• Channels updated for AP-203H

Regulatory Domain	Regulatory Changes
	• Support added for AP-303P
Mauritius	Support added for AP-303P
Mayotte	Support added for AP-303P
Moldova	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Monaco	Support added for AP-303P
Montenegro	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Morocco	Support added for AP-303P, AP-514 and AP-515
Mozambique	• Channels updated for AP-203H • Support added for AP-303P
Myanmar	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Namibia	• Channels updated for AP-203H • Support added for AP-303P
Nepal	Support added for AP-203H and AP-303P
Netherlands	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
New Caledonia	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
New Zealand	Support added for AP-303P
Niger	Support added for AP-303P
Northern Mariana Islands	Support added for AP-303P
Norway	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Poland	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Portugal	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Puerto Rico	Support added for AP-303P
Reunion	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Romania	• Channels updated for AP-203H

Regulatory Domain	Regulatory Changes
	• Support added for AP-303P, AP-514 and AP-515
Saint Barthelemy	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Saint Lucia	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Saint Martin	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Saint Pierre And Miquelon	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
San Marino	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Senegal	• Channels updated for AP-203H • Support added for AP-303P
Serbia	Support added for AP-303P
Slovakia	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Slovenia	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Spain	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Svalbard And Jan Mayen	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Sweden	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Switzerland	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Trinidad & Tobago	Support added for AP-203H and AP-303P
Turkey	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Turkmenistan	• Channels updated for AP-203H • Support added for AP-303P
United Kingdom	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
United States of America	Support added for AP-303P, AP-514 and AP-515
US Virgin Islands	Support added for AP-303P

Regulatory Domain	Regulatory Changes
Vatican City	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Wallis And Futuna	• Channels updated for AP-203H • Support added for AP-303P, AP-514 and AP-515
Zambia	Channels updated for AP-203H
Zimbabwe	Support added for AP-203H and AP-303P

1.0_67494

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 212: *1.0_67494*

Regulatory Domain	Regulatory Changes
Afghanistan	Channels updated for AP-305
Aland Islands	Channels updated for AP-305
Andorra	Channels updated for AP-305
Angola	Channels updated for AP-305
Austria	Channels updated for AP-305
Azerbaijan	Channels updated for AP-305
Belgium	Channels updated for AP-305
Bosnia And Herzegowina	Channels updated for AP-305
Botswana	Support added for AP-344 and AP-345
Bulgaria	Channels updated for AP-305
Cameroon	Channels updated for AP-305
Colombia	Support added for AP-344 and AP-345
Croatia	Channels updated for AP-305
Cyprus	Channels updated for AP-305
Czech Republic	Channels updated for AP-305
Denmark	Channels updated for AP-305
Estonia	Channels updated for AP-305
Faroe Islands	Channels updated for AP-305
Finland	Channels updated for AP-305
France	Channels updated for AP-305
French Guiana	Channels updated for AP-305

Regulatory Domain	Regulatory Changes
French Polynesia	Channels updated for AP-305
French Southern Territories	Channels updated for AP-305
Georgia	Channels updated for AP-305
Germany	Channels updated for AP-305
Greece	Channels updated for AP-305
Greenland	Channels updated for AP-305
Guadeloupe	Channels updated for AP-305
Guernsey	Channels updated for AP-305
Hungary	Channels updated for AP-305
Iceland	Channels updated for AP-305
Ireland	Channels updated for AP-305
Isle Of Man	Channels updated for AP-305
Italy	Channels updated for AP-305
Jersey	Channels updated for AP-305
Kosovo	Channels updated for AP-305
Latvia	Channels updated for AP-305
Libya	• Channels updated for AP-305 • Support added for AP-344 and AP-345
Liechtenstein	Channels updated for AP-305
Lithuania	Channels updated for AP-305
Luxembourg	Channels updated for AP-305
Macedonia	Channels updated for AP-305
Malawi	Support added for AP-344 and AP-345
Malta	Channels updated for AP-305
Martinique	Channels updated for AP-305

Regulatory Domain	Regulatory Changes
Mauritania	Channels updated for AP-305
Moldova	Channels updated for AP-305
Montenegro	Channels updated for AP-305
Morocco	Channels updated for AP-305
Mozambique	Channels updated for AP-305
Myanmar	Channels updated for AP-305
Namibia	Channels updated for AP-305
Nepal	Support added for AP-344 and AP-345
Netherlands	Channels updated for AP-305
New Caledonia	Channels updated for AP-305
Norway	Channels updated for AP-305
Poland	Channels updated for AP-305
Portugal	Channels updated for AP-305
Reunion	Channels updated for AP-305
Romania	Channels updated for AP-305
Saint Barthelemy	Channels updated for AP-305
Saint Lucia	Channels updated for AP-305
Saint Martin	Channels updated for AP-305
Saint Pierre And Miquelon	Channels updated for AP-305
San Marino	Channels updated for AP-305
Slovakia	Channels updated for AP-305
Slovenia	Channels updated for AP-305
Spain	Channels updated for AP-305
Svalbard And Jan Mayen	Channels updated for AP-305
Sweden	Channels updated for AP-305

Regulatory Domain	Regulatory Changes
Switzerland	Channels updated for AP-305
Trinidad and Tobago	Support added for AP-344 and AP-345
Turkey	Channels updated for AP-305
Turkmenistan	Channels updated for AP-305
United Kingdom	Channels updated for AP-305
Vatican City	Channels updated for AP-305
Wallis And Futuna	Channels updated for AP-305
Zambia	Channels updated for AP-305
Zimbabwe	Support added for AP-344 and AP-345

1.0_67280

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 213: *1.0_67280*

Regulatory Domain	Regulatory Changes
Oman	Support added for AP-318
Qatar	• Channels updated for AP-103H, AP-203H, AP-203R, AP-205H, AP-303H, AP-304, AP-305, AP-314, AP-315, AP-324, AP-325, AP-334, AP-335, AP-344, AP-345, RAP-108 and RAP-109 • Power limits updated for all APs
South Africa	Channels updated for AP-303H

1.0_67041

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 214: *1.0_67041*

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-303, AP-318, AP-374, AP-375 and AP-377
India	Channels updated for AP-303H, AP-304 and AP-305
Indonesia	• Support added for AP-375 and AP-377 • Channels updated for AP-214, AP-215, AP-334, AP-335 and AP-374
Mexico	Support added For AP-318 and AP-374
Nepal	Support added for AP-303, AP-318, AP-365, AP-367, AP-374, AP-375 and AP-377
Zambia	Updated this country domain for all APs to not allow outdoor operation in channels 36-64.

1.0_66781

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 215: *1.0_66781*

Regulatory Domain	Regulatory Changes
AFGHANISTAN	Channels updated for AP-303 and AP-303H
ALAND ISLANDS	Channels updated for AP-303 and AP-303H
ALBANIA	Channels updated for AP-303
ANDORRA	Channels updated for AP-303 and AP-303H
ANGOLA	Channels updated for AP-303 and AP-303H
AUSTRIA	Channels updated for AP-303 and AP-303H
AZERBAIJAN	Channels updated for AP-303 and AP-303H
BELGIUM	Channels updated for AP-303 and AP-303H
Bolivia	• Channels updated for AP-275 • Support added for AP-274, AP-318, AP-374, AP-375 and AP-377 • Update maximum allowed power levels and allowed outdoor channels
BOSNIA AND HERZEGOWINA	Channels updated for AP-303 and AP-303H
BULGARIA	Channels updated for AP-303 and AP-303H
CAMEROON	Channels updated for AP-303 and AP-303H
CROATIA	Channels updated for AP-303 and AP-303H
CYPRUS	Channels updated for AP-303 and AP-303H
CZECH REPUBLIC	Channels updated for AP-303 and AP-303H
DENMARK	Channels updated for AP-303 and AP-303H
ESTONIA	Channels updated for AP-303 and AP-303H
ETHIOPIA	Channels updated for AP-303
FAROE ISLANDS	Channels updated for AP-303 and AP-303H
FINLAND	Channels updated for AP-303 and AP-303H

Regulatory Domain	Regulatory Changes
FRANCE	Channels updated for AP-303 and AP-303H
FRENCH GUIANA	Channels updated for AP-303 and AP-303H
FRENCH POLYNESIA	Channels updated for AP-303 and AP-303H
FRENCH SOUTHERN TERRITORIES	Channels updated for AP-303 and AP-303H
GEORGIA	Channels updated for AP-303 and AP-303H
GERMANY	Channels updated for AP-303 and AP-303H
GREECE	Channels updated for AP-303 and AP-303H
GREENLAND	Channels updated for AP-303 and AP-303H
GUADELOUPE	Channels updated for AP-303 and AP-303H
GUERNSEY	Channels updated for AP-303 and AP-303H
HUNGARY	Channels updated for AP-303 and AP-303H
ICELAND	Channels updated for AP-303 and AP-303H
IRELAND	Channels updated for AP-303 and AP-303H
ISLE OF MAN	Channels updated for AP-303 and AP-303H
ITALY	Channels updated for AP-303 and AP-303H
JERSEY	Channels updated for AP-303 and AP-303H
KOSOVO	Channels updated for AP-303 and AP-303H
LATVIA	Channels updated for AP-303 and AP-303H
Laos	Support added for AP-304
LEBANON	Channels updated for AP-303
Libya	Support added for AP-304 and AP-305
LIECHTENSTEIN	Channels updated for AP-303 and AP-303H
LITHUANIA	Channels updated for AP-303 and AP-303H
LUXEMBOURG	Channels updated for AP-303 and AP-303H
MACEDONIA	Channels updated for AP-303 and AP-303H

Regulatory Domain	Regulatory Changes
Maldives	Support added for AP-304 and AP-305
MALTA	Channels updated for AP-303 and AP-303H
MARTINIQUE	Channels updated for AP-303 and AP-303H
MAURITANIA	Channels updated for AP-303 and AP-303H
MAURITIUS	Channels updated for AP-303
MAYOTTE	Channels updated for AP-303
Mexico	Support added for AP-375
MOLDOVA	Channels updated for AP-303 and AP-303H
MONACO	Channels updated for AP-303
MONTENEGRO	Channels updated for AP-303 and AP-303H
MOROCCO	Channels updated for AP-303 and AP-303H
MOZAMBIQUE	Channels updated for AP-303 and AP-303H
MYANMAR	Channels updated for AP-303 and AP-303H
NAMIBIA	Channels updated for AP-303 and AP-303H
Nepal	• Support added for AP-304 and AP-305 • Update the maximum allowed power levels
NETHERLANDS	Channels updated for AP-303 and AP-303H
NEW CALEDONIA	Channels updated for AP-303 and AP-303H
NIGER	Channels updated for AP-303
NORWAY	Channels updated for AP-303 and AP-303H
POLAND	Channels updated for AP-303 and AP-303H
PORTUGAL	Channels updated for AP-303 and AP-303H
REUNION	Channels updated for AP-303 and AP-303H
ROMANIA	Channels updated for AP-303 and AP-303H
SAINT BARTHELEMY	Channels updated for AP-303 and AP-303H

Regulatory Domain	Regulatory Changes
SAINT LUCIA	Channels updated for AP-303 and AP-303H
SAINT MARTIN	Channels updated for AP-303 and AP-303H
SAINT PIERRE AND MIQUELON	Channels updated for AP-303 and AP-303H
SAN MARINO	Channels updated for AP-303 and AP-303H
SENEGAL	Channels updated for AP-303 and AP-303H
SERBIA	Channels updated for AP-303
SLOVAKIA	Channels updated for AP-303 and AP-303H
SLOVENIA	Channels updated for AP-303 and AP-303H
SPAIN	Channels updated for AP-303 and AP-303H
SVALBARD AND JAN MAYEN	Channels updated for AP-303 and AP-303H
SWEDEN	Channels updated for AP-303 and AP-303H
SWITZERLAND	Channels updated for AP-303 and AP-303H
Thailand	Support added for AP-303 and AP-318
TURKEY	Channels updated for AP-303 and AP-303H
TURKMENISTAN	Channels updated for AP-303 and AP-303H
UNITED KINGDOM	Channels updated for AP-303 and AP-303H
Uzbekistan	Support added for AP-304 and AP-305
VATICAN CITY	Channels updated for AP-303 and AP-303H
Vietnam	Support added for AP-377
WALLIS AND FUTUNA	Channels updated for AP-303 and AP-303H
ZAMBIA	• Channels updated for AP-303 and AP-303H • Update this country domain DFS type

1.0_66547

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 216: *1.0_66547*

Regulatory Domain	Regulatory Changes
AFGHANISTAN	Support added for AP-303H
ALAND ISLANDS	Support added for AP-303H
ANDORRA	Support added for AP-303H
ANGOLA	Support added for AP-303H
AZERBAIJAN	Support added for AP-303H
BOSNIA AND HERZEGOWINA	Support added for AP-303H
CAMEROON	Support added for AP-303H
Chile	Support added for AP-303, AP-318, AP-344, AP-345, AP-374, AP-375 and AP-377
CROATIA	Support added for AP-303H
Ecuador	Support added for AP-228
FAROE ISLANDS	Support added for AP-303H
FRENCH GUIANA	Support added for AP-303H
FRENCH POLYNESIA	Support added for AP-303H
FRENCH SOUTHERN TERRITORIES	Support added for AP-303H
GEORGIA	Support added for AP-303H
GREENLAND	Support added for AP-303H
GUADELOUPE	Support added for AP-303H
GUERNSEY	Support added for AP-303H
Indonesia	Support added for AP-374
ISLE OF MAN	Support added for AP-303H

Regulatory Domain	Regulatory Changes
Jamaica	Support added for AP-318, AP-374, AP-375 and AP-377
Japan	Channels updated for AP-365 and AP-367
JERSEY	Support added for AP-303H
KOSOVO	Support added for AP-303H
MACEDONIA	Support added for AP-303H
MARTINIQUE	Support added for AP-303H
Mexico	Support added for AP-303 and AP-377
MONTENEGRO	Support added for AP-303H
MOROCCO	Support added for AP-303H
MYANMAR	Support added for AP-303H
NEW CALEDONIA	Support added for AP-303H
REUNION	Support added for AP-303H
Rwanda	• Support added for AP-103, AP-103H, AP-104, AP-105, AP-114, AP-115, AP-124, AP-125, AP-134, AP-135, AP-175AC, AP-175DC, AP-175P,AP-203H,AP-203R, AP-204, AP-205, AP-205H, AP-207, AP-214,AP-215, AP-224, AP-225, AP-228,AP-274, AP-275, AP-303H,AP-304, AP-305, AP-314, AP-315, AP-318, AP-324, AP-325, AP-334, AP-335, AP-344, AP-345, AP-365, AP-367,AP-374, AP-375, AP-377, AP-92, AP-93, AP-93H, RAP-108, RAP-109,RAP-155, RAP-155P, RAP-3WN, RAP-3WNP • Channels updated for AP-303
SAINT BARTHELEMY	Support added for AP-303H
SAINT LUCIA	Support added for AP-303H
SAINT MARTIN	Support added for AP-303H
SAINT PIERRE AND MIQUELON	Support added for AP-303H
SAN MARINO	Support added for AP-303H
SENEGAL	Support added for AP-303H
SVALBARD AND JAN MAYEN	Support added for AP-303H
Thailand	Support added for AP-228
Tunisia	Support added for AP-318

Regulatory Domain	Regulatory Changes
TURKMENISTAN	Support added for AP-303H
VATICAN CITY	Support added for AP-303H
Vietnam	Support added for AP-114, AP-224, AP-274, AP-303, RAP-108 and RAP-109
WALLIS AND FUTUNA	Support added for AP-303H

1.0_66351

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 217: *1.0_66351*

Regulatory Domain	Regulatory Changes
Afghanistan	Channels updated for AP-375 and AP-377
Aland Islands	Channels updated for AP-375 and AP-377
Albania	Channels updated for AP-375 and AP-377
Andorra	Channels updated for AP-375 and AP-377
Angola	Channels updated for AP-375 and AP-377
Austria	Channels updated for AP-365, AP-367, AP-375 and AP-377
Azerbaijan	Channels updated for AP-375 and AP-377
Belgium	Channels updated for AP-365, AP-367, AP-375 and AP-377
Bosnia and Herzegovina	Channels updated for AP-375 and AP-377
Brazil	Support added for AP-303
Bulgaria	Channels updated for AP-365, AP-367, AP-375 and AP-377
Cameroon	Channels updated for AP-375 and AP-377
Costa Rica	Support added for AP-318, AP-374, AP-375 and AP-377
Croatia	Channels updated for AP-375 and AP-377
Cyprus	Channels updated for AP-365, AP-367, AP-375 and AP-377
Czech Republic	Channels updated for AP-365, AP-367, AP-375 and AP-377
Denmark	Channels updated for AP-365, AP-367, AP-375 and AP-377
Estonia	Channels updated for AP-365, AP-367, AP-375 and AP-377
Faroe Islands	Channels updated for AP-375 and AP-377
Finland	Channels updated for AP-365, AP-367, AP-375 and AP-377
France	Channels updated for AP-365, AP-367, AP-375 and AP-377

Regulatory Domain	Regulatory Changes
French Guiana	Channels updated for AP-375 and AP-377
French Polynesia	Channels updated for AP-375 and AP-377
French Southern Territories	Channels updated for AP-375 and AP-377
Georgia	Channels updated for AP-375 and AP-377
Germany	Channels updated for AP-365, AP-367, AP-375 and AP-377
Ghana	Support added for ,AP-203H,AP-203R, AP-204, AP-205, AP-205H, AP-207, AP-214,AP-215, AP-224, AP-228,AP-274, AP-275, AP-277, AP-303, AP-303H,AP-304, AP-305, AP-314, AP-315, AP-318, AP-334, AP-335, AP-344, AP-345,AP-365, AP-367,AP-374, AP-375, AP-377,RAP-108 and RAP-155
Greece	Channels updated for AP-365, AP-367, AP-375 and AP-377
Greenland	Channels updated for AP-375 and AP-377
Guadeloupe	Channels updated for AP-375 and AP-377
Guernsey	Channels updated for AP-375 and AP-377
Hungary	Channels updated for AP-365, AP-367, AP-375 and AP-377
Iceland	Channels updated for AP-365, AP-367, AP-375 and AP-377
India	Channels updated for AP-365 and AP-367
Ireland	Channels updated for AP-365, AP-367, AP-375 and AP-377
Isle of Man	Channels updated for AP-375 and AP-377
Italy	Channels updated for AP-365, AP-367, AP-375 and AP-377
Jersey	Channels updated for AP-375 and AP-377
Kosovo	Channels updated for AP-365, AP-367, AP-375 and AP-377
Latvia	Channels updated for AP-365, AP-367, AP-375 and AP-377
Liechtenstein	Channels updated for AP-365, AP-367, AP-375 and AP-377
Lithuania	Channels updated for AP-365, AP-367, AP-375 and AP-377
Luxembourg	Channels updated for AP-365, AP-367, AP-375 and AP-377
Macedonia	Channels updated for AP-375 and AP-377

Regulatory Domain	Regulatory Changes
Malta	Channels updated for AP-365, AP-367, AP-375 and AP-377
Martinique	Channels updated for AP-375 and AP-377
Mauritania	Channels updated for AP-365, AP-367, AP-375 and AP-377
Moldova	Channels updated for AP-365, AP-367, AP-375 and AP-377
Montenegro	Channels updated for AP-375 and AP-377
Mozambique	Channels updated for AP-365, AP-367, AP-375 and AP-377
Myanmar	Channels updated for AP-365, AP-375 and AP-377
Namibia	Channels updated for AP-365, AP-367, AP-375 and AP-377
Netherlands	Channels updated for AP-365, AP-367, AP-375 and AP-377
New Caledonia	Channels updated for AP-375 and AP-377
Norway	Channels updated for AP-365, AP-367, AP-375 and AP-377
Poland	Channels updated for AP-365, AP-367, AP-375 and AP-377
Portugal	Channels updated for AP-365, AP-367, AP-375 and AP-377
Reunion	Channels updated for AP-375 and AP-377
Romania	Channels updated for AP-365, AP-367, AP-375 and AP-377
Saint Barthelemy	Channels updated for AP-375 and AP-377
Saint Lucia	Channels updated for AP-375 and AP-377
Saint pierr and Miquelon	Channels updated for AP-375 and AP-377
Saint Martin	Channels updated for AP-375 and AP-377
San Marino	Channels updated for AP-375 and AP-377
Senegal	Channels updated for AP-375 and AP-377
Slovak Republic	Channels updated for AP-365, AP-367, AP-375 and AP-377
Slovenia	Channels updated for AP-365, AP-367, AP-375 and AP-377
South Africa	Support added for AP-374, AP-375 and AP-377
Spain	Channels updated for AP-365, AP-367, AP-375 and AP-377

Regulatory Domain	Regulatory Changes
Svalbard and Jan Mayen	Channels updated for AP-375 and AP-377
Sweden	Channels updated for AP-365, AP-367, AP-375 and AP-377
Switzerland	Channels updated for AP-365, AP-367, AP-375 and AP-377
Turkey	Channels updated for AP-365, AP-367, AP-375 and AP-377
United Kingdom	Channels updated for AP-365, AP-367, AP-375 and AP-377
Vatican City	Channels updated for AP-375 and AP-377
Wallis and Futuna	Channels updated for AP-375 and AP-377
Zambia	Channels updated for AP-365, AP-367, AP-375 and AP-377
Zimbabwe	Support added for AP-207, RAP-108 and RAP-109

1.0_66152

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 218: *1.0_66152*

Regulatory Domain	Regulatory Changes
Botswana	Support added for AP-207, RAP-108 and RAP-109
Brazil	Support added for AP-318
Colombia	Support added for AP-318
Ecuador	Support added for AP-303, AP-318, AP-374, AP-375 and AP-377
Ghana	Support added for AP-324 and AP-325
Hong Kong	Support added for AP-303, AP-318, AP-344, AP-345, AP-374, AP-375 and AP-377
Indonesia	Support added for AP-303
Libya	Support added for AP-207, RAP-108 and RAP-109
Malawi	Support added for AP-207, RAP-108 and RAP-109
Malaysia	Support added for AP-318
Peru	Support added for AP-303, AP-318, AP-374, AP-375 and AP-377
Ukraine	Support added for AP-318, AP-374, AP-375 and AP-377

1.0_65937

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 219: *1.0_65937*

Regulatory Domain	Regulatory Changes
Bahrain	Support added for AP-374 and AP-377
Belarus	Support added for AP-318
Brunei Darussalam	Support added for AP-207 and AP-225
India	Add support for Channel 169 and Channel 173
Israel	Support added for AP-318, AP-374, AP-375 and AP-377
Kazakhstan	Support added for AP-318
Kuwait	Support added for AP-377
Malaysia	Support added for AP-374
Russia	Support added for AP-318
Serbia	Support added for AP-374
South Africa	Support added for AP-318
Ukraine	Support added for AP-303
United Arab Emirates	Channels and power limit updated for AP-274, AP-275 and AP-277
Vietnam	Support added for AP-374

1.0_65685

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 220: *1.0_65685*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-203R and AP-203RP
Brazil	Support added for AP-374, AP-375 and AP-377
Ecuador	Support added for AP-365 and AP-367
Indonesia	Support added for AP-345 and AP-318
Qatar	Support added for AP-318
South Africa	support added for AP-303
Vietnam	Support added for AP-214

1.0_65473

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 221: *1.0_65473*

Regulatory Domain	Regulatory Changes
Bahamas	Support added for AP-203H, AP-203R, AP-203RP, AP-205H, AP-318, RAP-3WN and RAP-3WNP
Bahrain	Support added for AP-375
Belarus	Support added for AP-374, AP-375 and AP-377
Jordan	Support added for AP-303 and AP-375
Kazakhstan	Support added for AP-374, AP-375 and AP-377
Maritime Forward Operating Base	Support added for AP-345
Maritime Offshore	Channels updated for AP-345
Mauritania	Support added for AP-103, AP-103H, AP-104, AP-105, AP-114, AP-115, AP-124, AP-125, AP-134, AP-135, AP-175AC, AP-175DC, AP-175P,AP-203H,AP-203R, AP-203RP,AP-204, AP-205, AP-205H, AP-214,AP-215, AP-224, AP-225, AP-228,AP-274, AP-275, AP-277, AP-303, AP-303H,AP-304, AP-305, AP-314, AP-315, AP-324, AP-325, AP-344, AP-345,AP-365, AP-367,AP-374, AP-375, AP-377, RAP-3WN, RAP-3WNP, RAP-155, RAP-155P, RAP-108, RAP-109, AP-92, AP-93, AP-93H
Morocco	• Support added for AP-367 • Channels updated for AP-203H, AP-203R, AP-203RP, AP-303H, AP-365, AP-375 and AP-377
Mozambique	Support added for AP-103, AP-103H, AP-104, AP-105, AP-114, AP-115, AP-124, AP-125, AP-134, AP-135, AP-175AC, AP-175DC, AP-175P,AP-203H,AP-203R, AP-203RP,AP-204, AP-205, AP-205H, AP-214,AP-215, AP-224, AP-225, AP-228,AP-274, AP-275, AP-277, AP-303, AP-303H,AP-304, AP-305, AP-314, AP-315, AP-324, AP-325, AP-344, AP-345,AP-365, AP-367,AP-374, AP-375, AP-377, RAP-3WN, RAP-3WNP, RAP-155, RAP-155P, RAP-108, RAP-109, AP-92, AP-93, AP-93H
Russia	Support added for AP-374, AP-375 and AP-377
Serbia	Support added for AP-375

Regulatory Domain	Regulatory Changes
Venezuela	Channels updated for AP-303
Vietnam	Support added for AP-303H
Zambia	• Support added for AP-103, AP-103H, AP-203H, AP-203R, AP-203RP,AP-204, AP-205, AP-205H, AP-207, AP-214,AP-215, AP-224, AP-225, AP-228,AP-274, AP-275, AP-277, AP-303, AP-303H,AP-304, AP-305, AP-314, AP-315, AP-318, AP-324, AP-325, AP-334, AP-335, AP-344, AP-365, AP-367,AP-374, AP-375, AP-377, RAP-3WN, RAP-3WNP, RAP-155, RAP-155P, RAP-108, RAP-109 • Channels updated for AP-345

1.0_65328

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 222: *1.0_65328*

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-344, AP-365 and AP-367
Australia	Support added for AP-303
Bahamas	Support added for AP-344, AP-345, AP-374, AP-375 and AP-377
Bahrain	Support added for AP-303 and AP-318
Belarus	Support added for AP-303
India	Channels updated for AP-277, AP-318, AP-365, AP-367, AP-374, AP-375 and AP-377
Kazakhstan	Support added for AP-303
Kuwait	Support added for AP-318
Morocco	Channels updated for AP-345
New Zealand	Support added for AP-303
Philippines	Support added for AP-303
Qatar	Support added for AP-303
Russia	Support added for AP-303, AP-344 and AP-345

1.0_65103

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 223: *1.0_65103*

Regulatory Domain	Regulatory Changes
Afghanistan	• Power limits set for channels 149-165
Aland Islands	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Albania	• Update this country domain for AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
American Samoa	DFS bands enabled for AP-318
Andorra	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Angola	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Argentina	Support added for AP-345
Austria	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Azerbaijan	• Power limits set for channels 149-165
Belarus	• Power limits set for channels 149-165
Belgium	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Bosnia and Herzegovina	• Update this country domain for AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Bulgaria	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Cameroon	• Power limits set for channels 149-165
Chad	• Power limits set for channels 149-165
Chile	Support added for AP-303H and AP-367

Regulatory Domain	Regulatory Changes
Croatia	• Update this country domain for AP-215; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Cyprus	• Update this country domain for AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Czech Republic	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Denmark	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Estonia	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Ethiopia	• Update this country domain for AP-325; • Power limits set for channels 149-165
Faroe Islands	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Federated States of Micronesia	DFS bands enabled for AP-318
Finland	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
France	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
French Guiana	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
French Polynesia	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
French Southern Territories	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Georgia	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Germany	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Greece	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277;

Regulatory Domain	Regulatory Changes
	AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Greenland	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Guadeloupe	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Guam	DFS bands enabled for AP-318
Guernsey	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Hungary	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Iceland	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Ireland	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Isle of Man	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Israel	• Support added for AP-303, AP-344 and AP-345 • Channels updated for AP-314, AP-315, AP-334 and AP-335 • Update Israel country domain allowed channels list for outdoor devices
Italy	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Jersey	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Kosovo	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Latvia	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Lebanon	• Power limits set for channels 149-165
Liechtenstein	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335

Regulatory Domain	Regulatory Changes
	• Power limits set for channels 149-165
Lithuania	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Luxembourg	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Macedonia	• Update this country domain for AP-325; AP-335 • Power limits set for channels 149-165
Mali	• Power limits set for channels 149-165
Malta	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Marshall Islands	DFS bands enabled for AP-318
Martinique	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Mauritania	• Update this country domain for AP-335 • Power limits set for channels 149-165
Mauritius	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Mayotte	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Moldova	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Monaco	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Montenegro	• Update this country domain for AP-325; AP-335 • Power limits set for channels 149-165
Morocco	• Update this country domain for AP-325; • Power limits set for channels 149-165
Mozambique	• Update this country domain for AP-335 • Power limits set for channels 149-165
Myanmar	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165

Regulatory Domain	Regulatory Changes
Namibia	• Power limits set for channels 149-165 • Support added for AP-103, AP-103H, AP-104, AP-114, AP-115, AP-175AC, AP-175DC, AP-175P,AP-203H,AP-203R, AP-203RP,AP-204, AP-205, AP-205H, AP-207, AP-214,AP-215, AP-224, AP-225, AP-228,AP-274, AP-275, AP-277, AP-303, AP-303H,AP-304, AP-324AP-305, AP-314, AP-315, AP-318, AP-324, AP-325, AP-334, AP-335, AP-344, AP-345,AP-365, AP-367,AP-374, AP-375, AP-377, RAP-3WN, RAP-3WNP, RAP-155, RAP-155P, RAP-108, RAP-109, AP-92, AP-93
Netherlands	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
New Caledonia	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Niger	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Northern Mariana Islands	DFS bands enabled for AP-318
Norway	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Oman	Support added for AP-303
Poland	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Portugal	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Puerto Rico	DFS bands enabled for AP-318
Qatar	• Support added for AP-375 and AP-377 • Channels updated for AP-374
Reunion	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Romania	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Saint Barthelemy	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Saint Lucia	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165

Regulatory Domain	Regulatory Changes
Saint pierr and Miquelon	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Saint Martin	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
San Marino	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Saudi Arabia	• support added for AP-318 and AP-374 • Channels updated for AP-303
Senegal	• Update this country domain for AP-325; • Power limits set for channels 149-165
Serbia	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Slovak Republic	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Slovenia	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Spain	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Svalbard and Jan Mayen	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Sweden	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Switzerland	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Taiwan	Support added for AP-318
Tanzania	• Power limits set for channels 149-165
Tunisia	• Update this country domain for AP-325 • Power limits set for channels 149-165
Turkey	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165

Regulatory Domain	Regulatory Changes
Turkmenistan	• Power limits set for channels 149-165
United Arab Emirates	support added for AP-318
United States of America	DFS bands enabled for AP-318
United Kingdom	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
US Virgin Islands	DFS bands enabled for AP-318
Vatican City	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165
Wallis and Futuna	• Update this country domain for AP-205; AP-215; AP-225; AP-275; AP-277; AP-315; AP-325; AP-335 • Power limits set for channels 149-165

1.0_64825

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 224: *1.0_64825*

Regulatory Domain	Regulatory Changes
Australia	Support added for AP-318
Cameroon	Support added for RAP-3WN and RAP-3WNP
China	Support added for AP-277
Indonesia	Support added for AP-344
Japan	Channels updated for AP-318, AP-344, AP-345, AP-374, AP-375 and AP-377
New Zealand	Support added for AP-318
Peru	Support added for AP-344 and AP-345
Qatar	• Support added for AP-374; • Updated Qatar maximum power limits
Senegal	• Support added for AP-103, AP-103H, AP-104, AP-114, AP-115, AP-175AC, AP-175DC, AP-175P,AP-203H,AP-205H, AP-214, AP-224, AP-225, AP-228,AP-274, AP-275, AP-277, AP-303H, AP-324, AP-325, AP-374, AP-375, AP-377, RAP-3WN, RAP-3WNP, RAP-155, RAP-155P, RAP-108, RAP-109 • Channels updated for AP-105,AP-134, AP-135,AP-204, AP-205, AP-215, AP-92, AP-93, AP-93H
Singapore	Support added for AP-318
Uganda	Support added for RAP-3WN and RAP-3WNP
United Arab Emirates	Support added for AP-377

1.0_64657

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 225: *1.0_64657*

Regulatory Domain	Regulatory Changes
India	Support added for AP-318
Kuwait	Support added for AP-374 and AP-375
Oman	Support added for AP-374 and AP-375
Philippines	Support added for AP-318, AP-374, AP-375 and AP-377
Thailand	Support added for AP-374, AP-375 and AP-377
Vietnam	Support added for AP-375

1.0_64450

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 226: *1.0_64450*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP-203H
Aland Islands	Support added for AP-203H
Andorra	Support added for AP-203H
Angola	Support added for AP-203H
Argentina	Support added for AP-203H, AP-203R and AP-203RP
Azerbaijan	Support added for AP-203H
Bosnia and Herzegovina	Support added for AP-203H
Cameroon	Support added for AP-203H
Croatia	Support added for AP-203H
Egypt	Support added for AP-318
Faroe Islands	Support added for AP-203H
French Guiana	Support added for AP-203H
French Polynesia	Support added for AP-203H
French Southern Territories	Support added for AP-203H
Georgia	Support added for AP-203H
Greenland	Support added for AP-203H
Guadeloupe	Support added for AP-203H
Guernsey	Support added for AP-203H
Isle of Man	Support added for AP-203H
Jersey	Support added for AP-203H
Kosovo	Support added for AP-203H

Regulatory Domain	Regulatory Changes
Macedonia	Support added for AP-203H
Malaysia	Support added for AP-303 and AP-377
Martinique	Support added for AP-203H
Montenegro	Support added for AP-203H
Morocco	Support added for AP-203H
Myanmar	Support added for AP-203H
New Caledonia	Support added for AP-203H
Philippines	Support added for AP-344 and AP-345
Reunion	Support added for AP-203H
Saint Barthelemy	Support added for AP-203H
Saint Lucia	Support added for AP-203H
Saint Martin	Support added for AP-203H
Saint Pierre and Miquelon	Support added for AP-203H
San Marino	Support added for AP-203H
Saudi Arabia	Support added for AP-375 and AP-377
South Africa	Support added for AP-344 and AP-345
South Korea	Support added for AP-318, AP-374, AP-375 and AP-377
Svalbard and Jan Mayen	Support added for AP-203H
Thailand	Support added for AP-344 and AP-345
Turkmenistan	Support added for AP-203H
Ukraine	Support added for AP-344 and AP-345
United Arab Emirates	Support added for AP-374 and AP-375
Vatican City	Support added for AP-203H
Vietnam	Support added for AP-318
Wallis and Futuna	Support added for AP-203H

1.0_64331

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 227: *1.0_64331*

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-303H
Australia	Channels updated for AP-103, AP-104, AP-105, AP-114, AP-115, AP-120, AP-121, AP-125, AP-134, AP-135, AP-203R, AP-203RP, AP-205, AP-205H, AP-207, AP-214, AP-215, AP-224,AP-225, AP-228, AP-274, AP-275, AP-277, AP-303H, AP-314, AP-315, AP-324, AP-325, AP-365, AP-367, AP-92 and RAP-108
Croatia	Support added for AP-277
India	Support added for AP-303
Malaysia	Support added for AP-375
New Zealand	Channels updated for AP-103, AP-104, AP-105, AP-114, AP-115, AP-120, AP-121, AP-125, AP-134, AP-135, AP-203R, AP-203RP, AP-205, AP-205H, AP-207, AP-214, AP-215, AP-224,AP-225, AP-228, AP-274, AP-275, AP-277, AP-303H, AP-314, AP-315, AP-324, AP-325, AP-365, AP-367, AP-92 and RAP-108
Taiwan	Channels updated for AP-103, AP-204, AP-205, AP-214, AP-215, AP-224 and AP-225

1.0_64134

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 228: *1.0_64134*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP-318
Aland Islands	Support added for AP-318
Albania	Support added for AP-318
American Samoa	Channels updated for AP-303
Andorra	Support added for AP-318
Angola	Support added for AP-318
Australia	• Support added for AP-344, AP-345, AP-374, AP-375 and AP-377; • Channels updated for AP-205H and AP-215
Austria	Support added for AP-318
Azerbaijan	Support added for AP-318
Belgium	Support added for AP-318
Bosnia and Herzegovina	Support added for AP-318
Bulgaria	Support added for AP-318
Canada	Channels updated for AP-374, AP-375 and AP-377
Cameroon	Support added for AP-318
Croatia	Support added for AP-318
Cyprus	Support added for AP-318
Czech Republic	Support added for AP-318
Denmark	Support added for AP-318
Estonia	Support added for AP-318
Ethiopia	Support added for AP-318

Regulatory Domain	Regulatory Changes
Faroe Islands	Support added for AP-318
Federated States of Micronesia	Channels updated for AP-303, AP-374, AP-375 and AP-377
Finland	Support added for AP-318
France	Support added for AP-318
French Guiana	Support added for AP-318
French Polynesia	Support added for AP-318
French Southern Territories	Support added for AP-318
Georgia	Support added for AP-318
Germany	Support added for AP-318
Greece	Support added for AP-318
Greenland	Support added for AP-318
Guadeloupe	Support added for AP-318
Guam	Channels updated for AP-303, AP-374, AP-375 and AP-377
Guernsey	Support added for AP-318
Hungary	Support added for AP-318
Iceland	Support added for AP-318
India	Support added for AP-203R and AP-203RP
Ireland	Support added for AP-318
Isle of Man	Support added for AP-318
Italy	Support added for AP-318
Jersey	Support added for AP-318
Kosovo	Support added for AP-318
Latvia	Support added for AP-318
Lebanon	Support added for AP-318
Liechtenstein	Support added for AP-318

Regulatory Domain	Regulatory Changes
Lithuania	Support added for AP-318
Luxembourg	Support added for AP-318
Macedonia	Support added for AP-318
Malta	Support added for AP-318
Marshall Islands	Channels updated for AP-303, AP-374, AP-375 and AP-377
Martinique	Support added for AP-318
Mauritania	Support added for AP-318
Mauritius	Support added for AP-318
Mayotte	Support added for AP-318
Mexico	Support added for AP-344 and AP-345
Moldova	Support added for AP-318
Monaco	Support added for AP-318
Montenegro	Support added for AP-318
Morocco	Support added for AP-318
Mozambique	Support added for AP-303, AP-334 and AP-335
Myanmar	Support added for AP-318
Netherlands	Support added for AP-318
New Caledonia	Support added for AP-318
New Zealand	• Support added for AP-344, AP-345, AP-374, AP-375 and AP-377; • Channels updated for AP-205H and AP-215
Niger	Support added for AP-318
North Mariana Islands	Channels updated for AP-303, AP-374, AP-375 and AP-377
Norway	Support added for AP-318
Poland	Support added for AP-318
Portugal	Support added for AP-318

Regulatory Domain	Regulatory Changes
Puert Rico	Channels updated for AP-303, AP-374, AP-375 and AP-377
Reunion	Support added for AP-318
Romania	Support added for AP-318
Rwanda	Support added for AP-303
Saint Barthelemy	Support added for AP-318
Saint Lucia	Support added for AP-318
Saint Martin	Support added for AP-318
San Marino	Support added for AP-318
Saint pierr and Miquelon	Support added for AP-318
Senegal	Support added for AP-318
Serbia	Support added for AP-318
Slovak Republic	Support added for AP-318
Slovenia	Support added for AP-318
South Korea	Support added for AP-344 and AP-345
Spain	Support added for AP-318
Svalbard and Jan Mayen	Support added for AP-318
Sweden	Support added for AP-318
Switzerland	Support added for AP-318
Taiwan	Support added for AP-303
Turkey	Support added for AP-318
Turkmenistan	Support added for AP-318
Ukraine	Support added for AP-205H, AP-303H, AP-365 and AP-367
United Arab Emirates	Support added for AP-303
United Kingdom	Support added for AP-318
United States of America	• Channels updated for AP-303, AP-374, AP-375 and AP-377 • Support added for AP-318

Regulatory Domain	Regulatory Changes
US Virgin Islands	Channels updated for AP-303, AP-374, AP-375 and AP-377
Vatican City	Support added for AP-318
Wallis and Futuna	Support added for AP-318

1.0_63879

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 229: *1.0_63879*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-303
American Samoa	Support added for AP-303
Antigua and Barbuda	Support added for AP-303
Armenia	Support added for AP-303
Bahamas	Support added for AP-303
Bangladesh	Support added for AP-303
Barbados	Support added for AP-303
Bermuda	Support added for AP-303
Bolivia	Support added for AP-303
Cameroon	Support added for AP-303
Canada	Support added for AP-303 and AP-318
Cayman Islands	Support added for AP-303
Colombia	Support added for AP-303
Costa Rica	Support added for AP-303
Curacao	Support added for AP-303
Dominican Republic	Support added for AP-303
Egypt	Support added for AP-303
El Salvadore	Support added for AP-303
Federated States of Micronesia	Support added for AP-303
Grenada	Support added for AP-303
Guam	Support added for AP-303

Regulatory Domain	Regulatory Changes
Guatemala	Support added for AP-303
Guyana	Support added for AP-303
Haiti	Support added for AP-303
Honduras	Support added for AP-303
India	Support added for AP-344, AP-345, AP-374, AP-375 and AP-377
Jamaica	Support added for AP-303
Kenya	Support added for AP-303
Kuwait	Support added for AP-303
Lao	Support added for AP-303
Lebanon	Support added for AP-303
Macau	Support added for AP-303
Marshall Islands	Support added for AP-303
Mauritania	Support added for AP-303
Nicaragua	Support added for AP-303
Nigeria	Support added for AP-303
North Mariana Islands	Support added for AP-303
Pakistan	Support added for AP-303
Panama	Support added for AP-303
Paraguay	Support added for AP-303
Puerto Rico	Support added for AP-303
Saint Vincent and the Grenadines	Support added for AP-303
Saudi Arabia	Support added for AP-303
Singapore	Support added for AP-303, AP-344, AP-345, AP-374 and AP-375
Sri Lanka	Support added for AP-303

Regulatory Domain	Regulatory Changes
Suriname	Support added for AP-303
Tanzania	Support added for AP-303
Trinidad and Tobago	Support added for AP-303
Tunisia	Support added for AP-303
Turkmenistan	Support added for AP-303
Uganda	Support added for AP-303
United States	Support added for AP-303 and AP-68P
Uruguay	Support added for AP-303
US Virgin Islands	Support added for AP-303
Venezuela	Support added for AP-303

1.0_63727

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 230: *1.0_63727*

Regulatory Domain	Regulatory Changes
Canada	Support added for AP-374, AP-375 and AP-377
China	Support added for AP-303, AP-318, AP-344, AP-345, AP-374, AP-375 and AP-377
Ecuador	Support added for AP-344 and AP-345
Mauritania	Support added for AP-334 and AP-335
Taiwan	Support added for AP-344 and AP-345

1.0_63516

his table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 231: *1.0_63516*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP-303
Aland Islands	Support added for AP-303
Albania	Support added for AP-303
Andorra	Support added for AP-303
Angola	Support added for AP-303
Austria	Support added for AP-303
Azerbaijan	Support added for AP-303
Belgium	Support added for AP-303
Bosnia and Herzegovina	Support added for AP-303
Brazil	Support added for AP-344 and AP-345
Bulgaria	Support added for AP-303
Cameroon	Support added for AP-303
Canada	Channels updated for AP-344 and AP-345
Croatia	Support added for AP-303
Cyprus	Support added for AP-303
Czech Republic	Support added for AP-303
Denmark	Support added for AP-303
Estonia	Support added for AP-303
Ethiopia	Support added for AP-303
Faroe Islands	Support added for AP-303

Regulatory Domain	Regulatory Changes
Finland	Support added for AP-303
France	Support added for AP-303
French Guiana	Support added for AP-303
French Polynesia	Support added for AP-303
French Southern Territories	Support added for AP-303
Georgia	Support added for AP-303
Germany	Support added for AP-303
Greece	Support added for AP-303
Greenland	Support added for AP-303
Guadeloupe	Support added for AP-303
Guernsey	Support added for AP-303
Hungary	Support added for AP-303
Iceland	Support added for AP-303
Ireland	Support added for AP-303
Isle of Man	Support added for AP-303
Italy	Support added for AP-303
Japan	Support added for AP-318, AP-344, AP-345, AP-374, AP-375 and AP-377
Jersey	Support added for AP-303
Kosovo	Support added for AP-303
Latvia	Support added for AP-303
Liechtenstein	Support added for AP-303
Lithuania	Support added for AP-303
Luxembourg	Support added for AP-303
Macedonia	Support added for AP-303
Malaysia	Support added for AP-344

Regulatory Domain	Regulatory Changes
Malta	Support added for AP-303
Martinique	Support added for AP-303
Mauritius	Support added for AP-303
Mayotte	Support added for AP-303
Moldova	Support added for AP-303
Monaco	Support added for AP-303
Montenegro	Support added for AP-303
Morocco	Support added for AP-303
Myanmar	Support added for AP-303
Netherlands	Support added for AP-303
New Caledonia	Support added for AP-303
Niger	Support added for AP-303
Norway	Support added for AP-303
Poland	Support added for AP-303
Portugal	Support added for AP-303
Reunion	Support added for AP-303
Romania	Support added for AP-303
Saint Barthelemy	Support added for AP-303
Saint Lucia	Support added for AP-303
Saint pierr and Miquelon	Support added for AP-303
Saint Martin	Support added for AP-303
San Marino	Support added for AP-303
Senegal	Support added for AP-303
Serbia	Support added for AP-303
Slovak Republic	Support added for AP-303

Regulatory Domain	Regulatory Changes
Slovenia	Support added for AP-303
Spain	Support added for AP-303
Svalbard and Jan Mayen	Support added for AP-303
Sweden	Support added for AP-303
Switzerland	Support added for AP-303
Tunisia	• Channels updated for AP-277 and AP-365 • Support added for AP-274, AP-275, AP-367, AP-374, AP-375 and AP-377
Turkey	Support added for AP-303
United Arab Emirates	Support added for AP-344 and AP-345
United Kingdom	Support added for AP-303
United States of America	Support added for AP-374, AP-375 and AP-377
Vatican City	Support added for AP-303
Wallis and Futuna	Support added for AP-303

1.0_63392

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 232: *1.0_63392*

Regulatory Domain	Regulatory Changes
Armenia	Support added for AP-305 and OC-30
Dominican Republic	Support added for AP-305 and OC-30
Japan	Support added for AP-303
Jordan	Support added for AP-344 and AP-345
Kenya	Support added for AP-134 and AP-135
Kuwait	Support added for RAP-3WN and RAP-3WNP
Laos	Support added for AP-305 and OC-30
Saudi Arabia	Support added for AP-344 and AP-345
Singapore	Support added for AP-365 and AP-367
South Korea	Support added for AP-303
Taiwan	Support added for AP-203R and AP-203RP
Tunisia	Channels updated for all outdoor APs
Turkmenistan	• Add support for country code Turkmenistan; • Support added for AP-305 and OC-30
Vietnam	Support added for AP-344 and AP-345

1.0_63102

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 233: *1.0_63102*

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-207, AP-304 and AP-305
Armenia	Support added for AP-103, AP-103H, AP-114, AP-115, AP-203H, AP-203R, AP-204, AP-205, AP-205H, AP-207, AP-214, AP-215, AP-224, AP-225, AP-228, AP-274, AP-275, AP-277, AP-303H, AP-314, AP-315, AP-324, AP-325, AP-334, AP-335, AP-344, AP-345, AP-365, AP-367, AP-374, AP-375, AP-377, RAP-108, RAP-109, RAP-155, RAP-155P, RAP-3WN and RAP-3WNP
Brazil	Support added for AP-203R and AP-203RP
Egypt	Support added for AP-203H, AP-367, AP-374, AP-375 and AP-377

1.0_63044

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 234: *1.0_63044*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP-374, AP-375 and AP-377
Aland Islands	Support added for AP-374, AP-375 and AP-377
Albania	Support added for AP-374, AP-375 and AP-377
American Samoa	Channels updated for AP-344 and AP-345
Andorra	Support added for AP-374, AP-375 and AP-377
Angola	Support added for AP-374, AP-375 and AP-377
Austria	Support added for AP-374, AP-375 and AP-377
Azerbaijan	Support added for AP-374, AP-375 and AP-377
Bahrain	Support added for AP-203H
Belgium	Support added for AP-374, AP-375 and AP-377
Bosnia and Herzegovina	Support added for AP-374, AP-375 and AP-377
Bulgaria	Support added for AP-374, AP-375 and AP-377
Cameroon	Support added for AP-374, AP-375 and AP-377
Chile	Support added for AP-365
Costa Rica	Support added for AP-203H, AP-203R, AP-203RP, AP-303H, AP-344, AP-345, AP-365 and AP-367
Croatia	Support added for AP-374, AP-375 and AP-377
Cyprus	Support added for AP-374, AP-375 and AP-377
Czech Republic	Support added for AP-374, AP-375 and AP-377
Denmark	Support added for AP-374, AP-375 and AP-377
Egypt	Support added for AP-303H

Regulatory Domain	Regulatory Changes
Estonia	Support added for AP-374, AP-375 and AP-377
Faroe Islands	Support added for AP-374, AP-375 and AP-377
Federated States of MIcronesia	Channels updated for AP-344 and AP-345
Finland	Support added for AP-374, AP-375 and AP-377
France	Support added for AP-374, AP-375 and AP-377
French Guiana	Support added for AP-374, AP-375 and AP-377
French Polynesia	Support added for AP-374, AP-375 and AP-377
French Southern Territories	Support added for AP-374, AP-375 and AP-377
Georgia	Support added for AP-374, AP-375 and AP-377
Germany	Support added for AP-374, AP-375 and AP-377
Greece	Support added for AP-374, AP-375 and AP-377
Greenland	Support added for AP-374, AP-375 and AP-377
Guadeloupe	Support added for AP-374, AP-375 and AP-377
Guam	Channels updated for AP-344 and AP-345
Guernsey	Support added for AP-374, AP-375 and AP-377
Hungary	Support added for AP-374, AP-375 and AP-377
Iceland	Support added for AP-374, AP-375 and AP-377
Ireland	Support added for AP-374, AP-375 and AP-377
Isle of Man	Support added for AP-374, AP-375 and AP-377
Israel	Channels updated for this country domain
Italy	Support added for AP-374, AP-375 and AP-377
Jersey	Support added for AP-374, AP-375 and AP-377
Kosovo	Support added for AP-374, AP-375 and AP-377
Latvia	Support added for AP-374, AP-375 and AP-377
Liechtenstein	Support added for AP-374, AP-375 and AP-377

Regulatory Domain	Regulatory Changes
Lithuania	Support added for AP-374, AP-375 and AP-377
Luxembourg	Support added for AP-374, AP-375 and AP-377
Macedonia	Support added for AP-374, AP-375 and AP-377
Malaysia	Support added for AP-345
Malta	Support added for AP-374, AP-375 and AP-377
Marshall Islands	Channels updated for AP-344 and AP-345
Martinique	Support added for AP-374, AP-375 and AP-377
Moldova	Support added for AP-374, AP-375 and AP-377
Montenegro	Support added for AP-374, AP-375 and AP-377
Morocco	• Support added for AP-374, AP-375 and AP-377 • Support added for AP-314 and AP-315
Myanmar	Support added for AP-374, AP-375 and AP-377
Netherlands	Support added for AP-374, AP-375 and AP-377
New Caledonia	Support added for AP-374, AP-375 and AP-377
Northern Mariana Islands	Channels updated for AP-344 and AP-345
Norway	Support added for AP-374, AP-375 and AP-377
Poland	Support added for AP-374, AP-375 and AP-377
Portugal	Support added for AP-374, AP-375 and AP-377
Puerto Rico	Channels updated for AP-344 and AP-345
Reunion	Support added for AP-374, AP-375 and AP-377
Romania	Support added for AP-374, AP-375 and AP-377
Russia	Channels updated for AP-304 and AP-305
Saint Barthelemy	Support added for AP-374, AP-375 and AP-377
Saint Lucia	Support added for AP-374, AP-375 and AP-377
Saint pierr and Miquelon	Support added for AP-374, AP-375 and AP-377

Regulatory Domain	Regulatory Changes
Saint Martin	Support added for AP-374, AP-375 and AP-377
San Marino	Support added for AP-374, AP-375 and AP-377
Slovak Republic	Support added for AP-374, AP-375 and AP-377
Slovenia	Support added for AP-374, AP-375 and AP-377
Spain	Support added for AP-374, AP-375 and AP-377
Sri Lanka	Support added for AP-204
Svalbard and Jan Mayen	Support added for AP-374, AP-375 and AP-377
Sweden	Support added for AP-374, AP-375 and AP-377
Switzerland	Support added for AP-374, AP-375 and AP-377
Turkey	Support added for AP-374, AP-375 and AP-377
United Kingdom	Support added for AP-374, AP-375 and AP-377
United States of America	Channels updated for AP-344 and AP-345
US Virgin Islands	Channels updated for AP-344 and AP-345
Vatican City	Support added for AP-374, AP-375 and AP-377
Wallis and Futuna	Support added for AP-374, AP-375 and AP-377

1.0_62783

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 235: *1.0_62783*

Regulatory Domain	Regulatory Changes
Afghanistan	• Channels updated for AP-304 • Support added for AP-305
Angola	• Support added for AP-207 • Support added for AP-304 and AP-305
Antigua and Barbuda	• Channels updated for AP-207 • Support added for AP-304 and AP-305
Azerbaijan	Support added for AP-304 and AP-305
Bahamas	• Channels updated for AP-207 • Limits updated for this country domain • Channels updated for AP-304 and AP-305
Bangladesh	• Support added for AP-207 • Support added for AP-304 and AP-305
Barbados	• Channels updated for AP-207 • Limits updated for this country domain • Channels updated for AP-304 and AP-305
Bermuda	• Channels updated for AP-207 • Limits updated for this country domain • Channels updated for AP-304 and AP-305
Bolivia	• Channels updated for AP-207 • Channels updated for AP-304 and AP-305
Cameroon	• Support added for AP-207 • Support added for AP-304 and AP-305
Cayman Islands	• Support added for AP-207 • Limits updated for this country domain • Support added for AP-304 and AP-305
Curacao	• Channels updated for AP-207 • Limits updated for this country domain • Channels updated for AP-304 and AP-305
Dominican Republic	Channels updated for AP-207
Ecuador	Support added for AP-303H
El Salvador	• Channels updated for AP-207 • Support added for AP-304 and AP-305

Regulatory Domain	Regulatory Changes
Ethiopia	Support added for AP-207
Georgia	Support added for AP-207
Grenada	• Channels updated for AP-207 • Limits updated for this country domain • Channels updated for AP-304 and AP-305
Guadelupe	• Channels updated for AP-207 • Support added for AP-304 and AP-305
Guatemala	• Channels updated for AP-207 • Channels updated for AP-304 and AP-305
Guyana	• Channels updated for AP-207 • Channels updated for AP-304 and AP-305
Haiti	• Channels updated for AP-207 • Limits updated for this country domain • Channels updated for AP-304 and AP-305
Honduras	• Channels updated for AP-207 • Limits updated for this country domain • Channels updated for AP-304 and AP-305
Jamaica	Channels updated for AP-304 and AP-305
Kosovo	Support added for AP-207
Lao	• Support added for AP-207 • Limits updated for this country domain
Mauritius	Support added for AP-207
Morocco	Support added for AP-304 and AP-305
Nicaragua	• Channels updated for AP-207 • Limits updated for this country domain • Channels updated for AP-304 and AP-305
Panama	• Channels updated for AP-207 • Limits updated for this country domain • Channels updated for AP-304 and AP-305
Paraguay	• Channels updated for AP-207 • Limits updated for this country domain • Channels updated for AP-304 and AP-305
Saint Lucia	• Channels updated for AP-207 • Channels updated for AP-304 and AP-305
Saint Vincent and the Grenadines	• Channels updated for AP-207 • Limits updated for this country domain • Support added for AP-304 • Channels updated for AP-305

Regulatory Domain	Regulatory Changes
Sri Lanka	• Support added for AP-103, AP-103H, AP-205, AP-205H, AP-214, AP-274, AP-275, AP-277, AP-304, AP-305, AP-324, AP-325, AP-344, AP-345, AP-367, RAP-108, RAP-109, RAP-3WN and RAP-3WNP • Channels updated for AP-203H, AP-203R, AP-203RP, AP-207, AP-215, AP-303H, AP-314, AP-315, AP-365
Suriname	• Channels updated for AP-207 • Channels updated for AP-304 and AP-305
Trinidad and Tobago	• Channels updated for AP-207 • Channels updated for AP-304 and AP-305
Uruguay	• Channels updated for AP-207 • Channels updated for AP-304 and AP-305
Venezuela	• Channels updated for AP-207 • Channels updated for AP-304 and AP-305

1.0_62496

This table describes the new regulatory changes to access points and channels introduced in this release.

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 236: *1.0_62496*

Regulatory Domain	Regulatory Changes
Aland Islands	Support added for AP-304 and AP-305
Andorra	Support added for AP-304 and AP-305
Canada	Channels updated for AP-207, AP-304 and AP-305
China	Support added for AP-203R and AP-203RP
Egypt	Egypt country domain updated for all APs to allow outdoor channels 36-64
Faroe Islands	Support added for AP-304 and AP-305
French Guiana	Support added for AP-304 and AP-305
French Polynesia	Support added for AP-304 and AP-305
French Southern Territories	Support added for AP-304 and AP-305
Greenland	Support added for AP-304 and AP-305
Guernsey	Support added for AP-304 and AP-305
Isle of Man	Support added for AP-304 and AP-305
Jersey	Support added for AP-304 and AP-305
Martinique	Support added for AP-304 and AP-305
New Caledonia	Support added for AP-304 and AP-305
Reunion	Support added for AP-304 and AP-305
Saint Barthelemy	Support added for AP-304 and AP-305
Saint Martin	Support added for AP-304 and AP-305
Saint Pierre and Miquelon	Support added for AP-304 and AP-305
San Marino	Support added for AP-304 and AP-305
Svalbard and Jan Mayen	Support added for AP-304 and AP-305

Regulatory Domain	Regulatory Changes
Trinidad and Tobago	Support added for AP-365 and AP-367
Vatican City	Support added for AP-304 and AP-305
Wallis and Futuna	Support added for AP-304 and AP-305

1.0_62311

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 237: *1.0_62311*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP-344 and AP-345
Aland Islands	Support added for AP-344 and AP-345
Albania	Support added for AP-344 and AP-345
Andorra	Support added for AP-344 and AP-345
Angola	Support added for AP-344 and AP-345
Austria	Support added for AP-344 and AP-345
Azerbaijan	Support added for AP-344 and AP-345
Belgium	Support added for AP-344 and AP-345
Bolivia	Support added for AP-344 and AP-345
Bosnia and Herzegovina	Support added for AP-344 and AP-345
Bulgaria	Support added for AP-344 and AP-345
Cameroon	Support added for AP-344 and AP-345
Croatia	Support added for AP-344 and AP-345
Cyprus	Support added for AP-344 and AP-345
Czech Republic	Support added for AP-344 and AP-345
Denmark	Support added for AP-344 and AP-345
Egypt	• Channels updated for AP-207, AP-304 and AP-305 • Support added for AP-344 and AP-345
Estonia	Support added for AP-344 and AP-345
Ethiopia	Support added for AP-344 and AP-345
Faroe Islands	Support added for AP-344 and AP-345

Regulatory Domain	Regulatory Changes
Finland	Support added for AP-344 and AP-345
France	Support added for AP-344 and AP-345
French Guiana	Support added for AP-344 and AP-345
French Polynesia	Support added for AP-344 and AP-345
French Southern Territories	Support added for AP-344 and AP-345
Georgia	Support added for AP-344 and AP-345
Germany	Support added for AP-344 and AP-345
Greece	Support added for AP-344 and AP-345
Greenland	Support added for AP-344 and AP-345
Guadeloupe	Support added for AP-344 and AP-345
Guernsey	Support added for AP-344 and AP-345
Haiti	Support added for AP-344 and AP-345
Hungary	Support added for AP-344 and AP-345
Iceland	Support added for AP-344 and AP-345
Ireland	Support added for AP-344 and AP-345
Isle of Man	Support added for AP-344 and AP-345
Italy	Support added for AP-344 and AP-345
Jamaica	Support added for AP-344 and AP-345
Jersey	Support added for AP-344 and AP-345
Kosovo	Support added for AP-344 and AP-345
Latvia	Support added for AP-344 and AP-345
Lebanon	Support added for AP-344 and AP-345
Liechtenstein	Support added for AP-344 and AP-345
Lithuania	Support added for AP-344 and AP-345
Luxembourg	Support added for AP-344 and AP-345

Regulatory Domain	Regulatory Changes
Macau	Support added for AP-344 and AP-345
Malta	Support added for AP-344 and AP-345
Macedonia	Support added for AP-344 and AP-345
Martinique	Support added for AP-344 and AP-345
Mauritius	Support added for AP-344 and AP-345
Mayotte	Support added for AP-344 and AP-345
Moldova	Support added for AP-344 and AP-345
Monaco	Support added for AP-344 and AP-345
Montenegro	Support added for AP-344 and AP-345
Morocco	Support added for AP-344 and AP-345
Myanmar	Support added for AP-344 and AP-345
Netherlands	Support added for AP-344 and AP-345
New Caledonia	Support added for AP-344 and AP-345
Niger	Support added for AP-344 and AP-345
Norway	Support added for AP-344 and AP-345
Pakistan	Support added for AP-344 and AP-345
Poland	Support added for AP-344 and AP-345
Portugal	Support added for AP-344 and AP-345
Reunion	Support added for AP-344 and AP-345
Romania	Support added for AP-344 and AP-345
Saint Barthelemy	Support added for AP-344 and AP-345
Saint Lucia	Support added for AP-344 and AP-345
Saint pierr and Miquelon	Support added for AP-344 and AP-345
Saint Martin	Support added for AP-344 and AP-345
San Marino	Support added for AP-344 and AP-345

Regulatory Domain	Regulatory Changes
Senegal	Support added for AP-344 and AP-345
Serbia	Support added for AP-344 and AP-345
Slovak Republic	Support added for AP-344 and AP-345
Slovenia	Support added for AP-344 and AP-345
Spain	Support added for AP-344 and AP-345
Suriname	Support added for AP-344 and AP-345
Svalbard and Jan Mayen	Support added for AP-344 and AP-345
Sweden	Support added for AP-344 and AP-345
Switzerland	Support added for AP-344 and AP-345
Tunisia	Support added for AP-344 and AP-345
Turkey	Support added for AP-344 and AP-345
United Kingdom	Support added for AP-344 and AP-345
Vatican City	Support added for AP-344 and AP-345
Wallis and Futuna	Support added for AP-344 and AP-345

1.0_62141

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 238: *1.0_62141*

Regulatory Domain	Regulatory Changes
Brazil	Support added for AP-203H
Ghana	Support added for RAP-109
Macau	• Support added for AP-205H • Support added for AP-224
Mexico	Support added for AP-203R and AP-203RP
Russia	Channels updated for AP-203H
South Africa	Support added for AP-277

1.0_61955

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 239: *1.0_61955*

Regulatory Domain	Regulatory Changes
Brazil	Support added for AP-303H
Canada	Channels updated for AP-303H
Malaysia	Support added for AP-120
Morocco	Support added for AP-207
Nepal	Support added for AP-325
Oman	Support added for AP-103H, AP-203H, AP-207 and AP-303H
Vietnam	Support added for AP-228

1.0_61690

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 240: *1.0_61527*

Regulatory Domain	Regulatory Changes
Mexico	Support added for AP-203H
Saudi Arabia	Channels updated for AP-203R and AP-203RP
Ukraine	Support added for AP-203R and AP-203RP
Moldova	Support added for all APs that support ETSI (CE)

1.0_61527

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 241: *1.0_61527*

Regulatory Domain	Regulatory Changes
Brazil	• Support added for AP-365 and AP-367 • Support added for AP-304 and AP-305 • Support added for AP-207
Indonesia	Support added for AP-203R and AP-203RP
Israel	• Support added for AP-303H • Support added for AP-365 and AP-367 • Support added for AP-203R and AP-203RP • Support added for AP-203H
Jordan	• Support added for AP-303H • Support added for AP-203H
Mexico	• Support added for AP-103H • Support added for AP-303H • Support added for AP-304 and AP-305 • Support added for RAP-3WN and RAP-3WNP
Pakistan	• Support added for AP-103H • Support added for AP-114 and AP-115 • Support added for AP-203H • Support added for AP-203R • Support added for AP-204 • Support added for AP-205H • Support added for AP-214 • Support added for AP-224 • Support added for AP-228 • Support added for AP-274 • Support added for AP-277 • Support added for AP-303H • Support added for RAP-108 • Channels updated for AP-103 • Channels updated for AP-105 • Channels updated for AP-135 • Channels updated for AP-205 • Channels updated for AP-207 • Channels updated for AP-215 • Channels updated for AP-275 • Channels updated for AP-304 and AP-305 • Channels updated for AP-314 and AP-315 • Channels updated for AP-324 and AP-325 • Channels updated for AP-334 and AP-335 • Channels updated for AP-365 and AP-367 • Channels updated for RAP-109 • Channels updated for RAP-155 and RAP-155P

Regulatory Domain	Regulatory Changes
Philippines	Support added for AP-203H
Qatar	• Support added for AP-303H • Support added for AP-203R and AP-203RP • Support added for AP-203H
Saudi Arabia	• Support added for AP-203R and AP-203RP
South Korea	• Support added for AP-203H • Support added for AP-203R and AP-203RP
Thailand	Support added for AP-203R and AP-203RP
Vietnam	• Support added for AP-203R and AP-203RP • Support added for AP-203H

1.0_61313

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 242: *1.0_61313*

Regulatory Domain	Regulatory Changes
Canada	• Channels updated for AP-303H • Channels updated for AP-365 and AP-367 • Channels updated for Canada country domain
Ecuador	• Support added for AP-203H • Support added for AP-203R and AP-203RP
Japan	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-365 and AP-367 • Channels updated for Japan country domain
Malaysia	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-365
Pakistan	• Channels updated for AP-225 • Channels updated for Pakistan country domain
Russia	• Support added for AP-203R and AP-203RP • Support added for AP-303H • Support added for AP-365 and AP-367
Singapore	• Support added for AP-203R and AP-203RP
Taiwan	• Channels updated for AP-304 and AP-305
Trinidad and Tobago	• Support added for AP-274
United States	• Channels updated for AP-203H • Channels updated for AP-203R and AP-203RP • Channels updated for AP-207 • Channels updated for AP-304 and AP-305 • Channels updated for AP-365 and AP-367

1.0_61045

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 243: *1.0_61045*

Regulatory Domain	Regulatory Changes
Indonesia	Channels updated for AP-325
Malaysia	Support added for AP-365
Maritime	• Support added for AP-303H • Support added for AP-304 and AP-305 • Support added for AP-334 and AP-335 • Support added for AP-374 and AP-375 • Support added for AP-377
Maritime Offshore	• Support added for AP-303H • Support added for AP-304 and AP-305 • Support added for AP-334 and AP-335 • Support added for AP-374 and AP-375 • Support added for AP-377
Puerto Rico	Support added for AP-203H
United States	Support added for AP-303H

1.0_60944

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 244: *1.0_60944*

Regulatory Domain	Regulatory Changes
Barbados	Support added for AP-207
Belarus	Support added for AP-203H
Chile	Support added for AP-203R and AP-203RP
Ecuador	Support added for AP-103H
Kyrgzstan	Kyrgzstan country domain added
Malaysia	Support added for AP-304 and AP-305
Oman	• Support added for AP-304 and AP-305 • Support added for AP-365 and AP-367
Russia	Support added for AP-203H
Taiwan	• Regulatory domain for Taiwan updated • Support added for AP-303H • Support added for AP-304 and AP-305
Ukraine	Support added for AP-203H
United Arab Emirates	• Support added for AP-203H • Support added for AP-203R and AP-203RP

1.0_60744

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 245: *1.0_60744*

Regulatory Domain	Regulatory Changes
Bermuda	Country domain Bermuda updated in regulatory domain
Hong Kong	• Channels updated for AP-204 and AP-205 • Channels updated for AP-205H • Channels updated for AP-207 • Channels updated for AP-214 and AP-215 • Channels updated for AP-228 • Channels updated for AP-274 and AP-275 • Channels updated for AP-277 • Channels updated for AP-304 and AP-305 • Channels updated for AP-314 and AP-315 • Channels updated for AP-324 and AP-325 • Channels updated for AP-334 and AP-335 • Channels updated for AP-365 and AP-367
Macau	• Channels updated for AP-204 • Channels updated for AP-207 • Channels updated for AP-214 and AP-215 • Channels updated for AP-274 and AP-275 • Channels updated for AP-277 • Channels updated for AP-304 and AP-305 • Channels updated for AP-314 and AP-315 • Channels updated for AP-324

1.0_60518

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 246: *1.0_60518*

Regulatory Domain	Regulatory Changes
Antigua and Barbuda	• Support added for AP-204 • Support added for AP-224
Argentina	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335 • Support added for RAP-3WN and RAP-3WNP • Channels updated for AP-114
Bahrain	Support added for AP-203R and AP-203RP
Bermuda	Support added for AP-303H
El Salvador	Support added for AP-303H
Federated States of Micronesia	Support added for AP-303H
Guam	Support added for AP-303H
Guatemala	Support added for AP-303H
Hong Kong	Support added for AP-203R and AP-203RP
Jordan	Support added for AP-203R and AP-203RP
Macau	Channels updated for AP-305
Mexico	Support added for AP-365 and AP-367
North Mariana Islands	Support added for AP-303H
Oman	Support added for AP-203R and AP-203RP
Puert Rico	Support added for AP-303H
South Africa	Channels updated for AP-103
United States	Channels updated for AP-303H

1.0_60362

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 247: *1.0_60362*

Regulatory Domain	Regulatory Changes
Australia	• Support added for AP-203H • Regulatory channels updated for Australia country domain
Austria	Support updated for AP-204 and AP-205
Antigua and Barbuda	• Support added for AP-207 • Channels updated for AP-225 • Channels updated forAP-228 • Regulatory channels updated for Antigua and Barbuda country domain
Belgium	Support updated for AP-204 and AP-205
Bosnia and Herzegovina	Support updated for AP-204 and AP-205
Bulgaria	Support updated for AP-204 and AP-205
Costa Rica	Support updated for AP-103
Côtes d'Ivorie	• Support added for AP-109 • Support added for AP-325
Croatia	Support updated for AP-204 and AP-205
Cyprus	Support updated for AP-204 and AP-205
Czech Republic	Support updated for AP-204 and AP-205
Denmark	Support updated for AP-204 and AP-205
Egypt	Support updated for AP-204 and AP-205
Estonia	Support updated for AP-204 and AP-205
Finland	Support updated for AP-204 and AP-205
France	Support updated for AP-204 and AP-205
Georgia	Support updated for AP-204 and AP-205
Germany	Support updated for AP-204 and AP-205
Greece	Support updated for AP-204 and AP-205

Regulatory Domain	Regulatory Changes
Hong Kong	U-NII-3 channel does not support AP-335
Hungary	Support updated for AP-204 and AP-205
Ireland	Support updated for AP-204 and AP-205
Italy	Support updated for AP-204 and AP-205
Japan	Support added for AP-334 and AP-335
Latvia	Support updated for AP-204 and AP-205
Lichtenstein	Support updated for AP-204 and AP-205
Lithuania	Support updated for AP-204 and AP-205
Luxembourg	Support updated for AP-204 and AP-205
Macau	• Support updated for AP-365 and AP-367 • Regulatory channels updated for Macau country domain
Macedonia	Support updated for AP-204 and AP-205
Malaysia	• Support added for AP-303H • Regulatory channels updated for Malaysia country domain
Malta	Support updated for AP-204 and AP-205
Montenegro	Support updated for AP-204 and AP-205
Netherlands	Support updated for AP-204 and AP-205
New Zealand	• Support updated for AP-203H • Support added for AP-203R and AP-203RP • Regulatory channels updated for New Zealand country domain
Norway	Support updated for AP-204 and AP-205
Peru	• Channels added for AP-203H • Channels added for AP-203R
Poland	Support updated for AP-204 and AP-205
Portugal	Support updated for AP-204 and AP-205
Romania	Support updated for AP-204 and AP-205
Serbia	Support updated for AP-204 and AP-205
Slovak Republic	Support updated for AP-204 and AP-205

Regulatory Domain	Regulatory Changes
Slovenia	Support updated for AP-204 and AP-205
South Korea	• Support added for AP-314 • Support added for AP-334 • Support added for AP-365 and AP-367
Spain	Support updated for AP-204 and AP-205
Sweden	Support updated for AP-204 and AP-205
Switzerland	Support updated for AP-204 and AP-205
Taiwan	Support added for AP-365 and AP-367
Turkey	Support updated for AP-204 and AP-205
Ukraine	Support updated for AP-204 and AP-205
United Kingdom	Support updated for AP-204 and AP-205
Uzbekistan	Support updated for AP-204 and AP-205

1.0_60114

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 248: *1.0_60114*

Regulatory Domain	Regulatory Changes
Grenada	PSD, DFS and Co-relation values updated for country domain
Jamaica	• Support added for AP-207 • PSD, DFS and Co-relation values updated for country domain
Maritime	Channels updated for AP-207
Maritime Offshore	Channels updated for AP-207
Peru	Channels updated for AP-207
Russia	Support added for AP-207
South Africa	Channels updated for AP-207
UAE	Channels updated for AP-207
Uganda	Channels updated for AP-207

1.0_59989

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 249: *1.0_59989*

Regulatory Domain	Regulatory Changes
Argentina	Support added for OC-20
Brazil	Support added for OC-20
Cameroon	Support added for AP-203H
Indonesia	Support added for OC-20
Macau	Channels updated for AP-365 and AP-367
Malaysia	• Support added for AP-367 • Support added for OC-20
Mexico	• Support added for AP-305 • Support added for OC-20 • Support added for AP-207
Niger	Support added for AP-203H
Pakistan	Channels updated for AP-215
Singapore	Support added for AP-203H
South Korea	• Support added for AP-303H • Support updated for AP-324 and AP-325 • Channels updated for South Korean regulatory domain
Zimbabwe	• Channels updated for AP-103 • Channels updated for AP-205 • Channels updated for AP-225

1.0_59783

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 250: *1.0_59783*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-303H
Azerbaijan	• Support added for AP-203R and AP-203RP • Support added for AP-303H
Cameroon	• Support added for AP-203R and AP-203RP • Support added for AP-303H
Colombia	Support added for AP-203R and AP-203RP
Egypt	• Support added for AP-203R and AP-203RP • Support added for AP-365
Ethiopia	• Support added for AP-303H • Support added for AP-365
India	Support added for AP-203H
Indonesia	Support added for AP-303H
Kuwait	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-303H
Lebanon	• Support added for AP-203R and AP-203RP • Support added for AP-303H
Macau	• Support added for AP-203H • Support added for AP-303H • Support added for AP-304 and AP-305 • Support added for AP-314 and AP-315 • Support added for AP-324 and AP-325 • Support added for AP-334 and AP-335 • Support added for AP-365 and AP-367
Mauritius	• Support added for AP-203R and AP-203RP • Support added for AP-303H
Morocco	• Support added for AP-203H • Support added for AP-365
Myanmar	Support added for AP-203R and AP-203RP
Nicaragua	Support added for AP-203R and AP-203RP

Regulatory Domain	Regulatory Changes
Niger	• Support added for AP-203R and AP-203RP • Support added for AP-303H • Support added for AP-365
Peru	Support added for AP-207
Philippines	Support added for AP-303H
Senegal	Support added for AP-203R and AP-203RP
Serbia	• Support added for AP-203R and AP-203RP • Support added for AP-303H • Support added for AP-365
Singapore	Support added for AP-303H
Sri Lanka	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-303H
Suriname	Support added for AP-303H
Thailand	Support added for AP-303H
Tunisia	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-303H
United Arab Emirates	Support added for AP-303H

1.0_59591

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 251: *1.0_59591*

Regulatory Domain	Regulatory Changes
American Samoa	Channels updated for AP-203H
Australia	Channels updated for AP-304 and AP-305
Austria	Channels updated for AP-203H
Azerbaijan	Support added for AP-334 and AP-335
Belgium	Channels updated for AP-203H
Bosnia and Herzegovina	Channels updated for AP-203H
Brazil	Channels updated for AP-203H
Bulgaria	Channels updated for AP-203H
Cameroon	• Support added for AP-314 • Support added for AP-334 and AP-335
Canada	Channels updated for AP-203H
Chile	• Support added for AP-207 • Support added for AP-304 and AP-305
Croatia	Channels updated for AP-203H
Cyprus	Channels updated for AP-203H
Czech Republic	Channels updated for AP-203H
Denmark	Channels updated for AP-203H
Egypt	Channels updated for AP-203H
Estonia	Channels updated for AP-203H
Ethiopia	• Support added for AP-314 • Support added for AP-334 and AP-335
Finland	Channels updated for AP-203H
France	Channels updated for AP-203H

Regulatory Domain	Regulatory Changes
Georgia	Channels updated for AP-203H
Germany	Channels updated for AP-203H
Greece	Channels updated for AP-203H
Guam	Channels updated for AP-203H
Hungary	Channels updated for AP-203H
India	• Support added for AP-303H • Support added for AP-365 and AP-367
Ireland	Channels updated for AP-203H
Italy	Channels updated for AP-203H
Jordan	Support added for AP-365 and AP-367
Kazakhstan	• Channels updated for AP-104 and AP-105 • Channels updated for AP-120 and AP-121 • Channels updated for AP-124 and AP-125 • Channels updated for AP-134 and AP-135 • Channels updated for AP-204 and AP-205 • Channels updated for AP-205H • Channels updated for AP-207 • Channels updated for AP-214 and AP-215 • Channels updated for AP-228 • Channels updated for AP-277 • Channels updated for AP-304 and AP-305 • Channels updated for AP-314 and AP-315 • Channels updated for AP-325 • Channels updated for AP-334 and AP-335
Latvia	Channels updated for AP-203H
Lebanon	• Support added for AP-224 • Support added for AP-334 and AP-335
Lichtenstein	Channels updated for AP-203H
Lithuania	Channels updated for AP-203H
Luxembourg	Channels updated for AP-203H
Macedonia	Channels updated for AP-203H
Maldives	Support added for AP-334 and AP-335
Malta	Channels updated for AP-203H
Mauritius	Support added for AP-334 and AP-335

Regulatory Domain	Regulatory Changes
Montenegro	Channels updated for AP-203H
Netherlands	Channels updated for AP-203H
New Zealand	Channels updated for AP-304 and AP-305
Niger	• Support added for AP-314 • Support added for AP-334 and AP-335
Northern Mariana Islands	Channels updated for AP-203H
Norway	Channels updated for AP-203H
Oman	Support added for AP-367
Peru	Support added for AP-365 and AP-367
Poland	Channels updated for AP-203H
Portugal	Channels updated for AP-203H
Puerto Rico	Channels updated for AP-203H
Quatar	• Support added for AP-274 and AP-275 • Support added for AP-277 • Support added for AP-344 and AP-345
Romania	Channels updated for AP-203H
Senegal	Support added for AP-334 and AP-335
Serbia	Channels updated for AP-203H
Slovak Republic	Channels updated for AP-203H
Slovenia	Channels updated for AP-203H
Spain	Channels updated for AP-203H
Sweden	Channels updated for AP-203H
Switzerland	Channels updated for AP-203H
Taiwan	• Support added for AP-203H • Support added for AP-207
Tanzania	Support added for AP-334 and AP-335
Tunisia	Support added for AP-334 and AP-335

Regulatory Domain	Regulatory Changes
Turkey	Channels updated for AP-203H
Ukraine	• Channels updated for AP-203H • Support added for AP-207
United Arab Emarites	Support added for AP-365 and AP-367
United Kingdom	Channels updated for AP-203H
United States	Channels updated for AP-203H
Uzbekistan	• Channels updated for AP-203H • Support added for AP-314 • Support added for AP-334 and AP-335
Vietnam	• Support added for AP-103H • Support added for AP-365 and AP-367
Virgin Islands (US)	Channels updated for AP-203H

1.0_59241

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 252: *1.0_59241*

Regulatory Domain	Regulatory Changes
Afghanistan	• Support added for AP-207 • Support added for AP-365
Australia	• Support updated for AP-303H • Support added for AP-365 • Support added for AP-367
Austria	• Support added for AP-365 • Support added for AP-367
Australia	• Support added for AP-365 • Support added for AP-367
Azerbaijan	• Support added for AP-103 • Support added for AP-207 • Support added for AP-215 • Support added for AP-314 • Support added for AP-315 • Support added for AP-367
Bahrain	Support added for AP-314
Belarus	Support added for AP-207
Belgium	• Support added for AP-365 • Support added for AP-367
Bosnia and Herzegovina	• Support added for AP-365 • Support added for AP-367
Brazil	• Support added for AP-365 • Support added for AP-367
Bulgaria	• Support added for AP-365 • Support added for AP-367
Canada	• Support added for AP-365 • Support added for AP-367
China	• Support added for AP-365 • Support added for AP-367
Croatia	• Support added for AP-365 • Support added for AP-367
Cyprus	• Support added for AP-365

Regulatory Domain	Regulatory Changes
	• Support added for AP-367
Czech Republic	• Support added for AP-365 • Support added for AP-367
Denmark	• Support added for AP-365 • Support added for AP-367
Ecuador	• Support added for AP-207 • Support added for AP-304 • Support added for AP-305
Egypt	• Support added for AP-365 • Support added for AP-367
Estonia	• Support added for AP-365 • Support added for AP-367
Finland	• Support added for AP-365 • Support added for AP-367
France	• Support added for AP-365 • Support added for AP-367
Georgia	• Support added for AP-365 • Support added for AP-367
Germany	• Support added for AP-303H • Support added for AP-365 • Support added for AP-367
Greece	• Support added for AP-365 • Support added for AP-367
Hong Kong	• Support updated for AP-207 • Support updated for AP-304 • Support added for AP-325 • Support added for AP-365 • Support added for AP-367
Hungary	• Support added for AP-365 • Support added for AP-367
India	• Support added for AP-365 • Support added for AP-367
Indonesia	• Support added for AP-365 • Support added for AP-367
Iran	• Support added for AP-365 • Support added for AP-367
Ireland	• Support added for AP-365 • Support added for AP-367
Israel	• Support added for AP-365 • Support added for AP-367

Regulatory Domain	Regulatory Changes
Italy	• Support added for AP-365 • Support added for AP-367
Japan	• Support added for AP-365 • Support added for AP-367
Jordan	• Support added for AP-314 • Support added for AP-315 • Support added for AP-275
Kuwait	Support added for AP-365
Latvia	• Support added for AP-365 • Support added for AP-367
Lebanon	• Support added for AP-103H • Support added for AP-314 • Support added for AP-315 • Support added for AP-365 • Support added for AP-367
Lichtenstein	• Support added for AP-365 • Support added for AP-367
Lithuania	• Support added for AP-365 • Support added for AP-367
Luxembourg	• Support added for AP-365 • Support added for AP-367
Macedonia	• Support added for AP-365 • Support added for AP-367
Malta	• Support added for AP-365 • Support added for AP-367
Malaysia	• Support added for AP-207 • Channels added for AP-214 • Channels added for AP-215 • Support added for AP-224 • Support added for AP-225 • Channels updated for AP-228 • Support added for AP-274 • Support added for AP-275 • Channels updated for AP-277 • Support added for AP-365 • Support added for AP-367
Mauritius	• Support added for AP-315 • Support added for AP-367
Montenegro	• Support added for AP-365 • Support added for AP-367
Myanmar	• Support added for AP-207 • Support added to AP-365

Regulatory Domain	Regulatory Changes
New Zealand	Support added for AP-303H
Netherlands	• Support added for AP-365 • Support added for AP-367
Norway	• Support added for AP-365 • Support added for AP-367
Oman	Support added for AP-207
Pakistan	• Support added for AP-365 • Support added for AP-367
Philippines	• Support added for AP-365 • Support added for AP-367
Poland	• Support added for AP-365 • Support added for AP-367
Portugal	• Support added for AP-365 • Support added for AP-367
Qatar	• Support added for AP-365 • Support added for AP-367
Romania	• Support added for AP-365 • Support added for AP-367
Senegal	• Support added for AP-314 • Support added for AP-315 • Support added for AP-365 • Support added for AP-367
Serbia	• Support added for AP-365 • Support added for AP-367
Singapore	• Support added for AP-365 • Support added for AP-367
Slovak Republic	• Support added for AP-365 • Support added for AP-367
Slovenia	• Support added for AP-365 • Support added for AP-367
South Africa	• Support added for AP-365 • Support added for AP-367
Spain	• Support added for AP-365 • Support added for AP-367
Sri Lanka	• Support added for AP-207 • Support added for AP-365
Sweden	• Support added for AP-365 • Support added for AP-367

Regulatory Domain	Regulatory Changes
Switzerland	• Support added for AP-365 • Support added for AP-367
Taiwan	• Support added for AP-365 • Support added for AP-367
Tanzania	Support added for AP-207
Thailand	• Support added for AP-365 • Support added for AP-367
Tunisia	• Support added for AP-207 • Support added for AP-314 • Channels updated for AP-325 • Support added for AP-365
Turkey	• Support added for AP-365 • Support added for AP-367
Ukraine	• Support added for AP-304 • Support added for AP-305 • Support added for AP-365 • Support added for AP-367
United Arab Emirates	• Support added for AP-314 • Channels updated for AP-315 • Support added for AP-365 • Support added for AP-367
United Kingdom	• Support added for AP-365 • Support added for AP-367
United States	• Support added for AP-203R • Support added for AP-203RP • Support added for AP-365 • Support added for AP-367
Uzbekistan	• Support added for AP-365 • Support added for AP-367
Venezuela	• Support added for AP-324 • Support added for AP-325
Yemen	• Support added for AP-365 • Support added for AP-367

1.0_59118

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 253: *1.0_59118*

Regulatory Domain	Regulatory Changes
Australia	• Support updated for country regulatory domain • Support updated for AP-203H
Austria	Support updated for AP-203H
Australia	Support updated for AP-203H
Belgium	Support updated for AP-203H
Bosnia and Herzegovina	Support updated for AP-203H
Brazil	Support updated for AP-203H
Bulgaria	Support updated for AP-203H
Canada	Support updated for AP-203H
China	Support updated for AP-203H
Croatia	Support updated for AP-203H
Cyprus	Support updated for AP-203H
Czech Republic	Support updated for AP-203H
Denmark	Support updated for AP-203H
Egypt	Support updated for AP-203H
Estonia	Support updated for AP-203H
Finland	Support updated for AP-203H
France	Support updated for AP-203H
Georgia	Support updated for AP-203H
Germany	Support updated for AP-203H
Greece	Support updated for AP-203H

Regulatory Domain	Regulatory Changes
Hong Kong	Support updated for AP-203H
Hungary	Support updated for AP-203H
India	Support updated for AP-203H
Indonesia	Support updated for AP-203H
Ireland	Support updated for AP-203H
Israel	Support updated for AP-203H
Italy	Support updated for AP-203H
Latvia	Support updated for AP-203H
Lichtenstein	Support updated for AP-203H
Lithuania	Support updated for AP-203H
Luxembourg	Support updated for AP-203H
Macedonia	Support updated for AP-203H
Malta	Support updated for AP-203H
Malaysia	Support updated for AP-203H
Montenegro	Support updated for AP-203H
Netherlands	Support updated for AP-203H
New Zealand	• Support updated for country regulatory domain • Support updated for AP-203H
Norway	Support updated for AP-203H
Poland	Support updated for AP-203H
Portugal	Support updated for AP-203H
Qatar	Support updated for AP-203H
Romania	Support updated for AP-203H
Serbia	Support updated for AP-203H
Singapore	Support updated for AP-203H
Slovak Republic	Support updated for AP-203H

Regulatory Domain	Regulatory Changes
Slovenia	Support updated for AP-203H
South Africa	Support updated for AP-203H
Spain	Support updated for AP-203H
Sweden	Support updated for AP-203H
Switzerland	Support updated for AP-203H
Taiwan	Support updated for AP-203H
Turkey	Support updated for AP-203H
Ukraine	Support updated for AP-203H
United Arab Emirates	Support updated for AP-203H
United Kingdom	Support updated for AP-203H
United States	Support updated for AP-203H Support updated for AP-365
Uzbekistan	Support updated for AP-203H

1.0_59015

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 254: *1.0_59015*

Regulatory Domain	Regulatory Changes
Afghanistan	Support added for AP-304
Albania	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Algeria	• Support added for AP-103 • Support added for AP-135 • Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-205 • Support added for AP-207 • Support added for AP-215 • Channels updated for AP-225 • Support added for AP-228 • Support added for AP-275 • Channels updated for AP-303H • Channels updated for AP-304 and AP-305 • Channels updatedfor AP-314 and AP-315 • Support added for AP-324 and AP-325 • Support added for AP-334 and AP-335 • Support added for AP-365 and AP-367
Australia	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H • Support added for AP-365 and AP-367
Austria	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Bahrain	Support added for AP-207
Belarus	• Channels updated for AP-103 • Channels updated for AP-103H

Regulatory Domain	Regulatory Changes
	• Support added for AP-104 and AP-105 • Support added for AP-114 and AP-115 • Channels updated for AP-120 • Channels updated for AP-121 • Channels updated for AP-124 and AP-125 • Channels updated for AP-134 and AP-135 • Support added for AP-175AC, AP-175DC, • Support added for AP-175P • Support added for AP-203H • Support added for AP-203R and AP-203RP • Channels updated for AP-204 and AP-205 • Support added for AP-205H • Support added for AP-207 • Channels updated AP-214 and AP-215 • Support added for AP-228 • Support added for AP-277 • Support added for AP-303H • Support added for AP-304 and AP-305 • Support added for AP-314 and AP-315 • Support added for AP-324 and AP-325 • Support added for AP-334 and AP-335 • Support added for AP-365 and AP-367 • Support added for AP-68 • Channels updated for AP-92 and AP-93 • Channels updated for AP-93H • Channels updated for RAP-108 and RAP-109 • Support added for RAP-155 and RAP-155P • Support added for RAP-3WN and RAP-3WNP
Belgium	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Bosnia and Herzegovina	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Brazil	Channels updated for AP-215
Bulgaria	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Canada	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
China	• Support added for AP-203H

Regulatory Domain	Regulatory Changes
	• Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Colombia	• Support added for AP-303H • Support added for AP-304 and AP-305 • Support added for AP-365 and AP-367
Costa Rica	Channels updated for AP-325
Croatia	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Cyprus	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Czech Republic	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Denmark	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Ethiopia	Support added for AP-304
Egypt	• Support added for AP-203R and AP-203RP • Channels updated for AP-215
Estonia	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Finland	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
France	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H

Regulatory Domain	Regulatory Changes
Georgia	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Germany	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Greece	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Guadeloupe	Support added for AP-204 and AP-205
Hong Kong	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Hungary	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
India	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Indonesia	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Ireland	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Israel	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-204 and AP-205 • Support added for AP-207 • Channels updated for AP-214 and AP-215 • Support added for AP-303H

Regulatory Domain	Regulatory Changes
	• Support added for AP-304 and AP-305 • Support added for AP-314 and AP-315 • Support added for AP-324 and AP-325
Italy	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Japan	• Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Jordan	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Kazakhstan	• Support added for AP-205 • Support added for AP-304
Kenya	• Support added for AP-203R and AP-203RP • Support added for AP-303H • Support added for AP-304 • Support added for AP-314and AP-315 • Support added for AP-365 and AP-367
Latvia	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Lichtenstein	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Lithuania	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Luxembourg	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Macau	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205

Regulatory Domain	Regulatory Changes
	• Channels updated for AP-214 and AP-215 • Support added for AP-303H • Support added for AP-304
Malta	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Macedonia	• Support added for AP-203R and AP-203RP • Channels updated for AP-215
Malaysia	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Maritime	• Support added for AP-203H • Support added for AP-304
Maritime Offshore	• Support added for AP-203H • Support added for AP-304
Mauritius	Support added for AP-304
Monaco	Channels updated for AP-204 and AP-205
Myanmar	Support added for AP-304
Montenegro	• Support added for AP-203R and AP-203RP • Channels updated for AP-214 and AP-215
Netherlands	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
New Zealand	• Support added for AP-365 and AP-367
Niger	Support added for AP-304
Nigeria	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-303H • Support added for AP-314and AP-315 • Support added for AP-334 and AP-335 • Support added AP-365 and AP-367
Norway	• Support added for AP-203R and AP-203RP • Support added for AP-203H

Regulatory Domain	Regulatory Changes
	• Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Pakistan	Support added for AP-207
Peru	Support added for AP-304 and AP-305
Poland	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Portugal	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Qatar	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-204 and AP-205 • Support added for AP-207 • Channels updated for AP-214 and AP-215 • Support added for AP-303H • Support added for AP-304
Republic of Moldova	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Romania	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Russian	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-304 and AP-305 • Support added for AP-334 and AP-335
Saudi Arabia	• Support added for AP-304 • Support added for AP-314and AP-315 • Support added for RAP-109
Senegal	• Support added for AP-204 and AP-205 • Support added for AP-304

Regulatory Domain	Regulatory Changes
Serbia	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-204 and AP-205 • Support added for AP-207 • Channels updated for AP-214 and AP-215 • Support added for AP-303H • Support added for AP-304 • Support added for AP-365 and AP-367
Singapore	Channels updated for AP-215
Slovak Republic	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Slovenia	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
South Africa	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335 • Support added for AP-365 and AP-367
South Korea	• Support added for AP-207 • Support added for AP-304 and AP-305
Spain	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Sweden	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Switzerland	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Taiwan	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205

Regulatory Domain	Regulatory Changes
	• Channels updated for AP-214 and AP-215 • Support added for AP-303H
Tanzania	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-303H • Support added for AP-304
Thailand	• Support added for AP-204 and AP-205 • Support added for AP-207 • Support added for AP-365 and AP-367
Turkey	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Uganda	• Support added for AP-203H • Support added for AP-203R and AP-203RP • Support added for AP-303H • Support added for AP-304 • Support added for AP-314and AP-315 • Support added for AP-334 and AP-335 • Support added for AP-365 and AP-367
Ukraine	• Support added for AP-203R and AP-203RP • Support added for AP-207 • Channels updated for AP-215 • Support added for AP-304
United Arab Emirates	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
United Kingdom	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
United States	• Support added for AP-203R and AP-203RP • Support added for AP-203H • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Support added for AP-303H
Uzbekistan	• Support added for AP-203R and AP-203RP • Channels updated for AP-215
Vietnam	Support added for AP-207

1.0_58653

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 255: *1.0_58653*

Regulatory Domain	Regulatory Changes
Angolia	Support added for AP-215 Support added for AP-275
Bahamas	• Channels updated for AP-314 and AP-315 • Support added for AP-334 and AP-335
Barbados	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Bermuda	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Bolivia	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Brazil	Support added for AP-314 and AP-315
Costa Rica	Support added for AP-304 and AP-305
Curaco	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Ecuador	Support added for AP-324 and AP-325
Grenada	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Guadeloupe	• Channels updated for AP-314 and AP-315 • Channels updated for AP-334 and AP-335
Guatemala	• Support added for AP-314 and AP-315 • Channels updated for AP-334 and AP-335
Guyana	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Haiti	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335

Regulatory Domain	Regulatory Changes
Honduras	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Jamaica	• Channels updated for AP-205
Lebanon	Support added for RAP-109
Mexico	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Nicaragua	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Pakistan	Support added for AP-304 and AP-305
Panama	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Paraguay	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Philippines	Support added for AP-207 Support added for AP-304 and AP-305
Qatar	Channels updated for AP-315
Saint Lucia	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Saint Vincent and the Grenadines	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Senegal	Support added for AP-215
Serbia	Support added for AP-277
Singapore	Support added for AP-207 Support added for AP-304 and AP-305
Suriname	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Trinidad and Tobago	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335

Regulatory Domain	Regulatory Changes
United Arab Emarites	Support added for AP-304
Uruguay	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Venezuela	• Support added for AP-205 • Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335

1.0_58258

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 256: *1.0_58258*

Regulatory Domain	Regulatory Changes
Albania	Support added for AP-304 and AP-305
Austria	Support added for AP-304 and AP-305
Belgium	Support added for AP-304 and AP-305
Bosnia and Herzegovina	Support added for AP-304 and AP-305
Bulgaria	Support added for AP-304 and AP-305
Croatia	Support added for AP-304 and AP-305
Cyprus	Support added for AP-304 and AP-305
Czech Republic	Support added for AP-304 and AP-305
Denmark	Support added for AP-304 and AP-305
Estonia	Support added for AP-304 and AP-305
Finland	Support added for AP-304 and AP-305
France	Support added for AP-304 and AP-305
Georgia	Support added for AP-304 and AP-305
Germany	Support added for AP-304 and AP-305
Greece	Support added for AP-304 and AP-305
Hungary	Support added for AP-304 and AP-305
Ireland	Support added for AP-304 and AP-305
Italy	Support added for AP-304 and AP-305
Latvia	Support added for AP-304 and AP-305
Lebanon	• Support added for AP-207 • Support added for AP-304 and AP-305

Regulatory Domain	Regulatory Changes
Lichtenstein	Support added for AP-304 and AP-305
Lithuania	Support added for AP-304 and AP-305
Luxembourg	Support added for AP-304 and AP-305
Malta	Support added for AP-304 and AP-305
Macedonia	Support added for AP-304 and AP-305
Montenegro	Support added for AP-304 and AP-305
Netherlands	Support added for AP-304 and AP-305
Norway	Support added for AP-304 and AP-305
Poland	Support added for AP-304 and AP-305
Portugal	Support added for AP-304 and AP-305
Romania	Support added for AP-304 and AP-305
Serbia	Support added for AP-304 and AP-305
Slovak Republic	Support added for AP-304 and AP-305
Slovenia	Support added for AP-304 and AP-305
Spain	Support added for AP-304 and AP-305
Sweden	Support added for AP-304 and AP-305
Switzerland	Support added for AP-304 and AP-305
Turkey	Support added for AP-304 and AP-305
Ukraine	Support added for AP-304 and AP-305
United Kingdom	Support added for AP-304 and AP-305

1.0_58226

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 257: *1.0_58226*

Regulatory Domain	Regulatory Changes
Australia	Support updated for AP-207
Austria	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Barbados	Support added for AP-304
Belgium	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Bermuda	Support added fr AP-304
Bolivia	Support added for AP-304
Bosnia and Herzegovina	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Brazil	Support added for AP-334 and AP-335
Bulgaria	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Costa Rica	Support added for AP-207
Croatia	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Curacao	Support added for AP-304
Cyprus	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Czech Republic	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Denmark	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Ecuador	• Support updated for AP-224 • Support updated for AP-277
Egypt	• Support added for AP-207 • Support added for AP-304 and AP-305
Estonia	• Support updated for AP-207

Regulatory Domain	Regulatory Changes
	• Support updated for AP-304 and AP-305
Finland	• Support updated for AP-207 • Support updated for AP-304 and AP-305
France	• Support updated for AP-207 • Support added for AP-277 • Support updated for AP-304 and AP-305
Georgia	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Germany	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Greece	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Grenada	Support added for AP-304
Guatemala	Support added for AP-304
Guyana	Support added for AP-304
Haiti	Support added for AP-304
Honduras	Support added for AP-304
Hungary	• Support updated for AP-207 • Support updated for AP-304 and AP-305
India	Support added for AP-207
Indonesia	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Ireland	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Israel	Support added for AP-334 and AP-335
Italy	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Jamaica	• Support added for AP-304
Japan	• Support added for AP-207 • Support added for AP-304 and AP-305
Jordan	Support added for AP-334 and AP-335
Latvia	• Support added for AP-207 • Support added for AP-304 and AP-305 • Support added for AP-324 and AP-325

Regulatory Domain	Regulatory Changes
Lebanon	• Support updated for AP-103 • Support updated for AP-207 • Support updated for AP-304 and AP-305
Liechtenstein	• Support added for AP-207 • Support added for AP-304 and AP-305
Lithuania	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Luxembourg	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Macedonia	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Malaysia	Support added AP-314 and AP-315
Malta	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Montenegro	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Myanmar	Support enabled for RAP-109
Netherlands	• Support updated for AP-207 • Support updated for AP-304 and AP-305
New Zealand	Support added for AP-207
Nicaragua	Support added for AP-304
Norway	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Panama	Support added for AP-304
Paraguay	Support added for AP-304
Poland	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Portugal	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Qatar	Support added for AP-314 and AP-315
Romania	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Saint Lucia	Support added for AP-304
Serbia	• Support updated for AP-207 • Support updated for AP-304 and AP-305

Regulatory Domain	Regulatory Changes
Slovak Republic	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Slovenia	• Support updated for AP-207 • Support updated for AP-304 and AP-305
South Korea	Support added for AP-228
Spain	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Sri Lanka	Support added for AP-334 and AP-335
Suriname	Support added for AP-304
Sweden	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Switzerland	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Taiwan	Support added for AP-228
Tanzania	• Tanzania country domain enabled • Support added for AP-205H • Support added for AP-277 • Support added for AP-305
Trinidad and Tobago	Support added for AP-304
Turkey	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Ukraine	• Support updated for AP-207 • Support updated for AP-304 and AP-305
United Arab Emarites	• Support added for AP-225 • Support added for AP-315 • Support added for AP-334 and AP-335
United Kingdom	• Support updated for AP-207 • Support updated for AP-304 and AP-305
Uruguay	Support added for AP-304
Venezuela	Support added for AP-304
Vietnam	Support added for AP-304 and AP-305

1.0_57815

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 258: *1.0_57815*

Regulatory Domain	Regulatory Changes
Nigeria	Support added for RAP-109
Oman	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
United Arab Emarites	• Channels updated for AP-205 • Channels updated for AP-205H

1.0_57776

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 259: *1.0_57776*

Regulatory Domain	Regulatory Changes
Austria	• Support updated for AP-207
Belgium	• Support updated for AP-207
Bosnia and Herzegovina	• Support updated for AP-207
Brazil	Support updated for RAP-155 and RAP-155P
Bulgaria	• Support updated for AP-207
Cambodia	Support added for RAP-109
Canada	• Support updated for AP-207
China	• Support added for AP-304 • Support added for AP-314 • Support updated for AP-315 • Support updated for AP-334 and AP-335
Croatia	• Support updated for AP-207
Cyprus	• Support updated for AP-207
Czech Republic	• Support updated for AP-207
Denmark	• Support updated for AP-207
Ecuador	Support added for AP-314 and AP-315
Estonia	• Support updated for AP-207
Finland	• Support updated for AP-207
France	• Support updated for AP-207
Georgia	• Support updated for AP-207
Germany	• Support updated for AP-207
Greece	• Support updated for AP-207

Regulatory Domain	Regulatory Changes
Haiti	Support added for AP-205
Honduras	Support added for AP-205
Hungary	• Support updated for AP-207
Indonesia	• Support added for AP-207
Ireland	• Support updated for AP-207
Italy	• Support updated for AP-207
Japan	• Support added for AP-305 • Support updated for AP-314 and AP-315 • Support added for AP-334 and AP-335
Latvia	• Support updated for AP-207
Liechtenstein	• Support updated for AP-207
Lithuania	• Support updated for AP-207
Luxembourg	• Support updated for AP-207
Macedonia	• Support updated for AP-207
Malta	• Support updated for AP-207
Montenegro	• Support updated for AP-207 • Support updated for AP-314 and AP-315
Netherlands	• Support updated for AP-207
Norway	• Support updated for AP-207
Peru	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Poland	• Support updated for AP-207
Portugal	• Support updated for AP-207
Romania	• Support updated for AP-207
Serbia	• Support updated for AP-207
Singapore	• Support updated for AP-314 and AP-315 • Support added for AP-334 and AP-335

Regulatory Domain	Regulatory Changes
Slovak Republic	• Support updated for AP-207
Slovenia	• Support updated for AP-207
Spain	• Support updated for AP-207
Sweden	• Support updated for AP-207
Switzerland	• Support updated for AP-207
Turkey	• Support updated for AP-207
Ukraine	• Support updated for AP-207
United Kingdom	• Support updated for AP-207
United States	• Support added for AP-207

1.0_57440

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 260: *1.0_57440*

Regulatory Domain	Regulatory Changes
American Samoa	Update to maximum power levels
Australia	• Support added for AP-207 • Support added for AP-304 and AP-305
Bahamas	• Support added for AP-207 • Support added for AP-305
Bahrain	• Support added for AP-207 • Support added for AP-305 • Support added for RAP-109
Barbados	• Support added for AP-207 • Support added for AP-305
Bermuda	• Support added for AP-103 • Support added for AP-205 • Support added for AP-205H • Support added for AP-207 • Support added for AP-305
Bolivia	• Support added for AP-205 • Support added for AP-207 • Support added for AP-305
Chile	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Curacao	• Support added for AP-103 • Support added for AP-205 • Support added for AP-205H • Support added for AP-207 • Support added for AP-305
Grenada	• Support added for AP-207 • Support added for AP-305
Guam	Update to maximum power levels
Guatemala	• Support updated for AP-207 • Support added for AP-305
Guyana	• Support added for AP-207 • Support added for AP-305
Hati	• Support added for AP-207 • Support added for AP-305

Table 260: *1.0_57440*

Regulatory Domain	Regulatory Changes
Honduras	• Support added for AP-207 • Support added for AP-305
Hong Kong	• Support added for AP-304 • Support added for AP-305
India	• Support added for AP-207 • Support added for AP-304 and AP-305
Jamaica	• Support added for AP-207 • Support added for AP-305
Japan	• Support added for AP-207 • Support added for AP-314 and AP-315
Jordan	Support added for RAP-109
Maldives	Support added for AP-314 and AP-315
Morocco	Support added for RAP-109
New Zealand	• Support added for AP-207 • Support added for AP-304 and AP-305
Nicaragua	• Support added for AP-103 • Support added for AP-205 • Support added for AP-205H • Support added for AP-207 • Support added for AP-305
Northern Mariana Islands	Update to maximum power levels
Panama	• Support added for AP-207 • Support added for AP-305
Paraguay	• Support added for AP-207 • Support added for AP-305
Puerto Rico	Update to maximum power levels
Saint Vincent and the Grenadines	• Support added for AP-207 • Support added for AP-305
Saint Lucia	• Support added for AP-103 • Support added for AP-205 • Support added for AP-205H • Support added for AP-207 • Support added for AP-305
Suriname	• Support added for AP-207 • Support added for AP-305
Trinadad and Tobago	• Support added for AP-207 • Support added for AP-305

Table 260: *1.0_57440*

Regulatory Domain	Regulatory Changes
United Arab Emarites	• Support added for AP-207 • Support added for AP-274 and AP-275 • Support added for AP-277
United States	Update to maximum power levels
Uruguay	• Support added for AP-207 • Support added for AP-305
US Virgin Islands	Update to maximum power levels
Venezuela	• Support added for AP-207 • Support added for AP-305
Vietnam	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335

1.0_57223

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 261: *1.0_57223*

Regulatory Domain	Regulatory Changes
Belarus	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-205H • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for AP-228 • Support added for AP-274 and AP-275 • Support added for AP-277 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WN and RAP-3WNP
Federated States of Micronesia	Support added for AP-304 and AP-305
Guam	Support added for AP-304 and AP-305
Israel	• Channel updated for AP-103 • Channels updated for AP-204 and AP-205 • Channels updated for AP-214 and AP-215 • Channels updated for AP-224 and AP-225
Honduras	• Support added for AP-103H • Support added for AP-205H
Kuwait	• Support added for AP-207 • Support added for AP-304 and AP-305 • Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Marshall Islands	Support added for AP-304 and AP-305
Nepal	• Support added for AP-205 • Support added for AP-205H • Support added for AP-215

Table 261: *1.0_57223*

Regulatory Domain	Regulatory Changes
Northern Marina Islands	Support added for AP-304 and AP-305
Puerto Rico	Support added for AP-207 Support added for AP-304 and AP-305
Serbia	• Support added for AP-103 and AP-103H • Support added for AP-204 • Support added for AP-214 • Support added for AP-274 and AP-275 • Support added for RAP-108 and RAP-109 • Support added for RAP-155 and RAP-155P • Support added for RAP-3WN and RAP-3WNP
Ukraine	• Channels updated for AP-103H • Channels updated for AP-114 and AP-115 • Channels updated for AP-214 and AP-215 • Channels added for AP-228 • Channels updated for AP-274 and AP-275 • Channels updated for AP-277 • Channels added for AP-314 and AP-315 • Channels updated for AP-324 and AP-325
United Arab Emirates	Support added for AP-305
US Virgin Islands	Support added for AP-304 and AP-305

1.0_57023

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 262: *1.0_57023*

Regulatory Domain	Regulatory Changes
Bangladesh	• Support added for AP-104 • Support added for AP-105 • Support added for AP-114 • Support added for AP-115 • Support added for AP-120 • Support added for AP-121 • Support added for AP-124 • Support added for AP-125 • Support added for AP-134 • Support added for AP-135 • Support added for AP-175AC • Support added for AP-175DC • Support added for AP-175P • Support added for AP-205H • Support added for AP-314 and AP-315 • Support added for AP-324 and AP-325 • Support added for AP-334 and AP-335
Barbados	Support added for AP-205H
Bolivia	Support added for AP-205H
China	Support added for AP-207 Support added for AP-315
Guyana	• Support added for AP-103 • Support added for AP-205 • Support added for AP-205H • Support added for AP-275 • Support added for AP-277
India	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Oman	Support added for AP-214 and AP-215

Regulatory Domain	Regulatory Changes
Paraguay	Support added for AP-205H
Russia	• Support updated for AP-314 and AP-315 • Support updated for AP-334 and AP-335
Saudi Arabia	Support added for AP-214 and AP-215
Suriname	• Support added for AP-103 • Support added for AP-205H

1.0_56912

This table describes the new regulatory changes to access points and channels introduced in this release.

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 263: *1.0_56912*

Regulatory Domain	Regulatory Changes
Afghanistan	• Support added for AP-324 and AP-325 • Support added for AP-334 and AP-335 • Support added for RAP-108 • Support added for RAP-109
Aland Island	Support added for AP-207
Albania	• Support added for AP-207 • Support added for AP-334 and AP-335
American Samoa	Support updated for AP-314 and AP-315
Andorra	Support added for AP-207
Austria	Support added for AP-207
Belgium	Support added for AP-207
Bosnia & Herzegovina	• Support added for AP-207 • Support added for AP-314 and AP-315 • Support added for AP-324 and AP-325
Bulgaria	Support added for AP-207
Canada	Support added for AP-207
Colombia	Support added for AP-314 and AP-315
Costa Rica	Support added for AP-314 and AP-315 Support added for AP-334 and AP-335
Croatia	• Support added for AP-314 and AP-315 • Support added for AP-324 and AP-325
Cyprus	Support added for AP-207
Czech Republic	Support added for AP-207
Denmark	Support added for AP-207
Dominican Republic	• Support added for AP-207 • Support added for AP-207 • Support added for AP-334 and AP-335

Regulatory Domain	Regulatory Changes
El Salvador	• Support added for AP-207 • Support added for AP-207 • Support added for AP-334 and AP-335
Estonia	Support added for AP-207
Faroe Island	Support added for AP-207
Federated States of Micronesia	• Support added for AP-207
France	Support added for AP-207
French Guiana	Support added for AP-207
French Polynesia	Support added for AP-207
French Southern Territories	Support added for AP-207
Georgia	• Support updated for AP-314 and AP-315 • Support added for AP-334 and AP-335
Germany	Support added for AP-207
Greece	Support added for AP-207
Greenland	Support added for AP-207
Grenada	Support updated for AP-205
Guadelupe	• Support updated for AP-324 and AP-325 • Support added for AP-334 and AP-335
Guam	• • Support added for AP-207 • Support updated for AP-314 and AP-315
Guatemala	• • Support added for AP-207 • Support updated for AP-314 and AP-315
Guernsey	Support added for AP-207
Hong Kong	Support updated for AP-314 and AP-315
Hungary	Support added for AP-207
Iceland	Support added for AP-207
Ireland	Support added for AP-207
Isle of Man	Support added for AP-207

Regulatory Domain	Regulatory Changes
Italy	Support added for AP-207
Jamaica	Support updated for AP-205
Japan	Support added for AP-228
Jersey	Support added for AP-207
Jordan	Support added for AP-324 and AP-325
Kazakstan	Support added for AP-324 and AP-325
Kenya	• Support added for RAP-108 • Support added for RAP-109
Kosovo	• Support added for AP-314 and AP-315 • Support added for AP-324 and AP-325 • Support added for AP-334 and AP-335
Laos	Support updated for AP-314 and AP-315 Support added for AP-334 and AP-335
Latvia	Support added for AP-207
Liechtenstein	Support added for AP-207
Lithuania	Support added for AP-207
Luxembourg	Support added for AP-207
Macau	Support added for AP-207
Macedonia	Support added for AP-207
Malaysia	Support added for AP-334 and AP-335
Maldives	Support added for AP-324 and AP-325
Malta	Support added for AP-207
Marshall Islands	Support added for AP-207
Martinique	Support added for AP-207
Monaco	Support added for AP-207
Montenegro	Support added for AP-207
Netherlands	Support added for AP-207

Regulatory Domain	Regulatory Changes
New Caledonia	Support added for AP-207
North Marina Islands	• Support added for AP-207 • Support updated for AP-314 and AP-315
Norway	Support added for AP-207
Pakistan	Support updated for AP-324 and AP-325
Peru	Support updated for AP-214 and AP-215
Poland	Support added for AP-207
Portugal	Support added for AP-207
Puerto Rico	Support updated for AP-314 and AP-315
Reunion	Support updated for AP-314 and AP-315
Romania	Support added for AP-207
Russia	• Regulatory updates for channels 36-64 • Support updated for AP-103 • Support updated for AP-103H • Support updated for AP-104 and AP-105 • Support updated for AP-114 and AP-115 • Support updated for AP-120 and AP-121 • Support updated for AP-124 and AP-125 • Support updated for AP-134 and AP-135 • Support updated for AP-175, AP-175AC, AP-175DC, and AP-175P • Support updated for AP-204 and AP-205 • Support updated for AP-214 and AP-215 • Support updated for AP-224 and AP-225 • Support updated for AP-228 • Support updated for AP-274 and AP-275 • Support updated for AP-277 • Support updated for AP-324 and AP-325 • Support updated for RAP-3WN and RAP-3WNP
San Marino	Support added for AP-207
Saint Barthelemy	Support added for AP-207
Saint Martin	Support added for AP-207
Saint Pierre and Miquelon	Support added for AP-207
Serbia	• Support updated for AP-314 and AP-315 • Support updated for AP-324 and AP-325 • Support added for AP-334 and AP-335
Slovak Republic	Support added for AP-207

Regulatory Domain	Regulatory Changes
Slovenia	Support added for AP-207
South Korea	• Support updated for AP-315 • Support updated for AP-335
Spain	Support added for AP-207
Svalbard and Jan Mayen	Support added for AP-207
Sweden	Support added for AP-207
Switzerland	Support added for AP-207
Thailand	• Support updated for AP-324 and AP-325 • Support added for AP-334 and AP-335
Turkey	Support added for AP-207
United Kingdom	Support added for AP-207
United States	Support added for AP-207
US Virgin Islands	• Support added for AP-207 • Support updated for AP-314 and AP-315
Vatican City	Support added for AP-207
Wallis And Fortuna	Support added for AP-207

1.0_56643

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 264: *1.0_56643*

Regulatory Domain	Regulatory Changes
Grenada	• Support added for AP-103 • Support added for AP-205H
Jamaica	• Support added for AP-103 • Support added for AP-205H
Nigeria	Support added for AP-324 and AP-325
Pakistan	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Philippines	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Saint Vincent and Grenadines	• Support added for AP-103 • Support added for AP-205 • Support added for AP-205H
Serbia	Support added for AP-114 and AP-115 Support added for AP-205H
Taiwan	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Uruguay	Support added for AP-205

1.0_56452

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 265: *1.0_56452*

Regulatory Domain	Regulatory Changes
Australia	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Bahamas	Support added for AP-103
Egypt	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Jordan	Support added for AP-214 and AP-215
New Zealand	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Paraguay	Support added for AP-205H
Thailand	Support added for AP-314 and AP-315
Uruguay	Support added for AP-103
Venezuela	• Support added for AP-103 • Support added for AP-205H
Vietnam	Support added for AP-325

1.0_56308

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 266:

Regulatory Domain	Regulatory Changes
Barbados	Support added for AP-205H
Ecuador	• Channels updated for AP-103 • Channels updated for AP-105 • Channels updated for AP-135 • Channels updated for AP-205 • Channels updated for AP-205H • Channels updated for AP-224 and AP-225 • Channel updated for AP-274 and AP-275 • Channel updated for RAP-155 and RAP-155P
Egypt	Support added for AP-214 and AP-215
Russia	• Channel updated for AP-105 • Channel updated for AP-125 • Channel updated for AP-134 and AP-135Channel updated for AP-324 and AP-325 • Channel updated for RAP-3WN
Sri Lanka	Support added for AP-225
Trinidad and Tobago	• Support added for AP-103 • Support added for AP-275 • Support added for AP-277

1.0_56128

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 267: *1.0_56128*

Regulatory Domain	Regulatory Changes
American Samoa	Support added for AP-314 and AP-315 Support added for AP-334 and AP-335
Bahamas	Support added for AP-277 Support added for AP-314 and AP-315
Barbados	Support added for AP-274
Canada	DFS channels updated for AP-314 and AP-315
Federated States of Micronesia	Support added for AP-314 and AP-315 Support added for AP-334 and AP-335
Guadeloupe	Guadeloupe regulatory domain enabled Support added for AP-103 Support added for AP-205 Support added for AP-205H Support added for AP-275 Support added for AP-277
Guam	Support added for AP-314 and AP-315 Support added for AP-334 and AP-335
Hong Kong	Channels updated for AP-205
Macau	Support added for AP-314 and AP-315 Support added for AP-334 and AP-335
Northern Mariana Islands	Support added for AP-314 and AP-315 Support added for AP-334 and AP-335

Regulatory Domain	Regulatory Changes
Puerto Rico	Support added for AP-314 and AP-315 Support added for AP-334 and AP-335
United States	DFS channels updated for AP-314 and AP-315 DFS channels updated for AP-334 and AP-335
US Virgin Islands	Support added for AP-314 and AP-315 Support added for AP-334 and AP-335

1.0_56050

This Downloadable Regulatory Table (DRT) supports the channel requirements described in the *HPE Aruba Support Advisory ARUBA-SA-20160516-01*, available for download from the **Announcements** section of the Aruba support site support.arubanetworks.com. This advisory describes FCC changes to the rules for operation in all of the 5 GHz bands for the US regulatory domain.

As a result of these changes, DFS channels (52, 56, 60 and 64) in the UNII-2A frequency band and (channels 100, 104, 108, 112, 116, 120, 124, 128, 132, 136, 140) in UNII-2C frequency band is enabled in this DRT for both controller and Instant-based versions of the following products:

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 268: *1.0_56050*

Regulatory Domain	Regulatory Changes
American Samoa	Channels updated for AP-103 and AP-103H Channels updated for AP-204 and AP-205 Channels updated for AP-214 and AP-215 Channels updated for AP-224 and AP-225 Channels updated for AP-228 Channels updated for AP-274 and AP-275 Channels updated for RAP-108 and RAP-109 Channels updated for RAP-155 and RAP-155P
Bahamas	Channels updated for AP-204 and AP-205 Channels updated for AP-224 and AP-225 Channels updated for AP-274 and AP-275
Federated States of Micronesia	Channels updated for AP-103 and AP-103H Channels updated for AP-204 and AP-205 Channels updated for AP-214 and AP-215 Channels updated for AP-224 and AP-225 Channels updated for AP-228 Channels updated for AP-274 and AP-275 Channels updated for RAP-108 and RAP-109 Channels updated for RAP-155 and RAP-155P
Guam	Channel 144 enabled for Guam regulatory domain

Regulatory Domain	Regulatory Changes
	Channels updated for AP-103 and AP-103H Channels updated for AP-204 and AP-205 Channels updated for AP-214 and AP-215 Channels updated for AP-224 and AP-225 Channels updated for AP-228 Channels updated for AP-274 and AP-275 Channels updated for RAP-108 and RAP-109 Channels updated for RAP-155 and RAP-155P
Hong Kong	Support added for AP-214 and AP-215 Support added for AP-334 and AP-335
Macau	Channels updated for AP-135 Channels updated for AP-205 Channels updated for AP-215 Channels updated for AP-225 Channels updated for AP-274 and AP-275 Support added for AP-314and AP-315 Channels updated for AP-325 Support added for AP-334and AP-335 Channels updated for AP-93
Marshall Islands	Channels updated forAP-103 Channels updated for AP-228
Mayotte	Support added for AP-314and AP-315 Support added for AP-334and AP-335
Myanmar	Support added for AP-335 Support added for AP-68 Support added for AP-92 and AP-93 Support added for AP-93H
Northern Mariana Islands	Channels updated for AP-103 and AP-103H Channels updated for AP-204 and AP-205 Channels updated for AP-214 and AP-215

Regulatory Domain	Regulatory Changes
	Channels updated for AP-224 and AP-225 Channels updated for AP-228 Channels updated for AP-274 and AP-275 Channels updated for RAP-108 and RAP-109 Channels updated for RAP-155 and RAP-155P
Puerto Rico	Channels updated for AP-103 and AP-103H Channels updated for AP-204 and AP-205 Channels updated for AP-214 and AP-215 Channels updated for AP-224 and AP-225 Channels updated for AP-228 Channels updated for AP-274 and AP-275 Channels updated for RAP-108 and RAP-109 Channels updated for RAP-155 and RAP-155P
United Arab Emirates	Channels updated for AP-214 and AP-215
United States	Channels updated for AP-103 and AP-103H Channels updated for AP-204 and AP-205 Channels updated for AP-214 and AP-215 Channels updated for AP-224 and AP-225 Channels updated for AP-228 Channels updated for AP-274 and AP-275 Channels updated for RAP-108 and RAP-109 Channels updated for RAP-155 and RAP-155P
US Virgin Islands	Channels updated for AP-103 and AP-103H Channels updated for AP-204 and AP-205 Channels updated for AP-214 and AP-215 Channels updated for AP-224 and AP-225 Channels updated for AP-228 Channels updated for AP-274 and AP-275 Channels updated for RAP-108 and RAP-109 Channels updated for RAP-155 and RAP-155P

1.0_55859

This Downloadable Regulatory Table (DRT) supports the channel requirements described in the *HPE Aruba Support Advisory ARUBA-SA-20160516-01*, available for download from the **Announcements** section of the Aruba support site support.arubanetworks.com. This advisory describes FCC changes to the rules for operation in all of the 5 GHz bands for the US regulatory domain.

As a result of these changes, DFS channels (52, 56, 60 and 64) in the UNII-2A frequency band and (channels 100, 104, 108, 112, 116, 120, 124, 128, 132, 136, 140) in UNII-2C frequency band are disabled in this DRT for both controller and Instant-based versions of the following products:

- Indoor: AP-314, AP-315, AP-334, AP-335
- Outdoor: N/A
- Remote AP: RAP-155, RAP-155P
- Hospitality: N/A

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 269: *1.0_55859*

Regulatory Domain	Regulatory Changes
American Samoa	Support added for AP-228
Azerbaijan	• Support added for AP-204 and AP-205 • Support added for AP-225
Canada	• DFS channels enabled for AP-103 • DFS channels enabled for AP-224 and AP-225 • DFS channels enabled for AP-228 • DFS channels enabled for AP-314 and AP-315
Dominican Republic	Support added for AP-228
Egypt	Support added for AP-228 Support added for AP-324 and AP-325
El Salvador	Support added for AP-228
Guam	Support added for AP-228
Guatemala	Support added for AP-228
Marshall Islands	Support added for AP-228
Federated States of Micronesia	Support added for AP-228
Myanmar	• Support added for AP-228 • Support added for AP-274 and AP-275 • Support added for AP-277 • Support added for AP-314 and AP-315

Regulatory Domain	Regulatory Changes
	• Support added for AP-324 and AP-325 • Support added for AP-334
Northern Marina Islands	Support added for AP-228
Panama	Support added for AP-325
Quatar	Support added for AP-175P
Tunesia	Support added for AP-214 and AP-215
United States	• DFS channels enabled for AP-103 and AP-103H • DFS channels enabled for AP-204 and AP-205 • DFS channels enabled for AP-214 and AP-215 • DFS channels enabled for AP-224 and AP-225 • DFS channels enabled for RAP-108 and RAP-109
US Virgin Islands	Support added for AP-228

1.0_55642

This Downloadable Regulatory Table (DRT) supports the channel requirements described in the *HPE Aruba Support Advisory ARUBA-SA-20160516-01*, available for download from the **Announcements** section of the Aruba support site support.arubanetworks.com. This advisory describes FCC changes to the rules for operation in all of the 5 GHz bands for the US regulatory domain.

As a result of these changes, DFS channels (52, 56, 60 and 64) in the UNII-2A frequency band and (channels 100, 104, 108, 112, 116, 120, 124, 128, 132, 136, 140) in UNII-2C frequency band are disabled in this DRT for both controller and Instant-based versions of the following products:

- Indoor: AP-103, AP-204, AP-205, AP-214, AP-215, AP-225, AP-314, AP-315, AP-334, AP-335
- Outdoor: N/A
- Remote AP: RAP-155, RAP-155P
- Hospitality: AP-103H

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 270: *EU Countries*

Regulatory Domain	Regulatory Changes
Austria	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Bahrain	Support updated for AP-214 and AP-215
Belgium	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Bulgaria	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Canada	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Croatia	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Republic of Cyprus	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Czech Republic	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Denmark	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Estonia	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Finland	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335

Regulatory Domain	Regulatory Changes
France	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Germany	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Greece	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Hong Kong	Support added for RAP-108 and RAP-109
Hungary	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Ireland	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Italy	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Kazakhstan	Support added for AP-205
Latvia	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Lithuania	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Luxembourg	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Malta	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Myanmar	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Netherlands	• Support added for AP-205H • Support added for AP-214 and AP-215 • Support added for AP-225 • Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Poland	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Portugal	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Romania	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Slovakia	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Slovenia	• Support added for AP-314 and AP-315

Regulatory Domain	Regulatory Changes
	• Support added for AP-334 and AP-335
Spain	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
Sweden	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
United Kingdom	• Support added for AP-314 and AP-315 • Support added for AP-334 and AP-335
United States	• DFS channels enabled for AP-205H • DFS channels enabled for AP-274 and AP-275 • DFS channels enabled for AP-277 • DFS channels enabled for AP-324 and AP-325

1.0_55489

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

This Downloadable Regulatory Table (DRT) supports the channel requirements described in the *HPE Aruba Support Advisory ARUBA-SA-20160516-01*, available for download from the **Announcements** section of the Aruba support site support.arubanetworks.com. This advisory describes FCC changes to the rules for operation in all of the 5 GHz bands for the US regulatory domain.

As a result of these changes, DFS channels (52, 56, 60 and 64) in the UNII-2A frequency band and (channels 100, 104, 108, 112, 116, 120, 124, 128, 132, 136, 140) in UNII-2C frequency band are disabled in this DRT for both controller and Instant-based versions of the following products:

- Indoor: AP-103, AP-204, AP-205, AP-214, AP-215, AP-224, AP-225
- Outdoor: AP-274, AP-275
- Remote AP: RAP-108, RAP-109, RAP-155, RAP-155P
- Hospitality: AP-103H

Table 271: *1.0_55489*

Regulatory Domain	Regulatory Changes
Japan	Channels updated for AP-275
Myanmar	• Support added for Myanmar regulatory domain • Support added for AP-103 and AP-103H • Support added for AP-104 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added forAP-120 and AP-121 • Support added for AP-124 and AP-125 • Support added for AP-134 and AP-135 • Support added for AP-175AC, AP-175DC, AP-175P • Support added for AP-204 and AP-205 • Support added for AP-224
Nigeria	Support added for RAP-155P

1.0_55384

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

This Downloadable Regulatory Table (DRT) supports the channel requirements described in the *HPE Aruba Support Advisory ARUBA-SA-20160516-01*, available for download from the **Announcements** section of the Aruba support site support.arubanetworks.com. This advisory describes FCC changes to the rules for operation in all of the 5 GHz bands for the US regulatory domain.

As a result of these changes, DFS channels (52, 56, 60 and 64) in the UNII-2A frequency band and (channels 100, 104, 108, 112, 116, 120, 124, 128, 132, 136, 140) in UNII-2C frequency band are disabled in this DRT for both controller and Instant-based versions of the following products:

- Indoor: AP-103, AP-204, AP-205, AP-214, AP-215, AP-224, AP-225
- Outdoor: AP-274, AP-275
- Remote AP: RAP-108, RAP-109, RAP-155, RAP-155P
- Hospitality: AP-103H

Table 272: *1.0_55384*

Regulatory Domain	Regulatory Changes
Angola	• Channels updated for Tunisia regulatory domain • Support added for AP-325
Argentina	Support added for AP-205H
Canada	Channels added for AP-205H
Curacao	Support added for AP-325
Morocco	• Channels updated for Tunisia regulatory domain • Support added for AP-325
Trinidad and Tobago	• Support added for AP-205 • Support added for AP-205H
Tunisia	• Channels updated for Tunisia regulatory domain • Support added for AP-325
United States	• Channels updated for AP-205H • Channels updated for AP-224 and AP-225 • Channels updated for AP-274 and AP-275 • Channels updated for AP-314 and AP-315 • Channels updated for AP-334 and AP-335

1.0_54870

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

This Downloadable Regulatory Table (DRT) supports the channel requirements described in the *HPE Aruba Support Advisory ARUBA-SA-20160516-01*, available for download from the **Announcements** section of the Aruba support site support.arubanetworks.com. This advisory describes FCC changes to the rules for operation in all of the 5 GHz bands for the US regulatory domain.

As a result of these changes, DFS channels (52, 56, 60 and 64) in the UNII-2A frequency band and (channels 100, 104, 108, 112, 116, 120, 124, 128, 132, 136, 140) in UNII-2C frequency band are disabled in this DRT for both controller and Instant-based versions of the following products:

- Indoor: AP-103, AP-204, AP-205, AP-214, AP-215, AP-224, AP-225
- Outdoor: AP-274, AP-275
- Remote AP: RAP-108, RAP-109, RAP-155, RAP-155P
- Hospitality: AP-103H

Table 273: *1.0_54870*

Regulatory Domain	Regulatory Changes
American Samoa	• DFS channels disabled for AP-103 • DFS channels disabled for AP-103H • DFS channels disabled for AP-204 • DFS channels disabled for AP-205 • DFS channels disabled for AP-214 • DFS channels disabled for AP-215 • DFS channels disabled for AP-224 • DFS channels disabled for AP-225 • DFS channels disabled for AP-274 • DFS channels disabled for AP-275 • DFS channels disabled for RAP-108 • DFS channels disabled for RAP-109 • DFS channels disabled for RAP-155 • DFS channels disabled for RAP-155P
Federated States of Micronesia	• DFS channels disabled for AP-103 • DFS channels disabled for AP-103H • DFS channels disabled for AP-204 • DFS channels disabled for AP-205 • DFS channels disabled for AP-214 • DFS channels disabled for AP-215 • DFS channels disabled for AP-224 • DFS channels disabled for AP-225 • DFS channels disabled for AP-274 • DFS channels disabled for AP-275 • DFS channels disabled for RAP-108 • DFS channels disabled for RAP-109 • DFS channels disabled for RAP-155 • DFS channels disabled for RAP-155P
Guam	• DFS channels disabled for AP-103 • DFS channels disabled for AP-103H • DFS channels disabled for AP-204 • DFS channels disabled for AP-205 • DFS channels disabled for AP-214 • DFS channels disabled for AP-215 • DFS channels disabled for AP-224 • DFS channels disabled for AP-225 • DFS channels disabled for AP-274

Table 273: *1.0_54870*

Regulatory Domain	Regulatory Changes
	• DFS channels disabled for AP-275 • DFS channels disabled for RAP-108 • DFS channels disabled for RAP-109 • DFS channels disabled for RAP-155 • DFS channels disabled for RAP-155P
Marshall Islands	• DFS channels disabled for AP-103 • DFS channels disabled for AP-103H • DFS channels disabled for AP-204 • DFS channels disabled for AP-205 • DFS channels disabled for AP-214 • DFS channels disabled for AP-215 • DFS channels disabled for AP-224 • DFS channels disabled for AP-225 • DFS channels disabled for AP-274 • DFS channels disabled for AP-275 • DFS channels disabled for RAP-108 • DFS channels disabled for RAP-109 • DFS channels disabled for RAP-155 • DFS channels disabled for RAP-155P
Northern Marina Islands	• DFS channels disabled for AP-103 • DFS channels disabled for AP-103H • DFS channels disabled for AP-204 • DFS channels disabled for AP-205 • DFS channels disabled for AP-214 • DFS channels disabled for AP-215 • DFS channels disabled for AP-224 • DFS channels disabled for AP-225 • DFS channels disabled for AP-274 • DFS channels disabled for AP-275 • DFS channels disabled for RAP-108 • DFS channels disabled for RAP-109 • DFS channels disabled for RAP-155 • DFS channels disabled for RAP-155P
Puerto Rico	• DFS channels disabled for AP-103 • DFS channels disabled for AP-103H • DFS channels disabled for AP-204

Table 273: *1.0_54870*

Regulatory Domain	Regulatory Changes
	• DFS channels disabled for AP-205 • DFS channels disabled for AP-214 • DFS channels disabled for AP-215 • DFS channels disabled for AP-224 • DFS channels disabled for AP-225 • DFS channels disabled for AP-274 • DFS channels disabled for AP-275 • DFS channels disabled for RAP-108 • DFS channels disabled for RAP-109 • DFS channels disabled for RAP-155 • DFS channels disabled for RAP-155P
United States	• DFS channels disabled for AP-103 • DFS channels disabled for AP-103H • DFS channels disabled for AP-204 • DFS channels disabled for AP-205 • DFS channels disabled for AP-214 • DFS channels disabled for AP-215 • DFS channels disabled for AP-224 • DFS channels disabled for AP-225 • DFS channels disabled for AP-274 • DFS channels disabled for AP-275 • DFS channels disabled for RAP-108 • DFS channels disabled for RAP-109 • DFS channels disabled for RAP-155 • DFS channels disabled for RAP-155P
US Virgin Islands	• DFS channels disabled for AP-103 • DFS channels disabled for AP-103H • DFS channels disabled for AP-204 • DFS channels disabled for AP-205 • DFS channels disabled for AP-214 • DFS channels disabled for AP-215 • DFS channels disabled for AP-224 • DFS channels disabled for AP-225 • DFS channels disabled for AP-274 • DFS channels disabled for AP-275 • DFS channels disabled for RAP-108 • DFS channels disabled for RAP-109

Table 273: *1.0_54870*

Regulatory Domain	Regulatory Changes
	• DFS channels disabled for RAP-155 • DFS channels disabled for RAP-155P

1.0_54672

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 274: *1.0_54672*

Regulatory Domain	Regulatory Changes
Austria	Support added for AP-214 and AP-215
Belgium	Support added for AP-214 and AP-215
Bosnia and Herzengovina	Support added for AP-214 and AP-215
Bulgaria	Support added for AP-214 and AP-215
Croatia	• Support added for AP-103 • Support added for AP-214 and AP-215
Cyprus	Support added for AP-214 and AP-215
Czech Republic	Support added for AP-214 and AP-215
Denmark	Support added for AP-214 and AP-215
Estonia	Support added for AP-214 and AP-215
Finland	Support added for AP-214 and AP-215
France	Support added for AP-214 and AP-215
Georgia	Support added for AP-214 and AP-215
Germany	Support added for AP-214 and AP-215
Greece	Support added for AP-214 and AP-215
Hungary	Support added for AP-214 and AP-215
Iceland	Support added for AP-214 and AP-215
Ireland	Support added for AP-214 and AP-215
Italy	Support added for AP-214 and AP-215
Latvia	Support added for AP-214 and AP-215
Liechtenstein	Support added for AP-214 and AP-215

Regulatory Domain	Regulatory Changes
Lithuania	Support added for AP-214 and AP-215
Luxembourg	Support added for AP-214 and AP-215
Macedonia	Support added for AP-214 and AP-215
Malta	Support added for AP-214 and AP-215
Montenegro	Support added for AP-214 and AP-215
Netherlands	Support added for AP-214 and AP-215
Norway	Support added for AP-214 and AP-215
Poland	Support added for AP-214 and AP-215
Portugal	Support added for AP-214 and AP-215
Romania	Support added for AP-214 and AP-215
Serbia	Support added for AP-214 and AP-215
Slovakia	Support added for AP-214 and AP-215
Slovenia	Support added for AP-214 and AP-215
Spain	Support added for AP-214 and AP-215
Sweden	Support added for AP-214 and AP-215
Switzerland	Support added for AP-214 and AP-215
Turkey	Support added for AP-214 and AP-215
United Kingdom	Support added for AP-214 and AP-215

1.0_54367

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 275: *1.0_54367*

Regulatory Domain	Regulatory Changes
Mexico	Support added for AP-205H
Myanmar	Support enabled for Myanmar regulatory domain
Pakistan	• Support updated for Pakistan regulatory domain • Support updated for AP-103 • Support updated for AP-105 • Support updated for AP-135 • Support updated for AP-205 • Support updated for AP-215 • Support updated for AP-225 • Support updated for AP-275 • Support updated for AP-325 • Support updated for RAP-109 • Support updated for RAP-155

1.0_54219

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 276: *1.0_54219*

Regulatory Domain	Regulatory Changes
Canada	DFS channels enabled for AP-277
India	Support added for AP-103H
Indonesia	Support added for AP-205H
Sri Lanka	• Maximum power values updated for channels 120, 124 and 128 • DFS channels updated for country domain

1.0_54079

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 277: *1.0_54079*

Regulatory Domain	Regulatory Changes
American Samoa	Support added for AP-277
Angola	• Support added for Angola regulatory domain • Support added for AP-135 • Support added for AP-225
Australia	Channels updated for AP-274 and AP-275
Bolivia	Support added for RAP-155 and RAP-155P
Dominican Republic	Support added for AP-277
El Salvador	• Support added for AP-277 • Support added for RAP-155
Federated States of Micronesia	Support added for AP-277
Guam	Support added for AP-277
Guatemala	• Support added for RAP-155 • Support added for RAP-155P • Support added for AP-277
Honduras	• Support added for RAP-155 • Support added for RAP-155P
Indonesia	Support added for AP-214
Kenya	Support added for RAP-155P
Laos	Support added for AP-277
Marshall Islands	Support added for AP-277
Northern Marina Islands	Support added for AP-277
Paraguay	Support added for RAP-155P
Peru	• Support added for RAP-155 • Support added for RAP-155P

Table 277: *1.0_54079*

Regulatory Domain	Regulatory Changes
South Korea	Support added for RAP-155P
Venezuela	• Support added for AP-214 • Support added for RAP-155 • Support added for RAP-155P • Support added for RAP-3WNP
US Virgin Islands	Support added for AP-277

1.0_53811

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 278: *1.0_53811*

Regulatory Domain	Regulatory Changes
United States	Channels updated for AP-277

1.0_53631

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 279: *1.0_53631*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-225 Support added for AP-228 Support added for AP-275 Support added for AP-325
Ethiopia	Ethiopia regulatory domain added Support added for AP-103 and AP-103H Support added for AP-104 and AP-105 Support added for AP-114 and AP-115 Support added for AP-121 Support added for AP-124 and AP-125 Support added for AP-134 and AP-135 Support added for AP-175AC, AP-175DC and AP-175P Support added for AP-204 and AP-205 Support added for AP-214 and AP-215 Support added for AP-224 and AP-225 Support added for AP-274 and AP-275 Support added for AP-277 Support added for AP-324 and AP-325 Support added for AP-68 Support added for AP-92 and AP-93 Support added for AP-93H Support added for RAP-108 and RAP-109 Support added for RAP-155 and RAP-155P Support added for RAP-3WN and RAP-3WNP
Mexico	Support added for AP-324 and AP-325
Nicaragua	Support added for AP-275
Zimbabwe	Support added for AP-225

1.0_53420

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 280: *1.0_53420*

Regulatory Domain	Regulatory Changes
Algeria	Channels updated for AP-135
Bolivia	Support added for AP-275
Ecuador	Support added for AP-205H
Lao	Support added for AP-68 Channels updated for AP-92 and AP-93 Support added for AP-93H Channels updated for AP-104 Channels updated for AP-105 Channels updated for AP-120 Support added for AP-121 Support added for AP-124 Channels updated for AP-125 Channels updated for AP-134 Channels updated for AP-175AC Support added for AP-175DC Channels updated for AP-205H Support added for AP-324 and AP-325 Support added for RAP-155 and RAP-155P Support added for RAP-3WNP
Malaysia	Support added for RAP-3WN
Pakistan	Support added for AP-103
South Korea	Support added for AP-277

1.0_53255

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 281: *1.0_53255*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-103
Indonesia	Support added for AP-324 and AP-325
Israel	• Support added for AP-103 and AP-103H • Support added for AP-205H • Support added for AP-277 • Support added for AP-324

1.0_52991

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 282: *1.0_52991*

Regulatory Domain	Regulatory Changes
Nicaragua	Support added AP-215
Pakistan	• Support added for AP-205 • Support added for AP-275 • Support added for AP-325

1.0_52858

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 283: *1.0_52858*

Regulatory Domain	Regulatory Changes
Antigua and Barbuda	• Channels 12 and 13 updated • Support added for AP-205 • Support added for AP-228 • Support added for AP-275
Iraq	• Channels 36, 40,44, and 48 added • Support added for AP-215 • Support added for AP-275 • Support added for RAP-3WNP
Macau	Support added for AP-228
Tunisia	Support added for AP-205

1.0_52699

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 284: *1.0_52699*

Regulatory Domain	Regulatory Changes
Bolivia	Support added for RAP-3WNP
Kenya	Support added for RAP-3WN
Nicaragua	• Support added for RAP-155 and RAP-155P • Support added for RAP-3WN
Panama	Support added for AP-115
Paraguay	• Support added for AP-103 • Support added for AP-204 • Support added for AP-214
Russia	Support added for AP-205H
Tunisia	Support added for ap-225
Ukraine	• Support added for AP-204 and AP-205 • Support added for AP-324 and AP-325
United States	Support added for AP-205H

1.0_52480

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 285: *1.0_52480*

Regulatory Domain	Regulatory Changes
American Samoa	Channels 120, 124 and 128 enabled
Antigua and Barbuda	Channels 120, 124 and 128 enabled
Aruba	Channels 120, 124 and 128 enabled
Bahamas	Channels 120, 124 and 128 enabled
Bangladesh	Channels 120, 124 and 128 enabled
Barbados	Channel 120 enabled
Bermuda	Channels 120, 124 and 128 enabled
Bolivia	• Support added for RAP-155 • Channels 120, 124 enabled
Bonaire Saint Eustatius and Saba	Channels 120, 124 and 128 enabled
Brazil	• Support added for AP-205H • Support added for AP-228
Brunei Darussalam	Channels 120, 124 and 128 enabled
Cameroon	Channels 120, 124 and 128 enabled
Chile	Support added for AP-277
Colombia	• Support added for AP-205H • Support added for AP-228 • Support added for AP-324 and AP-325 • Channels 120, 124 and 128 enabled
Costa Rica	Channels 120, 124 and 128 enabled
Cuba	Channels 120, 124 and 128 enabled
Curacao	Channels 120, 124 and 128 enabled
Dominica	Channels 120, 124 and 128 enabled
Dominican Republic	Channels 120, 124 and 128 enabledr

Regulatory Domain	Regulatory Changes
Ecuador	Support added for RAP-155P
El Salvador	Channels 120, 124 and 128 enabled
Federated States of Micronesia	Channels 120, 124 and 128 enabled
Guam	Channels 120, 124 and 128 enabled
Guatemala	Channels 120, 124 and 128 enabled
Iran	Channels 120, 124 and 128 enabled
Honduras	Channels 120, 124 and 128 enabled
Kazakhstan	Support added for AP-225
Lebanon	Support added for RAP-155P
Malaysia	Support added for AP-324 and AP-325
Marshall Islands	Channels 120, 124 and 128 enabled
Mexico	Channels 120, 124 and 128 enabled
Montserrat	Channels 120, 124 and 128 enabled
Nicaragua	Channels 120, 124 and 128 enabled
Northern Mariana Island	Channels 120, 124 and 128 enabled
Pakistan	Support added for AP-215
Panama	Channels 120, 124 and 128 enabled
Paraguay	Channels 120, 124 and 128 enabled
Puerto Rico	Channels 120, 124 and 128 enabled
Saint Kitts and Nevis	Channels 120, 124 and 128 enabled
Saint Vincent and Grenada	Channels 120, 124 and 128 enabled
South Africa	Support added for AP-324 and AP-325
South Korea	DFS channels updated for AP-324 and AP-325
Surinam	Channels 120, 124 and 128 enabled
Taiwan	Channels 120, 124 and 128 enabled

Regulatory Domain	Regulatory Changes
United Arab Emirates	Support added for AP-324 and AP-325
United States	Channels 120, 124 and 128 enabled
US Virgin Islands	Channels 120, 124 and 128 enabled
Vietnam	Support added for RAP-3WNP

1.0_52238

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 286: *1.0_52238*

Regulatory Domain	Regulatory Changes
American Samoa	Support added for AP-324 and AP-325
Bosnia and Herzgovina	Support added for AP-215
Costa Rica	Channels added for AP-324 and AP-325
Doninican Republic	Support added for AP-324 and AP-325
El Salvador	Support added for AP-324 and AP-325
Federated States of Micronesia	Support added for AP-324 and AP-325
Guam	Support added for AP-324 and AP-325
Guatemala	Support added for AP-324 and AP-325
Honduras	Support added for AP-275
Japan	Channels added for AP-103 Channels added for AP-103H Channels added for AP-104 Channels added for AP-114 Channels added for AP-120 and AP-121 Channels added for AP-124 and AP-125 Channels added for AP-134 and AP-135
Kuwait	Support added for AP-324 and AP-325
Marshall Islands	Support added for AP-324 and AP-325
Nigeria	Support added for AP-215 Support added for RAP-3WN and RAP-3WNP
Northern Marina Islands	Support added for AP-324 and AP-325

Regulatory Domain	Regulatory Changes
United States	
Venezuela	Support added for AP-275
Virgin Islands	Support added for AP-324 and AP-325

1.0_52042

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 287: *1.0_52042*

Regulatory Domain	Regulatory Changes
Lebanon	Support added for AP-215
Panama	Support added for RAP-109 Support added for RAP-155
Paraguay	Support added for RAP-3WNP

1.0_51997

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 288: *1.0_51997*

Regulatory Domain	Regulatory Changes
Aland Islands	Support added for AP-324 and AP-325
Albania	Support added for AP-324 and AP-325
American Samoa	Support added for AP-325
Andorra	Support added for AP-324 and AP-325
Australia	• Support updated for AP-274 and AP-275 • Support added for AP-324 and AP-325
Brazil	Support added for AP-205H • Support added for AP-228
Chile	• Support added for AP-277 • Support added for AP-324 and AP-325
China	Support added for AP-324 and AP-325
Columbia	• Support added for AP-228 • Support added for AP-277
Costa Rica	Support added for RAP-155
Faroe Islands	Support added for AP-325
French Guiana	Support added for AP-324 and AP-325
French Polynesia	Support added for AP-324 and AP-325
French Southern Territories	Support added for AP-324 and AP-325
Georgia	• Support added for AP-68 • Support added for AP-92, AP-93, and AP-93H • Support added for AP-103 and AP-103H • Support added for AP-104 and AP-105 • Support added for AP-114 and AP-115 • Support added for AP-120, AP-121, AP-124, and AP-125

Regulatory Domain	Regulatory Changes
	• Support added for AP-134 and AP-135 • Support added for AP-175AC, AP-175DC, and AP-175P • Support added for AP-204, AP-205, and AP-205H • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for AP-228 • Support added for AP-274 and AP-275 • Support added for AP-277 • Support added for AP-324 and AP-325 • Support added for RAP-3WN and RAP-3WNP • Support added for RAP-108 and RAP-109 • Support added for RAP-155 and RAP-155P
Greenland	Support added for AP-324 and AP-325
Guernsey	Support added for AP-324 and AP-325
Honduras	• Support added for RAP-155P • Support added for AP-215
Hong Kong	Support added for AP-324 and AP-325
India	Support added for AP-324 and AP-325
Isle of Man	Support added for AP-324 and AP-325
Japan	Support added for AP-324 and AP-325
Jersey	Support added for AP-324 and AP-325
Maritime	Support added for AP-324 and AP-325
Maritime Offshore	Support added for AP-324 and AP-325
Martinique	Support added for AP-324 and AP-325
Mayotte	• Support updated for AP-93 • Support updated for AP-103 and AP-103H • Support updated for AP-105 • Support updated for AP-114 and AP-115 • Support updated for AP-135 • Support updated for AP-175P • Support updated for AP-204 and AP-205 • Support added for AP-205H

Regulatory Domain	Regulatory Changes
	• Support updated for AP-214 and AP-215 • Support updated for AP-224 and AP-225 • Support updated for AP-274 • Support added for AP-277 • Support added for AP-324 and AP-325 • Support updated for RAP-3WN and RAP-3WNP • Support updated for RAP-108 and RAP-109
Mexico	Support added for AP-277
Monaco	Support added for AP-324 and AP-325
Morocco	Support added for RAP-155P
New Caledonia	Support added for AP-324 and AP-325
New Zealand	• Support updated for AP-274 and AP-275 • Support added for AP-324 and AP-325
Puerto Rico	• Support added for AP-103 • Support added for AP-204, AP-205, and AP-205H • Support added for AP-214 and AP-215 • Support added for AP-228 • Support added for AP-277 • Support added for AP-324 and AP-325
Reunion	Support added for AP-324 and AP-325
Saint Barthelemy	Support added for AP-324 and AP-325
Saint Martin	Support added for AP-324 and AP-325
Saint Pierre and Miquelon	Support added for AP-324 and AP-325
San Marino	Support added for AP-324 and AP-325
Svalbard and Jan Mayen	Support added for AP-324 and AP-325
Taiwan	Support added for AP-324 and AP-325
Uruguay	Support added for AP-275
Vatican City	Support added for AP-324 and AP-325
Wallis and Futuna	Support added for AP-324 and AP-325

1.0_51685

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 289: *1.0_51685*

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-277
Costa Rica	Support added for RAP-155
Ecuador	Support added for RAP-155 Support added for RAP-3WNP
Egypt	Support added for AP-324 and AP-325
Honduras	• Support added for AP-225 • Support added for RAP-3WNP
Japan	Support added for AP-205H
Kuwait	Support added for AP-228
Panama	Support added for RAP-155
Peru	Support added for AP-324 and AP-325
Phillipines	Support added for AP-324 and AP-325
Quatar	Support added for AP-324 and AP-325
Trinidad and Tobago	Support added for AP-275
Uruguay	Support added for RAP-155
Venezuela	Support added for AP-215

1.0_51477

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 290: *1.0_51477*

Regulatory Domain	Regulatory Changes
Austria	Support added for AP-324 and AP-325
Bahrain	Support added for AP-324 and AP-325
Belgium	Support added for AP-324 and AP-325
Bulgaria	Support added for AP-324 and AP-325
Canada	DFS bands enabled for AP-324 and AP-325
Costa Rica	Support added for AP-324
Croatia	Support added for AP-324 and AP-325
Republic of Cyprus	Support added for AP-324 and AP-325
Czech Republic	Support added for AP-324 and AP-325
Denmark	Support added for AP-324 and AP-325
Estonia	Support added for AP-324 and AP-325
Finland	Support added for AP-324 and AP-325
France	Support added for AP-324 and AP-325
Germany	Support added for AP-324 and AP-325
Greece	Support added for AP-324 and AP-325
Hungary	Support added for AP-324 and AP-325
Ireland	Support added for AP-324 and AP-325
Italy	Support added for AP-324 and AP-325
Jordan	Support added for AP-205H
Latvia	Support added for AP-324 and AP-325
Lithuania	Support added for AP-324 and AP-325

Regulatory Domain	Regulatory Changes
Luxembourg	Support added for AP-324 and AP-325
Malaysia	Support added for AP-205H
Malta	Support added for AP-324 and AP-325
Netherlands	Support added for AP-324 and AP-325
Oman	Support added for AP-324 and AP-325
Panama	Support added for RAP-3WN
Paraguay	• Support added for AP-215 • Support added for AP-225 • Support added for RAP-3WNP
Poland	Support added for AP-324 and AP-325
Portugal	Support added for AP-324 and AP-325
Romania	Support added for AP-324 and AP-325
Singapore	Support added for AP-324 and AP-325
Slovakia	Support added for AP-324 and AP-325
Slovenia	Support added for AP-324 and AP-325
Spain	Support added for AP-324 and AP-325
Sweden	Support added for AP-324 and AP-325
Trinidad and Tobago	Support updated for RAP-155
United Kingdom	Support added for AP-324 and AP-325
Vietnam	Support added for AP-275

1.0_51362

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 291: *EU Countries*

Regulatory Domain	Regulatory Changes
Brazil	Support added for AP-277
Costa Rica	Support added for AP-325
Croatia	Support added for AP-214 and AP-215
Saudi Arabia	Support added for AP-324 and AP-325
Zambia	Support added for AP-324 and AP-325

1.0_51155

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 292: *1.0_51155*

Regulatory Domain	Regulatory Changes
American Simoa	Support updated for AP-274 and AP-275
Canada	Support added for AP-324 and AP-325
Dominican Republic	Support added for AP-274 and AP-275
El Salvador	Support added for AP-274 and AP-275
Federated States of Micronesia	Support updated for AP-274 and AP-275
Ghana	Support added for AP-225
Guam	Support updated for AP-274 and AP-275
Guatemala	Support updated for AP-274 and AP-275
Kuwait	• Support added for AP-115 • Support added for AP-205
Laos	Support updated for AP-274 and AP-275
Marshall Islands	Support updated for AP-274 and AP-275
Mexico	Support updated for AP-228
Northern Mariana Island	Support updated for AP-274 and AP-275
Puerto Rico	Support updated for AP-274 and AP-275
Trinidad & Tobago	• Support added for AP-215 • Support added for RAP-155 • Support added for RAP-3WNP
Uruguay	Support added for RAP-3WNP
United States of America	• Support updated for AP-274 and AP-275 • Support added for AP-324 and AP-325 • DFS bands updated for RAP-155P and RAP-155
US virgin Islands	Support updated for AP-274 and AP-275

1.0_50970

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 293: *1.0_50970*

Regulatory Domain	Regulatory Changes
American Samoa	Support updated for AP-205H
Canada	Support updated for AP-205H
Costa Rica	Support updated for AP-205H
Dominican Republic	Support updated for AP-205H
El Salvadore	Support updated for AP-205H
Federated States of Micronesia	Support updated for AP-205H
Guam	Support updated for AP-205H
Guatemala	Support updated for AP-205H
Indonesia	• Support updated for AP-68 • Support updated for AP-92 • Support updated for AP-93 and AP-93H • Support updated for AP-104 • Support updated for AP-114 • Support updated for AP-134 • Support updated for AP-274 and AP-275 • Support updated for RAP-3WNP
Japan	• Support updated for AP-204 and AP-205 • Support updated for AP-214 and AP-205 • Support updated for AP-224 and AP-225 • Support updated for AP-274 and AP-275 • Support updated for AP-277
Laos	Support updated for AP-205H
Marshall Islands	Support updated for AP-205H
Northern Marina Islands	Support updated for AP-205H
Peru	Support updated for AP-205H

Table 293: *1.0_50970*

Regulatory Domain	Regulatory Changes
Singapore	Support updated for AP-205H
Taiwan	Support updated for AP-205H
United States	DFS bands added for AP-205H

1.0_50775

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 294: *1.0_50775*

Regulatory Domain	Regulatory Changes
Algeria	Support updated for AP-205 Support added for AP-215
Bahrain	Support added for AP-204 and AP-205 Support added for AP-214 and AP-215 Support added for AP-224 Support added for AP-274 and AP-275
Indonesia	Support added for AP-277
Saudi Arabia	Support added for AP-103

1.0_50552

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 295: *1.0_50552*

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-228
Bahrain	• Support added for AP-103 • Support added for AP-103H
Hong Kong	Support updated for RAP-3WNP
Kuwait	Support added for AP-228
South Africa	Support added for AP-205H
South Korea	Support added for AP-205H

1.0_50379

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 296: *1.0_50379*

Regulatory Domain	Regulatory Changes
Albania	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Aland Island	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Anndora	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Bermuda	Support added for AP-224 and AP-225
China	Support added for AP-205H
Faroe Island	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
French Guiana	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
French Polynesia	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
French Southern Territories	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Greenland	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Guernsey	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Hong Kong	Support added for AP-277
Isle of Man	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Jersey	• Support added for AP-205H

Table 296: *1.0_50379*

Regulatory Domain	Regulatory Changes
	• Support added for AP-228 • Support added for AP-277
Lao	Support added for AP-277
Macau	• Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-274 and AP-275 • Support added for AP-277
Martinique	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Monaco	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
New Caldonia	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Pakistan	• Support added for RAP-109 • Support added for RAP-155
Reunion	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Santa Barthelemy	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Saint Martin	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Saint Pierre and Miquelon	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
San Marino	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277

Table 296: *1.0_50379*

Regulatory Domain	Regulatory Changes
Svlabard and Jan Mayen	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Wallis and Futuna	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Vatican City	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277

1.0_50288

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 297:

Regulatory Domain	Regulatory Changes
China	Support added for AP-228
Hong Kong	Support added for AP-205H
Indonesia	Support added for AP-228
Israel	Support added for AP-274 and AP-275
Lebanon	Support added for AP-205H
Malaysia	Support added for AP-228 Support added for AP-277
Nigeria	Support added for AP-205 Support added for AP-275
Peru	Support added for AP-215
Taiwan	Support added for AP-205H Support added for AP-215

1.0_49986

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 298: *1.0_49986*

Regulatory Domain	Regulatory Changes
Egypt	Support added for AP-205H
Hong Kong	Support added for AP-228
Lebanon	• Support added for AP-205H • Support added for AP-277
Oman	Support added for AP-205H
Quatar	Support added for AP-205H
Russia	• Support added for AP-228 • Support added for AP-277
South Africa	Support added forAP-228

1.0_49810

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 299: *1.0_49810*

Regulatory Domain	Regulatory Changes
Austrailia	Support added for AP-205H
Bahrain	Support added for AP-205H
Bolivia	Support updated for AP-120 and AP-121 Support updated for AP-135
Costa Rica	Support added for AP-205H Support added for AP-228
Egypt	Support added for AP-228 Support updated for AP-274
India	Support added for AP-228
Japan	Support added for AP-277
Mexico	Support added for AP-228
New Zealand	Support added for AP-205H
Oman	Support added for AP-228
Peru	Support added for AP-214
Phillipines	Support added for AP-205H Support added for AP-228
Quatar	• Support added for AP-224 and AP-225 • Support added for AP-228
Saudi Arabia	Support added for AP-205H
United Arab Emirates	Support added for AP-205H

1.0_49596

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 300: *1.0_49596*

Regulatory Domain	Regulatory Changes
Australia	Support added for AP-228
Bahrain	Support added for AP-228
Bonaire Sint Eustatius and Saba	Support added for AP-225
Canada	Support added for AP-228
Chile	Support added for AP-228
Costa Rica	Support updated for AP-274 and AP-275
Curaco	Support added for AP-225
Dominica	Support added for AP-225
French Polynesia	• Support added for AP-93 • Support added for AP-103 and AP-103H • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for AP-274 and AP-275 • Support added for RAP-108 • Support added for RAP-109 • Support added for RAP-3WN and RAP-3WNP
India	Support added for AP-205H
Laos	• Support added for AP-103 and AP-103H • Support added for AP-114 and AP-115 • Support added for AP-175P • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP108 and RAP-109
New Caledonia	• Support added for AP-93 • Support added for AP-103 and AP-103H • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135

Table 300: *1.0_49596*

Regulatory Domain	Regulatory Changes
	• Support added for AP-175P • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for AP-274 and AP-275 • Support added for RAP-108 • Support added for RAP-109 • Support added for RAP-3WN and RAP-3WNP
New Zealand	Support added for AP-228
Peru	• Support added for AP-205H • Support added for AP-228 • Support added for AP-277
Saint Kitts and Nevis	Support added for AP-225
Saint Vincent and the Grenadines	Support added for AP-225
Saudi Arabia	Support added for AP-228
Singapore	• Support added for AP-224 and AP-225 • Support added for AP-228
United Arab Emarites	Support added for AP-228
United States of America	Support added for AP-228

1.0_49422

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 301: *1.0_49422*

Regulatory Domain	Regulatory Changes
Antigua and Barbuda	Support added for AP-225
Austria	Support added for AP-205H
Belgium	Support added for AP-205H
Chile	Support added for AP-205H
Costa Rica	Support added for AP-214 and AP-215
Croatia	Support added for AP-205H
Czech Republic	Support added for AP-205H
Denmark	Support added for AP-205H
Ecuador	• Support added for AP-215 • Support updated for AP-224 and AP-225 • Support updated for AP-275
Estonia	Support added for AP-205H
Finland	Support added for AP-205H
France	Support added for AP-205H
Germany	Support added for AP-205H
Greece	Support added for AP-205H
Hungary	Support added for AP-205H
Ireland	Support added for AP-205H
Italy	Support added for AP-205H
Latvia	Support added for AP-205H
Luxembourg	Support added for AP-205H
Malta	Support added for AP-205H

Table 301: *1.0_49422*

Regulatory Domain	Regulatory Changes
Netherlands	Support added for AP-205H
Pakistan	• Support added for AP-135 • Support enabled for AP-225
Poland	Support added for AP-205H
Portugal	Support added for AP-205H
Romania	Support added for AP-205H
Singapore	Support added for AP-105
Slovakia	Support added for AP-205H
Slovenia	Support added for AP-205H
Spain	Support added for AP-205H
Suriname	Support added for AP-225
Sweden	Support added for AP-205H
Thailand	• Support updated for AP-103 and AP-103H • Support updated for AP-104 • Support updated for AP-114 and AP-115 • Support updated for AP-120 and AP-121 • Support updated for AP-124 and AP-125 • Support updated for AP-135 • Support updated for AP-175DC • Support updated for AP-204 and AP-205 • Support updated for AP-214 and AP-215 • Support updated for AP-224 and AP-225 • Support updated for AP-274 and AP-275 • Support updated for AP-92 and AP-93 • Support updated for RAP-108 and RAP-109 • Support updated for RAP-155 and RAP-155P
United Kingdom	Support added for AP-205H

1.0_49142

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 302: *1.0_49142*

Regulatory Domain	Regulatory Changes
Albania	Support updated for AP-204 and AP-205
Austria	Support added for AP-228
Belgium	Support added for AP-228
Croatia	Support added for AP-228
Costa Rica	• Support updated for AP-204 and AP-205 • Support updated for AP-224 and AP-225 • Support updated for AP-274 and AP-275 • Support added for AP-277
Czech Republic	Support added for AP-228
Denmark	Support added for AP-228
Ecuador	• Support added for AP-204 and AP-205 • Support added for AP-224 and AP-225 • Support added for AP-275
Egypt	• Support added for AP-275 • Support added for AP-277
Estonia	Support added for AP-228
Finland	Support added for AP-228
France	Support added for AP-228
Germany	Support added for AP-228
Greece	Support added for AP-228
Hungary	Support added for AP-228
Ireland	Support added for AP-228
Italy	Support added for AP-228

Table 302: *1.0_49142*

Regulatory Domain	Regulatory Changes
Latvia	Support added for AP-228
Luxembourg	Support added for AP-228
Malta	Support added for AP-228
Maritime	• Support added for AP-68P • Support added for AP-103 • Support added for AP-114 and AP-115 • Support added for RAP-108 and RAP-109 • Support added for RAP-155 and RAP-155P
Maritime Offshore	• Support added for AP-68P • Support added for AP-103 • Support added for AP-114 and AP-115 • Support added for RAP-108 and RAP-109 • Support added for RAP-155 and RAP-155P
Netherlands	Support added for AP-228
Panama	• Support added for AP-215 • Support added for AP-103
Poland	Support added for AP-228
Portugal	Support added for AP-228
Romania	Support added for AP-228
Slovakia	Support added for AP-228
Slovenia	Support added for AP-228
Spain	Support added for AP-228
Sweden	Support added for AP-228
United Kingdom	Support added for AP-228

1.0_48902

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 303: *1.0_48902*

Regulatory Domain	Regulatory Changes
American Samoa	• Support added for AP-93 • Support added for AP-103 • Support added for AP-103H • Support added for AP-105 • Support added for AP-114 • Support added for AP-115 • Support added for AP-135 • Support added for AP-175P • Support added for AP-204 • Support added for AP-205 • Support added for AP-214 • Support added for AP-215 • Support added for AP-224 • Support added for AP-225 • Support added for AP-274 • Support added for AP-275 • Support added for AP-93 • Support added for RAP-108 • Support added for RAP-109 • Support added for RAP-3WNP
Dominican Republic	Support addded for AP-93 Support addded for AP-103 Support addded for AP-103H Support addded for AP-205 Support addded for AP-214 Support addded for AP-215
El Salvador	• Support addded for AP-103 • Support addded for AP-103H • Support addded for AP-205 • Support addded for AP-214

Table 303: *1.0_48902*

Regulatory Domain	Regulatory Changes
	• Support addded for AP-215 • Support addded for RAP-108 • Support addded for RAP-109 • Support addded forRAP-3WN
Equador	Support addded for AP-103
Federated States of Micronesioa	• Support added for AP-93 • Support added for AP-103 • Support added for AP-103H • Support added for AP-105 • Support added for AP-114 • Support added for AP-115 • Support added for AP-135 • Support added for AP-175P • Support added for AP-204 • Support added for AP-205 • Support added for AP-214 • Support added for AP-215 • Support added for AP-224 • Support added for AP-225 • Support added for AP-274 • Support added for AP-275 • Support added for AP-93 • Support added for RAP-108 • Support added for RAP-109 • Support added for RAP-3WNP
Guam	• Support added for AP-93 • Support added for AP-103 • Support added for AP-103H • Support added for AP-105 • Support added for AP-114 • Support added for AP-115 • Support added for AP-135 • Support added for AP-175P • Support added for AP-204 • Support added for AP-205 • Support added for AP-214

Table 303: *1.0_48902*

Regulatory Domain	Regulatory Changes
	• Support added for AP-215 • Support added for AP-224 • Support added for AP-225 • Support added for AP-274 • Support added for AP-275 • Support added for AP-93 • Support added for RAP-108 • Support added for RAP-109 • Support added for RAP-3WNP
Guatemala	• Support added for AP-93 • Support added for AP-103 • Support added for AP-103H • Support added for AP-105 • Support added for AP-115 • Support added for AP-135 • Support added for AP-175P • Support added for AP-204 • Support added for AP-205 • Support added for AP-214 • Support added for AP-215 • Support added for AP-224 • Support added for AP-225 • Support added for AP-274 • Support added for AP-275 • Support added for AP-93 • Support added for RAP-108 • Support added for RAP-109 • Support added for RAP-3WNP
Hong Kong	Support addded for AP-277
India	Support addded for AP-277
Israel	• Support addded for AP-214 • Support addded for AP-215
Marshall Islands	• Support added for AP-93 • Support added for AP-103 • Support added for AP-103H

Table 303: *1.0_48902*

Regulatory Domain	Regulatory Changes
	• Support added for AP-105 • Support added for AP-114 • Support added for AP-115 • Support added for AP-135 • Support added for AP-175P • Support added for AP-204 • Support added for AP-205 • Support added for AP-214 • Support added for AP-215 • Support added for AP-224 • Support added for AP-225 • Support added for AP-274 • Support added for AP-275 • Support added for AP-93 • Support added for RAP-108 • Support added for RAP-109 • Support added for RAP-3WNP
Mayotte	• Support added for AP-93 • Support added for AP-103 • Support added for AP-103H • Support added for AP-105 • Support added for AP-114 • Support added for AP-115 • Support added for AP-135 • Support added for AP-175P • Support added for AP-204 • Support added for AP-205 • Support added for AP-214 • Support added for AP-215 • Support added for AP-224 • Support added for AP-225 • Support added for AP-274 • Support added for AP-275 • Support added for AP-93 • Support added for RAP-108 • Support added for RAP-109 • Support added for RAP-3WNP

Table 303: *1.0_48902*

Regulatory Domain	Regulatory Changes
Mexico	Support updated for AP-104
Morocco	• Support addded for AP-103 • Support addded for AP-215
Nigeria	Support addded for AP-103

Table 303: *1.0_48902*

Regulatory Domain	Regulatory Changes
Northern Marina Islands	• Support added for AP-93 • Support added for AP-103 • Support added for AP-103H • Support added for AP-105 • Support added for AP-114 • Support added for AP-115 • Support added for AP-135 • Support added for AP-175P • Support added for AP-204 • Support added for AP-205 • Support added for AP-214 • Support added for AP-215 • Support added for AP-224 • Support added for AP-225 • Support added for AP-274 • Support added for AP-275 • Support added for AP-93 • Support added for RAP-108 • Support added for RAP-109 • Support added for RAP-3WNP
Ukraine	Support addded for AP-277
Virgin Islands (US)	• Support added for AP-93 • Support added for AP-103 • Support added for AP-103H • Support added for AP-105 • Support added for AP-114 • Support added for AP-115 • Support added for AP-135 • Support added for AP-175P • Support added for AP-204 • Support added for AP-205 • Support added for AP-214 • Support added for AP-215 • Support added for AP-224 • Support added for AP-225 • Support added for AP-274

Table 303: *1.0_48902*

Regulatory Domain	Regulatory Changes
	• Support added for AP-275 • Support added for AP-93 • Support added for RAP-108 • Support added for RAP-109 • Support added for RAP-3WNP

1.0_48713

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 304: *1.0_48713*

Regulatory Domain	Regulatory Changes
Aland Islands	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Albania	• Support added for AP-103H • Support added for AP-175P • Support added for AP-225 • Support added for RAP-108
Andorra	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Australia	Support updated for AP-277
Bangladesh	Support added for AP-224 and AP-225
Canada	Support added for AP-205H
Ecuador	• Support added for AP-135 • Support added for AP-204 and AP-205
El Salvador	Support added for AP-114 and AP-115
Faroe Islands	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP

Table 304: *1.0_48713*

Regulatory Domain	Regulatory Changes
French Guiana	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
French Southern Territories	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Greenland	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Guatemala	Support added for AP-114 and AP-115
Guernsey	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Island of Man	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Jersey	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215

Table 304: *1.0_48713*

Regulatory Domain	Regulatory Changes
	• Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Jordan	• Support updated for AP-225 • Support added for AP-277
Martinique	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Monaco	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
New Zealand	Support added for AP-277
Oman	• Support added for AP-204and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for AP-274 and AP-275 • Support added for AP-277
Panama	Support added for AP-205
Philippines	Support added for AP-277
Reunion	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Saint Barthélemy	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205

Table 304: *1.0_48713*

Regulatory Domain	Regulatory Changes
	• Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Saint Martin	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Saint Pierre and Miquelon	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
San Marino	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Svalbard and Jan Mayen	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP
Wallis and Futuna	• Support added for AP-103 and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-224 and AP-225 • Support added for RAP-108 and RAP-109 • Support added for RAP-3WNP

1.0_48460

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 305: *1.0_48460*

Regulatory Domain	Regulatory Changes
Aland Islands	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Andorra	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Argentina	Support updated for AP-224and AP-225
Aruba	Support added for AP-225
Australia	Support updated for AP-277
Bahrain	Support added for AP-277
Barbados	Support added for AP-225
Brazil	Support added for AP-214 and AP-215
China	Support updated for RAP-3WN
Faroe Islands	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
French Guiana	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P

Table 305: *1.0_48460*

Regulatory Domain	Regulatory Changes
French Southern Territories	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Greenland	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Grenada	Support added for AP-225
Guernsey	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Island of Man	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Jersey	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Jordan	Support added for AP-225
Kenya	Support added for AP-103
Kuwait	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P

Table 305: *1.0_48460*

Regulatory Domain	Regulatory Changes
Martinique	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Monaco	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Morocco	Support added for AP-205
New Zealand	Support added for AP-277
Oman	• Support updated for AP-93 • Support added for AP-103
Peru	Support added for AP-274
Reunion	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Saint Barthélemy	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Saint Lucia	Support added for AP-225
Saint Martin	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Saint Pierre and Miquelon	• Support added for AP-93

Table 305: *1.0_48460*

Regulatory Domain	Regulatory Changes
	• Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
San Marino	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
Saudi Arabia	Support added for AP-277
Singapore	Support added for AP-277
Svalbard and Jan Mayen	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P
United States of America	Support updated for AP-103
Vietnam	Support added for AP-215
Wallis and Futuna	• Support added for AP-93 • Support added for AP-105 • Support added for AP-114 and AP-115 • Support added for AP-135 • Support added for AP-175P

1.0_48188

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 306: *1.0_48188*

Regulatory Domain	Regulatory Changes
Argentina	• Support added for AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215
Australia	UNII-3 band enabled for: ▪ AP-204 and AP-205 ▪ AP-214 and AP-215 ▪ AP-224 and AP-225
Costa Rica	• Support updated for AP-103 and AP-103H • Support updated for RAP-3WN and RAP-3WNP
Colombia	Support added for AP-214 and AP-215
Egypt	• Support updated for AP-92, AP-93, andAP-93H • Support updated for AP-114 and AP-115 • Support updated for AP-124 and AP-125 • Support updated for AP-134 and AP-135 • Support updated for AP-175P • Support updated for AP-204 and AP-205 • Support updated for AP-224 and AP-225 • Support updated for AP-274 and AP-275
Kuwait	Support added for AP-215
Mexico	Support added for AP-214
New Zealand	UNII-3 band enabled for: ▪ AP-204 and AP-205 ▪ AP-214 and AP-215 ▪ AP-224 and AP-225
Thailand	Support updated for AP-214 and AP-215
United States of America	FCC DFS channels 52-64 added for: ▪ AP-274 and AP-275

1.0_48019

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 307: *1.0_48019*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-274
Australia	Support updated for AP-274 and AP-275
Azerbaijan	Support added for AP-225
Bahamas	• Support updated for AP-204 and AP-205 • Support updated for AP-225
Brazil	Support added for AP-103H
Croatia	Support added for AP-225
Egypt	• Support added for AP-103 • Support added for AP-103H • Support added for AP-105
El Salvador	Support available for AP-224 and AP-225
New Zealand	Support added for AP-274 and AP-275
Russia	Support updated for AP-224 and AP-225
Taiwan	Support added for AP-274 and AP-275
United States of America	Support updated for AP-135

1.0_47726

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 308: *1.0_47726*

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-205
Brazil	Support updated for AP-92 and AP-93
Jamacia	Support added for AP-225
Morocco	Support added for RAP-3WN and RAP-3WNP
Malasyia	Support added for AP-214
Oman	• Support added for RAP-109 • Support added for RAP-155
Peru	• Support added for AP-204 and AP-205 • Support added for AP-275 • Support added for RAP-3WNP • Support added for RAP-108
Russia	• Support added for AP-103and AP-103H • Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215 • Support added for AP-274 and AP-275
South Korea	Support added for AP-103H
Taiwan	Support added for AP-274 and AP-275
Tunisia	Support updated for AP-105
United Arab Emirates	Support added for AP-214
Zimbabwe	• Support added for AP-103 • Support added for AP-205

1.0_47469

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 309: *1.0_47469*

Regulatory Domain	Regulatory Changes
Austria	Support added for AP-277
Belgium	Support added for AP-277
Botswana	Support added for AP-135
Brazil	Support added for RAP-155 and RAP-155P
Bulgaria	Support added for AP-277
Canada	Support added for AP-277
Cyprus	Support added for AP-277
Czech Republic	Support added for AP-277
Denmark	Support added for AP-277
Estonia	Support added for AP-277
Finland	Support added for AP-277
France	Support added for AP-277
Germany	Support added for AP-277
Greece	Support added for AP-277
Hungary	Support added for AP-277
Iceland	Support added for AP-277
Indonesia	Support added for AP-215
Ireland	Support added for AP-277
Italy	Support added for AP-277
Jordan	Support added for AP-103
Kazakhstan	• Support added for RAP-108 and RAP-109 • Support added for RAP-155 and RAP-155P

Table 309: *1.0_47469*

Regulatory Domain	Regulatory Changes
Kenya	• Support added for AP-115 • Support added for AP-205 • Support added for AP-215 • Support added for AP-225 • Support added for AP-275
Latvia	Support added for AP-277
Liechtenstein	Support added for AP-277
Lithuania	Support added for AP-277
Luxembourg	Support added for AP-277
Macau	• Support updated for AP-103 • Support updated for AP-103H
Malaysia	Support added for AP-215
Malta	Support added for AP-277
Mexico	Support updated for RAP-155 and RAP-155P
Netherlands	Support added for AP-277
Nigeria	Service added for AP-225
Norway	Support added for AP-277
Peru	• Service updated for AP-225 • Service updated for RAP-109 • Service added for RAP-3WN
Poland	Support added for AP-277
Portugal	Support added for AP-277
Romania	Support added for AP-277
Slovak Republic	Support added for AP-277
Slovenia	Support added for AP-277
Spain	Support added for AP-277
Sweden	Support added for AP-277

Table 309: *1.0_47469*

Regulatory Domain	Regulatory Changes
Switzerland	Support added for AP-277
Turkey	Support added for AP-277
United Arab Emirates	Support added for AP-205
United Kingdom	Support added for AP-277
United States of America	Support added for AP-277
Vietnam	Support added for RAP-155P
ETSI Country Domains	• MAX-EIRP updated for AP-204 and AP-205 • MAX-EIRP updated for AP-214 and AP-215

1.0_47156

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 310: *1.0_47156*

Regulatory Domain	Regulatory Changes
Australia	Support added for AP-214 and AP-215
Bolivia	Support added fot AP-135
Canada	DFS bands enabled for AP-214 and AP-215 DFS bands enabled for AP-274 and AP-275
China	Support updated for RAP-3WN and RAP-3WNP
Costa Rica	Support added for AP-114 and AP-115 Support added for AP-204 and AP-205 Support added for AP-224 and AP-225 Support updated for RAP-108 and RAP-109 Support added for RAP-3WN and RAP-3WNP Support added for AP-274 and AP-275
Kuwait	Support added for AP-225
Lebanon	Support added for AP-225
Macedonia	Support added for AP-225
Mexico	Support updated for AP-103
New Zealand	Support added for AP-214 and AP-215
Panama	Support added for AP-225 Support added for AP-135
Peru	Support added for AP-103 Support added for AP-114 and AP-115 Support updated for AP-135 Support added for RAP-109 Support added for RAP-109

Table 310: *1.0_47156*

Regulatory Domain	Regulatory Changes
Singapore	Support added for AP-204
South Africa	Supportupdated for AP-134 and AP-135 Support added for AP-214 and AP-215
Taiwan	Support added for AP-103H
United Arab Emirates	Support added for AP-215

1.0_46705

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 311: *1.0_46705*

Regulatory Domain	Regulatory Changes
Indonesia	• Support added for AP-103H • Support updated for AP-204
Macau	Support added for AP-103
Macedonia	Support added for AP-225
Malaysia	Support added for AP-103H
Mexico	• Support updated for RAP-155 and RAP-155P • Support added for AP-215 • Support updated for AP-224 and AP-225
Panama	• Support added for AP-135 • Support added for AP-225
Peru	• Support added for AP-103H • Support added for RAP-108
Serbia	Support added for AP-225
South Africa	Support updated for AP-204 and AP-205
Vietnam	• Support updated for AP-104 • Support added for AP-205

1.0_46413

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 312: *1.0_46413*

Regulatory Domain	Regulatory Changes
Indonesia	Support updated for AP-204
Japan	Support updated for AP-274 and AP-275
Macau	Support added for AP-103
Mexico	Support added for AP-103H
Morocco	Support updated for AP-225
Namibia	Support added for AP-224 and AP-225
Peru	• Support added for AP-103H • Support added for RAP-108
Ukraine	• Support updated for AP-224 and AP-225 • Support added for RAP-3WN and RAP-3WNP
United Arabic Emirates	Support added for AP-204

1.0_46245

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 313: *1.0_46245*

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-204 and AP-205
Bahrain	Support added for AP-225
Brazil	Support added for AP-204 and AP-205
Canada	DFS channels added for AP-204 and AP-205
Chile	• Support added for AP-103H • Support added for AP-214 and AP-215
China	Support added for AP-214 and AP-215
Costa Rica	Support added for RAP-108 and RAP-109
Egypt	Support added for AP-103H
Hong Kong	• Support added for AP-103H • Support added for AP-214 and AP-215
India	Support added for AP-214 and AP-215
Indonesia	• Support removed for AP-105 • Support added for RAP-108 and RAP-109 • Support added for AP-115 • Support removed for AP-135 • Support added for RAP-155 and RAP-155P • Support added for AP-175P • Support added for AP-225
Israel	• Support added for AP-103 • Support added for AP-104 • Support added for AP-204 and AP-205
Japan	Support added for AP-274 and AP-275
Malaysia	Support added for AP-204 and AP-205

Table 313: *1.0_46245*

Regulatory Domain	Regulatory Changes
Mauritius	Support added for AP-135
Mexico	• Support added for RAP-155 and RAP-155P • Support added for AP-204 and AP-205 • Support added for AP-275
Morocco	Support added for AP-225
Philippines	• Support added for AP-103H • Support added for AP-214 and AP-215
Quatar	Support added for AP-214 and AP-215
Saudi Arabia	• Support added for AP-103H • Support added forAP-105 • Support added for AP-214 and AP-215
South Africa	• Support added for AP-103H • Support added for AP-204 and AP-205
South Korea	• Support added for AP-204 and AP-205 • Support added for AP-214 and AP-215
Sri Lanka	• Support added for AP-105 • Channel 144 removed for AP-105 • Support added for AP-135 • Channel 144 removed for AP-135 • Support added for AP-225
Taiwan	• Support added for AP-103 • Support added for AP-214 and AP-215 • Channel 165 removed for AP-214 and AP-215
Ukraine	• Support added for AP-103H • Support added for AP-214 and AP-215
United Arab Emirates	Support added for AP-103H
Uruguay	• Support added for AP-135 • Support added for AP-225
Vietnam	Support added for AP-104

1.0_45530

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 314: *1.0_45530*

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-274 and AP-275
Australia	Support added for AP-103H
Bolivia	Support added for AP-225
Botswana	Support added for AP-225
Brazil	Support added for AP-103
India	Support added for AP-204 and AP-205
Japan	Support added for AP-103H
New Zealand	Support added for AP-103H
Singapore	• Support added for AP-214 and AP-215 • Support added for AP-103H
South Korea	Support added for AP-274 and AP-275
Taiwan	Support added for AP-204 and AP-205
Venezuela	Channels 36-48 for 802.11a 80MHz (outdoor)

1.0_45134

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 315: *1.0_45134*

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-103
Australia	Support added for AP-204and AP-205
Austria	• Support added for AP-103H • Support added for AP-214 and AP-215
Bahamas	• Support added for AP-204and AP-205 • Support added for AP-224 and AP-225 • Support added for AP-274 and AP-275
Bosnia/Herzegovina	Support added for AP-103H
Belgium	• Support added for AP-103H • Support added for AP-214 and AP-215
Bulgaria	• Support added for AP-103H • Support added for AP-214 and AP-215
Canada	Support added for AP-103H Support added for AP-214 and AP-215
China	Support added for AP-275
Colombia	• FCC DFS channels added to AP-224 and AP-225 • Support added for AP-103H
Croatia	• Support added for AP-103H • Support added for AP-214 and AP-215
Cyprus	Support added for AP-103H
Czech Republic	• Support added for AP-103H • Support added for AP-214 and AP-215
Denmark	• Support added for AP-103H • Support added for AP-214 and AP-215
Dominica Republic	FCC DFS channels added to AP-224 and AP-225
Estonia	• Support added for AP-103H • Support added for AP-214 and AP-215
Finland	• Support added for AP-103H • Support added for AP-214 and AP-215

Table 315: *1.0_45134*

Regulatory Domain	Regulatory Changes
France	• Support added for AP-103H • Support added for AP-214 and AP-215
Germany	• Support added for AP-103H • Support added for AP-214 and AP-215
Hong Kong	• Support added for AP-204 and • Channels 141-165 enabled for AP-120, AP-121, AP-124, and AP-125
Hungary	• Support added for AP-103H • Support added for AP-214 and AP-215
India	Support added for AP-274 and AP-275
Ireland	• Support added for AP-103H • Support added for AP-214 and AP-215
Israel	• Support ended for 802.11g 40MHz (indoor) 8-12 and 9-13 • Support ended for 802.11g 40MHz (outdoor) 8-12 and 9-13
Italy	• Support added for AP-103H • Support added for AP-214 and AP-215
Japan	Support added for AP-204and AP-205
Israel	Support added for AP-204and AP-205
Latvia	• Support added for AP-103H • Support added for AP-214 and AP-215
Lithuania	• Support added for AP-103H • Support added for AP-214 and AP-215
Luxembourg	• Support added for AP-103H • Support added for AP-214 and AP-215
Macedonia	• Support added for AP-204and AP-205 • Support added for AP-103H
Malta	• Support added for AP-103H • Support added for AP-214 and AP-215
Maritime	Support added for this domain
Maritime Offshore	Support added for this domain
Mauritius	Support added for AP-224 and AP-225
Mexico	Support added for AP-103
Montenegro	Support added for AP-103H
Netherlands	• Support added for AP-103H

Table 315: *1.0_45134*

Regulatory Domain	Regulatory Changes
	• Support added for AP-214 and AP-215
New Zealand	Support added for AP-204and AP-205
Philippines	• Support added for RAP-108 • Support added for AP-204and AP-205
Poland	• Support added for AP-103H • Support added for AP-214 and AP-215
Portugal	• Support added for AP-103H • Support added for AP-214 and AP-215
Puerto Rico	• FCC DFS channels added to AP-224 and AP-225 • Support added for AP-103H
Qatar	Support added for AP-204and AP-205
Romania	• Support added for AP-103H • Support added for AP-214 and AP-215
Saudi Arabia	Support added for AP-204and AP-205
Slovakia	• Support added for AP-103H • Support added for AP-214 and AP-215
Slovenia	• Support added for AP-103H • Support added for AP-214 and AP-215
South Africa	Support added for AP-274 and AP-275
South Korea	Support added for AP-274 and AP-275
Sweden	Support added for AP-103H
Thailand	Support added for AP-103H
Ukraine	Support added for AP-204and AP-205
United Kingdom	• Support added for AP-103H • Support added for AP-214 and AP-215
United States of America	Support added for AP-103H Support added for AP-214 and AP-215
Venezuela	Support added for AP-225
Vietnam	• Support added for AP-225 • Support added for AP-115

1.0_44265

This table describes the new regulatory changes to access points and channels introduced in this release.

NOTE

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

Table 316: *1.0_44265*

Regulatory Domain	Regulatory Changes
Chile	Support added for AP-270 Series
Hong Kong	Support added for AP-220 Series
Puerto Rico	Support added for AP-270 Series